

INTERNATIONAL STANDARD

**Coaxial communication cables –
Part 1-119: Electrical test methods – RF power rating**

Withhold
IECNORM.COM: Click to view the full PDF of IEC 61196-1-119:2012



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2012 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

Useful links:

IEC publications search - www.iec.ch/searchpub

The advanced search enables you to find IEC publications by a variety of criteria (reference number, text, technical committee,...).

It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available on-line and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary (IEV) on-line.

Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

INTERNATIONAL STANDARD

**Coaxial communication cables –
Part 1-119: Electrical test methods – RF power rating**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE

K

ICS 33.120.10

ISBN 978-2-83220-391-0

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	3
1 Scope.....	5
2 Normative references.....	5
3 Terms and definitions	5
4 Symbols	5
5 Methodology	7
5.1 Method A.....	7
5.2 Method B.....	7
6 Temperature test	7
6.1 Procedure: General considerations	7
6.2 Procedure: RF test – Method A	7
6.3 Procedure: Low frequency power AC test – Method B.....	8
7 Attenuation test.....	8
7.1 Conduct attenuation test	8
7.2 Calculate A and B coefficients – Method B	8
7.3 Calculate the A_i and A_o coefficients – Method B.....	9
8 Power calculation.....	9
8.1 Determined from AC test – Method B	9
8.2 Determined from RF test – Method A	10
8.3 Adjustment to other frequencies.....	10
9 Test report.....	10
10 Requirements.....	10

INTERNATIONAL ELECTROTECHNICAL COMMISSION

COAXIAL COMMUNICATION CABLES –

Part 1-119: Electrical test methods – RF power rating

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61196-1-119 has been prepared by subcommittee 46A: Coaxial cables, of IEC technical committee 46: Cables, wires, waveguides, R.F. connectors, R.F. and microwave passive components and accessories.

The text of this standard is based on the following documents:

FDIS	Report on voting
46A/1094/FDIS	46A/1116/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all the parts in the IEC 61196 series published under the general title *Coaxial communication cables* can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

IECNORM.COM: Click to view the full PDF of IEC 61196-1-119:2012

Withdrawn

COAXIAL COMMUNICATION CABLES –

Part 1-119: Electrical test methods – RF power rating

1 Scope

This part of IEC 61196 defines the requirements to determine the average power handling capability of a coaxial cable at specified frequencies at ambient temperatures.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61196-1, *Coaxial communication cables – Part 1: Generic specification – General, definitions and requirements*

IEC 61196-1-113, *Coaxial communication cables – Part 1-113: Electrical test methods – Test for attenuation constant*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 61196-1, as well as the following apply.

3.1

RF power rating

maximum average input power that a cable can continuously handle when terminated in its characteristic impedance at a reference ambient temperature and RF frequency

Note 1 to entry: RF power rating is determined by the power level at which the temperature at any location in the cable does not exceed the allowable maximum temperature rating of the materials used in the cable's construction.

Note 2 to entry: Typically, the inner conductor temperature determines the maximum operating temperature.

Note 3 to entry: The test RF signal is a pure sinusoidal, without any modulation.

4 Symbols

For the purposes of this document, the following symbols apply.

K_i thermal constant of the insulation (W/(°C·m))

K_o thermal constant of outer sheath (W/(°C·m))

A attenuation constant associated with the conductors $\left(\frac{\text{dB}}{\text{m} \cdot \sqrt{\text{MHz}}} \right)$

A_i attenuation constant of inner conductor $\left(\frac{\text{dB}}{\text{m} \cdot \sqrt{\text{MHz}}} \right)$

A_o	attenuation constant of outer conductor $\left(\frac{\text{dB}}{\text{m} \cdot \sqrt{\text{MHz}}} \right)$
B	attenuation constant for the dielectric material $\left(\frac{\text{dB}}{\text{m} \cdot \text{MHz}} \right)$
a	mean outer diameter of inner conductor (mm) Corrugated: Mean = (peak + root)/2 Smooth wall = (max + min)/2
b	mean inner diameter of outer conductor (mm) Corrugated: Mean = (peak + root)/2 Smooth wall = (max + min)/2
C_i	corrugation factor of inner conductor: Ratio of the distance that compares the non-corrugated (conversion of corrugated length to an equivalent smooth wall length) to the cable corrugated length. $C_i > 1$ for corrugated cable $C_i = 1$ for smooth wall
C_o	corrugation factor of outer conductor Ratio of the distance that compares the non-corrugated (conversion of corrugated length to an equivalent smooth wall length) to the cable corrugated length. $C_i > 1$ for corrugated cable $C_i = 1$ for smooth wall
P_{in}	RF input power (W)
P_r	rated RF power (W) at frequency f
P_{rf1}	rated RF power (W) at frequency f_1
P_{rf2}	rated RF power (W) at frequency f_2
P_i	power dissipated in inner conductor (W/m)
P_o	power dissipated in outer conductor (W/m)
σ_i	conductivity of inner conductor (relative to copper)
σ_o	conductivity of outer conductor (relative to copper)
γ_i	temperature coefficient of resistance for inner conductor
γ_o	temperature coefficient of resistance for outer conductor
α_c	attenuation of cable, at frequency f (dB/100 m)
α_{f1}	attenuation of cable, at frequency f_1 (dB/100 m)
α_{f2}	attenuation of cable, at frequency f_2 (dB/100 m)
α_i	attenuation of inner conductor, at frequency f (dB/100 m)
α_o	attenuation of outer conductor, at frequency f (dB/100 m)
T_i	inner conductor temperature (°C)
T_o	outer conductor temperature (°C)
T_a	test ambient temperature (°C)
T_{ri}	inner conductor temperature rise (°C)
T_{ro}	outer conductor temperature rise (°C)
R_T	maximum rated ambient temperature (°C)

5 Methodology

5.1 Method A

If a suitable RF power source is available, it is possible to determine the input power required for a conductor temperature to reach its limiting value (i.e. the average power rating), per 6.2. This provides measurements at one frequency and generally needs to be adjusted to other frequencies by knowing the RF cable attenuation.

5.2 Method B

Cables of large diameter, however, have high average power ratings, and a suitable RF source may not be available for such direct test. The following methodology allows the RF average power rating to be determined by using low frequency (50 Hz or 60 Hz) AC power to determine the required thermal characteristics. The low frequency AC data needs to be combined with RF data because the relative conductor power dissipations are different. Also there is no dissipation in the dielectric in the low frequency case, but at RF frequencies this becomes significant.

6 Temperature test

6.1 Procedure: General considerations

A cable of sufficient length shall be used so that the temperatures measured at the centre of the cable are not influenced by heat sinking effects at the ends of the cable.

Thermocouples should be chosen and sized to eliminate the possibility of heat sinking effects, particularly with thin walled cables.

There shall be sufficient air space around the cable under test to allow natural air circulation.

Temperature measurements on the inner and outer conductors shall be made at the centre of the cable length and 0,5 m away from both sides of the centre point.

Sufficient power should be applied for a conductor temperature to reach its maximum value, determined by the materials used in the cable construction.

The test is conducted for sufficient duration for the conductors to reach constant temperatures.

The measured results and determination of the average power rating are adjusted for an ambient temperature of 40 °C (or other specified ambient temperature).

6.2 Procedure: RF test – Method A

The input of the cable shall be connected to the RF power source capable of delivering the specified power at the specified test frequency at the load.

The load side of the cable shall be terminated in its characteristic impedance that is capable of handling the power.

The input power, P_{in} , at the test frequency shall be monitored.

It is recommended to drill a small hole into the cable just above the inner conductor. A fibre optic thermocouple should be placed within 1 mm above the surface of the inner conductor to measure the temperature.

The input power, at room temperature (T_a), shall be increased in stages until maximum component temperature ratings are reached. The conductor temperatures are allowed to stabilize at each stage and then recorded.

Each conductor temperature rise (T_{ri} and T_{ro}) at each stage above the room temperature (T_a) is determined for each input power level by subtracting the T_a from the measured conductors (T_i or T_o) temperature.

For each stage, T_i and T_o shall be determined for R_T by adding T_{ri} and T_{ro} to R_T .

Compare the recalculated T_i and T_o at R_T to the maximum temperature ratings of the cable components. The power rating is the level that does not exceed the maximum temperature ratings of the cable components.

The increase in conductor temperature above ambient temperature is determined for each input power level. The average power rating is that power which will cause an increase in conductor temperature above ambient equal to the difference between the maximum conductor temperature and the reference ambient (usually 40 °C).

6.3 Procedure: Low frequency power AC test – Method B

The input of the cable shall be connected to a 50 Hz or 60 Hz source capable of delivering sufficient current carrying capacity.

The opposite cable end shall be short circuited by connecting the inner conductor to the outer conductor.

Adjust the current levels to within 15 % of the maximum temperature ratings of the cable components.

The current, the voltages across both inner and outer conductors and the conductor temperatures (when they have stabilized) shall be measured and recorded. From the voltage and current values, the dissipated powers in the inner and outer conductors (P_i and P_o) are determined.

The thermal constants K_i and K_o are derived from the following equations:

$$P_i = K_i \times (T_i - T_o) \quad (1)$$

$$P_i + P_o = K_o \times (T_o - T_a) \quad (2)$$

7 Attenuation test

7.1 Conduct attenuation test

An attenuation test shall be conducted in accordance with IEC 61196-1-113 to determine the attenuation at a test ambient at several frequencies over the operating band of the cable. This attenuation response will be used to determine the coefficient for the conductors and dielectric which will then be used in the RF power calculations or used in determining RF power at other frequencies.

7.2 Calculate A and B coefficients – Method B

The A and B coefficients in Formula (3) are calculated by performing a least squares analysis, which is a fit of the measured attenuation and frequency data:

$$\alpha_c = A \times \sqrt{f} + B \times f \quad (\text{dB/100 m}) \quad (3)$$

where

A is the coefficient for the conductors;

B is the coefficient for the dielectric;

f is the frequency in MHz.

The A and B coefficients are calculated from the attenuation test from the following formulas:

$$A = \frac{\left[\left(\sum_{i=1}^n f_i - \sum_{i=1}^n \left(\frac{\alpha_i}{\sqrt{f_i}} \right) \right) - \left(\sum_{i=1}^n \sqrt{f_i} - \sum_{i=1}^n \alpha_i \right) \right]}{\left[n \times \sum_{i=1}^n f_i - \left(\sum_{i=1}^n \sqrt{f_i} \right)^2 \right]} \quad (4)$$

$$B = \frac{\left[n \times \sum_{i=1}^n \alpha_i - \left(\sum_{i=1}^n \sqrt{f_i} \times \sum_{i=1}^n \left(\frac{\alpha_i}{\sqrt{f_i}} \right) \right) \right]}{\left[n \times \sum_{i=1}^n f_i - \left(\sum_{i=1}^n \sqrt{f_i} \right)^2 \right]} \quad (5)$$

7.3 Calculate the A_i and A_o coefficients – Method B

The A coefficient represents the contribution of the inner and outer conductors. To calculate the power, the conductor inner and outer conductor coefficients (A_i and A_o) are needed and are determined from the conductivity of the inner and outer conductor. It is determined as follows:

$$A_i = A \times \frac{\frac{C_i}{a \times \sqrt{\sigma_i}}}{\frac{C_i}{a \times \sqrt{\sigma_i}} + \frac{C_o}{b \times \sqrt{\sigma_o}}} \quad (6)$$

$$A_o = A \times \frac{\frac{C_o}{b \times \sqrt{\sigma_o}}}{\frac{C_i}{a \times \sqrt{\sigma_i}} + \frac{C_o}{b \times \sqrt{\sigma_o}}} \quad (7)$$

8 Power calculation

8.1 Determined from AC test – Method B

The maximum RF power (P_r) can now be determined by solving the following equations numerically (e.g. by using a suitable spreadsheet) for any given frequency and ambient temperature and some limiting value for either inner or outer conductor temperature.