

TECHNICAL REPORT

**Information technology – Generic cabling for customer premises –
Part 9905: Guidelines for the use of installed cabling to support 25GBASE-T
application**

IECNORM.COM : Click to view the full PDF of ISO/IEC TR 11801-9905:2018



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2018 ISO/IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about ISO/IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing 21 000 terms and definitions in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IECNORM.COM : Click to view the full PDF of IEC 60139-1:2018



TECHNICAL REPORT

**Information technology – Generic cabling for customer premises –
Part 9905: Guidelines for the use of installed cabling to support 25GBASE-T
application**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	7
1 Scope.....	8
2 Normative references	8
3 Terms, definitions and abbreviations	8
4 Cabling channel specifications for 25 GBASE-T.....	9
4.1 General.....	9
4.2 25GBASE-T application specifications	9
4.2.1 Return loss	9
4.2.2 Insertion loss/attenuation.....	10
4.2.3 NEXT.....	11
4.2.4 Attenuation to crosstalk ratio at the near-end (ACR-N)	13
4.2.5 Attenuation to crosstalk ratio at the far-end (ACR-F).....	13
4.2.6 Propagation delay.....	15
4.2.7 Delay skew	15
4.2.8 Unbalance attenuation and coupling attenuation	15
4.2.9 Alien crosstalk	16
4.3 Associated risk of 25GBASE-T operation over installed cabling	17
4.4 Characterization of balanced channels using Category 7 _A components	17
4.4.1 General	17
4.4.2 Selection of channels for qualification.....	18
4.4.3 Return loss	18
4.4.4 Insertion loss	19
4.4.5 Near-end crosstalk loss (NEXT).....	19
4.4.6 Attenuation to crosstalk loss ratio near-end (ACR-N)	21
4.4.7 Attenuation to crosstalk ratio far-end (ACR-F)	22
4.4.8 Alien (exogenous) crosstalk.....	24
4.4.9 Propagation delay.....	25
4.4.10 Delay skew	25
4.4.11 Coupling attenuation.....	25
4.4.12 Alien crosstalk and coupling attenuation	26
4.5 Characterization of balanced channels using Category 7 components.....	26
4.5.1 General	26
4.5.2 Selection of channels for qualification.....	27
4.5.3 Return loss	27
4.5.4 Insertion loss	28
4.5.5 Near-end crosstalk loss (NEXT).....	28
4.5.6 Attenuation to crosstalk loss ratio near-end (ACR-N)	30
4.5.7 Attenuation to crosstalk ratio far-end (ACR-F)	31
4.5.8 Alien (exogenous) crosstalk.....	33
4.5.9 Propagation delay.....	34
4.5.10 Delay skew	34
4.5.11 Coupling attenuation.....	34
4.5.12 Alien crosstalk and coupling attenuation	35
4.6 Characterization of balanced channels using Category 6 _A components	35
4.6.1 General	35
4.6.2 Selection of channels for qualification.....	36

4.6.3	Test specifications for channels made out of Category 6A components	36
5	Guidance for mitigation procedures to improve the cabling of existing installations	36
5.1	General.....	36
5.2	Mitigation procedures related to internal noise	36
5.3	Mitigation procedures related to exogenous noise (alien crosstalk)	36
6	Guidance for cabling for new installations.....	37
	Bibliography.....	38
	Table 1 – Return loss for a channel	9
	Table 2 –Return loss values for a channel at key frequencies	10
	Table 3 – Insertion loss for a channel	10
	Table 4 – Insertion loss values for a channel at key frequencies	11
	Table 5 – NEXT for a channel	11
	Table 6 – NEXT values for a channel at key frequencies.....	12
	Table 7 – PS NEXT for a channel	12
	Table 8 – PS NEXT values for a channel at key frequencies	13
	Table 9 – ACR-F for a channel.....	13
	Table 10 – ACR-F values for a channel at key frequencies	14
	Table 11 – PS ACR -F for a channel	14
	Table 12 – PS ACR-F values for a channel at key frequencies	14
	Table 13 – Propagation delay for a channel	15
	Table 14 – Propagation delay values for a channel at key frequencies.....	15
	Table 15 – Delay skew for a channel	15
	Table 16 – PS ANEXT for a channel	16
	Table 17 – PS ANEXT values for a channel at key frequencies	16
	Table 18 – PS AACR-F for a channel	17
	Table 19 – PS AACR-F values for a channel at key frequencies	17
	Table 20 – Risk of 25GBASE-T operation over installed cabling channels.....	17
	Table 21 – Formulae for return loss limits for a channel	18
	Table 22 – Return loss limits for a channel at key frequencies	18
	Table 23 – Formula for insertion loss limits for a channel.....	19
	Table 24 – Insertion loss limits for a channel at key frequencies	19
	Table 25 – Formulae for pair-to-pair NEXT limits for a channel	19
	Table 26 – Pair-to-pair NEXT limits for a channel at key frequencies	20
	Table 27 – Formulae for PS NEXT limits for a channel.....	20
	Table 28 –PS NEXT limits for a channel at key frequencies	20
	Table 29 – ACR-N limits for a channel at key frequencies	21
	Table 30 – PS ACR-N limits for a channel at key frequencies	22
	Table 31 – Formulae for ACR-F limits for a channel	22
	Table 32 – ACR-F limits for a channel at key frequencies	23
	Table 33 – Formulae for PS ACR-F limits for a channel	23
	Table 34 – PS ACR-F limits for a channel at key frequencies	23
	Table 35 – Formulae for PS ANEXT limits for a channel	24
	Table 36 – PS ANEXT limits for a channel at key frequencies	24

Table 37 – Formula for PS AACR-F limits for a channel	24
Table 38 – PS AACR-F limits for a channel at key frequencies	25
Table 39 – Formula for propagation delay limits for a channel.....	25
Table 40 – Propagation delay limits for a channel at key frequencies.....	25
Table 41 – Formula for coupling attenuation limits for a channel	26
Table 42 – Coupling attenuation limits for a channel at key frequencies.....	26
Table 43 – Alien crosstalk and coupling attenuation.....	26
Table 44 – Formulae for return loss limits for a channel	27
Table 45 – Return loss limits for a channel at key frequencies	27
Table 46 – Formula for insertion loss limits for a channel.....	28
Table 47 – Insertion loss limits for a channel at key frequencies	28
Table 48 – Formulae for pair-to-pair NEXT limits for a channel	28
Table 49 – Pair-to-pair NEXT limits for a channel at key frequencies	29
Table 50 – Formulae for PS NEXT limits for a channel.....	29
Table 51 – PS NEXT limits for a channel at key frequencies	29
Table 52 – ACR-N limits for a channel at key frequencies.....	30
Table 53- PS ACR-N limits for a channel at key frequencies.....	31
Table 54 – Formulae for ACR-F limits for a channel.....	31
Table 55 – ACR-F limits for a channel at key frequencies	32
Table 56 – Formulae for PS ACR-F limits for a channel	32
Table 57 – PS ACR-F limits for a channel at key frequencies.....	32
Table 58 – Formulae for PS ANEXT limits for a channel	33
Table 59 – PS ANEXT limits for a channel at key frequencies.....	33
Table 60 – Formula for PS AACR-F limits for a channel	33
Table 61 – PS AACR-F limits for a channel at key frequencies	34
Table 62 – Formula for propagation delay limits for a channel.....	34
Table 63 – Propagation delay limits for a channel at key frequencies.....	34
Table 64 – Formula for coupling attenuation limits for a channel	35
Table 65 – Coupling attenuation limits for a channel at key frequencies.....	35
Table 66 – Alien crosstalk and coupling attenuation for shielded channels.....	35

INFORMATION TECHNOLOGY – GENERIC CABLING FOR CUSTOMER PREMISES –

Part 9905: Guidelines for the use of installed cabling to support 25GBASE-T application

FOREWORD

- 1) ISO (International Organization for Standardization) and IEC (International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards. Their preparation is entrusted to technical committees; any ISO and IEC member body interested in the subject dealt with may participate in this preparatory work. International governmental and non-governmental organizations liaising with ISO and IEC also participate in this preparation.
- 2) In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.
- 3) The formal decisions or agreements of IEC and ISO on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC and ISO member bodies.
- 4) IEC, ISO and ISO/IEC publications have the form of recommendations for international use and are accepted by IEC and ISO member bodies in that sense. While all reasonable efforts are made to ensure that the technical content of IEC, ISO and ISO/IEC publications is accurate, IEC or ISO cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 5) In order to promote international uniformity, IEC and ISO member bodies undertake to apply IEC, ISO and ISO/IEC publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any ISO/IEC publication and the corresponding national or regional publication should be clearly indicated in the latter.
- 6) ISO and IEC provide no marking procedure to indicate their approval and cannot be rendered responsible for any equipment declared to be in conformity with an ISO/IEC publication.
- 7) All users should ensure that they have the latest edition of this publication.
- 8) No liability shall attach to IEC or ISO or its directors, employees, servants or agents including individual experts and members of their technical committees and IEC or ISO member bodies for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication of, use of, or reliance upon, this ISO/IEC publication or any other IEC, ISO or ISO/IEC publications.
- 9) Attention is drawn to the normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 10) Attention is drawn to the possibility that some of the elements of this ISO/IEC publication may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

The main task of the joint technical committee is to prepare International Standards. However, the joint technical committee may propose the publication of a Technical Report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

ISO/IEC TR 11801-9905, which is a Technical Report, was prepared by subcommittee 25: Interconnection of information technology equipment, of ISO/IEC joint technical committee 1: Information technology.

The list of all currently available parts of the ISO/IEC 11801 series, under the general title *Information technology — Generic cabling for customer premises*, can be found on the IEC website.

This Technical Report has been approved by vote of the member bodies, and the voting results may be obtained from the address given on the second title page.

This Technical Report is to be read in conjunction with ISO/IEC/IEEE 8802.3:2017/AMD3.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

IECNORM.COM : Click to view the full PDF of ISO/IEC TR 11801-9905:2018

INTRODUCTION

This document provides guidance to determine whether and which installed channels will support 25GBASE-T. It takes into account the design goals for 25GBASE-T equipment such as:

- a) the frequency signal range up to 1 250 MHz;
- b) the support of two-connector channels up to 30 m in length.

The requirements of 25GBASE-T are fully defined in ISO/IEC/IEEE 8802-3:2017/AMD3.

Installed two-connector channels which are characterized up to 1 250 MHz and support all the requirements of the ISO/IEC/IEEE 8802-3:2017/AMD3 link segment are expected to support the 25GBASE-T application.

Characterization of channels using Category 7_A components is described in 4.4.

Characterization of channels using Category 7 components is described in 4.5.

Characterization of channels using Category 6_A components is described in 4.6.

This document also provides mitigation procedures to improve the performance of installed channels to the point where the 25GBASE-T application is supported. Additionally, this document recommends the use of Class I and Class II channels to support 25GBASE-T in new installations.

Class I and Class II channels according to ISO/IEC 11801-1 will support 25GBASE-T without mitigation.

Component requirements are not provided in this document and should not be inferred from the channel limits provided.

INFORMATION TECHNOLOGY – GENERIC CABLING FOR CUSTOMER PREMISES –

Part 9905: Guidelines for the use of installed cabling to support 25GBASE-T application

1 Scope

This part of ISO/IEC 11801, which is a Technical Report,

- a) provides guidance on how to select and assess installed channels which conform to ISO/IEC 11801-1, and clarify if they also support ISO/IEC/IEEE 8802-3:2017/AMD3 for 25GBASE-T;
- b) specifies the methods to assess whether installed channels constructed with Category 7_A, 7, or 6_A components meet the 25GBASE-T requirements;
- c) provides guidance to identify which channels are likely to meet the 25GBASE-T requirements to avoid unnecessary testing;
- d) provides mitigation techniques to improve the performance of installed channels to meet the 25GBASE-T requirements;
- e) provides cabling recommendations for new installations.

NOTE 1 The channel transmission performance specified in this document is derived from the 25GBASE-T requirements in ISO/IEC/IEEE 8802-3:2017/AMD3.

NOTE 2 This document does not re-specify component or channel definitions of ISO/IEC 11801-1.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO/IEC 11801-1, *Information technology – Generic cabling systems – Part 1: General requirements*

ISO/IEC/IEEE 8802-3:2017/AMD3, *Information technology – Telecommunications and information exchange between systems – Local and metropolitan area networks – Specific requirements – Part 3: Standard for Ethernet – Amendment 3: Physical layers and management parameters for 25 Gb/s and 40 Gb/s operation, types 25GBASE-T and 40GBASE-T*

3 Terms, definitions and abbreviations

For the purposes of this document, the terms, definitions and abbreviations given in ISO/IEC 11801-1 apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

4 Cabling channel specifications for 25 GBASE-T

4.1 General

This document provides guidelines for the assessment of installed cabling channels for the additional requirements of ISO/IEC/IEEE 8802-3:2017/AMD3 for 25GBASE-T. It is assumed that each installed channel does fulfil the requirements of its appropriate cabling class defined in ISO/IEC 11801-1.

The requirements defined in Clause 4 are a combination of the original class requirements of the installed cabling and the requirements in support of 25GBASE-T.

For a balanced cabling installation covered by this document:

- the channel performance is specified according to ISO/IEC 11801-1 and additionally according to Clause 4 (or appropriate subclause);
- the interfaces to the cabling are specified according to ISO/IEC 11801-1:2017, Clause 10, with respect to mating interfaces;
- local regulations concerning safety and EMC apply.

The test procedures for balanced cabling installations are specified in IEC 61935-1 in accordance with ISO/IEC 11801-1 and ISO/IEC 14763-2.

4.2 25GBASE-T application specifications

NOTE 1 These specifications are consistent with the link segment specifications of ISO/IEC/IEEE 8802-3:2017/AMD3.

NOTE 2 All specifications are based on a channel length of 30 m with 2 connections.

4.2.1 Return loss

The return loss (RL) of each pair of a channel is specified in Table 1. The limits shown in Table 2 are derived from the formulae at key frequencies.

The return loss requirement is specified for both ends of the cabling. Return loss (RL) values at frequencies where the insertion loss (IL) is below 3,0 dB are for information only.

Table 1 – Return loss for a channel

Class	Frequency MHz	Minimum return loss dB
I	$1 \leq f < 10$	19,0
	$10 \leq f < 40$	$24 - 5\lg(f)$
	$40 \leq f < 130$	16,0
	$130 \leq f < 1\,000$	$35 - 9\lg(f)$
	$1\,000 \leq f \leq 1\,250$	8,0

Table 2 –Return loss values for a channel at key frequencies

Frequency MHz	Minimum return loss dB
	Class
	I
1	19,0
16	18,0
100	16,0
250	13,4
500	10,7
600	10,0
1 000	8,0
1 250	8,0

4.2.2 Insertion loss/attenuation

The insertion loss (IL) of each pair of a channel is specified in Table 3. The limits shown in Table 4 are derived from the formulae at key frequencies.

Table 3 – Insertion loss for a channel

Class	Frequency MHz	Maximum insertion loss ^a dB
I	$1 < f \leq 500$	$\left(0,634\sqrt{f} + 0,00156 \times f + \frac{0,078}{\sqrt{f}} \right)^b$
	$500 < f \leq 1250$	$\left(0,60698\sqrt{f} + 0,00277 \times f + \frac{0,078}{\sqrt{f}} \right)^c$

^a Insertion loss (IL) at frequencies that correspond to calculated values of less than 4,0 dB revert to a maximum requirement of 4,0 dB.

^b This formula is derived using: $0,312 \times \left(1,8\sqrt{f} + 0,005 \times f + \frac{0,25}{\sqrt{f}} \right) + 2 \times (0,02 \times \sqrt{f}) + 0,0324 \times \sqrt{f}$

^c This formula is derived using:
 $0,312 \times \left(1,8\sqrt{f} + 0,005 \times f + \frac{0,25}{\sqrt{f}} \right) + 2 \times (0,00649 \times \sqrt{f} + 0,000605 \times f) + 0,0324 \times \sqrt{f}$

Table 4 – Insertion loss values for a channel at key frequencies

Frequency MHz	Maximum insertion loss dB
	Class
	I
1	4,0
16	4,0
100	6,5
250	10,4
500	15,0
600	16,5
1 000	22,0
1 250	24,9

4.2.3 NEXT

4.2.3.1 Pair-to-pair NEXT

The NEXT between each pair combination of a channel is specified in Table 5. The limits shown in Table 6 are derived from the formulae at key frequencies.

The NEXT requirement is specified for both ends of the cabling. NEXT values at frequencies where the insertion loss (IL) is below 4,0 dB are for information only.

Table 5 – NEXT for a channel

Class	Frequency MHz	Minimum NEXT ^a dB
I	$1 \leq f \leq 500$	$-20 \lg \left(\frac{75,3 - 15 \lg(f)}{10 - 20} + 2 \times \frac{94 - 20 \lg(f)}{10 - 20} \right)$
	$500 < f \leq 1250$	$-20 \lg \left(\frac{75,3 - 15 \lg(f)}{10 - 20} + 2 \times \frac{40 - 38 \lg(f/500)}{10 - 20} \right)$
^a NEXT at frequencies that correspond to calculated values of greater than 65,0 dB revert to a minimum requirement of 65,0 dB.		

**Table 6 – NEXT values for a channel
at key frequencies**

Frequency MHz	Minimum channel NEXT dB
	Class
	I
0,1	–
1	65,0
16	53,9
100	40,5
250	33,6
500	28,4
600	26,2
1 000	19,6
1 250	16,5

4.2.3.2 Power sum NEXT (PS NEXT)

The PS NEXT of each pair of a channel is specified in Table 7. The limits shown in Table 8 are derived from the formulae at key frequencies.

Table 7 – PS NEXT for a channel

Class	Frequency MHz	Minimum PS NEXT ^a dB
I	$1 \leq f \leq 500$	$-20 \lg \left(10^{\frac{72,3 - 15 \lg(f)}{-20}} + 2 \times 10^{\frac{91 - 20 \lg(f)}{-20}} \right)$
	$500 < f \leq 1\,250$	$-20 \lg \left(10^{\frac{72,3 - 15 \lg(f)}{-20}} + 2 \times 10^{\frac{37 - 38 \lg(f/500)}{-20}} \right)$
^a PS NEXT at frequencies that correspond to calculated values of greater than 62,0 dB revert to a minimum requirement of 62,0 dB.		

Table 8 – PS NEXT values for a channel at key frequencies

Frequency MHz	Minimum PS NEXT dB
	Class
	I
1	62,0
16	50,9
100	37,5
250	30,6
500	25,4
600	23,2
1 000	16,6
1 250	13,5

4.2.4 Attenuation to crosstalk ratio at the near-end (ACR-N)

4.2.4.1 Pair-to-pair ACR-N

ACR-N performance is dependent upon NEXT and IL, and is not an independent specification included for 25GBASE-T.

4.2.4.2 Power sum ACR-N (PS ACR-N)

PS ACR-N performance is dependent upon PS NEXT and IL, and is not an independent specification included for 25GBASE-T.

4.2.5 Attenuation to crosstalk ratio at the far-end (ACR-F).

4.2.5.1 Pair-to-pair ACR-F

The ACR-F of each pair combination of a channel is specified in Table 9. The limits shown in Table 10 are derived from the formula at key frequencies.

Table 9 – ACR-F for a channel

Class	Frequency MHz	Minimum ACR-F ^{a, b} dB
I	$1 \leq f \leq 1250$	$-20 \lg \left(\frac{79 - 20 \lg(f)}{10 - 20} + 2 \times \frac{83,1 - 20 \lg(f)}{10 - 20} \right)$
^a ACR-F at frequencies that correspond to measured FEXT values of greater than 70,0 dB are for information only. ^b The ACR-F limit at frequencies that correspond to calculated values of greater than 65,0 dB revert to a minimum requirement of 65,0 dB.		

Table 10 – ACR-F values for a channel at key frequencies

Frequency MHz	Minimum ACR-F dB
	Class
	I
1	65,0
16	47,9
100	32,0
250	24,0
500	18,0
600	16,4
1 000	12,0
1 250	10,0

4.2.5.2 Power sum ACR-F (PS ACR-F)

The PS ACR-F of each pair of a channel is specified in Table 11. The limits shown in Table 12 are derived from the formula at key frequencies.

Table 11 – PS ACR -F for a channel

Class	Frequency MHz	Minimum PS ACR-F ^{a, b} dB
I	$1 \leq f \leq 1250$	$-20 \lg \left(10^{\frac{76 - 20 \lg(f)}{-20}} + 2 \times 10^{\frac{80,1 - 20 \lg(f)}{-20}} \right)$
^a PS ACR-F at frequencies that correspond to calculated PS FEXT values of greater than 67,0 dB are for information only. ^b The PS ACR-F limit at frequencies that correspond to calculated values of greater than 62,0 dB revert to a minimum requirement of 62,0 dB.		

Table 12 – PS ACR-F values for a channel at key frequencies

Frequency MHz	Minimum PS ACR-F dB
	Class
	I
1	62,0
16	44,9
100	29,0
250	21,0
500	15,0
600	13,4
1 000	9,0
1 250	7,0

4.2.6 Propagation delay

The propagation delay of each pair of a channel is specified in Table 13. The limits shown in Table 14 are derived from the formula at key frequencies.

Table 13 – Propagation delay for a channel

Class	Frequency MHz	Maximum propagation delay μs
I	$1 \leq f \leq 1250$	$0,3 \times \left(0,534 + 0,036/\sqrt{f}\right) + 2 \times 0,0025$

Table 14 – Propagation delay values for a channel at key frequencies

Frequency MHz	Maximum propagation delay μs
	Class
	I
0,1	–
1	0,176
16	0,168
100	0,166
250	0,166
500	0,166
600	0,166
1 000	0,166
1 250	0,166

4.2.7 Delay skew

The delay skew between all pairs of a channel is specified in Table 15.

Table 15 – Delay skew for a channel

Class	Frequency MHz	Maximum delay skew μs
I	$1 \leq f \leq 1250$	0,016 ^{a, b}
^a This is the result of the calculation $0,045 \times 0,3 + 2 \times 0,00125$. ^b Skew between any two channel pairs due to environmental conditions is specified to not vary by more than 3 ns within the channel delay skew requirement (this is met by design).		

4.2.8 Unbalance attenuation and coupling attenuation

4.2.8.1 Unbalance attenuation, near-end

This parameter is not specified by ISO/IEC/IEEE 8802-3:2017/AMD3 for 25GBASE-T.

4.2.8.2 Coupling attenuation

This parameter is not specified by ISO/IEC/IEEE 8802-3:2017/AMD3 for 25GBASE-T.

4.2.9 Alien crosstalk

4.2.9.1 Power sum alien NEXT (PS ANEXT)

The PS ANEXT of each pair of a channel is specified by the formula in Table 16. The limits shown in Table 17 are derived from the formula at key frequencies.

The PS ANEXT requirement is specified for both ends of the channel.

Table 16 – PS ANEXT for a channel

Class	Frequency MHz	Minimum PS ANEXT dB
I ^a	$1 \leq f < 100$	$105 - 10\lg(f)$
	$100 \leq f \leq 1250$	$115 - 15\lg(f)$
^a PS ANEXT at frequencies that correspond to calculated values of greater than 75,0 dB revert to a minimum requirement of 75,0 dB.		

**Table 17 – PS ANEXT values for a channel
at key frequencies**

Frequency MHz	Minimum PS ANEXT dB
	Class
	I
1	75,0
100	75,0
250	75,0
500	74,5
1 000	70,0
1 250	68,5

4.2.9.2 Power sum alien ACR-F (PS AACR-F)

4.2.9.2.1 General

The PS AACR-F of each pair of a channel is specified to meet the requirements in Table 18. The limits shown in Table 19 are derived from the formula at key frequencies.

The PS AACR-F is specified for both ends of the channel.

The PS AACR-F is computed based on AFEXT, and insertion losses of disturbing and disturbed channels (see ISO/IEC 11801-1:2017, 6.3.3.13.4).

4.2.9.2.2 PS AFEXT

See ISO/IEC 11801-1:2017, 6.3.3.13.4 for an explanation of PS AFEXT calculations.

4.2.9.2.3 PS AACR-F

Table 18 – PS AACR-F for a channel

Class	Frequency MHz	Minimum PS AACR-F ^a dB
I	$1 \leq f \leq 1250$	$101 - 20\lg(f)$
^a PS AACR-F at frequencies that correspond to calculated values of greater than 75,0 dB revert to a minimum requirement of 75,0 dB.		

**Table 19 – PS AACR-F values for a channel
at key frequencies**

Frequency MHz	Minimum PS AACR-F dB
	Class
	I
1 ^a	75,0
100	61,0
250	53,0
500	47,0
1 000	41,0
1 250	39,1
^a PS AACR-F values at 1 MHz is affected by the computed insertion loss.	

4.3 Associated risk of 25GBASE-T operation over installed cabling

Table 20 shows the risk associated with 25GBASE-T operation over installed cabling channels.

Table 20 – Risk of 25GBASE-T operation over installed cabling channels

Channel type	Channel length ^a		
Component category	< 10 m	10 m to 20 m	20 m to 30 m
7 _A	Low	Low	Low
7	Medium	High	High
6 _A	Medium	High	High
^a Risk level is based on meeting performance requirements of 4.1.			

4.4 Characterization of balanced channels using Category 7_A components

4.4.1 General

For channels made out of Category 7_A components, the support of 25GBASE-T requires compliance to channel requirements exceeding the original class specifications. Before qualification is started, the manufacturer should be consulted to determine whether the installed cable is rated up to 1250 MHz.

Compared to Class F_A channels, 25GBASE-T has an upper frequency range 1250 MHz and has more stringent requirements for insertion loss, return loss, alien crosstalk, propagation delay, delay skew and coupling attenuation as defined below.

Other parameters like NEXT, PS NEXT, ACR-N, PS ACR-N, ACR-F, PS ACR-F need to be validated to a higher upper frequency range of 1 000 MHz to 1 250 MHz.

4.4.2 Selection of channels for qualification

Channels made out of Category 7_A components may support 25GBASE-T up to 30 m. Before testing, test reports should be consulted to find channels which do have a length up to 30 m and sufficient RL margin. Those channels should be investigated further. Longer channels might be assessed too, but failure is likely.

Tests required for channels up to and including 30 m:

- For internal parameters: Retest all parameters given in 4.4.3 to 4.4.7, 4.4.9 and 4.4.10 from 1 MHz to 1 250 MHz.
- For coupling attenuation: Contact the manufacturer for a test report demonstrating the compliance of a channel made out of identical components with requirements of 4.4.11.
- For alien crosstalk: If a coupling attenuation test report is available and shows compliance to 4.4.12, alien crosstalk verification is not required. Otherwise execute alien crosstalk field testing according to IEC 61935-1.

4.4.3 Return loss

The return loss for each pair of a two-connector channel is specified to meet the limits computed using the formulae of Table 21. The limits shown in Table 22 are derived from the formulae at key frequencies.

Table 21 – Formulae for return loss limits for a channel

Frequency MHz	Minimum return loss dB
$1 \leq f < 10$	19,0
$10 \leq f < 40$	$24 - 5 \log(f)$
$40 \leq f < 130$	16
$130 \leq f < 1\,000$	$35 - 9 \log(f)$
$1\,000 \leq f \leq 1\,250$	8

**Table 22 – Return loss limits for a channel
at key frequencies**

Frequency MHz	Minimum return loss dB
1,0	19,0
16,0	18,0
100,0	16,0
250,0	13,4
500,0	10,7
600,0	10,0
1 000,0	8,0
1 250,0	8,0

4.4.4 Insertion loss

The insertion loss for each pair of a two-connector channel is specified to not exceed the limits computed using the formula of Table 23. The limits shown in Table 24 are derived from the formula at key frequencies.

Table 23 – Formula for insertion loss limits for a channel

Frequency MHz	Maximum insertion loss ^a dB
$1 \leq f \leq 1250$	$0,32 \left(1,8\sqrt{f} + 0,005f + 0,25/\sqrt{f} \right) + 2 \times 0,02\sqrt{f}$
^a Values below 4 dB revert to 4 dB.	

Table 24 – Insertion loss limits for a channel at key frequencies

Frequency MHz	Maximum insertion loss dB
1,0	4,0
16,0	4,0
100,0	6,3
250,0	10,1
500,0	14,6
600,0	16,1
1 000,0	21,1
1 250,0	23,8

4.4.5 Near-end crosstalk loss (NEXT)

4.4.5.1 Pair-to-pair NEXT

The pair-to-pair NEXT for each pair combination of a channel is specified to meet the limits computed using the formulae of Table 25. The limits shown in Table 26 are derived from the formulae at key frequencies. The length dependency of cables and channels is neglected because it affects only low frequencies.

Table 25 – Formulae for pair-to-pair NEXT limits for a channel

Frequency MHz	Minimum pair-to-pair NEXT ^{a, b} dB
$1 \leq f \leq 1000$	$-20 \lg \left(\frac{105,4 - 15 \lg(f)}{10^{-20}} + \frac{116,3 - 20 \lg(f)}{2 \times 10^{-20}} \right)$
$1000 \leq f \leq 1250$	$-20 \lg \left(\frac{105,4 - 15 \lg(f)}{10^{-20}} + \frac{56,3 - 90 \lg(f/1000)}{2 \times 10^{-20}} \right)$

^a NEXT at frequencies that correspond to calculated values of greater than 65,0 dB revert to a minimum requirement of 65,0 dB.

^b Whenever the channel insertion loss at 900 MHz is less than 17 dB, subtract the term $2,8((f - 900)/100)$ from the formula stated above for the range of 900 MHz to 1 250 MHz, but not less than 30 dB (NEXT values smaller than 30 dB revert to a minimum requirement of 30 dB).

Table 26 – Pair-to-pair NEXT limits for a channel at key frequencies

Frequency MHz	Minimum pair-to-pair NEXT dB
1,0	65,0
16,0	65,0
100,0	65,0
250,0	59,1
500,0	53,6
600,0	52,1
1 000,0	47,9
1 250,0	40,5

4.4.5.2 Power sum NEXT (PS NEXT)

The PS NEXT for each pair combination of a channel is specified to meet the limits computed, to one decimal place, using the formulae of Table 27. The limits shown in Table 28 are derived from the formulae at key frequencies. The length dependency of cables and channels is neglected because it affects only low frequencies.

Table 27 – Formulae for PS NEXT limits for a channel

Frequency MHz	Minimum PS NEXT ^{a, b} dB
$1 \leq f \leq 1\,000$	$-20 \lg \left(10^{\frac{102,4-15 \lg(f)}{-20}} + 2 \times 10^{\frac{113,3-20 \lg(f)}{-20}} \right)$
$1\,000 \leq f \leq 1\,250$	$-20 \lg \left(10^{\frac{102,4-15 \lg(f)}{-20}} + 2 \times 10^{\frac{53,3-90 \lg(f/1000)}{-20}} \right)$
^a PS NEXT at frequencies that correspond to calculated values of greater than 62,0 dB revert to a minimum requirement of 62,0 dB. ^b Whenever the channel insertion loss at 900 MHz is less than 17 dB, subtract the term $2,8((f - 900)/100)$ from the formula stated above for the range of 900 MHz to 1 250 MHz, but not less than 27 dB (PS NEXT values smaller than 27 dB revert to a minimum requirement of 27 dB).	

Table 28 –PS NEXT limits for a channel at key frequencies

Frequency MHz	Minimum PS NEXT dB
1,0	62,0
16,0	62,0
100,0	62,0
250,0	56,1
500,0	50,6
600,0	49,1
1 000,0	44,9
1 250,0	37,5

4.4.6 Attenuation to crosstalk loss ratio near-end (ACR-N)

4.4.6.1 General

ACR-N performance is dependent upon NEXT and IL, and is not an independent specification included for 25GBASE-T.

4.4.6.2 Pair-to-pair ACR-N

The ACR-N for each pair combination of a channel is specified to meet the limits computed according to Equation (1), to one decimal place. The limits shown in Table 29 are derived from Equation (1) at key frequencies. The requirement is automatically satisfied when both insertion loss and NEXT requirements are met.

The ACR-N requirement is specified to be met at both ends of the cabling.

ACR-N_{ik} of pairs *i* and *k* is computed as follows:

$$\text{ACR-N}_{ik} = \text{NEXT}_{ik} - \text{IL}_k \text{ dB} \quad (1)$$

where

i is the number of the disturbing pair;

k is the number of the disturbed pair;

NEXT_{ik} is the near-end crosstalk loss coupled from pair *i* into pair *k*;

IL_k is the insertion loss of disturbed pair *k*. When required, it should be measured according to IEC 61935-1.

Table 29 – ACR-N limits for a channel at key frequencies

Frequency MHz	Minimum ACR-N dB
1,0	61,0
16,0	61,0
100,0	58,7
250,0	49,0
500,0	39,0
600,0	36,0
1 000,0	26,8
1 250,0	16,7

4.4.6.3 Power sum ACR-N (PS ACR-N)

PS ACR-N performance is dependent upon PS NEXT and IL, and is not an independent specification included for 25GBASE-T.

The PS ACR for each pair of a channel is specified to meet the limits computed according to Equation (2), to one decimal place. The limits shown in Table 30 are derived with Equation (2) at key frequencies. The requirement is automatically satisfied when both insertion loss and PS NEXT requirements are met.

PS ACR-N_k of pair *k* is computed as follows:

$$\text{PS ACR-N}_k = \text{PS NEXT}_k - \text{IL}_k \text{ dB} \quad (2)$$

where

k is the number of the disturbed pair;

PS NEXT_k is the power sum near-end crosstalk loss of pair *k*;

IL_k is the insertion loss of pair *k*. When required, it should be measured according to IEC 61935-1.

The PS ACR-N requirement is specified for both ends of the cabling.

Table 30 – PS ACR-N limits for a channel at key frequencies

Frequency MHz	Minimum PS ACR-N dB
1,0	58,0
16,0	58,0
100,0	55,7
250,0	46,0
500,0	36,0
600,0	33,0
1 000,0	23,8
1 250,0	13,7

4.4.7 Attenuation to crosstalk ratio far-end (ACR-F)

4.4.7.1 Pair-to-pair ACR-F

The ACR-F for each pair combination of a channel is specified to meet the limits computed using the formulae of Table 31. The limits shown in Table 32 are derived from the formulae at key frequencies.

Table 31 – Formulae for ACR-F limits for a channel

Frequency MHz	Minimum ACR-F ^{a, b} dB
$1 \leq f \leq 1000$	$-20 \lg \left(10^{\frac{95,3-20 \lg(f)}{-20}} + 4 \times 10^{\frac{103,9-20 \lg(f)}{-20}} \right)$ 65 maximum
$1000 \leq f \leq 1250$	$-20 \lg \left(10^{\frac{95,3-20 \lg(f)}{-20}} + 4 \times 10^{\frac{43,9-90 \lg(f/1000)}{-20}} \right)$
^a ACR-F at frequencies that correspond to measured FEXT values of greater than 70,0 dB are for information only. ^b The ACR-F limit at frequencies that correspond to calculated values of greater than 65,0 dB revert to a minimum requirement of 65,0 dB.	

**Table 32 – ACR-F limits for a channel
at key frequencies**

Frequency MHz	Minimum ACR-F dB
1,0	65,0
16,0	63,3
100,0	47,7
250,0	39,4
500,0	33,4
600,0	31,8
1 000,0	27,4
1 250,0	20,8

4.4.7.2 Power sum ACR-F (PS ACR-F)

The PS ACR-F for each pair combination of a channel is specified to meet the limits computed using the formulae of Table 33. The limits shown in Table 34 are derived from the formulae at key frequencies.

Table 33 – Formulae for PS ACR-F limits for a channel

Frequency MHz	Minimum PS ACR-F ^{a, b} dB
$1 \leq f \leq 1000$	$-20 \lg \left(10^{\frac{92,3 - 20 \lg(f)}{-20}} + 4 \times 10^{\frac{100,9 - 20 \lg(f)}{-20}} \right)$
$1000 \leq f \leq 1250$	$-20 \lg \left(10^{\frac{92,3 - 20 \lg(f)}{-20}} + 4 \times 10^{\frac{40,9 - 90 \lg(f/1000)}{-20}} \right)$
^a PS ACR-F at frequencies that correspond to measured FEXT values of greater than 70,0 dB are for information only. ^b The PS ACR-F limit at frequencies that correspond to calculated values of greater than 62,0 dB revert to a minimum requirement of 62,0 dB.	

**Table 34 – PS ACR-F limits for a channel
at key frequencies**

Frequency MHz	Minimum PS ACR-F dB
1,0	62,0
16,0	60,3
100,0	44,4
250,0	36,4
500,0	30,4
600,0	28,8
1 000,0	24,4
1 250,0	17,8

4.4.8 Alien (exogenous) crosstalk**4.4.8.1 PS ANEXT**

The PS ANEXT for each pair combination of a channel is specified to meet the limits computed using the formulae of Table 35. The limits shown in Table 36 are derived from the formulae at key frequencies.

Table 35 – Formulae for PS ANEXT limits for a channel

Frequency MHz	Minimum PS ANEXT ^a dB
$1 \leq f < 100$	$105 - 10\lg(f)$
$100 \leq f < 1250$	$115 - 15\lg(f)$

^a PS ANEXT at frequencies that correspond to calculated values of greater than 75,0 dB revert to a minimum requirement of 75,0 dB.

Table 36 – PS ANEXT limits for a channel at key frequencies

Frequency MHz	Minimum PS ANEXT dB
1,0	75
16,0	75
100,0	75
250,0	75
500,0	74,5
600,0	73,3
1 000,0	70,0
1 250,0	68,5

4.4.8.2 PS AACR-F

The PS AACR-F for each pair combination of a channel is specified to meet the limits computed using the formula of Table 37. The limits shown in Table 38 are derived from the formula at key frequencies.

Table 37 – Formula for PS AACR-F limits for a channel

Frequency MHz	Minimum PS AACR-F ^{a, b} dB
$1 \leq f < 1250$	$101 - 20\lg(f)$

^a PS AACR-F at frequencies that correspond to calculated PS AFEXT values of greater than 67,0 dB or $102 - 15\lg(f)$ dB are for information only.

^b PS AACR-F at frequencies that correspond to calculated values of greater than 75,0 dB revert to a minimum requirement of 75,0 dB.

Table 38 – PS AACR-F limits for a channel at key frequencies

Frequency MHz	Minimum PS AACR-F dB
1,0	75,0
16,0	75,0
100,0	61,0
250,0	53,0
500,0	47,0
600,0	45,4
1 000,0	41,0
1 250,0	39,1

4.4.9 Propagation delay

The propagation delay for each pair of a channel is specified to not exceed the limits computed, to three decimal places, using the formula of Table 39. The limits shown in Table 40 are derived from the formula at key frequencies.

Table 39 – Formula for propagation delay limits for a channel

Frequency MHz	Maximum propagation delay μs
$1 \leq f < 1\,250$	$0,3 \times (0,534 + 0,036/\sqrt{f}) + 2 \times 0,002\,5$

Table 40 – Propagation delay limits for a channel at key frequencies

Frequency MHz	Maximum propagation delay μs
1,0	0,176
16,0	0,168
100,0	0,166
250,0	0,166
500,0	0,166
600,0	0,166
1 000,0	0,166
1 250,0	0,165

4.4.10 Delay skew

The skew between all pairs of a channel is specified to not exceed 0,010 μs .

4.4.11 Coupling attenuation

The coupling attenuation for each pair of a shielded channel is specified to meet the limits computed using the formula of Table 41. The limits shown in Table 42 are derived from the formula at key frequencies.

Table 41 – Formula for coupling attenuation limits for a channel

Frequency MHz	Minimum coupling attenuation dB
$30 \leq f \leq 100$	50
$100 \leq f \leq 1\,250$	$90 - 20\lg(f)$

Table 42 – Coupling attenuation limits for a channel at key frequencies

Frequency MHz	Minimum coupling attenuation dB
1,0	N/A
16,0	N/A
100,0	50,0
250,0	42,0
500,0	36,0
600,0	34,4
1 000,0	30,0
1 250,0	28,1

4.4.12 Alien crosstalk and coupling attenuation

When coupling attenuation for a channel meets or exceeds the value of Table 43, the PS ANEXT limits are met.

When coupling attenuation for a channel meets or exceeds the values of Table 43, the PS AACR-F limits are met.

Table 43 – Alien crosstalk and coupling attenuation

Frequency MHz	Minimum coupling attenuation to meet PS ANEXT limits dB	Minimum coupling attenuation to meet PS AACR-F limits dB
$30 \leq f \leq 100$	65	65
$100 \leq f \leq 1\,250$	$105 - 20\lg(f)$	$105 - 20\lg(f)$

4.5 Characterization of balanced channels using Category 7 components

4.5.1 General

For channels made out of Category 7 components, the support of 25GBASE-T requires compliance to channel requirements exceeding the Class F specifications. Compared to Class F channels, 25GBASE-T has more stringent requirements for insertion loss, return loss, alien crosstalk, propagation delay, delay skew and coupling attenuation as defined below.

Other parameters like NEXT, PS NEXT, ACR-F, PS ACR-F need to be validated to a higher upper frequency range of 600 MHz to 1 250 MHz.

When component behaviour in the additional frequency range, namely insertion loss, return loss and alien crosstalk, is not adequate, some installed cabling channels at shorter length might still be able to meet the requirements contained in ISO/IEC/IEEE 8802-3:2017/AMD3 for 25GBASE-T application.

4.5.2 Selection of channels for qualification

Channels made out of Category 7 components may support 25GBASE-T up to 12 m. Before testing, existing channel test reports should be consulted to find channels, which do have a length up to 12 m and sufficient RL margin up to 600 MHz. Those channels should be investigated further. Longer channels might be assessed too, but failure is likely.

Tests required for channels up to and including 12 m:

- For internal parameters: Retest all parameters from 4.5.3 to 4.5.7 and 4.5.9 and 4.5.10 from 1 MHz to 1250 MHz.
- For coupling attenuation: Contact the manufacturer for a test report demonstrating the compliance of a channel made out of identical components with requirements of 4.5.11.
- For alien crosstalk: If a coupling attenuation test report is available and shows compliance to 4.5.12, alien crosstalk verification is not required. Otherwise execute alien crosstalk field testing according to IEC 61935-1.

4.5.3 Return loss

The return loss for each pair of a two-connector channel is specified to meet the limits computed using the formulae of Table 44. The limits shown in Table 45 are derived from the formulae at key frequencies.

Table 44 – Formulae for return loss limits for a channel

Frequency MHz	Minimum return loss dB
$1 \leq f < 10$	19,0
$10 \leq f < 40$	$24 - 5 \log(f)$
$40 \leq f < 130$	16
$130 \leq f < 1\,000$	$35 - 9 \log(f)$
$1\,000 \leq f \leq 1\,250$	8

**Table 45 – Return loss limits for a channel
at key frequencies**

Frequency MHz	Minimum return loss dB
1,0	19,0
16,0	18,0
100,0	16,0
250,0	13,4
500,0	10,7
600,0	10,0
1 000,0	8,0
1 250,0	8,0

4.5.4 Insertion loss

The insertion loss for each pair of a two-connector channel is specified to not exceed the limits computed using the formula of Table 46. The limits shown in Table 47 are derived from the formula at key frequencies.

Table 46 – Formula for insertion loss limits for a channel

Frequency MHz	Maximum insertion loss dB
$1 \leq f \leq 1\,250$	$0,32 \left(1,8\sqrt{f} + 0,005f + 0,25/\sqrt{f} \right) + 2 \times 0,02\sqrt{f}$
NOTE Values below 4 dB revert to 4 dB.	

Table 47 – Insertion loss limits for a channel at key frequencies

Frequency MHz	Maximum insertion loss dB
1,0	4,0
16,0	4,0
100,0	6,3
250,0	10,1
500,0	14,6
600,0	16,1
1 000,0	21,1
1 250,0	23,8

4.5.5 Near-end crosstalk loss (NEXT)

4.5.5.1 Pair-to-pair NEXT

The pair-to-pair NEXT for each pair combination of a channel is specified to meet the limits computed using the formulae of Table 48. The limits shown in Table 49 are derived from the formulae at key frequencies. The length dependency of cables and channels is neglected because it affects only low frequencies.

Table 48 – Formulae for pair-to-pair NEXT limits for a channel

Frequency MHz	Minimum pair-to-pair NEXT ^a dB
$1 \leq f \leq 600$	$-20 \lg \left(10^{\frac{102,4 - 15 \lg(f)}{-20}} + 2 \times 10^{\frac{102,4 - 20 \lg(f)}{-20}} \right)$
$600 \leq f \leq 1\,250$	$-20 \lg \left(10^{\frac{75,3 - 15 \lg(f)}{-20}} + 2 \times 10^{\frac{40 - 38 \lg(f/500)}{-20}} \right)$
^a NEXT at frequencies that correspond to calculated values of greater than 65,0 dB revert to a minimum requirement of 65,0 dB.	

Table 49 – Pair-to-pair NEXT limits for a channel at key frequencies

Frequency MHz	Minimum pair-to-pair NEXT dB
1,0	65,0
16,0	65,0
100,0	65,0
250,0	56,9
500,0	52,4
600,0	51,2
1 000,0	19,6
1 250,0	16,5

4.5.5.2 Power sum NEXT (PS NEXT)

The PS NEXT for each pair combination of a channel is specified to meet the limits computed, to one decimal place, using the formulae of Table 50. The limits shown in Table 51 are derived from the formulae at key frequencies. The length dependency of cables and channels is neglected because it affects only low frequencies.

Table 50 – Formulae for PS NEXT limits for a channel

Frequency MHz	Minimum PS NEXT ^a dB
$1 \leq f \leq 600$	$-20 \lg \left(10^{\frac{99,4-15 \lg(f)}{-20}} + 2 \times 10^{\frac{99,4-15 \lg(f)}{-20}} \right)$
$600 \leq f \leq 1\,250$	$-20 \lg \left(10^{\frac{72,3-15 \lg(f)}{-20}} + 2 \times 10^{\frac{37-38 \lg(f/500)}{-20}} \right)$
^a PS NEXT at frequencies that correspond to calculated values of greater than 62,0 dB revert to a minimum requirement of 62,0 dB.	

Table 51 – PS NEXT limits for a channel at key frequencies

Frequency MHz	Minimum PS NEXT dB
1,0	62,0
16,0	62,0
100,0	59,9
250,0	53,9
500,0	49,4
600,0	48,2
1 000,0	16,6
1 250,0	13,5

4.5.6 Attenuation to crosstalk loss ratio near-end (ACR-N)

4.5.6.1 Pair-to-pair ACR-N

The ACR-N for each pair combination of a channel is specified to meet the limits computed according to Equation (3), to one decimal place. The limits shown in Table 52 are derived from Equation (3) at key frequencies. The requirement is automatically satisfied when both insertion loss and NEXT requirements are met.

The ACR-N requirement is specified for both ends of the cabling.

ACR-N_{ik} of pairs *i* and *k* is computed as follows:

$$\text{ACR-N}_{ik} = \text{NEXT}_{ik} - \text{IL}_k \text{ dB} \quad (3)$$

where

i is the number of the disturbing pair;

k is the number of the disturbed pair;

NEXT_{ik} is the near-end crosstalk loss coupled from pair *i* into pair *k*;

IL_k is the insertion loss of disturbed pair *k*. When required, it should be measured according to IEC 61935-1.

Table 52 – ACR-N limits for a channel at key frequencies

Frequency MHz	Minimum ACR-N dB
1,0	61,0
16,0	61,0
100,0	56,5
250,0	46,7
500,0	37,8
600,0	35,1
1 000,0	–1,5
1 250,0	–7,3

4.5.6.2 Power sum ACR-N (PS ACR-N)

The PS ACR-N for each pair of a channel is specified to meet the limits computed according to Equation (4), to one decimal place. The limits shown in Table 53 are derived with Equation (4) at key frequencies. The requirement is automatically satisfied when both insertion loss and PS NEXT requirements are met.

PS ACR-N_k of pair *k* is computed as follows:

$$\text{PS ACR-N}_k = \text{PS NEXT}_k - \text{IL}_k \text{ dB} \quad (4)$$

where

k is the number of the disturbed pair;

PS NEXT_k is the power sum near-end crosstalk loss of pair *k*;

IL_k is the insertion loss of pair *k*. When required, it should be measured according to IEC 61935-1.

The PS ACR-N requirement is specified for both ends of the cabling.

Table 53- PS ACR-N limits for a channel at key frequencies

Frequency MHz	Minimum PS ACR-N dB
1,0	58,0
16,0	58,0
100,0	53,4
250,0	43,7
500,0	34,8
600,0	32,1
1 000,0	-4,5
1 250,0	-10,3

4.5.7 Attenuation to crosstalk ratio far-end (ACR-F)

4.5.7.1 Pair-to-pair ACR-F

The ACR-F for each pair combination of a channel is specified to meet the limits computed using the formulae of Table 54. The limits shown in Table 55 are derived from the formulae at key frequencies.

Table 54 – Formulae for ACR-F limits for a channel

Frequency MHz	Minimum ACR-F ^{a, b} dB
$1 \leq f \leq 600$	$-20 \lg \left(\frac{94 - 20 \lg(f)}{10^{-20}} + 4 \times 10^{\frac{90 - 15 \lg(f)}{-20}} \right)$ 65 maximum
$600 \leq f \leq 1250$	$-20 \lg \left(\frac{79 - 20 \lg(f)}{10^{-20}} + 2 \times 10^{\frac{83,1 - 20 \lg(f)}{-20}} \right)$
^a ACR-F at frequencies that correspond to measured FEXT values of greater than 70,0 dB are for information only. ^b The ACR-F limit at frequencies that correspond to calculated values of greater than 65,0 dB revert to a minimum requirement of 65,0 dB.	