

Third edition
2006-05-01

AMENDMENT 1
2017-10

Rolling bearings — Static load ratings
AMENDMENT 1

Roulements — Charges statiques de base
AMENDEMENT 1

STANDARDSISO.COM : Click to view the full PDF of ISO 76:2006/Amd 1:2017



Reference number
ISO 76:2006/Amd.1:2017(E)

© ISO 2017

STANDARDSISO.COM : Click to view the full PDF of ISO 76:2006/Amd 1:2017



COPYRIGHT PROTECTED DOCUMENT

© ISO 2017, Published in Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular the different approval criteria needed for the different types of ISO documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation on the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see the following URL: www.iso.org/iso/foreword.html.

This document was prepared by Technical Committee ISO/TC 4, *Rolling bearings*, Subcommittee SC 8, *Load ratings and life*.

STANDARDSISO.COM : Click to view the full PDF of ISO 76:2006/Amd 1:2017

Rolling bearings — Static load ratings

AMENDMENT 1

Clause 4

Insert the following symbols:

$E(\kappa)$	complete elliptic integral of the second kind
$K(\kappa)$	complete elliptic integral of the first kind
$\Sigma\rho_e$	curvature sum at the outer ring contact
$\Sigma\rho_i$	curvature sum at the inner ring contact
$F(\rho)$	curvature difference of a point contact
γ	auxiliary parameter, $\gamma = D_w \cos \alpha / D_{pw}$
κ	ratio of semi major to semi minor axis of the contact ellipse

5.1.1

Replace the subclause with the following:

5.1.1 Basic static radial load rating for single bearings

The basic static radial load rating for radial ball bearings is given by Formula (1):

$$C_{0r} = f_0 i Z D_w^2 \cos \alpha \quad (1)$$

where, except for radial self-aligning ball bearings

$$f_0 = \min \{ f_{0,i}, f_{0,e} \}$$

in which

$$f_{0,i} = 2,399\ 05 \cdot \kappa_i \cdot \left[\frac{E(\kappa_i)}{2 + \frac{\gamma}{1 - \gamma} - \frac{D_w}{2 \cdot r_i}} \right]^2 \quad (2)$$

$$f_{0,e} = 2,399\ 05 \cdot \kappa_e \cdot \left[\frac{E(\kappa_e)}{2 - \frac{\gamma}{1 + \gamma} - \frac{D_w}{2 \cdot r_e}} \right]^2 \quad (3)$$

where

i is the inner ring;

e is the outer ring.

The calculation of the Hertzian parameters, κ and $E(\kappa)$, is described in Annex B.

For a radial self-aligning ball bearing, the factor, f_0 , is given by Formula (4):

$$f_0 = 3,151\ 84 \cdot \left[\frac{\pi}{4} \cdot (1 + \gamma) \right]^2 \quad (4)$$

The guide values given in Table 1 apply to bearings with a cross-sectional raceway groove radius not larger than $0,52D_w$ in radial and angular contact ball bearing inner rings, and $0,53D_w$ in radial and angular contact ball bearing outer rings and self-aligning ball bearing inner rings. The load-carrying ability of a bearing is not necessarily increased by the use of a smaller groove radius, but is reduced by the use of a groove radius larger than those indicated above. In the latter case, the value f_0 shall be calculated by the formulae given here.

Annex C gives a graphical representation of the value f_0 in dependency of the bearing internal geometry. The results of the formulae given here are preferred over Table 1 and Annex C.

5.2.1

Renumber Formula (2) and Formula (3) respectively into Formula (5) and Formula (6).

6.1

Replace the subclause with the following:

6.1 Basic static axial load rating

The basic static axial load rating for single-direction and double-direction thrust ball bearings is given by Formula (7):

$$C_{0a} = f_0 Z D_w^2 \sin \alpha \quad (7)$$

where

$$f_0 = \min \{ f_{0,i}, f_{0,e} \}$$

in which

$$f_{0,i} = 11,995\ 2 \cdot \kappa_i \cdot \left[\frac{E(\kappa_i)}{2 + \frac{\gamma}{1 - \gamma} - \frac{D_w}{2 \cdot r_i}} \right]^2 \quad (8)$$

$$f_{0,e} = 11,995\ 2 \cdot \kappa_e \cdot \left[\frac{E(\kappa_e)}{2 - \frac{\gamma}{1 + \gamma} - \frac{D_w}{2 \cdot r_e}} \right]^2 \quad (9)$$

where

- i is the inner ring or shaft washer;
- e is the outer ring or housing washer.

The guide values given in Table 1 apply to bearings with cross-sectional raceway groove radii not larger than $0,54D_w$. The load-carrying ability of a bearing is not necessarily increased by the use of a smaller groove radius smaller than $0,54D_w$, but is reduced by the use of a larger groove radius. In the latter case, the value f_0 shall be calculated by the formulae given here.

Annex C gives a graphical representation of the value f_0 . The results of the formulae given here are preferred over Table 1 and Annex C.

6.2

Renumber Formula (5) and Formula (6) respectively into Formula (10) and Formula (11).

7.1.1

Renumber Formula (7) into Formula (12).

In the NOTE, replace "Equation (7)" by "Formula (12)".

7.2.1

Renumber Formula (8), Formula (9) and Formula (10) respectively into Formula (13), Formula (14) and Formula (15).

8.1.1

Renumber Formula (11) into Formula (16).

In the NOTE, replace "Equation (11)" by "Formula (16)".

8.2.1

Renumber Formula (12) and Formula (13) respectively into Formula (17) and Formula (18).

8.2.2

Replace "Equation (12)" by "Formula (17)".

9.1

Renumber Formula (14) and Formula (15) respectively into Formula (19) and Formula (20).

Replace "Equation (14)" and "Equation (15)" respectively by "Formula (19)" and "Formula (20)".

In all the document

Replace the term "Equation" by "Formula".

A.5.1

Replace "according to Equation (1)" with "according to Formula (1)".

A.5.2

Add the following text at the end of the subclause:

For a single-row angular contact ball bearing having the same internal dimensions as above but radial bearing conformities, Formula (A.1) gives

$$C_{0ar} = 18\,731/0,26 = 72\,042$$

$$C_{0ar} = 72\,000\text{ N}$$

A.5.3

Add the following text at the end of the subclause:

For a single-row angular contact ball bearing having the same internal dimensions as above and radial bearing conformities, Formula (A.2) gives

$$C_{0aa} = 1,43 \times 76\,049 = 108\,750$$

$$C_{0aa} = 109\,000\text{ N}$$

STANDARDSISO.COM : Click to view the full PDF of ISO 76:2006/Amd 1:2017

Annex B and Annex C

Add the following annexes after Annex A:

Annex B
(informative)

Calculation of the Hertzian parameters for point contact

The ratio of semi-major to semi-minor axis of the contact ellipse, κ , is independent of the modulus of elasticity and Poisson's ratio of the contacting bodies. It can be derived iteratively from Formula (B.1):

$$1 - \frac{2}{\kappa^2 - 1} \cdot \left[\frac{K(\kappa)}{E(\kappa)} - 1 \right] - F(\rho) = 0 \quad (\text{B.1})$$

The complete elliptic integral of the first kind, $K(\kappa)$, is as shown in Formula (B.2):

$$K(\kappa) = \int_0^{\frac{\pi}{2}} \left[1 - \left(1 - \frac{1}{\kappa^2} \right) \cdot (\sin \phi)^2 \right]^{-\frac{1}{2}} d\phi \quad (\text{B.2})$$

The complete elliptic integral of the second kind, $E(\kappa)$, is as shown in Formula (B.3):

$$E(\kappa) = \int_0^{\frac{\pi}{2}} \left[1 - \left(1 - \frac{1}{\kappa^2} \right) \cdot (\sin \phi)^2 \right]^{\frac{1}{2}} d\phi \quad (\text{B.3})$$

The curvature sum of the inner ring (shaft washer) raceway contacts is as shown in Formula (B.4):

$$\sum \rho_i = \frac{2}{D_w} \cdot \left[2 + \frac{\gamma}{1 - \gamma} - \frac{D_w}{2 \cdot r_i} \right] \quad (\text{B.4})$$

The curvature sum of the outer ring (housing washer) raceway contacts is as shown in Formula (B.5):

$$\sum \rho_e = \frac{2}{D_w} \cdot \left[2 - \frac{\gamma}{1 + \gamma} - \frac{D_w}{2 \cdot r_e} \right] \quad (\text{B.5})$$

The relative curvature difference of the inner ring (shaft washer) raceway contacts is as shown in Formula (B.6):

$$F_i(\rho) = \frac{\frac{\gamma}{1 - \gamma} + \frac{D_w}{2 \cdot r_i}}{2 + \frac{\gamma}{1 - \gamma} - \frac{D_w}{2 \cdot r_i}} \quad (\text{B.6})$$

and the relative curvature difference of the outer ring (housing washer) raceway contacts is as shown in Formula (B.7):

$$F_e(\rho) = \frac{\frac{-\gamma}{1 + \gamma} + \frac{D_w}{2 \cdot r_e}}{2 - \frac{\gamma}{1 + \gamma} - \frac{D_w}{2 \cdot r_e}} \quad (\text{B.7})$$