

INTERNATIONAL STANDARD

ISO/IEC
14776-326

First edition
2002-08

**Information technology –
Small computer system interface (SCSI) –
Part 326:
Reduced block commands (RBC)**



Reference number
ISO/IEC 14776-326:2002(E)

INTERNATIONAL STANDARD

ISO/IEC
14776-326

First edition
2002-08

**Information technology –
Small computer system interface (SCSI) –
Part 326:
Reduced block commands (RBC)**

© ISO/IEC 2002

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

ISO/IEC Copyright Office • Case postale 56 • CH-1211 Genève 20 • Switzerland



PRICE CODE

R

For price, see current catalogue

CONTENTS

FOREWORD	5
INTRODUCTION	6
1 Scope	7
2 Normative references.....	7
3 Definitions, acronyms, keywords and conventions.....	8
3.1 Definitions	8
3.2 Acronyms	9
3.3 Keywords.....	9
3.4 Conventions	10
3.4.1 Non-numeric values	10
3.4.2 Numeric values	10
4 RBC device model	10
4.0 General	10
4.1 Removable medium device	11
4.2 Command usage.....	11
4.2.0 General.....	11
4.2.1 Using the INQUIRY command.....	11
4.2.2 Using the REQUEST SENSE command	12
4.2.3 FORMAT UNIT command progress determination	12
4.3 Using the PREVENT ALLOW MEDIUM REMOVAL command.....	12
4.3.0 General.....	12
4.3.1 START STOP UNIT command state restrictions.....	12
4.4 Logical blocks.....	13
4.5 Reservations	13
5 Reduced block commands	15
5.0 General	15
5.1 FORMAT UNIT command	15
5.2 READ(10) command	17
5.3 READ CAPACITY command	17
5.4 START STOP UNIT command	18
5.4.0 General.....	18
5.4.1 Power conditions	19
5.4.2 Control bits	20
5.5 SYNCHRONIZE CACHE command	20
5.6 WRITE(10) command.....	21
5.7 VERIFY command	22
5.8 MODE parameters	22
5.8.0 General.....	22
5.8.1 Mode parameter list	23
5.8.2 Mode parameter header.....	23
5.8.3 RBC device parameter page	23
6 SPC-2 Implementation requirements for RBC devices.....	24
6.0 General	24
6.1 INQUIRY command	25

6.1.0	General.....	25
6.1.1	INQUIRY vital product data pages	26
6.2	MODE SELECT(6) command.....	26
6.2.0	General.....	26
6.2.1	Save pages (SP) bit support	27
6.3	MODE SENSE(6) command.....	27
6.4	PREVENT ALLOW MEDIUM REMOVAL	27
6.5	REQUEST SENSE command.....	28
6.6	TEST UNIT READY command	28
6.7	WRITE BUFFER command	29
6.7.0	General.....	29
6.7.1	Download Microcode and save mode (101b).....	29
6.7.2	Download Microcode with offsets and save mode (111b)	29
7	Asynchronous event notification for RBC devices	30
7.0	General	30
7.1	Unit attention	30
7.1.0	General.....	30
7.1.1	Power condition change notification	30
7.2	Deferred errors	31
7.3	Information exception condition notification	31
7.4	Event status notification.....	31
7.4.0	General.....	31
7.4.1	Event status sense information	31
7.4.2	POWER MANAGEMENT CLASS INFORMATION field	32
7.4.3	MEDIA CLASS EVENT INFORMATION field	33
7.4.4	DEVICE BUSY CLASS EVENT INFORMATION values	34
7.4.5	Event status retention	35
7.4.6	Removable medium device initial response	35
Annex A (normative)	RBC device implementation requirements for SBP-2	36
A.1	SBP-2 definitions	36
A.2	Acronyms	37
A.3	SBP-2 storage model (informative)	38
A.3.0	General.....	38
A.3.1	Model configuration	38
A.3.2	Reconnect/Power reset support (normative).....	39
A.4	Configuration ROM support (normative).....	40
A.4.0	General.....	40
A.4.1	Unit Directory – Command_Set_Spec_ID	40
A.4.2	Unit Directory – Command_Set.....	40
A.4.3	Unit Directory – Logical_Unit_Number	40
A.5	Security support (normative).....	41
A.6	Status block support (normative).....	41
A.7	Unsolicited status support (normative)	41
A.7.0	General.....	41
A.7.1	Unit attention condition	42
A.7.2	Event status retention	42

Figure A.1 – Mass storage interface block diagram	38
---	----

Table 1 – RBC direct access commands that are allowed in the presence of various reservations	14
Table 2 – Reduced Block Command set	15
Table 3 – FORMAT UNIT command	16
Table 4 – READ(10) Command Descriptor Block	17
Table 5 – READ CAPACITY Command Descriptor Block	17
Table 6 – READ CAPACITY data	18
Table 7 – START STOP UNIT Command Descriptor Block	18
Table 8 – POWER CONDITIONS	19
Table 9 – START STOP control bit definitions	20
Table 10 – SYNCHRONIZE CACHE Command Descriptor Block	21
Table 11 – WRITE(10) Command Descriptor Block	21
Table 12 – VERIFY Command Descriptor Block	22
Table 13 – Mode parameter list	23
Table 14 – RBC Device Parameter's page format	23
Table 15 – Required SPC-2 commands	25
Table 16 – Standard Inquiry data format	25
Table 17 – MODE SELECT(6) Command Descriptor Block	26
Table 18 – MODE SENSE(6) Command Descriptor Block	27
Table 19 – FAILURE PREDICTION ASCQ XY definitions	28
Table 20 – WRITE BUFFER Command Descriptor Block	29
Table 21 – Asynchronous Event conditions	30
Table 22 – Power condition sense code and qualifier values	30
Table 23 – Event status ASCQ values	31
Table 24 – EVENT STATUS INFORMATION field format	32
Table 25 – POWER MANAGEMENT CLASS INFORMATION field format	32
Table 26 – POWER MANAGEMENT CLASS EVENT field	32
Table 27 – POWER MANAGEMENT CLASS STATUS field	33
Table 28 – MEDIA CLASS INFORMATION field format	33
Table 29 – MEDIA CLASS EVENT field	33
Table 30 – DEVICE BUSY CLASS INFORMATION field format	34
Table 31 – DEVICE BUSY CLASS EVENT field	34
Table 32 – DEVICE BUSY CLASS STATUS field	34

INFORMATION TECHNOLOGY – SMALL COMPUTER SYSTEM INTERFACE (SCSI) –

Part 326: Reduced Block Commands (RBC)

FOREWORD

- 1) ISO (International Organization for Standardization) and IEC (International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.
- 2) In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.
- 3) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

International Standard ISO/IEC 14776-326 was prepared by subcommittee 25: Interconnection of information technology equipment, of ISO/IEC joint technical committee 1: Information technology.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC 14776-326.pdf

INTRODUCTION

This part of ISO/IEC 14776 specifies the functional requirements for the SCSI Reduced Block Command set (RBC). RBC permits SCSI block logical units, such as flexible disks, rigid disks, optical disks, etc., to be attached to computers, and it provides the definition for their use.

The Reduced Block Command set is designed to provide very efficient initiator-to-device operation of input/output logical units by an operating system.

Annex A contains an implementation guide for RBC devices using SBP-2.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC 14776-326:2002

INFORMATION TECHNOLOGY – SMALL COMPUTER SYSTEM INTERFACE (SCSI) –

Part 326: Reduced Block Commands (RBC)

1 Scope

This part of ISO/IEC 14776 defines a Reduced Block Command set for logical block devices. The Reduced Block Commands, along with the required SPC-2 commands and their restrictions described in this standard, fully specify the complete command set for RBC logical block devices.

The purpose of this standard is to provide a command set of reduced requirements and options from SCSI Block Commands (SBC) for block devices (see ISO/IEC 14776-321). The reduced command set is intended to more closely match the functionality required for simple block logical units. The specified commands place no restrictions on device performance. The basic focus of this command set is to enable the command and control of rigid disks and removable media devices attached to Serial Bus and utilizing SCSI Serial Bus Protocol 2 (SBP-2) (ISO/IEC 14776-232).

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO/IEC 13213:1994, *Information technology – Microprocessor systems – Control and status register (CSR) architecture for microcomputer buses*

ISO/IEC 14776-232:2001, *Information technology – Small Computer System Interface (SCSI) – Part 232: Serial Bus Protocol 2 (SBP-2)*

ISO/IEC 14776-312,– *Information technology – Small Computer System Interface (SCSI) – Part 312: Primary commands 2 (SPC-2)*¹⁾

ISO/IEC 14776-321,– *Information technology – Small Computer System Interface (SCSI-3) – Part 321: Block commands (SBC)*²⁾

ISO/IEC 14776-362,– *Information technology – Small Computer System Interface (SCSI) – Part 362: Multimedia commands 2 (MMC-2)*²⁾

ISO/IEC 14776-412,– *Information technology – Small Computer System Interface (SCSI) – Part 412: Architecture model 2 (SAM-2)*¹⁾

ANSI X3.301:1997, *Information technology – SCSI-3 Primary Commands 2 (SPC)*

ANSI/IEEE 1394:1995, *High Performance Serial Bus*

IEEE 1394a:2000, *High Performance Serial Bus (Supplement to ANSI/IEEE 1394)*

¹⁾ Under consideration.

²⁾ To be published.

3 Definitions, acronyms, keywords and conventions

3.1 Definitions

For the purpose of this document the following terms and definitions apply.

3.1.1

additional sense code

field in the sense data (see definition in ISO/IEC 14776-312)

3.1.2

additional sense code qualifier

field in the sense data (see definition in ISO/IEC 14776-312)

3.1.3

byte

eight bits of data

3.1.4

command descriptor block

structure of up to 16 bytes in length used to communicate a command from an initiator to a device

3.1.5

event field

byte 0 of the sense data INFORMATION field (see Table 24 for the Event Status INFORMATION field format) when the sense code indicates EVENT STATUS NOTIFICATION (38h)

3.1.6

logical unit

part of the target that is an instance of a device model, for example, mass storage, CD-ROM or printer. In devices that implement one or more logical units, the device type of the logical units may differ

3.1.7

sense data

data describing an error or exceptional device condition that a device delivers to an initiator (see definition in ISO/IEC 14776-312)

3.1.8

sense key

field in the sense data (see definition in ISO/IEC 14776-312)

3.1.9

status

response information sent from a device to an initiator upon completion of each command

3.1.10

unit attention condition

state that a logical unit maintains while it has asynchronous status information to report to one or more initiators

3.1.11

vendor-specific

an item (for example, a bit, field, code value, etc.) which is not defined by this standard and may be vendor defined

3.2 Acronyms

The following abbreviations are used in this standard:

ASC	Additional Sense Code
ASCQ	Additional Sense Code Qualifier
CDB	Command Descriptor Block
RBC	Reduced Block Commands (this standard)
SPC-2	SCSI Primary Commands 2

3.3 Keywords

Several keywords are used to differentiate levels of requirements and options, as follows:

3.3.1

expected

keyword used to describe the behavior of the hardware or software in the design models assumed by this standard. Other hardware and software design models may also be implemented

3.3.2

ignored

keyword that describes bits, bytes, quadlets, or fields whose values are not checked by the recipient

3.3.3

mandatory

keyword that indicates items required to be implemented as defined by this standard

3.3.4

may

keyword that indicates flexibility of choice with no implied preference

3.3.5

optional

keyword that describes features which are not required to be implemented by this standard. However, if any optional feature defined by this standard is implemented, it shall be implemented as defined

3.3.6

reserved

keyword used to describe objects – bits, bytes and fields – or the code values assigned to these objects in cases where either the object or the code value is set aside for future standardization. Usage and interpretation may be specified by future extensions to this or other standards. A reserved object shall be zeroed or, upon development of a future standard, set to a value specified by such a standard. The recipient of a reserved object shall not check its value. The recipient of a defined object shall check its value and reject reserved code values

3.3.7

shall

keyword that indicates a mandatory requirement. Designers are required to implement all such mandatory requirements to assure interoperability with other products conforming to this standard

3.4 Conventions

The following conventions are used.

3.4.1 Non-numeric values

Lowercase is used for words having the normal English meaning. Certain words and terms used in this standard have a specific meaning beyond the normal English meaning. These words and terms are defined either in Clause 3 or in the text where they first appear.

Listed items in RBC do not represent any priority. Any priority is explicitly indicated. Formal lists (for example, (a) red; (b) blue; (c) green) connoted by letters are in an arbitrary order. Formal lists (for example, (1) red; (2) blue; (3) green) connoted by numbers are in a required sequential order.

If a conflict arises between text, tables or figures, the order of precedence is as follows: text; tables; figures. Not all the tables or figures are fully described in the text. Tables show data format and values. Notes and IMPLEMENTATION notes do not constitute any requirements for implementations.

- a) The names of abbreviations, commands and acronyms are in all uppercase, for example TEST UNIT READY command.
- b) Fields containing only one bit are usually referred to as the "NAME" bit instead of the "NAME" field.
- c) Fields are shown in capital letters, for example LOGICAL BLOCK ADDRESS.

3.4.2 Numeric values

The ISO/IEC convention of numbering is used (i.e., the thousands and higher multiples are separated by a space, and a comma is used as the decimal point, as in 65 536 or 0,5).

- a) Decimal numbers are represented by Arabic numerals without subscripts or by their English names, for example 42, or twelve.
- b) Hexadecimal numbers are represented by digits from the character set 0 – 9 and A – F followed by lower-case h, for example 2Ah.
- c) Binary numbers are represented by digits from the character set 0 and 1, followed by lower-case b, for example 0010 1010b.
- d) The most significant bit of a binary quantity is shown on the left side and represents the highest algebraic value position in the quantity.
- e) For the sake of legibility, binary and hexadecimal numbers are separated into groups of four digits separated by spaces.

4 RBC device model

4.0 General

RBC logical units store blocks of data for later retrieval. Each block of data is stored at a unique location. Initiators issue WRITE commands to store the blocks of data (write operations) and READ commands to retrieve the blocks of data (read operations). Other commands issued by the initiator may also cause write and read operations to occur. A write operation causes one or more blocks of data to be written on the medium. A read operation causes one or more blocks of data to be read from the medium. A verify operation confirms that one or more blocks of data were correctly written and may be read without error from the medium.

Blocks of data are stored by a process that causes localized changes or transitions within the medium. The changes made to the medium to store the blocks of data may be volatile (i.e. not retained through off/on power cycles) or non-volatile (retained through off/on power cycles). The medium may be divided in parts that are used for data blocks, parts that are reserved for

defect management, and parts that are reserved for use by the target for the management of the logical unit.

4.1 Removable medium device

The medium in a RBC device may be removable (for example, used in a floppy disk drive) or non-removable (for example, used in a fixed disk drive). Typically, removable medium is contained within a cartridge (or jacket) to prevent damage to the recording surfaces.

A removable medium has an attribute of being mounted or de-mounted on a suitable transport mechanism. A removable medium is mounted when the device/media combination is capable of performing write or read operations and the initiator is informed of this status. A removable medium is de-mounted at any other time (for example, during loading, unloading, or storage).

Initiators may determine whether a RBC removable medium device is capable of performing read or write operations by one of three methods:

- a) Enabling AERC in the device and examining the event information transmitted from the device.
- b) Issuing a TEST UNIT READY command and examining the returned status information.
- c) Issuing a MODE SENSE command for Mode Page 06h (see 5.8.3) and examining the state of the READD or WRITED bits in byte 11. If the READD bit is set to one, then the media is not readable. If the WRITED bit is set to one, then the media is not writable.

Until the RBC removable medium device and media are ready to be accessed, a READ(10) command shall cause the device to return status of CHECK CONDITION (02h), sense key of NOT READY (02h), and an ASC of LOGICAL UNIT NOT READY (04h). The ASCQ shall reflect the current state of the device/media.

When the device becomes ready, a unit attention condition shall be established. The sense key field shall be set to UNIT ATTENTION (06h), and the ASC/ASCQ to EVENT STATUS NOTIFICATION/MEDIA CLASS EVENT (38h/04h). The EVENT field contained within the SENSE DATA INFORMATION field shall be set to NEW MEDIA READY FOR ACCESS (02h). When the unit attention condition is delivered to the initiator, the status field shall be set to CHECK CONDITION(02h).

4.2 Command usage

4.2.0 General

RBC devices are not required to support the REQUEST SENSE command or the SEND DIAGNOSTIC command. Devices which do not provide the Auto Sense function, Asynchronous Event Reporting, or the GET EVENT STATUS NOTIFICATION (see MMC-2 for definition) command shall implement the REQUEST SENSE command.

All SENSE KEY, ADDITIONAL SENSE CODE and ADDITIONAL SENSE CODE QUALIFIER names and values contained in this standard are defined in ISO/IEC 14776-312. No additional or alternative meaning is intended by the use of such names and values in this standard.

4.2.1 Using the INQUIRY command

The INQUIRY command may be used by an initiator to determine the configuration of a logical unit. RBC devices return information that includes type and standard version. The device may also return the vendor identification number, model number and other vendor specific information. It is recommended that devices provide the capability to return this information upon completing power-on initialization. A device may take more time to return certain portions of this information, especially if the information must be retrieved from the medium.

4.2.2 Using the REQUEST SENSE command

Whenever a command completes with CHECK CONDITION status and AUTOSENSE Data is not provided, the initiator that received the error status should issue a REQUEST SENSE command to acquire the sense data describing the cause of the condition. If the initiator issues a command other than REQUEST SENSE, the sense data is lost.

Devices may be required to support the REQUEST SENSE command if they are unable to provide command progress information by any other method.

4.2.3 FORMAT UNIT command progress determination

The FORMAT UNIT command requires IMMEDIATE bit support because it may consume significantly more time to complete than normal read or write commands. If the IMMEDIATE bit is one, the device is required to return status as soon as the command descriptor block is validated. The device then completes the format operation. Initiators may determine the progress of the format operation in several ways.

RBC devices may provide format progress information using one of three methods. The first two mechanisms return data in the Event Status Notification format described in 7.4.

The first mechanism is progress reporting via Asynchronous Event Reporting. If the initiator and device support this feature, the RBC device initiates progress reporting.

The second mechanism is progress reporting via the GET EVENT STATUS NOTIFICATION command (see ISO/IEC 14776-362 for command definitions). Following the return of GOOD status, the initiator may poll the device for command progress by issuing a GET EVENT STATUS NOTIFICATION command. The returned data contains progress information as defined in 7.4.

The third mechanism is progress reporting via the PROGRESS INDICATION field in the sense-key specific bytes of REQUEST SENSE command sense data. See the SPC standard (ANSI X3.301:1997) for a description of this method.

4.3 Using the PREVENT ALLOW MEDIUM REMOVAL command

4.3.0 General

The PREVENT ALLOW MEDIUM REMOVAL command allows an initiator to restrict the de-mounting of the medium. This is useful in maintaining system integrity. If the removable medium device implements cache memory, the command allows the initiator to ensure that all logical blocks of the medium contain the most recent data prior to permitting de-mounting of the removable medium.

If the initiator issues a START STOP UNIT command to eject the cartridge and the removable medium device is prevented from de-mounting by the PREVENT ALLOW MEDIUM REMOVAL command, the START STOP unit command is rejected by the device.

When set to one, the RMB bit in the standard INQUIRY command data indicates the PREVENT ALLOW MEDIUM REMOVAL command is not being supported.

4.3.1 START STOP UNIT command state restrictions

A removable medium device shall be in either prevent state 00b or 10b in order to successfully execute a START STOP UNIT command with the POWER CONDITIONS field set to the Sleep state (5).

If a removable medium device, in either prevent state 01b or 11b, receives a START STOP UNIT command with the POWER CONDITIONS field set to the Sleep state (5), the device

shall respond with status set to CHECK CONDITION (02h), the sense key to ILLEGAL REQUEST (05h) and the ASC/ASCQ to ILLEGAL POWER CONDITION REQUEST (2Ch/05h).

A removable medium device in the Sleep State shall eject the media without causing the media to spin up in accordance with the PREVENT/ALLOW MEDIUM REMOVAL command requirements.

Refer to 5.4.1 for a description of the POWER CONDITIONS field values.

4.4 Logical Blocks

Data are addressed on the RBC device in a group referred to as a Logical Block. This is a common attribute of RBC devices in that they are block addressable only.

Blocks of data are stored on the medium along with additional information that the medium controller uses to manage the storage and retrieval of the blocks. The format of the additional information is defined by other standards or is vendor specific and is hidden from the application client during normal read or write operations.

The address of the first logical block is zero. The address of the last logical block is $[n-1]$, where $[n]$ is the number of logical blocks available on the medium. A READ CAPACITY command may be issued to determine the value of $[n-1]$. If a command is issued that requests access to a logical block not within the capacity of the medium, the command is terminated with a status of CHECK CONDITION (02h), a sense key of ILLEGAL REQUEST (05h) and an ASC/ASCQ of LOGICAL BLOCK ADDRESS OUT OF RANGE (21h/00h).

The number of bytes of data contained in a logical block is known as the block length. Each logical block has a block length associated with it. The block length is almost always greater than one byte and is typically (but by no means always) a multiple of 512 bytes. In addition, a logical block does not necessarily bear any relation to the physical block size of the storage medium.

The LOGICAL BLOCK SIZE field in the RBC Device Parameters MODE SENSE page (see Table 14) describes the block length that is used on the medium. A MODE SELECT command may be used to set the logical block size, if the field is changeable.

The default NUMBER OF LOGICAL BLOCKS value may be obtained by requesting the Default MODE SENSE data for the RBC Device Parameters MODE SENSE page. The current NUMBER OF LOGICAL BLOCKS value may be obtained by requesting the saved MODE SENSE data for this page.

The location of a logical block on the medium does not necessarily have a relationship to the location of any other logical block. However, in a typical logical unit the logical blocks are located in an ascending order. The time to access the logical block at address $[x]$ and then the logical block at address $[x+1]$ need not be less than time to access $[x]$ and then $[x+100]$.

4.5 Reservations

If the bus protocol does not inherently provide the ability to reserve and release access to a device, then this function may be supported by the RESERVE and RELEASE commands.

Reservation restrictions are placed on commands as a result of access qualifiers associated with the type of reservation.

The details of what commands are allowed under what types of reservations are described in Table 1. For the reservation restrictions placed on commands for the Reserve/Release management method see Table 1 column [A]. For the reservation restrictions placed on

commands for the Persistent Reservations management method, see the columns under (B) in Table 1. In Table 1 the following key words are used:

allowed: Commands issued by initiators not holding the reservation or by initiators not registered when a registrant's only persistent reservation is present should complete normally.

conflict: Commands issued by initiators not holding the reservation or by initiators not registered when a registrant's only persistent reservation is present shall not be performed and the device server shall terminate the command with a RESERVATION CONFLICT status.

Commands from initiators holding a reservation should complete normally. The behavior of commands from registered initiators when a registrant's only persistent reservation is present is specified in Table 1.

A command that does not explicitly write the medium shall be checked for reservation conflicts before the command enters the current task state for the first time. Once the command has entered the current task state, it shall not be terminated with a RESERVATION CONFLICT due to a subsequent reservation.

A command that explicitly writes the medium shall be checked for reservation conflicts, before the device server modifies the medium or cache as a result of the command. Once the command has modified the medium, it shall not be terminated with a RESERVATION CONFLICT due to a subsequent reservation. For each command, this standard, ISO/IEC 14776-312, or a related command standard defines the conditions that result in RESERVATION CONFLICT. Depending on the particular command standard the conditions are defined in that standard's device model clause or in the clauses that define the specific commands.

Table 1 – RBC direct access commands that are allowed in the presence of various reservations

Command	Addressed LU is reserved by another Initiator (A)	Addressed LU has this type of persistent reservation held by another Initiator (B)				
		From any Initiator		From registered Initiator (RO all types)	From Initiator not registered	
		Write Excl	Excl Access		Write Excl – RO	Excl Access – RO
FORMAT UNIT	Conflict	Conflict	Conflict	Allowed	Conflict	Conflict
READ(10)	Conflict	Allowed	Conflict	Allowed	Allowed	Conflict
READ CAPACITY	Allowed	Allowed	Allowed	Allowed	Allowed	Allowed
START STOP UNIT Start = 0 and Power Condition = 0	Allowed	Allowed	Allowed	Allowed	Allowed	Allowed
START STOP UNIT Start = 1 or Power Condition <>0	Conflict	Conflict	Conflict	Allowed	Conflict	Conflict
VERIFY(10)	Conflict	Allowed	Conflict	Allowed	Allowed	Conflict
WRITE(10)	Conflict	Conflict	Conflict	Allowed	Conflict	Conflict

5 Reduced block commands

5.0 General

The Reduced Block Command set (RBC) for block device logical units is shown in Table 2. The SCSI Primary Commands 2 (see ISO/IEC 14776-312: SCSI SPC-2) required for RBC device implementations are also shown in Table 2. Support is indicated for fixed or removable drives.

Table 2 – Reduced Block Command set

Command name	OpCode	Command Support		Reference
		Fixed	Removable	
FORMAT UNIT	04h	O	O	RBC
INQUIRY	12h	M	M	SPC-2 ^a
MODE SELECT(6)	15h	M	M	SPC-2 ^a
MODE SENSE(6)	1Ah	M	M	SPC-2 ^a
PERSISTENT RESERVE IN	5Eh	O	O	SPC-2 ^a
PERSISTENT RESERVE OUT	5Fh	O	O	SPC-2 ^a
PREVENT/ALLOW MEDIUM REMOVAL	1Eh	N/A	M	SPC-2 ^a
READ(10)	28h	M	M	RBC
READ CAPACITY	25h	M	M	RBC
RELEASE(6)	17h	O	O	SPC-2 ^a
REQUEST SENSE	03h	O	O	SPC-2 ^a
RESERVE(6)	16h	O	O	SPC-2 ^a
START STOP UNIT	1Bh	M	M	RBC
SYNCHRONIZE CACHE	35h	O	O	RBC
TEST UNIT READY	00h	M	M	SPC-2 ^a
VERIFY(10)	2Fh	M	M	RBC
WRITE(10)	2Ah	M	M	RBC
WRITE BUFFER	3Bh	M	O	SPC-2 ^a
NOTE 1 Command Support key: M = support is mandatory; N/A = not applicable; O = support is optional.				
NOTE 2 SPC-2 = ISO/IEC 14776-312.				
^a See clause 6, in ISO/IEC 14776-312, implementation requirements for RBC devices.				

The control byte (the last byte of the CDB) shall be set to zero.

5.1 FORMAT UNIT command

This command (see Table 3) formats the media into addressable logical blocks. This command is optional for both fixed and removable medium devices. An Initiator shall examine the state of the FORMATD bit in the MODE SENSE RBC Device Parameters page (Table 14) to determine whether the device supports this command.

Table 3 – FORMAT UNIT command

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (04h)							
1	Reserved							
2	Reserved				IMMED	PROGRESS	PERCENT/ TIME	INCREMENT
3	Reserved							
4	Reserved							
5	CONTROL = 00h							

An IMMEDIATE (IMMED) bit value of zero indicates that status shall be returned after the format operation has completed. An IMMED bit value of one indicates that this device shall return status as soon as the command descriptor block has been validated.

The PROGRESS bit indicates whether the initiator is requesting periodic format progress updates. If this bit is set to zero, no progress report shall be generated. If the PROGRESS bit is set to one then the device shall generate format progress based upon the values of the PERCENT/TIME and the INCREMENT bit. Refer to 4.2.3 for a description of the progress reporting mechanisms for the format operation.

The PERCENT/TIME bit and INCREMENT bit determine the method used to report format progress, whether in a percentage of completion or in total elapsed time.

If the PERCENT/TIME bit is zero, format progress shall be reported in total time elapsed. If the PERCENT/TIME bit is set to one, format progress shall be reported in percentage of completion.

The INCREMENT bit specifies the granularity of progress reported. When set to zero, the device reports progress in 5 % or 5 s increments, depending on the value of the PERCENT/TIME bit. When set to one, the device reports progress in 1 % or 1 s increments, depending on the value of the PERCENT/TIME bit.

NOTE Initiators should set the INCREMENT bit value to zero to avoid the bus usage penalties associated with a value of one.

Format progress (when requested by setting the PROGRESS bit to one in the CDB) shall be reported with a status of CHECK CONDITION (02h), a sense key of NOT READY (02h), and an ASC/ASCQ of LOGICAL UNIT NOT READY, FORMAT IN PROGRESS (04h/04h). The SENSE DATA INFORMATION field shall contain the total number of increments (percentage complete or time in seconds) that have elapsed since command inception.

Upon successful completion of the FORMAT UNIT command, status shall be set to CHECK CONDITION (02h), the sense key to UNIT ATTENTION (06h), and the ASC/ASCQ to EVENT STATUS NOTIFICATION/MEDIA CLASS EVENT (38h/04h). The EVENT field contained within the SENSE DATA INFORMATION field shall be set to NEW MEDIA READY FOR ACCESS (02h). The initiator shall respond by issuing a MODE SENSE command followed by READ CAPACITY command.

If the FORMAT UNIT command fails, the device shall return a status of CHECK CONDITION (02h), a sense key of MEDIA ERROR (03h), an ASC/ASCQ of FORMAT COMMAND FAILED (31h/01h).

After the problem is corrected (for example, media replaced), and the device becomes ready, the initiator shall issue a MODE SENSE command, followed by a READ CAPACITY command to determine the device's physical parameters.

READ CAPACITY data (see Table 6) shall be returned to the initiator prior to sending GOOD status for the command.

Table 6 – READ CAPACITY data

Bit Byte	7	6	5	4	3	2	1	0
0	(MSB)	RETURNED LOGICAL BLOCK ADDRESS						
1								
2								
3								(LSB)
4	(MSB)	BLOCK LENGTH IN BYTES						
5								
6								
7								(LSB)

The BLOCK LENGTH BYTES and the RETURNED LOGICAL BLOCK ADDRESS are those of the last logical block of the media contained in the device.

If the device does not contain media, then it shall return status of CHECK CONDITION (02h), sense key of NOT READY (02h), and an ASC of LOGICAL UNIT NOT READY (04h). The ASCQ shall reflect the current state of the device/media.

5.4 START STOP UNIT command

5.4.0 General

The START STOP UNIT command (see Table 7) requests that the device enable or disable the Logical Unit for media access operations and controls certain power conditions.

Table 7 – START STOP UNIT Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (1Bh)							
1	Reserved							IMMED
2	Reserved							
3	Reserved							
4	POWER CONDITIONS				Reserved		LOEJ	START
5	CONTROL = 00h							

An IMMEDIATE (IMMED) bit of zero indicates that status shall be returned after the operation is completed. An IMMED bit of one indicates that status shall be returned as soon as the command descriptor block has been validated.

The other fields in the START STOP UNIT command are described in the following sub-clauses.

5.4.1 Power conditions

The POWER CONDITIONS field requests that the logical unit be placed into the power condition defined in Table 12. If this field contains any valid value other than zero then the START and the LOEJ bits shall be ignored.

The POWER CONDITIONS field states are shown in Table 8. RBC device support for each state is also shown.

Table 8 – POWER CONDITIONS

Code	Support	Description
0	M	No change in power condition
1	M	Place device in Active condition
2	M	Place device in Idle condition
3	M	Place device in Standby condition
4	–	Reserved
5	M	Place device in Sleep condition
6	–	Reserved
7	O	Device Control
8h - Fh	–	Reserved
Key: M = Command implementation is mandatory O = Command implementation is optional		

Active (condition 1): Devices in Active state are at their highest power consumption level.

For hard disk drives, this typically means that the drive is spinning and capable of executing a media access command without a significant delay.

Idle (condition 2): Devices in Idle state are at a lower power consumption level than when in Active condition, but still have a significant portion of their circuitry consuming power. For hard disk drives, this typically means that the drive is spinning, but not capable of performing a media access command without a delay.

Standby (condition 3): Devices in Standby state are at a lower power consumption level than when in Idle condition and do not have a significant portion of their circuitry consuming power. For hard disk drives, this typically means that the drive is not spinning, but the interface is fully active. Prior to entering Standby state the device shall ensure that logical blocks in cache have their most recent data value recorded on the physical medium.

Sleep (condition 5): Devices in Sleep state are at a lower power consumption level than when in Standby condition and have very little of the drive circuitry consuming power. A device reset may be required before access to the device is allowed. Prior to entering Sleep state the device shall ensure that logical blocks in cache have their most recent data value recorded on the physical medium.

Device Control (condition 7): Devices in the Device Control state are allowed to control their own power consumption level. However, the level of Device Control is governed by the value of the POWER/PERFORMANCE field in RBC device parameter page (see Table 14).

The device shall terminate any command received that requires more power consumption than allowed by the START STOP UNIT command's most recent power condition setting. Status shall be set to CHECK CONDITION (02h), the sense key to ILLEGAL REQUEST (05h), and the ASC/ASCQ to LOW POWER CONDITION ACTIVE (5Eh/00h).

It is not an error to request a device be placed into the same power consumption level in which it currently resides.

5.4.2 Control bits

A LOAD/EJECT (LOEJ) bit of zero requests that no action be taken regarding loading or ejecting the medium. A LOEJ bit of one requests that the medium shall be ejected if the START bit is zero. A LOEJ bit, when set to one, requests that the medium is to be loaded if the START bit is one.

A START bit of zero requests that the device be stopped (media is inaccessible for data transfers). A START bit of one requests the device be made ready for use. Table 9 describes the functional relationship of the START STOP UNIT control bits.

Table 9 – START STOP control bit definitions

Power conditions	Load/Eject	START	Description
1 – 7	X	X	LOEJ and START ignored
0	0	0	Stop the medium
0	0	1	Make medium ready
0	1	0	Unload medium
0	1	1	Load medium

5.5 SYNCHRONIZE CACHE command

The SYNCHRONIZE CACHE command (see Table 10) ensures that logical blocks in cache have their most recent data value recorded on the physical medium. If a more recent data value for a logical block exists in the cache memory than on the physical medium, then the logical block from the cache memory shall be written to the physical medium. Logical blocks are not necessarily removed from the cache memory as a result of the SYNCHRONIZE CACHE operation.

Devices that report the WCD bit set to one in the MODE SENSE RBC Device Parameters page may return status of CHECK CONDITION (02h), a sense key of ILLEGAL REQUEST (05h) and an ASC of INVALID COMMAND OPERATION CODE (20h).

Table 10 – SYNCHRONIZE CACHE Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (35h)							
1	Reserved WCD							
2	Reserved WCD							
3	Reserved WCD							
4	Reserved WCD							
5	Reserved WCD							
6	Reserved WCD							
7	Reserved WCD							
8	Reserved WCD							
9	CONTROL = 00h							

5.6 WRITE(10) command

The WRITE(10) command (see Table 11) requests that the device write data transferred from the initiator to the medium.

Table 11 – WRITE(10) Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0	
0	OPERATION CODE (2Ah)								
1	Reserved				FUA	Reserved			
2	(MSB) _____								
3	LOGICAL BLOCK ADDRESS								_____
4									_____
5									_____
6	Reserved								(LSB)
7	(MSB) _____								_____
8	TRANSFER LENGTH								(LSB)
9	CONTROL = 00h								

A FORCE UNIT ACCESS (FUA) bit of zero indicates that the device may satisfy the command by accessing the cache memory if the WCD bit in RBC mode page 06h (see 5.8.3) is set to zero. For write operations, logical blocks may be transferred directly to the cache memory. GOOD status may be returned to the initiator prior to writing the logical blocks to the medium. Any error that occurs after GOOD status is returned is a deferred error.

A FUA bit of one indicates that the device shall access the media in performing the command prior to returning GOOD status. A WRITE command shall not return GOOD status until the logical blocks have actually been written on the media (for example, the data is not write cached).

If the device supports write caching, FUA support shall be implemented. If write caching is NOT supported then the FUA bit may be ignored.

The LOGICAL BLOCK ADDRESS field specifies the first logical block of the range of logical blocks that shall be written.

The TRANSFER LENGTH field specifies the number of contiguous logical blocks of data that shall be transferred. A TRANSFER LENGTH of zero indicates that no logical blocks shall be transferred. This condition shall not be considered an error. Any other value indicates the number of logical blocks that shall be transferred.

5.7 VERIFY command

The VERIFY command (see Table 12) requests that the device verify the data written on the medium.

Table 12 – VERIFY Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (2Fh)							
1	Reserved							
2	(MSB)	LOGICAL BLOCK ADDRESS						
3								
4								
5								(LSB)
6	Reserved							
7	(MSB)	VERIFICATION LENGTH						
8								(LSB)
9	CONTROL = 00h							

The LOGICAL BLOCK ADDRESS field specifies the starting logical block address on the device for the data to be accessed.

The VERIFICATION LENGTH field specifies the number of contiguous logical blocks of data that shall be verified. A VERIFICATION LENGTH of zero indicates that no logical blocks shall be verified. This condition shall not be considered an error. Any other value indicates the number of logical blocks that shall be verified.

The VERIFY command verifies that the data written on the media by a previous WRITE command is readable without any uncorrectable errors at the time of execution of the command. It does not guarantee the information is complete or valid.

5.8 MODE parameters

5.8.0 General

This clause describes the header and page used with the MODE SELECT and MODE SENSE commands that are applicable to RBC devices.

5.8.1 Mode parameter list

The mode parameter list shown in Table 13 contains a header followed by the RBC Device Parameters page. No block descriptor is required for RBC devices.

Table 13 – Mode parameter list

Bit Byte	7	6	5	4	3	2	1	0
0 – 3	MODE PARAMETER HEADER							
4 – 17	RBC device parameter page							

5.8.2 Mode parameter header

The mode parameter header is described in SPC-2. For RBC devices the MEDIUM TYPE; DEVICE-SPECIFIC PARAMETER and BLOCK DESCRIPTOR LENGTH fields shall contain zero.

5.8.3 RBC device parameter page

The RBC Device Parameters page (see Table 14) is intended to provide general configuration information and to allow modification of that configuration, when permitted by the device. An initiator may attempt to change any or all parameters contained in the page. No error status shall be returned for parameters that are not changeable.

The initiator may issue a MODE SENSE command for the same page in order to determine which parameters have changed.

Table 14 – RBC Device Parameter's page format

Bit Byte	7	6	5	4	3	2	1	0
0	PS = 1	rsvd	PAGE CODE (06h)					
1	PAGE LENGTH (0Bh)							
2	Reserved							WCD
3	(MSB)	LOGICAL BLOCK SIZE						
4								
5	(MSB)	NUMBER OF LOGICAL BLOCKS						
6								
7								
8								
9		(LSB)						
10	POWER/PERFORMANCE							
11	Reserved				READD	WRITED	FORMATD	LOCKD
12	Reserved							

A WRITE CACHE DISABLE (WCD) bit of zero specifies that the device may return GOOD status for a WRITE command after successfully receiving the data and prior to having successfully written it to the medium. A WCD bit of one specifies that the device shall return GOOD status for a WRITE command after successfully writing all of the data to the medium.

Devices that cannot physically lock the media or are unable to prevent media removal (for example, floppy drives, PCMCIA drives, Flash cards, etc.) shall ignore the WCD bit and shall report WCD equal to 1 in Mode Sense information.

The LOGICAL BLOCK SIZE field indicates the number of user data bytes contained in a logical block.

The NUMBER OF LOGICAL BLOCKS field indicates the number of logical blocks contained in the user data area.

Setting the POWER CONDITIONS field of the START STOP UNIT command to Device Control (07h) enables the POWER/PERFORMANCE field.

The POWER/PERFORMANCE field specifies the POWER/PERFORMANCE management level. Higher values permit the device to give more emphasis to performance than power conservation. A value of FFh causes the drive to provide the highest performance possible, not affected by power conservation. A value of 00h causes the drive to provide the highest power conservation, regardless of its effect on performance.

Changes in the level of power and performance for specific values of the POWER/PERFORMANCE field are vendor specific.

A READ DISABLED (READD) bit of zero indicates that the media may be read by an initiator. A READD bit of one indicates that an initiator cannot read the media.

A WRITE DISABLED (WRITED) bit of zero indicates that the media may be written. A WRITED bit of one indicates that an initiator cannot write the media.

A FORMAT DISABLED (FORMATD) bit of zero indicates that the media may be formatted. A FORMATD bit of one indicates that an initiator cannot format the media. The FORMATD bit shall not be set to zero if the WRITED bit is set to one.

A LOCK DISABLED (LOCKD) bit of zero indicates that the media may be locked by the PREVENT/ALLOW MEDIUM REMOVAL command. A LOCKD bit, when set to one, indicates that the media cannot be locked by the PREVENT/ALLOW MEDIUM REMOVAL command. If the RMB bit in the standard INQUIRY command data is not set to one, then the LOCKD bit shall be set to one.

6 SPC-2 implementation requirements for RBC devices

6.0 General

RBC devices require several commands defined in SPC-2 to function in a system. Bit and field exceptions contained in those commands listed in Table 15 are described in the following clauses.

Table 15 – Required SPC-2 commands

Command name	Opcode	Command Support		Reference
		Fixed	Removable	
INQUIRY	12h	M	M	SPC-2
MODE SELECT(6)	15h	M	M	SPC-2
MODE SENSE(6)	1Ah	M	M	SPC-2
PREVENT/ALLOW MEDIUM REMOVAL	1Eh	N/A	M	SPC-2
REQUEST SENSE	03h	O	O	SPC-2
TEST UNIT READY	00h	M	M	SPC-2
WRITE BUFFER	3Bh	M	O	SPC-2
Command Support key: M = support is mandatory; N/A = not applicable; O = support is optional.				

6.1 INQUIRY command

6.1.0 General

The standard INQUIRY data format is reproduced in Table 16. Several INQUIRY data bits and fields are restricted for RBC compatibility. Only the restricted fields and their values are shown. Refer to SPC-2 for descriptions of fields and bits not shown.

Table 16 – Standard Inquiry data format

Bit Byte	7	6	5	4	3	2	1	0
0				PERIPHERAL DEVICE TYPE= 0E h				
1	RMB							
2								
3	AERC		NACA=0					
4								
5								
6								
7	RELADR=0				LINKED=0			
8								
9								
—								
n								

RBC devices are identified by a PERIPHERAL DEVICE TYPE field set to 0E h.

A REMOVABLE MEDIUM BIT (RMB) of zero indicates that the medium is not removable. A RMB bit of one indicates that the medium is removable.

If the transport protocol provides a mechanism for asynchronous event reporting, RBC devices shall support the function and indicate that support by setting the ASYNCHRONOUS EVENT REPORTING CAPABILITY (AERC) bit to one.

RBC devices shall report sense data using the AUTONSENSE method if the transport protocol supports this function. RBC devices shall clear all tasks as the result of any device error.

RBC devices shall not support Auto Contingent Allegiance and ignore the Normal ACA bit in the CDB Control byte. Therefore, RBC devices shall return a zero in the Normal ACA bit in Inquiry data (shown as NACA in table 15).

The RELADR bit shall be set to zero. Relative Addressing is not supported by RBC devices.

The LINKED bit shall be set to zero. LINKED commands are not supported by RBC devices.

Support of other bits and fields in the Inquiry command is not defined in this standard. For additional requirements, refer to SPC-2.

6.1.1 INQUIRY vital product data pages

6.1.1.0 General

This clause describes the vital product data pages that are mandatory for RBC devices. This standard defines the required pages but not the page content.

6.1.1.1 Unit serial number page

The Unit Serial Number page, 80h, shall be supported by RBC devices.

6.1.1.2 Device Identification page

The Vital Product Data Device Identification page, 83h, shall be supported by RBC devices.

6.2 MODE SELECT(6) command

6.2.0 General

The MODE SELECT(6) command (see Table 17) provides a means for an initiator to specify device parameters to a RBC device. RBC devices shall also implement the MODE SENSE(6) command.

Table 17 – MODE SELECT(6) Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (15h)							
1				PF = 1				SP
2	Reserved							
3	Reserved							
4	PARAMETER LIST LENGTH							
4	Reserved							
5	CONTROL = 00h							
The PAGE FORMAT (PF) bit shall be set to one.								

An initiator may attempt to change any or all parameters contained in a mode page. The device shall ignore non-changeable parameters in the MODE SELECT parameter data. This shall not be considered an error.

The initiator may issue a MODE SENSE command for the same page in order to determine which parameters have changed.

6.2.1 Save pages (SP) bit support

For non-removable medium devices the SAVE PAGES (SP) bit shall be set to one. This indicates that the device shall perform the specified MODE SELECT operation and shall save, to a non-volatile vendor-specific location, all the changeable pages, including any sent with the command.

For removable medium devices support of the SP bit is optional. Such devices may be unable to save changeable information to a non-volatile medium. Therefore, if the SP bit is set to one, removable medium devices may return a status of CHECK CONDITION (02h), a sense key of ILLEGAL REQUEST (05h) and an ASC of INVALID FIELD IN CDB (24h).

6.3 MODE SENSE(6) command

The MODE SENSE(6) command (see Table 18) provides a means for an RBC device to report device parameters to an initiator. It is a complementary command to the MODE SELECT(6) command.

Table 18 – MODE SENSE(6) Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (1Ah)							
1					DBD = 1			
2	PC		PAGE CODE					
3	Reserved							
4	ALLOCATION LENGTH (LSB)							
5	CONTROL = 00h							
The DISABLE BLOCK DESCRIPTORS (DBD) bit shall be set to one.								

The PAGE CONTROL (PC) field defines the type of mode parameter values to be returned in the mode page.

The device shall respond to PC values in the following manner:

- if Current values are requested, report the Current values of the mode parameters established by the last MODE SELECT command. If the device implements no distinction between current and saved parameters, then it shall report identical values in response to a PC of either 00b or 11b. If Saved or Current values are not available, report Default values;
- if Default values are requested, report the Default values;
- if Saved values are requested, report valid restored mode parameters, or restore the mode parameters and report them.

6.4 PREVENT ALLOW MEDIUM REMOVAL

RBC devices shall support the PREVENT ALLOW MEDIUM REMOVAL command if the REMOVABLE MEDIUM BIT (RMB) bit is set to one in the INQUIRY command standard data.

6.5 REQUEST SENSE command

RBC devices shall support the REQUEST SENSE command if AUTOSENSE Data is not provided or if either Asynchronous Event Notification or the GET EVENT STATUS NOTIFICATION command is not supported.

If the REQUEST SENSE command is supported it shall be implemented as described in the SPC-2 specification.

6.6 TEST UNIT READY command

RBC devices shall report information exceptions via the unit attention condition (with the associated asynchronous event notification, if enabled) or the TEST UNIT READY response. The TEST UNIT READY status response shall include information exception status only after a threshold has been exceeded. Once the associated asynchronous event notification has been successfully sent to the initiator the device shall clear the information exception status from the TEST UNIT READY response. The required Sense Key is RECOVERED ERROR (01h), and the ASC is FAILURE PREDICTION THRESHOLD EXCEEDED (5Dh). The ASCQ values are described in Table 19.

Table 19 – FAILURE PREDICTION ASCQ XY definitions

ASCQ X	Description	ASCQ Y	Description
0h	Defined by SPC-2	0h	General hard drive failure
1h	Hardware impending failure	1h	Drive error threshold exceeding limits
2h	Controller impending failure	2h	Data error rate exceeding limits
3h	Data Channel impending failure	3h	Seek error rate exceeding limits
4h	Servo impending failure	4h	LBA reassignment exceeding limits
5h	Spindle impending failure	5h	Access times exceeding limits
6h	Firmware impending failure	6h	Start Unit times exceeding limits
7h	Reserved	7h	Channel parametrics indicate impending failure
8h	Vendor Specific in SPC-2	8h	Controller detected impending failure
9h	Vendor Specific in SPC-2	9h	Throughput performance
Ah	Vendor Specific in SPC-2	Ah	Seek time performance
Bh	Vendor Specific in SPC-2	Bh	Spin-up retry count
Ch	Vendor Specific in SPC-2	Ch	Drive calibration retry count
Dh	Vendor Specific in SPC-2	Dh	Reserved
Eh	Vendor Specific in SPC-2	Eh	Reserved
Fh	Refer to SPC-2	Fh	Reserved

SPC-2 = ISO/IEC 14776-312.

6.7 WRITE BUFFER command

6.7.0 General

The WRITE BUFFER command (see Table 20) is used to download and save microcode. RBC devices are required to support Modes 101b and 111b. Support for all other modes is optional.

Table 20 – WRITE BUFFER Command Descriptor Block

Bit Byte	7	6	5	4	3	2	1	0
0	OPERATION CODE (3Bh)							
1	Reserved					MODE		
2	Reserved							
3	(MSB)	BUFFER OFFSET						
4								
5								(LSB)
6	(MSB)	PARAMETER LIST LENGTH						
7								
8								(LSB)
9	CONTROL = 00h							

6.7.1 Download Microcode and save mode (101b)

In this mode, vendor-specific Microcode or control information shall be transferred to the device and, if the WRITE BUFFER command is completed successfully, shall also be saved in a non-volatile memory space (semiconductor, disk, or other). The downloaded code shall then be effective after each power-cycle and reset until it is supplanted in another download Microcode and save operation. When the WRITE BUFFER command has completed successfully, the device shall generate a unit attention condition. If asynchronous event notification is enabled, all initiators except the one that issued the WRITE BUFFER command shall be notified of the unit attention condition. The device shall set the sense key to UNIT ATTENTION (02h) and the ASC/ASCQ to MICROCODE HAS BEEN CHANGED (3Fh / 01h).

The PARAMETER LIST LENGTH specifies the maximum number of bytes that shall be transferred from the initiator to the device.

If the logical unit cannot accept this command because of a device condition, the device shall terminate the command and return a status of CHECK CONDITION (02h), a sense key of ILLEGAL REQUEST (05h) and an ASC of COMMAND SEQUENCE ERROR (2Ch).

6.7.2 Download Microcode with offsets and save mode (111b)

In this mode, the initiator may split the transfer of the vendor-specific microcode or control information over two or more WRITE BUFFER commands. If the logical unit cannot accept this command because of a device condition, the device shall terminate the command and return a status of CHECK CONDITION (02h), a sense key of ILLEGAL REQUEST (05h) and an ASC of COMMAND SEQUENCE ERROR (2Ch).

Refer to ISO/IEC 14776-312 for a complete description of this mode.

7 Asynchronous event notification for RBC devices

7.0 General

RBC devices shall notify initiators of the ability to support asynchronous event notification by setting the ASYNCHRONOUS EVENT REPORTING CAPABILITY (AERC) bit to one in the standard data format of the INQUIRY command (see ISO/IEC 14776-312).

Table 21 describes conditions that may be communicated to an initiator as an asynchronous event.

Table 21 – Asynchronous Event conditions

Sense key	ASC	Description
01h	5Dh	RECOVERED ERROR. FAILURE PREDICTION THRESHOLD EXCEEDED.
02h	04h	LOGICAL UNIT NOT READY (reported only on transition or at power on).
03h	nnh	MEDIUM ERROR. Multiple causes.
06h	38h	Unit Attention. Event Status Notification.
06h	5Eh	Unit Attention. Power condition Change Notification.
06h	28h	Unit Attention. Not Ready to Ready transition. Medium may have changed.
06h	29h	Unit Attention. Power on reset, bus reset, etc.
This list is for illustration purposes. It is not an exhaustive list.		

7.1 Unit attention

7.1.0 General

A unit attention condition may be reported via asynchronous event notification. Logical units may queue unit attention conditions; more than one unit attention condition may exist at the same time. Refer to Table 21 for a description of unit attention conditions that may be reported via asynchronous event notification.

7.1.1 Power condition change notification

RBC devices shall notify an initiator of the intent to change power conditions via asynchronous event notification. The status value shall be set to CHECK CONDITION (02h), the sense key to UNIT ATTENTION (06h), and the ASC to POWER CONDITION CHANGE NOTIFICATION (5Eh). The ASCQ shall be set to the value of the new power condition plus 40h as shown in Table 22.

Table 22 – Power condition sense code and qualifier values

ASC	ASCQ	Description
5E h	41h	POWER CONDITION CHANGE TO ACTIVE
5E h	42h	POWER CONDITION CHANGE TO IDLE
5E h	43h	POWER CONDITION CHANGE TO STANDBY
5E h	45h	POWER CONDITION CHANGE TO SLEEP
5E h	47h	POWER CONDITION CHANGE TO DEVICE CONTROL

An initiator shall respond with a START STOP UNIT command within 8 s, if it intends to manage the power transition. If the initiator does not respond within 8 s, the device may transition to a new power condition. If the initiator responds with a START STOP UNIT command within 8 s and sets the power condition value equal-to or greater-than the current value, the device shall not transition to a lower power condition.

7.2 Deferred errors

Deferred errors shall also be reported via asynchronous event notification. Deferred errors may be produced as a result of cached data management or support of the Immediate function in commands such as START STOP UNIT or FORMAT.

7.3 Information exception condition notification

RBC devices shall notify the initiator when an information exception condition exists via asynchronous event notification. The status field shall be set to CHECK CONDITION (02h), the sense key to RECOVERED ERROR (01h), the ASC to FAILURE PREDICTION THRESHOLD EXCEEDED (5Dh), and the ASCQ to the failure prediction threshold descriptor value. Refer to Table 19 for failure prediction ASCQ values.

7.4 Event status notification

7.4.0 General

Through the use of asynchronous event notification, RBC devices may report asynchronous events the moment they occur.

If the initiator does not support asynchronous event notification, alternative methods shall be used to determine the state of the device/media combination. Refer to the GET EVENT STATUS NOTIFICATION command for a description of those alternative methods.

7.4.1 Event status sense information

The following sense data shall be used for the event status notification and unit attention condition. The status value shall be set to CHECK CONDITION (02h). The sense key shall be set to UNIT ATTENTION (06h). The ASC shall be set to EVENT STATUS NOTIFICATION (38h). The ASCQ shall be set to the appropriate value shown in Table 23.

Table 23 – Event status ASCQ values

ASCQ	Name	Description
02h	POWER MANAGEMENT CLASS EVENT	Indicates that a Power Management Class event has occurred or is impending.
04h	MEDIA CLASS EVENT	Indicates that a Media Class event has occurred.
06h	DEVICE BUSY CLASS EVENT	Indicates that a Device Busy Class event has occurred.

For each value of the sense key, ASC and ASCQ above, the contents of the sense data INFORMATION field further describe the event status. The general format of the sense data INFORMATION field is shown in Table 24.

Table 24 – EVENT STATUS INFORMATION field format

Bit Byte	7	6	5	4	3	2	1	0
0	EVENT							
1	STATUS							
2	EVENT SPECIFIC							
3	EVENT SPECIFIC							

The following clauses provide specific sense data INFORMATION field definitions for each ASCQ value described in Table 23.

7.4.2 POWER MANAGEMENT CLASS INFORMATION field

Table 25 displays the INFORMATION field format for POWER MANAGEMENT CLASS EVENTS.

Table 25 – POWER MANAGEMENT CLASS INFORMATION field format

Bit Byte	7	6	5	4	3	2	1	0
0	EVENT							
1	STATUS							
2	Reserved							
3	Reserved							

Table 26 describes the EVENT field values associated with POWER MANAGEMENT CLASS EVENTS.

Table 26 – POWER MANAGEMENT CLASS EVENT field

EVENT field	Description
00h	No power condition change.
01h	The device successfully changed to the specified power condition.
02h	The device failed to enter the last commanded power condition and is still operating at the state specified in the Power Status field.
03h – FFh	Reserved

Table 27 describes the STATUS field values for POWER MANAGEMENT CLASS events. The state names and values match those specified in the START STOP UNIT command, power condition field.

Table 27 – POWER MANAGEMENT CLASS STATUS field

STATUS field	Description
00h	Reserved
01h	The device is in the Active state.
02h	The device is in the Idle state.
03h	The device is in the Standby state.
04h	Reserved
05h	Not Applicable (Sleep state).
06h	Reserved
07h	The device is in the Device Control state.
08h – FFh	Reserved

7.4.3 MEDIA CLASS EVENT INFORMATION field

Table 28 displays the INFORMATION field format for MEDIA CLASS events.

Table 28 – MEDIA CLASS INFORMATION field format

Bit Byte	7	6	5	4	3	2	1	0
0	EVENT							
1	Reserved						MEDIA PRESENT	DOOR OR TRAY OPEN
2	START SLOT							
3	END SLOT							

Table 29 describes the EVENT field values associated with MEDIA CLASS events.

Table 29 – MEDIA CLASS EVENT field

EVENT field	Description
00h	Media status is unchanged.
01h	Eject request. The user has issued a request to eject the slot or media.
02h	The specified slot has received new media and the media is ready to be accessed.
03h	Media Removal. The media has been removed from the specified slot and the device is unable to access the media without user intervention.
04h – FFh	Reserved

The DOOR OR TRAY OPEN bit indicates the mechanical position of the device's door or tray. A DOOR OR TRAY OPEN value of one indicates that the door or tray is open. A value of zero indicates that the door or tray is closed.

The MEDIA PRESENT bit indicates whether media is installed in the device. A value of one indicates that media is present in the device. A value of zero indicates that no media is present. The MEDIA PRESENT bit is reported independently from the DOOR OR TRAY OPEN bit. If the device cannot report the media state while the door or tray is open, this bit shall be set to zero when the DOOR OR TRAY OPEN bit is zero.

The START SLOT field defines the first slot of a multiple slot device that the media status notification applies to. For devices that do not support multiple slots, this field shall be reserved.

The END SLOT field defines the last slot of a multiple slot device that the media status notification applies to. For devices that do not support multiple slots, this field shall be reserved.

7.4.4 DEVICE BUSY CLASS EVENT INFORMATION values

Table 30 displays the INFORMATION field format for DEVICE BUSY CLASS events.

Table 30 – DEVICE BUSY CLASS INFORMATION field format

Bit Byte	7	6	5	4	3	2	1	0
0	EVENT							
1	STATUS							
2	TIME							
3								

Table 31 describes the EVENT field values associated with DEVICE BUSY CLASS events.

Table 31 – DEVICE BUSY CLASS EVENT field

EVENT field	Description
00h	No event is available.
01h	A time-out has occurred.
02h	Immediate command progress indication.
02h – FFh	Reserved

Table 32 describes the STATUS field values for DEVICE BUSY class events.

Table 32 – DEVICE BUSY CLASS STATUS field

STATUS field	Description
00h	No event. The device is ready to accept commands.
01h	The device is in the process of waking up from a lower power condition.
02h	The device is in the process of completing an earlier command.
03h	The device is in the process of completing a deferred operation, such as a write.
04h – FFh	Reserved

For DEVICE BUSY class events with an EVENT field value of 02h, the TIME field is the percent completion of an immediate command. For EVENT field values other than 02h, the TIME field is the predicted amount of time remaining for the device to become not busy, in units of 100 ms.