

---

---

**Information technology — JPEG XS  
low-latency lightweight image coding  
system —**

**Part 2:  
Profiles and buffer models**

*Technologies de l'information — Système de codage d'images léger à  
faible latence JPEG XS —*

*Partie 2: Profils et modèles tampons*

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC 21122-2:2022



**COPYRIGHT PROTECTED DOCUMENT**

© ISO/IEC 2022

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office  
CP 401 • Ch. de Blandonnet 8  
CH-1214 Vernier, Geneva  
Phone: +41 22 749 01 11  
Email: [copyright@iso.org](mailto:copyright@iso.org)  
Website: [www.iso.org](http://www.iso.org)

Published in Switzerland

# Contents

Page

|                                                                                                                                                      |           |
|------------------------------------------------------------------------------------------------------------------------------------------------------|-----------|
| <b>Foreword</b>                                                                                                                                      | <b>iv</b> |
| <b>Introduction</b>                                                                                                                                  | <b>v</b>  |
| <b>1 Scope</b>                                                                                                                                       | <b>1</b>  |
| <b>2 Normative references</b>                                                                                                                        | <b>1</b>  |
| <b>3 Terms, definitions, symbols and abbreviated terms</b>                                                                                           | <b>1</b>  |
| 3.1 Terms and definitions                                                                                                                            | 1         |
| 3.2 Abbreviated terms                                                                                                                                | 4         |
| 3.3 Symbols                                                                                                                                          | 4         |
| <b>4 Conventions</b>                                                                                                                                 | <b>6</b>  |
| 4.1 Conformance language                                                                                                                             | 6         |
| 4.2 Operators                                                                                                                                        | 6         |
| 4.2.1 Arithmetic operators                                                                                                                           | 6         |
| 4.2.2 Logical operators                                                                                                                              | 6         |
| 4.2.3 Relational operators                                                                                                                           | 6         |
| 4.2.4 Precedence order of operators                                                                                                                  | 6         |
| 4.2.5 Mathematical functions                                                                                                                         | 7         |
| <b>5 Buffer model</b>                                                                                                                                | <b>7</b>  |
| 5.1 General system block diagram                                                                                                                     | 7         |
| 5.2 Influencing variables on the required buffer sizes                                                                                               | 8         |
| 5.3 Role of the buffer model                                                                                                                         | 9         |
| <b>6 Interpretation of Bayer data</b>                                                                                                                | <b>9</b>  |
| <b>Annex A (normative) Profiles, levels and sublevels</b>                                                                                            | <b>11</b> |
| <b>Annex B (normative) Packet-based JPEG XS decoder model</b>                                                                                        | <b>25</b> |
| <b>Annex C (normative) Packet-based constant bit rate buffer model</b>                                                                               | <b>31</b> |
| <b>Annex D (informative) Encoder model, latency bounds and codestream conformance properties for the packet-based constant bit rate buffer model</b> | <b>37</b> |
| <b>Annex E (informative) JPEG XS latency analysis</b>                                                                                                | <b>42</b> |
| <b>Bibliography</b>                                                                                                                                  | <b>49</b> |

## Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of document should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see [www.iso.org/directives](http://www.iso.org/directives) or [www.iec.ch/members\\_experts/refdocs](http://www.iec.ch/members_experts/refdocs)).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see [www.iso.org/patents](http://www.iso.org/patents)) or the IEC list of patent declarations received (see [patents.iec.ch](http://patents.iec.ch)).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see [www.iso.org/iso/foreword.html](http://www.iso.org/iso/foreword.html). In the IEC, see [www.iec.ch/understanding-standards](http://www.iec.ch/understanding-standards).

This document was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*.

This second edition cancels and replaces the first edition (ISO/IEC 21122-2:2019), which has been technically revised.

The main changes are as follows:

- addition of new profiles to compress colour filter array images (CFA images), to allow mathematically lossless image compression, and to compress 4:2:0 colour sampled images.

A list of all parts in the ISO/IEC 21122 series can be found on the ISO and IEC websites.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at [www.iso.org/members.html](http://www.iso.org/members.html) and [www.iec.ch/national-committees](http://www.iec.ch/national-committees).

## Introduction

This document is part of a series of standards for a low-latency lightweight image coding system, denoted as JPEG XS.

While ISO/IEC 21122-1 specifies a full set of compression coding tools needed to satisfy all of the requirements of JPEG XS, a targeted application can often work with a simpler and reduced set of coding tools, and with or without tighter constraints, to meet its targeted goals. For this reason, profiles, levels, and sublevels are defined in this document. These three concepts facilitate partial and reduced complexity implementations of ISO/IEC 21122-1 for such specific application use cases, while also safeguarding interoperability.

This document specifies a limited number of profiles to represent interoperability subsets of the codestream syntax specified in ISO/IEC 21122-1 with each profile serving specific application use cases. In other word, profiles select a subset of the available coding tools. In addition, levels and sublevels provide limits to the maximum throughput in respectively the encoded (codestream) and the decoded (spatial/pixel) domains. In this way, profiles, levels and sublevels allow designing cost-efficient implementations that serve the needs of the desired applications.

In addition to being light-weight, another major requirement of JPEG XS is to allow low end-to-end latency, limited to a fraction of the frame size. To ensure this low-latency property, this document also specifies a buffer model, consisting of a decoder model and a transmission channel model. The models show the interaction of a hypothetical reference decoder, including its smoothing buffer with a constant bitrate channel feeding this buffer. The size of the decoder smoothing buffer is computed from the profile, level, and sublevel. Codestreams are formed such that the buffer of a decoder, operating according to this buffer model, never overflows or underflows. In effect, the buffer model provides encoders with the necessary information to generate codestreams that can be decoded by an arbitrary decoder implementation, ensuring system interoperability.

In addition to the size of the decoder smoothing buffer, end-to-end latency also depends on the latency inherent to each processing step of the encoding-decoding chain whose methods are described in ISO/IEC 21122-1. To help implementers estimate the latency of their device, this document gives extra information on the minimum latency that can be achieved by the different methods described in ISO/IEC 21122-1.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC 21122-2:2022

# Information technology — JPEG XS low-latency lightweight image coding system —

## Part 2: Profiles and buffer models

### 1 Scope

This document defines a number of subsets of the syntax specified in ISO/IEC 21122-1 as profiles. It also defines lower bounds on the throughput in the decoded domain via levels and the encoded domain via sublevels that a conforming decoder implementation shall support. Furthermore, it defines a buffer model to ensure interoperability between implementations in the presence of a latency constraint.

### 2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO/IEC 21122-1, *JPEG XS low-latency lightweight image coding system — Part 1: Core coding system*

### 3 Terms, definitions, symbols and abbreviated terms

#### 3.1 Terms and definitions

For the purposes of this document, the terms and definitions given in ISO/IEC 21122-1 and the following apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- ISO Online browsing platform: available at <https://www.iso.org/obp>
- IEC Electropedia: available at <https://www.electropedia.org/>

##### 3.1.1

##### **blanking codestream fragment**

placeholder *codestream fragment* representing blanking periods

##### 3.1.2

##### **buffer model**

combination of a *decoder model* and a *channel model* whose behaviour can be defined by a set of parameters

##### 3.1.3

##### **buffer model instance**

specific configuration of a *buffer model* specified by the assignment of well-defined values to the buffer model parameters

##### 3.1.4

##### **channel model**

model describing the temporal behaviour of the *transmission channel* connecting an encoder and a decoder

**3.1.5**

**coded codestream fragment**

continuous sequence of bits in the codestream containing exactly one packet body and a well-defined number of packet headers, markers and marker segments

**3.1.6**

**codestream fragment**

either *coded codestream fragment*, or *blanking codestream fragment*

**3.1.7**

**cycle**

single clock period of an encoder or decoder clocked implementation

**3.1.8**

**decoder model**

combination of a *decoder unit* and a *decoder smoothing buffer*

**3.1.9**

**decoder smoothing buffer**

memory buffer that is used to level out changes in the number of bits read by a *decoder unit* per time unit

**3.1.10**

**decoder unit**

module reading a variable number of bits per time unit to generate decoded output *pixels* with a fixed rate

**3.1.11**

**decomposition level**

set of wavelet coefficients resulting from a particular *level* of recursive application of a wavelet transform

**3.1.12**

**encoder model**

combination of an *encoder unit* and an *encoder smoothing buffer*

**3.1.13**

**encoder smoothing buffer**

memory buffer that is used to level out changes in the number of bits generated by an *encoder unit* per time unit

**3.1.14**

**encoder unit**

module transforming a sequence of input *pixels* with constant rate into a conforming codestream, producing a bit sequence with variable number of bits generated per time unit

**3.1.15**

**fill level**

number of bits stored in the encoder or *decoder smoothing buffer*

**3.1.16**

**horizontal blanking period**

timespan expressed in units of the grid point sampling rate between the last *pixel* of an image line — not being the last line of an image — and the first pixel of the next image line

**3.1.17****level**

defined set of constraints on the amount of decoded *samples* to be processed by an encoder or decoder, both in the spatial and time dimensions

Note 1 to entry: The same set of levels is defined for all profiles. Individual implementations may, within the specified constraints, support a different level for each supported profile.

**3.1.18****nominal bits per pixel value**

mean number of bits allocated per encoded *pixel* which is used to derive the *sublevel* constraints by assuming an image with well-defined dimensions and frame rate derived from the *level*

**3.1.19****profile**

specified subset of the codestream syntax together with admissible parameter values

**3.1.20****sampling grid point**

position on the *sample grid*, specified by integer horizontal and vertical offset relative to the origin of the sample grid

**3.1.21****smoothing buffer unit**

*level* and *sublevel* dependent number of bits by which the smoothing buffer size of the *decoder model* is specified

**3.1.22****start of transmission****SoT**

time at which the *transmission channel* starts transmission relative to the start of encoding of the first *codestream fragment* of a codestream

**3.1.23****sublevel**

defined set of constraints on the amount of codestream bits to be processed by an encoder or decoder, per unit of time, per column, and per image

Note 1 to entry: The same set of sublevels is defined for all profiles. Individual implementations may, within the specified constraints, support a different sublevel for each supported profile.

**3.1.24****transmission channel**

facility transferring bits from a source entity to a target entity

**3.1.25****transmission channel capacity**

maximum number of bits per time unit that a *transmission channel* can transfer from a source entity to a target entity

**3.1.26****vertical blanking period**

timespan in units of the grid point sampling rate between the last line of an image — including the *horizontal blanking periods* — and the first line of the next image

### 3.2 Abbreviated terms

|      |                                     |
|------|-------------------------------------|
| bpp  | bits per pixel                      |
| CFA  | colour filter array                 |
| DWT  | discrete wavelet transform          |
| IDWT | inverse discrete wavelet transform  |
| RCT  | reversible colour transform         |
| IRCT | inverse reversible colour transform |

### 3.3 Symbols

|                             |                                                                                                                                                                                     |
|-----------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| $C(i)$                      | codestream $i$                                                                                                                                                                      |
| $D_{\text{c2d}}$            | number of clock cycles between the first bit written into the decoding smoothing buffer and the decoding start of the first codestream fragment of a stream of codestream fragments |
| $F_{\text{first}}(C(i))$    | first codestream fragment of codestream $C(i)$                                                                                                                                      |
| $F_{\text{last}}(C(i))$     | last codestream fragment of codestream $C(i)$                                                                                                                                       |
| $H_{\text{f}}$              | height of the image in sampling grid points                                                                                                                                         |
| $H_{\text{max}}$            | maximum picture height in sampling grid points                                                                                                                                      |
| $L_{\text{max}}$            | maximum number of sampling grid points per image                                                                                                                                    |
| $l_{\text{enc}}(t)$         | fill level of the encoding smoothing buffer in bits at the end of cycle $t$                                                                                                         |
| $l_{\text{dec}}(t)$         | fill level of the decoding smoothing buffer in bits at the end of cycle $t$                                                                                                         |
| $l_{\text{enc,max}}$        | capacity in bits of the encoding smoothing buffer                                                                                                                                   |
| $l_{\text{dec,max}}$        | capacity in bits of the decoding smoothing buffer                                                                                                                                   |
| $\tilde{l}_{\text{dec}}(t)$ | number of bits that can be read from the decoding smoothing buffer in cycle $t$                                                                                                     |
| $l_{\text{sum}}(t)$         | sum of encoder and decoder smoothing buffer fill level in bits at cycle $t$                                                                                                         |
| $\mathbb{N}$                | all integer numbers being strictly larger than zero                                                                                                                                 |
| $\mathbb{N}_0$              | all integer numbers being greater than or equal to zero                                                                                                                             |
| $N_{\text{b,x}}$            | size of the horizontal blanking line in sampling grid point clock periods                                                                                                           |
| $N_{\text{b,y}}$            | size of the vertical blanking period in sampling grid lines                                                                                                                         |
| $N_{\text{bpp}}$            | nominal number of bits allocated per pixel for compression                                                                                                                          |
| $N_{\text{c}}$              | number of components in an image                                                                                                                                                    |
| $N_{\text{cg}}(f)$          | number of coefficient groups within codestream fragment $f$                                                                                                                         |
| $N_{\text{cg,hz}}$          | number of coefficient groups associated to a codestream fragment representing a horizontal blanking period                                                                          |

|                        |                                                                                                          |
|------------------------|----------------------------------------------------------------------------------------------------------|
| $N_{cg,vt}$            | number of coefficient groups associated to a codestream fragment representing a vertical blanking period |
| $N_f(i)$               | number of codestream fragments within a codestream $i$                                                   |
| $N_g$                  | number of coefficients in a code group                                                                   |
| $N_{L,x}$              | number of horizontal decomposition levels                                                                |
| $N_{L,y}$              | number of vertical decomposition levels                                                                  |
| $N_{p,x}$              | number of precincts per sampling grid line                                                               |
| $N_{p,y}$              | number of precincts per sampling grid column                                                             |
| $N_{sbu}$              | number of decoder smoothing buffer units for a given profile                                             |
| $\mathbb{Q}$           | set of rational numbers                                                                                  |
| $r_{dec}(t)$           | number of bits read and removed from the decoder smoothing buffer in clock cycle $t$                     |
| $R_{trans}$            | transmission channel capacity, expressed in bits per cycle (having a duration of $T$ )                   |
| $R_{t,max}(l_m, l_s)$  | maximum admissible encoded throughput in bits per second for a given level                               |
| $R_{s,max}$            | maximum grid point sample rate (in samples per second) at decoder output                                 |
| $S_{bits}(f)$          | number of bits forming the codestream fragment $f$                                                       |
| $S_{c,max}$            | targeted maximum number of bytes of an encoded codestream                                                |
| $S_{sbu}(l_m, l_s)$    | size of the smoothing buffer unit in bytes for level $l_m$ and sublevel $l_s$                            |
| $S_{sbo}(p)$           | smoothing buffer offset in bits for a profile $p$                                                        |
| $S_{sl,max}(l_m, l_s)$ | maximum size of an encoded codestream in bytes of level $l_m$ and sublevel $l_s$                         |
| $s_x[i]$               | sampling factor of component $i$ in horizontal direction                                                 |
| $s_y[i]$               | sampling factor of component $i$ in vertical direction                                                   |
| $T_{enc}$              | clock period defining the frequency by which code groups are processed by an encoder                     |
| $T_{dec}$              | clock period defining the frequency by which code groups are processed by a decoder                      |
| $t_{enc,write}(f)$     | timestamp in cycles at which the codestream fragment $f$ is written to the encoder smoothing buffer      |
| $t_{dec,start}(f)$     | timestamp in cycles at which decoder starts decoding codestream fragment $f$                             |
| $t_{dec,read}(f)$      | timestamp in cycles at which codestream fragment $f$ is removed from the decoder smoothing buffer        |
| $Tbmd$                 | buffer model type                                                                                        |
| $W_c[i]$               | width of component $i$ in samples                                                                        |
| $W_{c,max}$            | maximum column width in sampling grid points for a given profile                                         |
| $w_{dec}(t)$           | number of bits written into the decoder smoothing buffer in clock cycle $t$                              |

|              |                                               |
|--------------|-----------------------------------------------|
| $W_f$        | width of the image in sampling grid points    |
| $W_{\max}$   | maximum picture width in sampling grid points |
| $\mathbb{Z}$ | set of all integer numbers                    |

## 4 Conventions

### 4.1 Conformance language

The keyword "reserved" indicates a provision that is not specified at this time, shall not be used, and may be specified in the future. The keyword "forbidden" indicates "reserved" and in addition indicates that the provision will never be specified in the future.

### 4.2 Operators

NOTE Many of the operators used in document are similar to those used in the C programming language.

#### 4.2.1 Arithmetic operators

|   |                                                                             |
|---|-----------------------------------------------------------------------------|
| + | addition                                                                    |
| − | subtraction (as a binary operator) or negation (as a unary prefix operator) |
| × | multiplication                                                              |
| / | division without truncation or rounding                                     |

#### 4.2.2 Logical operators

|    |             |
|----|-------------|
|    | logical OR  |
| && | logical AND |
| !  | logical NOT |

#### 4.2.3 Relational operators

|    |                          |
|----|--------------------------|
| >  | greater than             |
| ≥  | greater than or equal to |
| <  | less than                |
| ≤  | less than or equal to    |
| == | equal to                 |
| != | not equal to             |

#### 4.2.4 Precedence order of operators

Operators are listed in descending order of precedence. If several operators appear in the same line, they have equal precedence. When several operators of equal precedence appear at the same level in an expression, evaluation proceeds according to the associativity of the operator either from right to left or from left to right.

| Operators  | Type of operation        | Associativity |
|------------|--------------------------|---------------|
| ()         | expression               | left to right |
| []         | indexing of arrays       | left to right |
| -          | unary negation           |               |
| ×, /       | multiplication, division | left to right |
| +, -       | addition and subtraction | left to right |
| <, >, ≤, ≥ | relational               | left to right |
| &          | bitwise AND              | left to right |
|            | bitwise OR               | left to right |


#### 4.2.5 Mathematical functions

|                     |                                                                                         |
|---------------------|-----------------------------------------------------------------------------------------|
| $\lceil x \rceil$   | ceil of $x$ : returns the smallest integer that is greater than or equal to $x$         |
| $\lfloor x \rfloor$ | floor of $x$ : returns the largest integer that is less than or equal to $x$            |
| $ x $               | absolute value of $x$ , $ x $ equals $-x$ for $x < 0$ , otherwise $x$                   |
| $\text{sign}(x)$    | sign of $x$ , 0 if $x$ is 0, +1 if $x$ is positive, -1 if $x$ is negative               |
| $\xi(t)$            | step function $\xi(t) = \begin{cases} 1 & t \geq 0 \\ 0 & \text{otherwise} \end{cases}$ |
| $\max_i(x_i)$       | maximum of a sequence of numbers $[x_i]$ enumerated by the index $i$                    |

## 5 Buffer model

### 5.1 General system block diagram

The JPEG XS coding system addresses applications where coded images are transferred from a source to a target, as shown in [Figure 1](#). To this end, the encoder is compressing a continuous stream of input pixels into a sequence of bits. These bits are forwarded by means of a transmission channel to the decoder that decompresses the bits to produce a continuous stream of output pixels.



**Figure 1 — General system block diagram**

The time instances at which the encoder processes each pixel are determined by an encoding clock. Similarly, the time instances at which the decoder produces each output pixel are determined by a decoding clock. Both clocks are generated by the system.

**NOTE** In implementations, these clocks can be the same or differ in both frequency and phase. The presented model is independent of whether clocks are synchronized or not.

In accordance with ISO/IEC 21122-1, the pixels of an image are translated into coefficient groups represented as code groups in the codestream. The number of bits necessary to code these code groups may vary from group to group. As a consequence, the encoder writes encoded bits at a variable rate into the encoder smoothing buffer. Similarly, the decoder reads the codestream at a variable rate from the decoder smoothing buffer.

In case the maximum bit rate of the transmission channel is below the peak bit rate generated by the encoder, an encoder smoothing buffer is necessary to decouple generation of bits by the encoder from transmission of bits over the transmission channel. Similarly, a decoder smoothing buffer needs to be provided that decouples the arrival of bits at the rate afforded by the transmission channel and the consumption of bits by the decoder per clock.

Correct operation requires that the decoder buffer never overflows. This is because the decoder is not able to pause the arrival of bits from the transmission channel. Moreover, a buffer underflow in the decoder buffer needs to be avoided. This is because the decoder is required to output pixels in accordance with the timing of its output interface. Hence it needs to be ensured that the bits to be read from the decoding buffer to produce the next pixel in accordance with the decoding clock are available in this decoding buffer.

## 5.2 Influencing variables on the required buffer sizes

Avoiding any buffer overflow or underflow, as discussed in [subclause 5.1](#), requires sizing the decoder smoothing buffer properly. Moreover, the time at which decoding starts is delayed relative to the starting time of encoding and the start of transmission needs to be carefully set. Those values are influenced by many system parameters, for example:

- The maximum transmission channel bit rate.
- The granularity at which the encoder writes the encoded data and the decoder reads the encoded data.

- The rate control strategy applied by the encoder.

These dependencies cause that encoders and decoders are only interoperable in well-defined conditions. Defining these conditions is the purpose of the buffer model defined in [Annex B](#) and [Annex C](#).

### 5.3 Role of the buffer model


The core coding system defined in ISO/IEC 21122-1 can be implemented on a large variety of platforms using many different implementation strategies. Thus, interoperability cannot be achieved by precisely specifying the temporal behaviour of a conforming decoding implementation. Instead, the buffer model defines a simplified decoder model. Interoperability is then achieved by mandating that a conforming decoder shall decode all bit streams being decodable by the simplified decoder model. Similarly, a conforming encoder shall not create bit streams that cannot be decoded by the simplified decoder model.

To this end, [Annex B](#) defines a generic JPEG XS decoder model that precisely defines the temporal behaviour of the decoder model assuming a processing granularity of codestream packets. While such a model already defines some fundamental properties of the decodable codestreams, it is still not sufficient to ensure interoperability. The reason is that otherwise codestreams could be constructed that would only be decodable by the decoder model if the transmission channel could transport bits arbitrarily fast. In practice, this is obviously not the case. Consequently, interoperability also requires defining a channel model over which an encoder sends the codestreams to the decoder.

[Annex C](#) defines such a channel model assuming a transmission channel with a fixed upper bit rate that is related to the target compression ratio. Together with the decoder model of [Annex B](#), it defines the packet-based constant bit rate buffer model. It describes the conditions for a low latency interoperability between any conforming encoder and any decoder. These conditions are expressed by buffer model parameters that are specified by the profiles and levels defined in [Annex A](#). The properties of such conforming implementations are exemplified in [Annex D](#). Since these properties are direct consequences of [Annex B](#) and [Annex C](#), [Annex D](#) is informative only.

## 6 Interpretation of Bayer data

ISO/IEC 21122-1 defines coding tools and signalling for compression of Bayer-type CFA image data. According to this specification, each sampling grid point represents a super-pixel of four sensor elements containing at least one sample of each component. Thus Bayer data is interpreted as an image having four components, where each sampling grid point describes four spatially disjoint sensor elements (one element per Bayer channel).



Squares represent individual sensor elements and circles represent sampling grid points. Groups of four sensor elements overlapping with the same sampling grid point form one super-pixel.

**Figure 2 — Example of the interpretation of a GRBG Bayer-type CFA image**

Moreover, regardless of the Bayer sensor spatial subpixel arrangement, the Star-Tetrix color transform of ISO/IEC 21122-1 defines a strict order on the components assigning the red channel to component 0, the green channels to components 1 and 2, and the blue channel to component 3. The spatial subpixel arrangement is signalled by the CRG marker. [Figure 2](#) shows only one of the four potential subpixel arrangements of a Bayer-type CFA.

## Annex A (normative)

### Profiles, levels and sublevels

#### A.1 General

Profiles, levels and sublevels specify restrictions on codestreams and hence limits on the capabilities needed to decode the codestreams. Profiles, levels and sublevels may also be used to indicate interoperability points between individual decoder implementations.


Each profile specifies a subset of algorithmic features and limits on their parameterization that shall be supported by all decoders conforming to that profile. Encoders are not required to make use of all features supported in a profile.

The combination of a level and a sublevel defines a lower bound on the throughput a conforming decoder implementation shall support. To this end, the level gives upper bounds for the image parameters in the decoded domain, namely the maximum image width, the maximum image height and the maximum number of sampling grid points to be processed per second.

The sublevel defines upper bounds in the coded domain, such as the nominal bits per pixel value allocated for an encoded image having maximum width and height. In combination with the constraints set by the levels in the decoded domain, this allows the derivation of upper bounds on the admissible encoded image size and the upper number of bits a decoder is required to decode per second. Moreover, it defines the decoder smoothing buffer unit, whose size is specified in [subclause A.4.1](#).

By these means, the decoding smoothing buffer size can be derived from the profile. In combination with the tool selection performed by a profile, this allows to control the complexity of a decoder implementation.

[Figure A.1](#) depicts the relation between level, sublevel, profile and the corresponding constraints they impose.



**Figure A.1 — Relationship between the different conformance constraints and the impact on the decoder complexity**

## A.2 Profiles

### A.2.1 Definitions of profiles

Profiles specify subsets of coding tools which conforming decoders shall support. Moreover, profiles limit the permitted parameter values. Consequently, profiles are differentiated along the following features:

- decoder smoothing buffer size expressed in smoothing buffer units<sup>1</sup> ( $N_{\text{sbu}}$ );
- smoothing buffer offset<sup>2</sup> ( $S_{\text{sbo}}$ );
- component bit precision ( $B[i]$ );
- internal precision ( $Bw$ , see ISO/IEC 21122-1);
- number of fractional bits for DWT coefficients ( $Fq$ , see ISO/IEC 21122-1);
- non-linear transform;
- raw-mode selection per packet flag ( $Rl$ , see ISO/IEC 21122-1);
- chroma sampling formats;
- colour transformation ( $Cpih$ , see ISO/IEC 21122-1);
- size and extent of the colour transformation<sup>3</sup> ( $Cf$ , see ISO/IEC 21122-1);
- number of vertical wavelet decompositions;
- number of horizontal wavelet decompositions<sup>4</sup>;
- number of components for which to suppress the wavelet decomposition ( $Sd$ , see ISO/IEC 21122-1);

- supported quantizer types ( $Q_{pih}$ , see ISO/IEC 21122-1);
- maximum column width<sup>5</sup> ( $Cw$ , see ISO/IEC 21122-1);
- slice height
- buffer model ( $Tbmd$ )<sup>6</sup>
- long precinct header enforcement flag ( $Lh$ , see ISO/IEC 21122-1).

NOTE 1 The smoothing buffer unit size is determined by the maximum column width in Light-Subline profile and the maximum image width in other profiles. See [Formulae \(A.3\)](#) and [\(A.4\)](#).

NOTE 2 The commonly used value of 1024 bits (128 bytes) has been derived from a typical size of the picture header without any extension markers.

NOTE 3 The size and extent of the colour transformation is signalled in the CTS marker when  $C_{pih}$  is set to 3 (see ISO/IEC 21122-1). For other values of  $C_{pih}$ , the CTS marker is not present.

NOTE 4 As defined in ISO/IEC 21122-1, the number of vertical wavelet decompositions is always lower than or equal to the number of horizontal wavelet decompositions.

NOTE 5 The column width in sampling grid points is given by 
$$\begin{cases} 8 \times Cw \times \max_i(s_x[i]) \times 2^{N_{L,x}} & \text{if } Cw > 0, \\ W_f & \text{otherwise} \end{cases}$$

where  $Cw$  is indicated in the picture header (see ISO/IEC 21122-1),  $W_f$  is the image width,  $s_x[i]$  is the sampling factor for component  $i$ , and  $N_{L,x}$  is the number of horizontal wavelet decompositions.

NOTE 6  $Tbmd = 2$  includes  $Tbmd = 1$ . This means that a decoder that supports  $Tbmd = 2$  automatically also supports  $Tbmd = 1$ .

For all profiles, the bit precision  $B[i]$  ( $0 \leq i < N_c$ ) of all components, shall be identical.

Profile settings that allow the choice between more than one value shall always be selected in accordance with ISO/IEC 21122-1.

[Table A.1](#), [Table A.2](#), [Table A.3](#), [Table A.4](#), and [Table A.5](#) list all of the profiles specified in this document.

**Table A.1 — JPEG XS Main profiles**

| Profile                                                                                                                                                          | Main<br>420.12 | Main<br>422.10 | Main<br>444.12          | Main<br>4444.12                               |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|----------------|-------------------------|-----------------------------------------------|
| Number $N_{sbu}$ of smoothing buffer units of the decoder model                                                                                                  | 16             | 16             | 16                      | 16                                            |
| Smoothing buffer offset $S_{sbo}$ in bits                                                                                                                        | 1 024          | 1 024          | 1 024                   | 1 024                                         |
| Component bit precision ( $B[i]$ )                                                                                                                               | 8, 10, 12      | 8, 10          | 8, 10, 12               | 8, 10, 12                                     |
| Internal precision ( $Bw$ )                                                                                                                                      | 20             | 20             | 20                      | 20                                            |
| # fractional bits for DWT coefficients ( $Fq$ )                                                                                                                  | 8              | 8              | 8                       | 8                                             |
| Non-linear transform                                                                                                                                             | Disallowed     | Disallowed     | Disallowed              | Disallowed                                    |
| Raw-mode selection per packet flag ( $Rl$ )                                                                                                                      | 0              | 0              | 0                       | 0                                             |
| Chroma sampling formats                                                                                                                                          | 4:2:0          | 4:0:0<br>4:2:2 | 4:0:0<br>4:2:2<br>4:4:4 | 4:0:0<br>4:2:2<br>4:4:4<br>4:2:2:4<br>4:4:4:4 |
| <sup>a</sup> One column of full width if number of vertical decompositions larger than 0, otherwise any column width conforming with ISO/IEC 21122-1 is allowed. |                |                |                         |                                               |

Table A.1 (continued)

| Profile                                                                                                                                                          | Main<br>420.12           | Main<br>422.10                                                                          | Main<br>444.12                                                                          | Main<br>444.12                                                                          |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------|-----------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------|
| Colour transformation ( <i>Cp</i> <i>ih</i> )                                                                                                                    | 0 (None)                 | 0 (None)                                                                                | 0 (None) for any sampling format, or optionally 1 (RCT) for 4:4:4                       | 0 (None) for any sampling format, or optionally 1 (RCT) for 4:4:4 and 4:4:4:4           |
| Number of vertical decompositions                                                                                                                                | 1                        | 0, 1                                                                                    | 0, 1                                                                                    | 0, 1                                                                                    |
| Number of horizontal decompositions                                                                                                                              | [1-5]                    | [1-5]                                                                                   | [1-5]                                                                                   | [1-5]                                                                                   |
| Number components with suppressed decomposition ( <i>Sd</i> )                                                                                                    | 0                        | 0                                                                                       | 0                                                                                       | 0                                                                                       |
| Quantizer type ( <i>Qp</i> <i>ih</i> )                                                                                                                           | 0 (DZQ)<br>1 (Uniform)   | 0 (DZQ)<br>1 (Uniform)                                                                  | 0 (DZQ)<br>1 (Uniform)                                                                  | 0 (DZQ)<br>1 (Uniform)                                                                  |
| Column mode ( <i>Cw</i> )                                                                                                                                        | One column of full width | One column except when the number of vertical decomposition levels is zero <sup>a</sup> | One column except when the number of vertical decomposition levels is zero <sup>a</sup> | One column except when the number of vertical decomposition levels is zero <sup>a</sup> |
| Slice height in number of image rows                                                                                                                             | 16                       | 16                                                                                      | 16                                                                                      | 16                                                                                      |
| Buffer model ( <i>Tbmd</i> )                                                                                                                                     | 1, 2                     | 1, 2                                                                                    | 1, 2                                                                                    | 1, 2                                                                                    |
| Long precinct header enforcement flag ( <i>Lh</i> )                                                                                                              | 0                        | 0                                                                                       | 0                                                                                       | 0                                                                                       |
| <sup>a</sup> One column of full width if number of vertical decompositions larger than 0, otherwise any column width conforming with ISO/IEC 21122-1 is allowed. |                          |                                                                                         |                                                                                         |                                                                                         |

Table A.2 — JPEG XS Light profiles

| Profile                                                                | Light<br>422.10 | Light<br>444.12                                                   | Light-Subline<br>422.10 |
|------------------------------------------------------------------------|-----------------|-------------------------------------------------------------------|-------------------------|
| Number $N_{\text{sbu}}$ of smoothing buffer units of the decoder model | 4               | 4                                                                 | 2                       |
| Smoothing buffer offset $S_{\text{sbo}}$ in bits                       | 1 024           | 1 024                                                             | 1 024                   |
| Component bit precision ( $B[i]$ )                                     | 8, 10           | 8, 10, 12                                                         | 8, 10                   |
| Internal precision ( $Bw$ )                                            | 20              | 20                                                                | 20                      |
| # fractional bits for DWT coefficients ( $Fq$ )                        | 8               | 8                                                                 | 8                       |
| Non-linear transform                                                   | Disallowed      | Disallowed                                                        | Disallowed              |
| Raw-mode selection per packet flag ( <i>Rl</i> )                       | 0               | 0                                                                 | 0                       |
| Chroma sampling formats                                                | 4:0:0<br>4:2:2  | 4:0:0<br>4:2:2<br>4:4:4                                           | 4:0:0<br>4:2:2          |
| Colour transformation                                                  | 0 (None)        | 0 (None) for any sampling format, or optionally 1 (RCT) for 4:4:4 | 0 (None)                |
| Number of vertical decompositions                                      | 0, 1            | 0, 1                                                              | 0                       |
| Number of horizontal decompositions                                    | [1-5]           | [1-5]                                                             | [1-5]                   |
| Number components with suppressed decomposition ( <i>Sd</i> )          | 0               | 0                                                                 | 0                       |

Table A.2 (continued)

| Profile                                             | Light<br>422.10                        | Light<br>444.12                        | Light-Subline<br>422.10                   |
|-----------------------------------------------------|----------------------------------------|----------------------------------------|-------------------------------------------|
| Quantizer type ( <i>Qp<sub>ih</sub></i> )           | 0 (DZQ)                                | 0 (DZQ)                                | 0 (DZQ)<br>1 (Uniform)                    |
| Column mode ( <i>C<sub>w</sub></i> )                | Only one column permitted (full width) | Only one column permitted (full width) | Maximum column width of 2 048 grid points |
| Slice height in number of image rows                | 16                                     | 16                                     | 16                                        |
| Buffer model ( <i>Tb<sub>md</sub></i> )             | 1, 2                                   | 1, 2                                   | 1, 2                                      |
| Long precinct header enforcement flag ( <i>Lh</i> ) | 0                                      | 0                                      | 0                                         |

Table A.3 — JPEG XS High profiles

| Profile                                                                | High<br>444.12                                                                          | High<br>4444.12                                                                         |
|------------------------------------------------------------------------|-----------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------|
| Number $N_{\text{sbu}}$ of smoothing buffer units of the decoder model | 16                                                                                      | 16                                                                                      |
| Smoothing buffer offset $S_{\text{sbo}}$ in bits                       | 1 024                                                                                   | 1 024                                                                                   |
| Component bit precision ( $B[i]$ )                                     | 8, 10, 12                                                                               | 8, 10, 12                                                                               |
| Internal precision ( $Bw$ )                                            | 20                                                                                      | 20                                                                                      |
| # fractional bits for DWT coefficients ( $Fq$ )                        | 8                                                                                       | 8                                                                                       |
| Non-linear transform                                                   | Disallowed                                                                              | Disallowed                                                                              |
| Raw-mode selection per packet flag ( <i>RI</i> )                       | 0                                                                                       | 0                                                                                       |
| Chroma sampling formats                                                | 4:0:0<br>4:2:2<br>4:4:4                                                                 | 4:0:0<br>4:2:2<br>4:4:4<br>4:2:2:4<br>4:4:4:4                                           |
| Colour transformation                                                  | 0 (None) for any sampling format, or optionally 1 (RCT) for 4:4:4                       | 0 (None) for any sampling format, or optionally 1 (RCT) for 4:4:4 and 4:4:4:4           |
| Number of vertical decompositions                                      | 0, 1, 2                                                                                 | 0, 1, 2                                                                                 |
| Number of horizontal decompositions                                    | [1-5]                                                                                   | [1-5]                                                                                   |
| Number components with suppressed decomposition ( <i>Sd</i> )          | 0                                                                                       | 0                                                                                       |
| Quantizer type ( <i>Qp<sub>ih</sub></i> )                              | 0 (DZQ)<br>1 (Uniform)                                                                  | 0 (DZQ)<br>1 (Uniform)                                                                  |
| Column mode ( <i>C<sub>w</sub></i> )                                   | One column except when the number of vertical decomposition levels is zero <sup>a</sup> | One column except when the number of vertical decomposition levels is zero <sup>a</sup> |
| Slice height in number of image rows                                   | 16                                                                                      | 16                                                                                      |
| Buffer model ( <i>Tb<sub>md</sub></i> )                                | 1, 2                                                                                    | 1, 2                                                                                    |
| Long precinct header enforcement flag ( <i>Lh</i> )                    | 0                                                                                       | 0                                                                                       |

<sup>a</sup> One column of full width if number of vertical decompositions larger than 0, otherwise any column width conforming with ISO/IEC 21122-1 is allowed.

Table A.4 — JPEG XS MLS profiles

| Profile                                                                                                                                                                                                                                                                                                      | MLS.12                                                                                  |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------|
| Number $N_{\text{sbu}}$ of smoothing buffer units of the decoder model                                                                                                                                                                                                                                       | Unconstrained                                                                           |
| Smoothing buffer offset $S_{\text{sbo}}$ in bits                                                                                                                                                                                                                                                             | n.a.                                                                                    |
| Component bit precision ( $B[i]$ )                                                                                                                                                                                                                                                                           | 8, 10, 12                                                                               |
| Internal precision ( $Bw$ )                                                                                                                                                                                                                                                                                  | Component precision                                                                     |
| # fractional bits for DWT coefficients ( $Fq$ )                                                                                                                                                                                                                                                              | 0                                                                                       |
| Non-linear transform                                                                                                                                                                                                                                                                                         | Disallowed                                                                              |
| Raw-mode selection per packet flag (RI)                                                                                                                                                                                                                                                                      | 0                                                                                       |
| Chroma sampling formats                                                                                                                                                                                                                                                                                      | 4:0:0<br>4:2:0<br>4:2:2<br>4:4:4<br>4:2:2:4<br>4:4:4:4                                  |
| Colour transformation                                                                                                                                                                                                                                                                                        | 0 (None) for any sampling format, or optionally 1 (RCT) for 4:4:4 and 4:4:4:4           |
| Number of vertical decompositions                                                                                                                                                                                                                                                                            | 0 (except for 4:2:0), 1, 2 <sup>b</sup>                                                 |
| Number of horizontal decompositions                                                                                                                                                                                                                                                                          | [1-5]                                                                                   |
| Number components with suppressed decomposition ( $Sa$ )                                                                                                                                                                                                                                                     | 0                                                                                       |
| Quantizer type ( $Qpih$ )                                                                                                                                                                                                                                                                                    | 0 (DZQ)<br>1 (Uniform)                                                                  |
| Column mode ( $Cw$ )                                                                                                                                                                                                                                                                                         | One column except when the number of vertical decomposition levels is zero <sup>a</sup> |
| Slice height in number of image rows                                                                                                                                                                                                                                                                         | 16                                                                                      |
| Buffer model ( $Tbmd$ )                                                                                                                                                                                                                                                                                      | 0 (Unconstrained)                                                                       |
| Long precinct header enforcement flag ( $Lh$ )                                                                                                                                                                                                                                                               | 0                                                                                       |
| <sup>a</sup> One column of full width if number of vertical decompositions larger than 0, otherwise any column width conforming with ISO/IEC 21122-1 is allowed.<br><sup>b</sup> Conforming with ISO/IEC 21122-1, zero (0) vertical decompositions cannot be used in combination with 4:2:0 chroma sampling. |                                                                                         |

Table A.5 — JPEG XS Bayer profiles

| Profile                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | LightBayer                                                 | MainBayer                                                  | HighBayer                                                  |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------|------------------------------------------------------------|------------------------------------------------------------|
| Number $N_{\text{sbu}}$ of smoothing buffer units of the decoder model                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      | 4                                                          | 8                                                          | 16                                                         |
| Smoothing buffer offset $S_{\text{sbo}}$ in bits                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 1 024                                                      | 1 024                                                      | 1 024                                                      |
| Component bit precision ( $B[i]$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | 10, 12, 14, 16                                             | 10, 12, 14, 16                                             | 10, 12, 14, 16                                             |
| Internal precision ( $Bw$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 | 18 if an NLT is used,<br>20 if no NLT is used <sup>a</sup> | 18 if an NLT is used,<br>20 if no NLT is used <sup>a</sup> | 18 if an NLT is used,<br>20 if no NLT is used <sup>a</sup> |
| # fractional bits for DWT coefficients ( $Fq$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | 6 if $Bw$ is 18,<br>8 if $Bw$ is 20 <sup>b</sup>           | 6 if $Bw$ is 18,<br>8 if $Bw$ is 20 <sup>b</sup>           | 6 if $Bw$ is 18,<br>8 if $Bw$ is 20 <sup>b</sup>           |
| Non-linear transform                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | None,<br>Quadratic,<br>Extended                            | None,<br>Quadratic,<br>Extended                            | None,<br>Quadratic,<br>Extended                            |
| Raw-mode selection per packet flag ( $RI$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 | 1 <sup>c</sup>                                             | 1                                                          | 1                                                          |
| Chroma sampling formats                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | Bayer pattern interpreted as 4-dimensional vectors         | Bayer pattern interpreted as 4-dimensional vectors         | Bayer pattern interpreted as 4-dimensional vectors         |
| Colour transformation ( $Cpih$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 3 (Star-Tetrix)                                            | 3 (Star-Tetrix)                                            | 3 (Star-Tetrix)                                            |
| Size and extent of the colour transformation ( $Cf$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       | 3 (Inline)                                                 | 0 (Full),<br>3 (Inline)                                    | 0 (Full),<br>3 (Inline)                                    |
| Number of vertical decompositions                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 0                                                          | 0, 1                                                       | 0, 1, 2                                                    |
| Number of horizontal decompositions                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | [1-5]                                                      | [1-5]                                                      | [1-5]                                                      |
| Number components with suppressed decomposition ( $Sd$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | 1                                                          | 1                                                          | 1                                                          |
| Quantizer type ( $Qpih$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   | 0 (DZQ)<br>1 (Uniform)                                     | 0 (DZQ)<br>1 (Uniform)                                     | 0 (DZQ)<br>1 (Uniform)                                     |
| Column mode ( $Cw$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | Disallowed                                                 | Disallowed                                                 | Disallowed                                                 |
| Slice height in number of image rows                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | 16                                                         | 16                                                         | 16                                                         |
| Buffer model ( $Tbmd$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     | 1, 2                                                       | 1, 2                                                       | 1, 2                                                       |
| Long precinct header enforcement flag ( $Lh$ )                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              | 0, 1                                                       | 0, 1                                                       | 0, 1                                                       |
| <sup>a</sup> The internal precision ( $Bw$ ) is selected in conformance with ISO/IEC 21122-1. The value 20 is used when the non-linear transform is not used (i.e. no NLT is marker is present), otherwise the value 18 is used.<br><sup>b</sup> The number of fractional bits for DWT coefficients ( $Fq$ ) is selected as specified in ISO/IEC 21122-1. The value 6 is used when $Bw$ is set to 18, while the value 8 is used when $Bw$ is set to 20.<br><sup>c</sup> In this profile, with zero vertical decompositions, the raw-mode selection per packet flag will not influence the resulting codestream. However, it is set to 1 to match with the MainBayer and HighBayer profiles. |                                                            |                                                            |                                                            |

Figure A.2 represents the relation of the profiles defined in Table A.1, Table A.2, Table A.3, Table A.4, and Table A.5 in terms of inclusivity. The Light422.10 profile is for instance contained in both the Main422.10 profile and the Light444.12 profile. The Main422.10 profile is again included in the Main444.12 profile, etc. Some profiles are not included in other profiles, like the Main420.12 and the MLS.12 profiles.

The Light and Light-Subline profiles are independent subsets of the Main profile. They need lower memory and logic resources, and allow for lower latency, at the expense of a lower compression efficiency.



The profile of a codestream defines the capabilities of a decoder implementation necessary to decode the image. This profile shall be indicated in the *Ppih* field in the picture header by the values defined in [Table A.7](#).

The *unrestricted* profile uses the full syntax defined in ISO/IEC 21122-1 without any further constraint. This *unrestricted* profile shall not be considered as a conformance point.

NOTE The *unrestricted* profile is not a conformance point because the syntax defined in ISO/IEC 21122-1 can evolve in the future.

**Table A.7 — Mapping of profiles to values of the *Ppjh* field in the picture header**

| Profile                       | <i>Ppjh</i>         |        |
|-------------------------------|---------------------|--------|
|                               | Binary              | Hex    |
| Unrestricted                  | 0000 0000 0000 0000 | 0x0000 |
| Light 422.10                  | 0001 0101 0000 0000 | 0x1500 |
| Light 444.12                  | 0001 1010 0000 0000 | 0x1A00 |
| Light-Subline 422.10          | 0010 0101 0000 0000 | 0x2500 |
| Main 420.12                   | 0011 0010 0100 0000 | 0x3240 |
| Main 422.10                   | 0011 0101 0100 0000 | 0x3540 |
| Main 444.12                   | 0011 1010 0100 0000 | 0x3A40 |
| Main 4444.12                  | 0011 1110 0100 0000 | 0x3E40 |
| High 444.12                   | 0100 1010 0100 0000 | 0x4A40 |
| High 4444.12                  | 0100 1110 0100 0000 | 0x4E40 |
| MLS.12                        | 0110 1110 1100 0000 | 0x6EC0 |
| LightBayer                    | 1001 0011 0000 0000 | 0x9300 |
| MainBayer                     | 1011 0011 0100 0000 | 0xB340 |
| HighBayer                     | 1100 0011 0100 0000 | 0xC340 |
| Reserved for ISO/IEC purposes | all other values    |        |

### A.3 Levels

Levels define a lower bound on the throughput in the decoded domain that a conforming decoder implementation shall support. Levels are defined along the maximum permissible sampling grid points per line, the maximum number of sampling grid points per column height, the maximum number of sampling grid points per image, and the maximum sampling rate of grid points per second. These levels apply to all the profiles defined. [Table A.8](#) defines all available levels.

**Table A.8 — JPEG XS levels**

| Level <sup>1</sup> | Maximum picture width $W_{\max}$ [sampling grid points] <sup>2</sup> | Max picture height $H_{\max}$ [sampling grid points] <sup>2</sup> | Max number of sampling grid points $L_{\max}$ per image [sampling grid points] <sup>2</sup> | Max grid point sample rate $R_{s,\max}$ [sampling grid points/s] <sup>2,3</sup> | Example resolutions for non-Bayer data                                                                  | Example resolutions for Bayer data [sensor elements @ framerate] <sup>4</sup>                             |
|--------------------|----------------------------------------------------------------------|-------------------------------------------------------------------|---------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------|
| 1k-1/<br>bayer2k-1 | 1 280                                                                | 5 120                                                             | 2 621 440                                                                                   | 83 558 400                                                                      | 1 280x720@60                                                                                            | 2 048x1 080@60<br>2 560x1 440@60                                                                          |
| 2k-1/<br>bayer4k-1 | 2 048                                                                | 8 192                                                             | 4 194 304                                                                                   | 133 693 440                                                                     | 1 280x720@120<br>1 920x1 080@30<br>1 920x1 080@60<br>2 048x1 536@30<br>2 048x2 048@30<br>2 048x1 080@60 | 2 560x1 440@120<br>3 840x2 160@30<br>3 840x2 160@60<br>4 096x3 072@30<br>4 096x4 096@30<br>4 096x2 160@60 |
| 4k-1/<br>bayer8k-1 | 4 096                                                                | 16 384                                                            | 8 912 896                                                                                   | 267 386 880                                                                     | 1 920x1 080@120<br>3 840x2 160@30<br>4 096x2 160@30                                                     | 3 840x2 160@120<br>7 680x4 320@30<br>8 192x4 320@30                                                       |

Table A.8 (continued)

| Level <sup>1</sup>   | Maximum picture width $W_{\max}$ [sampling grid points] <sup>2</sup> | Max picture height $H_{\max}$ [sampling grid points] <sup>2</sup> | Max number of sampling grid points $L_{\max}$ per image [sampling grid points] <sup>2</sup> | Max grid point sample rate $R_{s,\max}$ [sampling grid points/s] <sup>2,3</sup> | Example resolutions for non-Bayer data                                                                       | Example resolutions for Bayer data [sensor elements @ framerate] <sup>4</sup>                                      |
|----------------------|----------------------------------------------------------------------|-------------------------------------------------------------------|---------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------|
| 4k-2/<br>bayer8k-2   | 4 096                                                                | 16 384                                                            | 16 777 216                                                                                  | 534 773 760                                                                     | 1 920×1 080@240<br>3 840×2 160@60<br>4 096×3 072@30<br>4 096×4 096@30<br>4 096×2 160@60                      | 3840x2160@240<br>7 680x4 320@60<br>8 192x6 144@30<br>8 192x8 192@30<br>8 192x4 320@60                              |
| 4k-3/<br>bayer8k-3   | 4 096                                                                | 16 384                                                            | 16 777 216                                                                                  | 1 069 547 520                                                                   | 1 920×1 080@480<br>2 048×1 080@480<br>4 096×3 072@60<br>4 096×4 096@60<br>3 840×2 160@120<br>4 096×2 160@120 | 3840x2160@480<br>4 096x2 160@480<br>8 192x6 144@60<br>8 192x8 192@60<br>7 680x4 320@120<br>8 192x4 320@120         |
| 8k-1/<br>bayer16k-1  | 8 192                                                                | 32 768                                                            | 35 651 584                                                                                  | 1 069 547 520                                                                   | 3 840×2 160@120<br>7 680×4 320@30<br>8 192×4 320@30                                                          | 7 680x4 320@120<br>15 360x8 640@30<br>16 384x8 640@30                                                              |
| 8k-2/<br>bayer16k-2  | 8 192                                                                | 32 768                                                            | 67 108 864                                                                                  | 2 139 095 040                                                                   | 3 840×2 160@240<br>8 192×6 144@30<br>8 192×8 192@30<br>7 680×4 320@60<br>8 192×4 320@60                      | 7 680x4 320@240<br>16 384x12 288@30<br>16 384x16 384@30<br>15 360x8 640@60<br>16 384x8 640@60                      |
| 8k-3/<br>bayer16k-3  | 8 192                                                                | 32 768                                                            | 67 108 864                                                                                  | 4 278 190 080                                                                   | 3 840×2 160@480<br>4 096×2 160@480<br>8 192×6 144@60<br>8 192×8 192@60<br>7 680×4 320@120<br>8 192×4 320@120 | 7 680x4 320@480<br>8 192x4 320@480<br>16 384x12 288@60<br>16 384x16 384@60<br>15 360x8 640@120<br>16 384x8 640@120 |
| 10k-1/<br>bayer20k-1 | 10 240                                                               | 40 960                                                            | 104 857 600                                                                                 | 3 342 336 000                                                                   | 10 240×7 680@30<br>10 240×10 240@30<br>10 240×4 320@60<br>10 240×5 400@60                                    | 20 480x15 360@30<br>20 480x20 480@30<br>20 480x8 640@60<br>20 480x10 800@60                                        |

NOTE 1 Levels have double names in order to allow logical association with their supported resolutions. In the case of Bayer data, each sampling grid represents a super-pixel. This means that the total number of sampling grid points required to represent a Bayer image is four times smaller (i.e. width / 2 and height / 2) than the total number of sensor elements.

NOTE 2 Since levels define maximum permissible sample counts and sample rates, a decoder conforming to a specific level is also conforming to all levels that only require a smaller sample count and sample rate than the given level.

NOTE 3 The maximum number of sampling grid points is not identical to the product of the maximum picture height and the maximum picture width.

NOTE 4 In the case of Bayer pattern data, each sampling grid point represents a super-pixel, i.e. a 2x2 arrangement of sensor elements.

## A.4 Sublevels

### A.4.1 Definition of sublevels

Sublevels define a lower bound on the throughput in the encoded domain that a conforming decoder implementation shall support. Each sublevel is defined by a nominal bits per pixel (bpp)<sup>1</sup> value  $N_{\text{bpp}}$  giving the maximum amount of bits per pixel for an encoded image of maximum permissible number of sampling grid points according to the level to which the decoder is conforming (see Table A.6). Decoders

conforming to a particular level and sublevel shall conform to the following constraints derived from  $N_{\text{bpp}}$ :

- $S_{\text{sl,max}}$ : Maximum admissible size of the entire codestream in bytes from SOC to EOC, including all markers.  $S_{\text{sl,max}}$  is derived from  $N_{\text{bpp}}$  and the maximum permissible number of sampling grid points  $L_{\text{max}}$  defined by the level as follows:

$$S_{\text{sl,max}} = \left\lfloor \frac{L_{\text{max}} \times N_{\text{bpp}}}{8} \right\rfloor \quad (\text{A.1})$$

NOTE The bits per pixel is here referred to as the total amount of bits required across all the component sample values at a given sampling grid point. For Bayer images this represents the total amount of bits required to represent a super-pixel (see [clause 6](#)).

- $R_{\text{t,max}}$ : Maximum admissible encoded throughput in bits per second.  $R_{\text{t,max}}$  is derived from the maximum grid point sample rate  $R_{\text{s,max}}$  of the level and the nominal bits per pixel value  $N_{\text{bpp}}$  as follows:

$$R_{\text{t,max}} = R_{\text{s,max}} \times N_{\text{bpp}} \quad (\text{A.2})$$

Moreover, the size of the smoothing buffer unit  $S_{\text{sbu}}$  in bits is derived, permitting computation of the overall smoothing buffer of the decoder model defined in [Annex B](#) and [Annex C](#).

$$S_{\text{sbu}} = \begin{cases} \infty & \text{if level is unrestricted or sublevel is unrestricted} \\ W_{\text{c,max}} \times N_{\text{bpp}} & \text{otherwise} \end{cases} \quad (\text{A.3})$$

$W_{\text{c,max}}$  is defined to be the maximum column width and depends on the chosen profile as follows:

$$W_{\text{c,max}} = \begin{cases} 2048 & \text{if profile is Light-Subline422.10} \\ W_{\text{max}} & \text{otherwise} \end{cases} \quad (\text{A.4})$$

The actual column width is computed by

$$C_s = \begin{cases} 8 \times Cw \times \max_i(s_x[i]) \times 2^{N_{\text{L},x}} & \text{if } Cw > 0 \\ W_f & \text{otherwise} \end{cases} \quad (\text{A.5})$$

where

$Cw$  is indicated in the picture header;

$W_f$  is the image width;

$s_x[i]$  is the chroma sampling factor of component  $i$ ;

$N_{\text{L},x}$  is the number of horizontal wavelet decompositions;

$C_s$  is the column width in sampling grid points (see ISO/IEC 21122-1).

$W_{\text{c,max}}$  is an upper bound for the allowed column width:  $C_s \leq W_{\text{c,max}}$ .

The nominal bits per pixel,  $N_{\text{bpp}}$ , is not identical to the maximum permissible amount of bits per pixel for an encoded image that does not have maximum width and height. In this case, the amount of bits per pixel for the encoded image may be larger than  $N_{\text{bpp}}$  as long as the constraints on the codestream defined by the sublevels are followed.

#### A.4.2 List of sublevels

[Table A.9](#) lists the sublevels defined in this document. The Full sublevel shall only be used if the profile value ( $P_{\text{pih}}$ ) is not *unrestricted*.

Table A.9 — List of sublevels

| Sublevel    | Nominal bpp, $N_{\text{bpp}}$        |
|-------------|--------------------------------------|
| Full        | Maximum decoded bpp (See Table A.6). |
| Sublev12bpp | 12                                   |
| Sublev9bpp  | 9                                    |
| Sublev6bpp  | 6                                    |
| Sublev3bpp  | 3                                    |
| Sublev2bpp  | 2                                    |

NOTE 1 By this definition, a decoder conforming to a sublevel defined by a given value of  $N_{\text{bpp}}$  is also conforming to all sublevels defined by a smaller value of  $N_{\text{bpp}}$ . That is, sublevels are inclusive.

NOTE 2 Specifying the Full sublevel is different from specifying an *unrestricted* sublevel, as the Full sublevel still restricts the maximum decoded bits per pixel.

NOTE 3 Compressing data as mathematically lossless in the MLS.12 profile can require setting the sublevel to *unrestricted*.

NOTE 4 In the case of Bayer pattern data, the nominal bits per pixel,  $N_{\text{bpp}}$ , represents the number of bits per super-pixel. The resulting constraints on conforming codestreams are listed in Table A.10, Table A.11, Table A.12, Table A.13, and Table A.14.

NOTE 5 Since the constraint on conforming codestreams for the Full sublevel depends on the selected profile, they are not listed in the tables hereunder.

Table A.10 — Codestream constraints for sublevel Sublev2bpp

| Level | Size of a smoothing buffer unit $S_{\text{sbu}}$ [bits] | Max codestream size $S_{\text{sl,max}}$ [bytes] | Max encoded rate $R_{\text{t,max}}$ [Mbits/s] |
|-------|---------------------------------------------------------|-------------------------------------------------|-----------------------------------------------|
| 1k-1  | 2 560                                                   | 655 360                                         | 167                                           |
| 2k-1  | 4 096                                                   | 1 048 576                                       | 267                                           |
| 4k-1  | 8 192                                                   | 2 228 224                                       | 534                                           |
| 4k-2  | 8 192                                                   | 4 194 304                                       | 1 069                                         |
| 4k-3  | 8 192                                                   | 4 194 304                                       | 2 139                                         |
| 8k-1  | 16 384                                                  | 8 912 896                                       | 2 139                                         |
| 8k-2  | 16 384                                                  | 16 777 216                                      | 4 278                                         |
| 8k-3  | 16 384                                                  | 16 777 216                                      | 8 556                                         |
| 10k-1 | 20 480                                                  | 26 214 400                                      | 6 684                                         |

Table A.11 — Codestream constraints for sublevel Sublev3bpp

| Level | Size of a smoothing buffer unit $S_{\text{sbu}}$ [bits] | Max codestream size $S_{\text{sl,max}}$ [bytes] | Max encoded rate $R_{\text{t,max}}$ [Mbits/s] |
|-------|---------------------------------------------------------|-------------------------------------------------|-----------------------------------------------|
| 1k-1  | 3 840                                                   | 983 040                                         | 250                                           |
| 2k-1  | 6 144                                                   | 1 572 864                                       | 401                                           |
| 4k-1  | 12 288                                                  | 3 342 336                                       | 802                                           |
| 4k-2  | 12 288                                                  | 6 291 456                                       | 1 604                                         |
| 4k-3  | 12 288                                                  | 6 291 456                                       | 3 209                                         |
| 8k-1  | 24 576                                                  | 13 369 344                                      | 3 209                                         |
| 8k-2  | 24 576                                                  | 25 165 824                                      | 6 417                                         |
| 8k-3  | 24 576                                                  | 25 165 824                                      | 12 835                                        |
| 10k-1 | 30 720                                                  | 39 321 600                                      | 10 027                                        |

**Table A.12 — Codestream constraints for sublevel Sublev6bpp**

| Level | Size of a smoothing buffer unit $S_{sbu}$ [bits] | Max codestream size $S_{sl,max}$ [bytes] | Max encoded rate $R_{t,max}$ [Mbits/s] |
|-------|--------------------------------------------------|------------------------------------------|----------------------------------------|
| 1k-1  | 7 680                                            | 1 966 080                                | 501                                    |
| 2k-1  | 12 288                                           | 3 145 728                                | 802                                    |
| 4k-1  | 24 576                                           | 6 684 672                                | 1 604                                  |
| 4k-2  | 24 576                                           | 12 582 912                               | 3 209                                  |
| 4k-3  | 24 576                                           | 12 582 912                               | 6 417                                  |
| 8k-1  | 49 152                                           | 26 738 688                               | 6 417                                  |
| 8k-2  | 49 152                                           | 50 331 648                               | 12 835                                 |
| 8k-3  | 49 152                                           | 50 331 648                               | 25 669                                 |
| 10k-1 | 61 440                                           | 78 643 200                               | 20 054                                 |

**Table A.13 — Codestream constraints for sublevel Sublev9bpp**

| Level | Size of a smoothing buffer unit $S_{sbu}$ [bits] | Max codestream size $S_{sl,max}$ [bytes] | Max encoded rate $R_{t,max}$ [Mbits/s] |
|-------|--------------------------------------------------|------------------------------------------|----------------------------------------|
| 1k-1  | 11 520                                           | 2 949 120                                | 752                                    |
| 2k-1  | 18 432                                           | 4 718 592                                | 1 203                                  |
| 4k-1  | 36 864                                           | 10 027 008                               | 2 406                                  |
| 4k-2  | 36 864                                           | 18 874 368                               | 4 812                                  |
| 4k-3  | 36 864                                           | 18 874 368                               | 9 625                                  |
| 8k-1  | 73 728                                           | 40 108 032                               | 9 625                                  |
| 8k-2  | 73 728                                           | 75 497 472                               | 19 251                                 |
| 8k-3  | 73 728                                           | 75 497 472                               | 38 503                                 |
| 10k-1 | 92 160                                           | 117 964 800                              | 30 081                                 |

**Table A.14 — Codestream constraints for sublevel Sublev12bpp**

| Level | Size of a smoothing buffer unit $S_{sbu}$ [bits] | Max codestream size $S_{sl,max}$ [bytes] | Max encoded rate $R_{t,max}$ [Mbits/s] |
|-------|--------------------------------------------------|------------------------------------------|----------------------------------------|
| 1k-1  | 15 360                                           | 3 932 160                                | 1 002                                  |
| 2k-1  | 24 576                                           | 6 291 456                                | 1 604                                  |
| 4k-1  | 49 152                                           | 13 369 344                               | 3 209                                  |
| 4k-2  | 49 152                                           | 25 165 824                               | 6 417                                  |
| 4k-3  | 49 152                                           | 25 165 824                               | 12 835                                 |
| 8k-1  | 98 304                                           | 53 477 376                               | 12 835                                 |
| 8k-2  | 98 304                                           | 100 663 296                              | 25 669                                 |
| 8k-3  | 98 304                                           | 100 663 296                              | 51 338                                 |
| 10k-1 | 122 880                                          | 157 286 400                              | 40 108                                 |

## A.5 Signalling of levels and sublevels in the *Plev* field of picture header

The level and sublevel of a codestream define a lower bound on the throughput in both the encoded and decoded domains which a conforming decoder implementation shall support when decoding the codestream into an image. The level and sublevel shall be indicated in the *Plev* field of the picture header defined in ISO/IEC 21122-1 by the values defined in [Table A.15](#) and [Table A.16](#).

The *unrestricted* level does not impose any constraint on maximum picture width, maximum picture height, maximum number of grid point samples, or maximum grid point sample rate. The *unrestricted* sublevel does not impose any constraint on the nominal bits per pixel.

The *unrestricted* level and sublevel shall not be considered as conformance points.

**Table A.15 — Signalling of the levels of a codestream in the *Plev* field**

| Level                             | Binary value of <i>Plev</i> field |
|-----------------------------------|-----------------------------------|
| Unrestricted                      | 0000 0000 XXXX XXXX               |
| 1k-1                              | 0000 0100 XXXX XXXX               |
| 2k-1                              | 0001 0000 XXXX XXXX               |
| 4k-1                              | 0010 0000 XXXX XXXX               |
| 4k-2                              | 0010 0100 XXXX XXXX               |
| 4k-3                              | 0010 1000 XXXX XXXX               |
| 8k-1                              | 0011 0000 XXXX XXXX               |
| 8k-2                              | 0011 0100 XXXX XXXX               |
| 8k-3                              | 0011 1000 XXXX XXXX               |
| 10k-1                             | 0100 0000 XXXX XXXX               |
| Reserved for ISO/IEC purposes     | all other values                  |
| An X indicates either a 0 or a 1. |                                   |

**Table A.16 — Signalling of the sublevels of a codestream in the *Plev* field**

| Sublevel                          | Binary value of <i>Plev</i> field |
|-----------------------------------|-----------------------------------|
| Unrestricted                      | XXXX XXXX 0000 0000               |
| Full                              | XXXX XXXX 1000 0000               |
| Sublev12bpp                       | XXXX XXXX 0001 0000               |
| Sublev9bpp                        | XXXX XXXX 0000 1100               |
| Sublev6bpp                        | XXXX XXXX 0000 1000               |
| Sublev3bpp                        | XXXX XXXX 0000 0100               |
| Sublev2bpp                        | XXXX XXXX 0000 0011               |
| Reserved for ISO/IEC purposes     | all other values                  |
| An X indicates either a 0 or a 1. |                                   |

Annex B  
(normative)

Packet-based JPEG XS decoder model

B.1 General

This annex defines a generic JPEG XS decoder model that precisely defines the temporal behaviour of a decoder model assuming a processing granularity of codestream packets. The temporal behaviour is necessary to derive the requirements on conforming codestreams for a given transmission channel as defined in [Annex C](#). The profiles and levels define the relevant parameters of the decoder model and transmission channel model to impose requirements on the codestreams and thus ensure interoperability of any decoder implementation.

B.2 Codestream fragments

B.2.1 Coded codestream fragments

ISO/IEC 21122-1 defines the JPEG XS codestream as a sequence of packets, complemented by several marker segments and packet headers located in various positions of the codestream. Each packet consists of a packet header and a packet body. The last packet of a precinct may be followed by fill bytes.

A coded codestream fragment shall be a subset of consecutive bits of the codestream which is built according to the following rules:

- Each coded codestream fragment shall contain exactly one packet, consisting of its packet header and its packet body.
- All headers, marker segments and markers shall be assigned to the subsequent coded codestream fragment of the same codestream. If such a coded codestream fragment does not exist, they shall be assigned to the previous coded codestream fragment.
- The padding bits of a precinct shall be assigned to the previous coded codestream fragment.

[Figure B.1](#) depicts the segmentation of a codestream into fragments.





Figure B.1 — Coded codestream fragment

NOTE See ISO/IEC 21122-3 for the definition of boxes that can precede the codestream header.

### B.2.2 Blanking codestream fragments

In some systems, images may be embedded into larger pixel containers as illustrated in [Figure B.2](#). The active image pixels are complemented by blanking periods that are not intended for display but that pad the active image to a specified container size.




#### Key

- |                  |                     |
|------------------|---------------------|
| 1 active pixel   | 3 active image area |
| 2 blanking pixel | 4 blanking region   |

**Figure B.2 — Blanking area**

When the underlying transport channel allows transmission of bits of encoded data during the blanking periods, improved image quality, in terms of increased target amount of bits per pixel, can be achieved by considering the blanking regions during which transmission occurs in the buffer model. This shall be done by inserting so called blanking codestream fragments into the sequence of coded codestream fragments as depicted in [Figure B.3](#).



**Figure B.3 — Blanking codestream fragments ( $n = N_{p,x}$ ,  $m = N_{p,y}$ )**

According to ISO/IEC 21122-1, the codestream comprises  $n = N_{p,x}$  horizontally aligned precincts, where  $N_{p,x}$  is the number of columns, and  $m = N_{p,y}$  vertically aligned precincts. For consideration of the blanking period in the buffer model, a horizontal blanking codestream fragment  $f$  shall be inserted after each

coded codestream fragment that terminates a row of horizontally aligned precincts. The size in bits of the horizontal blanking codestream fragment shall equal  $S_{\text{bit}}(f) = 0$ . The duration of the horizontal blanking codestream fragment is expressed in number of coefficient groups  $N_{\text{cg,hz}}$  associated to the horizontal blanking codestream fragment.

After the last coded codestream fragment of an image, a vertical blanking codestream fragment  $f$  is inserted. The size in bits of the vertical blanking codestream fragment shall equal  $S_{\text{bit}}(f) = 0$ . The duration of the vertical blanking codestream fragment is expressed in number of coefficient groups  $N_{\text{cg,vt}}$  associated to the vertical blanking codestream fragment.

NOTE 1 The time unit for the buffer model is based on coefficients groups. Since the number of all coefficients covered by all coefficient groups in the codestream is possibly larger than the number of image samples due to padding (as explained in ISO/IEC 21122-1), there is no strict integer relation between a pixel clock and a coefficient group clock. In order to avoid using different clocks in the buffer model, the blanking periods are defined as a multiple of coefficient groups instead of pixels.

NOTE 2 The values of  $N_{\text{cg,hz}}$  and  $N_{\text{cg,vt}}$  are not signalled in the codestream itself but in the Buffer Model Description box, specified in ISO/IEC 21122-3.

### B.2.3 Computation of the number of coefficient groups belonging to a horizontal blanking codestream fragment

The duration of the horizontal blanking period in pixels can be computed by

$$2^{N_{L,y}} \times N_{b,x} \quad (\text{B.1})$$

Since  $\sum_{i=1}^{N_c} \frac{1}{s_x[i]}$  coefficient groups represent up to  $N_g$  pixels, one coefficient group corresponds to up to:

$$\frac{N_g}{\sum_{i=1}^{N_c} \frac{1}{s_x[i]}} \quad (\text{B.2})$$

pixels. Hence,  $N_{\text{cg,hz}}$  may be computed as:

$$N_{\text{cg,hz}} = \frac{2^{N_{L,y}} \times N_{b,x} \times \sum_{i=1}^{N_c} \frac{1}{s_x[i]}}{N_g} \quad (\text{B.3})$$

where

$N_{L,y}$  is the number of vertical decomposition levels;

$N_c$  is the number of components in an image;

$N_{b,x}$  is the number of horizontal blanking periods in the pixel domain during which the transmission channel continues transmission of the codestream;

$s_x[i]$  is the sampling factor of component  $i$  in horizontal direction;

$N_g$  is the number of coefficients in a code group.

This relation is informative only, because the relation between the duration of a pixel and a coefficient group is not prescribed by this document.

### B.2.4 Computation of the number of coefficient groups belonging to a vertical blanking codestream fragment

The duration of the vertical blanking period in pixels can be computed by:

$$N_{b,y} \times (W_f + N_{b,x}) \quad (\text{B.4})$$

Consequently,  $N_{cg,vt}$  may be computed as:

$$N_{cg,vt} = \left\lfloor \frac{N_{b,y} \times (W_f + N_{b,x}) \times \sum_{i=1}^{N_c} \frac{1}{s_x[i]}}{N_g} \right\rfloor \quad (\text{B.5})$$

where

$W_f$  is the width of the image in samples;

$N_c$  is the number of components in an image;

$N_{b,x}$  is the number of horizontal blanking periods in the pixel domain during which the transmission channel continues transmission of the codestream;

$N_{b,y}$  is the number of vertical blanking periods during which the transmission channel continues transmission of the codestream bits;


$s_x[i]$  is the sampling factor of component  $i$  in horizontal direction;

$N_g$  is the number of coefficients in a code group.

This relation is informative only, because the relation between the duration of a pixel and a coefficient group is not prescribed by this document.

### B.3 Decoder model block diagram

[Figure B.4](#) depicts the decoder block diagram that forms the base of any buffer model.

**Key**

- |   |                          |   |               |
|---|--------------------------|---|---------------|
| 1 | clock                    | 4 | decoder unit  |
| 2 | transmission channel     | 5 | output pixels |
| 3 | decoder smoothing buffer | 6 | decoder model |

**Figure B.4 — JPEG XS decoder model**

The decoder model consists of a decoder unit, clocked by a periodic signal with period  $T$ . With each new clock cycle, the decoder unit starts decoding a new coefficient group, which — when not being blanking coefficient groups — may eventually be output in form of decoded output pixels. For this purpose, the decoder unit reads with each clock cycle a variable number of bits from a decoder smoothing buffer. This decoder smoothing buffer has well-defined capacity, allowing a maximum amount of bits to be stored. The decoder shall be able to read a variable number of bits per clock cycle, following a first-in-first-out semantic. This means that when a bit  $v_1$  is written into the decoder smoothing buffer before bit  $v_2$ , then this bit  $v_1$  shall not be read after bit  $v_2$ .

The decoder smoothing buffer is connected to a bit source that writes bits into the decoder smoothing buffer. In [Figure B.4](#), this bit source is represented as a transmission channel, because for typical low latency applications, a decoder is connected to an encoder by means of such a transmission channel. However, in general, any other bit source is valid as well. The value  $D_{c2d}$  in [Figure B.4](#) defines the number of clock cycles the start of decoding needs to be delayed relative to the time at which the first bit of the codestream arrives in the decoding smoothing buffer. Different methods are possible to generate this value, and this document does not prescribe any of them.

**B.4 Decoder smoothing buffer**

Bits written at clock cycle  $t$  into the decoding smoothing buffer are available to the decoder unit immediately at clock cycle  $t$ . Let  $l_{\text{dec,max}} \in \mathbb{N}$  be the maximum number of bits that can be stored in the decoder smoothing buffer. Let  $l_{\text{dec}}(t)$  be the number of bits stored in the decoder smoothing buffer at the end of clock cycle  $t$ . Let  $w_{\text{dec}}(t)$  be the number of bits written into the decoder smoothing buffer in clock cycle  $t$ . Let  $r_{\text{dec}}(t)$  be the number of bits read and removed from the decoder smoothing buffer in clock cycle  $t$ . Then the following shall hold for a conforming implementation of the decoder model:

$$\tilde{l}_{\text{dec}}(t) = l_{\text{dec}}(t-1) + w_{\text{dec}}(t) \quad (\text{B.6})$$

$$r_{\text{dec}}(t) \leq \tilde{l}_{\text{dec}}(t) \leq l_{\text{dec},\text{max}} \quad (\text{B.7})$$

$$l_{\text{dec}}(t) = l_{\text{dec}}(t-1) + w_{\text{dec}}(t) - r_{\text{dec}}(t) = \tilde{l}_{\text{dec}}(t) - r_{\text{dec}}(t) \quad (\text{B.8})$$

## B.5 Buffer model types

[Table B.1](#) defines the buffer model types defined in this document.

**Table B.1 — Buffer model types**

| Value of <i>Tbmd</i> | Meaning                                                                                                                                     |
|----------------------|---------------------------------------------------------------------------------------------------------------------------------------------|
| 0                    | No upper limit of the decoder buffer assumed                                                                                                |
| 1                    | Constant bit rate buffer model with limited transmission latency, see <a href="#">Formula (C.7)</a>                                         |
| 2                    | Constant bit rate buffer model with full use of decoder smoothing buffer (variable transmission latency), see <a href="#">Formula (C.7)</a> |
| 3-255                | Reserved for ISO/IEC purposes                                                                                                               |

## Annex C (normative)

### Packet-based constant bit rate buffer model

#### C.1 General

This annex defines transmission channel models assuming a fixed upper bit rate that is related to the target compression ratio. Together with the decoder model of [Annex B](#), it defines the packet-based constant bit rate buffer model. It describes the conditions for a low latency interoperability of any conforming decoder. These conditions are expressed by buffer model parameters that are specified by the profiles and levels defined in [Annex A](#).

#### C.2 Decoder unit

In order to decode a codestream fragment  $f \geq 1$ , the decoder unit reads all bits that have been generated by the encoder for this codestream fragment  $f$ . Processing of codestream fragment  $f \in \mathbb{N}$  starts at cycle  $t_{\text{dec,start}}(f)$ :

$$t_{\text{dec,start}}(f) = t_{\text{channel,start}} + D_{\text{c2d}} + \sum_{i=1}^{f-1} N_{\text{cg}}(i) \quad (C.1)$$

$$t_{\text{dec,start}}(f) = \begin{cases} t_{\text{channel,start}} + D_{\text{c2d}} & f = 1 \\ t_{\text{dec,start}}(f-1) + N_{\text{cg}}(f) & \text{otherwise} \end{cases}$$

$D_{\text{c2d}} \in \mathbb{N}$  is the delay of the decoding start relative to the start of the transmission channel.  $t_{\text{channel,start}} \in \mathbb{Z}$  is the clock cycle in which the transmission channel writes the first bit of the considered codestream into the decoding smoothing buffer. In order to process codestream fragment  $f$ , all coded bits of codestream fragment  $f$  shall be contained in the smoothing buffer:

$$\tilde{l}_{\text{dec}}(t_{\text{dec,start}}(f)) \geq S_{\text{bits}}(f) \quad (C.2)$$

The coded bits of each codestream fragment  $f \in \mathbb{N}$  are removed from the decoder smoothing buffer at cycle  $t_{\text{dec,read}}(f) \in \mathbb{N}$ . The latter is computed as follows:

$$t_{\text{dec,read}}(f) = t_{\text{dec,start}}(f) + N_{\text{cg}}(f) - 1 \quad (C.3)$$

$$t_{\text{dec,read}}(f) = t_{\text{channel,start}} + D_{\text{c2d}} + \left( \sum_{i=1}^f N_{\text{cg}}(i) \right) - 1$$

The number of bits removed from the decoding smoothing buffer is defined as follows:

$$r_{\text{dec}}(t) = \begin{cases} S_{\text{bits}}(f) & \exists f : t_{\text{dec,read}}(f) = t \\ 0 & \text{otherwise} \end{cases} \quad (C.4)$$

where  $\exists$  stands for "there exists".

The decoder model is described by pseudo code in [Table C.1](#).

Table C.1 — Decoder model pseudo code

| Operation                               | Notes                                                                                                                 |
|-----------------------------------------|-----------------------------------------------------------------------------------------------------------------------|
| wait ( $t_{\text{dec,start}}(0)$ )      | Wait for $t_{\text{dec,start}}(0)$ clock cycles                                                                       |
| $f = 1$                                 | Reset the codestream fragment counter                                                                                 |
| while(!end of stream) {                 | Repeat until the end of the codestream is reached                                                                     |
|                                         | At this time, all bits required to decode codestream fragment $f$ shall be available in the decoding smoothing buffer |
| wait ( $N_{\text{cg}}(f) - 1$ )         | Wait for $N_{\text{cg}}(f) - 1$ clock cycles. $N_{\text{cg}}(f)$ is the processing time of codestream fragment $f$ .  |
| bits= readBits ( $S_{\text{bits}}(f)$ ) | Read $S_{\text{bits}}(f)$ from the smoothing buffer and remove them from smoothing buffer                             |
| decode_bits                             | Decode the bits in the codestream fragment $f$                                                                        |
| wait(1)                                 | Wait another cycle to complete codestream fragment $f$                                                                |
| $f = f + 1$                             | Advance to the next codestream fragment                                                                               |
| }                                       |                                                                                                                       |

C.3 Encoder-decoder system model

The packet-based constant bit rate buffer model is intended for applications where an encoder is connected to a decoder by a transmission channel with a maximum upper bit rate  $R_{\text{trans}}$  (for VBR applications) or a constant bit rate  $R_{\text{trans}}$  (for CBR applications) that equals the target compression rate.




Figure C.1 — System model (dashed elements are informative only)

Figure C.1 illustrates the corresponding block diagram. It extends the decoder model of Figure B.4 by showing the encoder feeding the transmission channel. Both the encoder and the decoder are assumed to be clocked by a common periodic signal with period  $T$ .

The packet-based constant bit rate buffer model can also be applied in situations where the transmission channel operates in bursts and can hence only be approximated by a constant bit rate channel or a

channel with a maximum bit rate. Then, however, means shall be provided to transform the actual transmission behaviour into one corresponding to [subclause C.4](#).

## C.4 Transmission channel model

### C.4.1 Transmission channel with maximum bit rate

The transmission channel model shall write at most  $R_{\text{trans}} \in \mathbb{Q}$  bits per clock cycle into the decoder smoothing buffer for all cycles  $t \geq t_{\text{channel,start}}$ .

NOTE This includes the blanking regions defined by  $N_{\text{cg,hz}}$  and  $N_{\text{cg,vt}}$ .

$$R_{\text{trans}} = \frac{S_{\text{c,max}} \times 8}{\sum_{f=1}^{N_f} N_{\text{cg}}(f)} \quad (\text{C.5})$$

where

$S_{\text{c,max}}$  is the maximum size of the entire codestream in bytes from SOC to EOC, including all markers. In case the *Lcod* field of the picture header is unequal to zero,  $S_{\text{c,max}}$  shall equal the *Lcod* value;

$N_f$  is the number of codestream fragments including the blanking codestream fragments;

$N_{\text{cg}}(f)$  is the number of coefficient groups in codestream fragment  $f$ .

In many applications, the compression to apply is defined by a bit per pixel value  $B_r$ . In such a case,  $S_{\text{c,max}}$  can be computed as:

$$S_{\text{c,max}} = W_f \times H_f \times B_r \quad (\text{C.6})$$

The cumulative number of bits written into the decoder smoothing buffer can be computed as:

$$\sum_{\tau=0}^t w_{\text{dec}}(\tau) \leq \lfloor (t - t_{\text{channel,start}}) \times R_{\text{trans}} \rfloor \quad (\text{C.7})$$

The value of  $t_{\text{channel,start}}$  depends on the system configuration, and in particular on the encoder. In a full system,  $t_{\text{channel,start}}$  should be determined by the encoder in such a way that the decoder buffer does not overflow.

### C.4.2 Transmission channel with constant bit rate

For transmission channels with constant bit rate, the transmission channel model shall write  $R_{\text{trans}} \in \mathbb{Q}$  bits per clock cycle into the decoder smoothing buffer for all cycles  $t \geq t_{\text{channel,start}}$ .

NOTE This includes the blanking regions defined by  $N_{\text{b,x}}$  and  $N_{\text{b,y}}$ .

The value of  $t_{\text{channel,start}}$  shall be set in such a way that the transmission channel (or any other bit source) is able to generate a continuous stream of bits without any interruptions.

The cumulative number of bits written into the decoder smoothing buffer can be computed as

$$\sum_{\tau=0}^t w_{\text{dec}}(\tau) = \lfloor (t - t_{\text{channel,start}}) \times R_{\text{trans}} \rfloor \quad (\text{C.8})$$

The value of  $t_{\text{channel,start}}$  depends on the system configuration, and in particular on the encoder. In a full system,  $t_{\text{channel,start}}$  should be determined by the encoder.

The transmission channel is therefore described by [Table C.2](#).

Table C.2 — Transmission channel pseudo code

| Operation                                                         | Notes                                                                             |
|-------------------------------------------------------------------|-----------------------------------------------------------------------------------|
| $r = 0$                                                           | Remaining fractional bits                                                         |
| wait ( $t_{\text{channel,start}}$ )                               | Wait until transmission channel starts to write bits                              |
| while (!end of stream) {                                          | Repeat until the source stops sending bits                                        |
| writeBits ( $\lfloor R_{\text{trans}} + r \rfloor$ )              | Write $\lfloor R_{\text{trans}} + r \rfloor$ bits to the decoder smoothing buffer |
| $r = R_{\text{trans}} + r - \lfloor R_{\text{trans}} + r \rfloor$ | Update the number of fractional bits                                              |
| wait (1)                                                          | Wait for one cycle                                                                |
| }                                                                 | Continue sending data                                                             |

### C.4.3 Relation between the two channel models

In case an encoder generates only codestreams having the maximum size  $S_{c,\text{max}}$ , both channel models defined in [subclauses C.4.1](#) and [C.4.2](#) are effectively the same due to the definition of  $R_{\text{trans}}$  in [Formula \(C.5\)](#). Consequently, the transmission channel model with constant bit rate can be used to dimension the system. The transmission channel with maximum bit rate then allows interrupting transmission in case the encoder does not pad the codestream to the maximum size.

It is the responsibility of the encoder to manage the transmission in such a way that the decoder buffer does not overflow.

### C.5 Decoder smoothing buffer

The decoder smoothing buffer shall behave as described in [subclause B.4](#). Based on the selected buffer model type defined in [subclause B.5](#), the size of the decoding smoothing buffer  $l_{\text{dec,max}}$  is computed as follows:

$$l_{\text{dec,max}}^* = S_{\text{sbo}} + \begin{cases} \infty & T_{\text{bmd}} = 0 \\ \min \left( l_{\text{dec,max}}^{\text{cbr}}, \left\lfloor R_{\text{trans}} \times \frac{W_f}{N_g} \times \Delta T_{\text{max,lines}} \times \sum_{i=1}^{N_c} \frac{1}{s_x[i] \times s_y[i]} \right\rfloor \right) & T_{\text{bmd}} = 1 \\ l_{\text{dec,max}}^{\text{cbr}} & T_{\text{bmd}} = 2 \end{cases} \quad (\text{C.9})$$

where  $l_{\text{dec,max}} := \left\lfloor \frac{l_{\text{dec,max}}^*}{R_{\text{trans}}} \right\rfloor \times R_{\text{trans}} \leq l_{\text{dec,max}}^*$

NOTE  $T_{\text{bmd}} = 1$  essentially leads to a system where the maximum transmission latency in lines is independent of the image width  $W_f$  and the target compression rate  $R_{\text{trans}}$ . See [subclause D.3](#).

### C.6 Buffer model instance

The following buffer model parameters are specified for the profiles, levels or sublevels, referring to the buffer model defined in [subclause C.5](#):

$l_{\text{dec,max}}^{\text{cbr}} \in \mathbb{N}$  base size of the decoder smoothing buffer in bits due to sublevel and profile, not including the smoothing buffer offset defined in [Table C.3](#). Can be infinite, if the level is unrestricted, or the sublevel is unrestricted.

NOTE 1 The actual number of bits that can be stored in the decoder smoothing buffer is given by [Formula \(C.7\)](#).

NOTE 2 In practice, in the case that  $l_{\text{dec,max}}^{\text{cbr}} = \infty$ , the buffer model does not apply at all. This happens when the level or sublevel is set to be unrestricted.

$\Delta T_{\max, \text{lines}}$  upper bound for the transmission latency in lines. Can be infinite.

$S_{\text{sbo}}$  offset to the buffer size computation.

The buffer model combined with those values is called a buffer model instance.

## C.7 Buffer model instance parameters

Table C.3 specifies how to derive the buffer model instance parameters from the profile, level and sublevel constraints for implementations conforming to the packet-based constant bit rate buffer model defined in [subclauses C.4.2](#) and [C.5](#).

**Table C.3 — Derivation of the buffer model parameters for the packet-based constant bit rate buffer model**

| Buffer model instance parameters    | Value                                                                                                                                                                 |
|-------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| $l_{\text{dec}, \max}^{\text{cbr}}$ | $N_{\text{sbo}} \times S_{\text{sbo}}$ (see <a href="#">subclause A.4</a> )                                                                                           |
| $\Delta T_{\max, \text{lines}}$     | $N_{\text{sbo}}$ (see <a href="#">Table A.1</a> , <a href="#">Table A.2</a> , <a href="#">Table A.3</a> , <a href="#">Table A.4</a> , and <a href="#">Table A.5</a> ) |
| $S_{\text{sbo}}$                    | See <a href="#">Table A.1</a> , <a href="#">Table A.2</a> , <a href="#">Table A.3</a> , <a href="#">Table A.4</a> , and <a href="#">Table A.5</a>                     |

## C.8 Buffer model conformance

### C.8.1 Conformance of a single codestream

A single codestream conforming to the buffer model instance shall also be conforming with ISO/IEC 21122-1. Finally, there shall exist a value  $D_{\text{c2d}} \in \mathbb{N}$  such that [Formulae \(B.6\) to \(B.8\)](#) and [\(C.2\)](#) are valid for all cycles  $t$ , when the temporal behaviour of the channel and decoder models corresponds to the specifications in [subclauses C.2 to C.6](#).

In case the transmission channel uses variable bit rate as defined in [subclause C.4.1](#), [Formula \(C.5\)](#) only establishes an upper bound on the number of bits  $\sum_{\tau=0}^t w_{\text{dec}}(\tau)$  written to the decoder smoothing buffer. For a conforming codestream, there shall exist a function  $w_{\text{dec}}(\tau)$  that is consistent with [Formula \(C.5\)](#) and for which [Formulae \(B.6\) to \(B.8\)](#) and [\(C.2\)](#) are true.

### C.8.2 Conformance of a sequence of codestreams

This subclause defines the conformance of a sequence  $C = [C(1), \dots, C(n)]$  of codestreams to a buffer model instance. For that, define the symbol  $t_{\text{channel}, \text{start}}(i)$  as the clock cycle where the transmission channel writes the first bit of codestream  $C(i)$ . Further, define the symbol  $D_{\text{c2d}}(1)$  to be the delay between  $t_{\text{channel}, \text{start}}(1)$  and the start of decoding of codestream  $C(1)$ . Moreover, define the symbol  $F_{\text{first}}(C(i))$  to be the first codestream fragment of codestream  $C(i)$  and  $F_{\text{last}}(C(i))$  to be the last codestream fragment of  $C(i)$ . Define  $S_{\text{c}, \max}(C(i))$  to be the maximum size in bytes of codestream  $C(i)$ , and define  $N_f(C(i))$  to be the number of codestream fragments for codestream  $C(i)$ .

Then, for conformance of  $C$  to a given buffer model instance, each codestream  $C(i)$  shall be conforming to this buffer model instance according to [subclause C.8.1](#), and in addition, the following shall hold:

$$\forall 1 \leq i < n: t_{\text{dec}, \text{start}}(F_{\text{first}}(C(i+1))) = t_{\text{dec}, \text{read}}(F_{\text{last}}(C(i))) + 1 \quad (\text{C.9})$$

and

$$\frac{S_{\text{c}, \max}(C(i)) \times 8}{\sum_{f=1}^{N_f(C(i))} N_{\text{cg}}(f)} = \text{const} = R_{\text{trans}} \quad (\text{C.10})$$

### C.8.3 Decoder conformance

A decoder conforming to a buffer model instance shall be able to decode all codestreams that are conforming with the buffer model instance.

### C.8.4 Encoder conformance

An encoder is conforming to a buffer model instance if all codestreams it generates are conforming to the buffer model instance. Moreover, the encoder shall provide the codestream fragments at such time instances so that the decoder can receive them through the transmission channel at the time instances assumed by the buffer model.

### C.8.5 Decoder implementation deviations

A decoder implementation conforming to a buffer model instance may deviate from the temporal behaviour of the decoder model defined in [subclause C.2](#). However, it is then the responsibility of the implementation to take all necessary measures to ensure that this implementation is able to decode all conforming codestreams correctly.

### C.8.6 Transmission channel deviations

Decoder implementations conforming to a buffer model instance assume a bit rate transmission behaviour as defined in [subclause C.4](#). In case the actual transmission channel violates these assumptions, means shall be provided to transform the actual transmission behaviour into one corresponding to [subclause C.4](#). These means should be defined in application-specific specifications.

## Annex D (informative)

### Encoder model, latency bounds and codestream conformance properties for the packet-based constant bit rate buffer model

#### D.1 General

[Annex B](#) and [Annex C](#) define the requirements on conforming decoders and codestreams such that encoder and decoder implementations of different vendors are interoperable. Moreover, they ensure that system implementations with low end-to-end latency are possible independent of the image content contained in the codestream.

Based on the subclauses of [Annex B](#) and [Annex C](#), it is possible to derive some fundamental properties of conforming codestreams and system implementations, consisting of a conforming encoder and decoder. This includes in particular a latency bound of conforming encoder-decoder systems.

#### D.2 Encoder model

The encoder unit of the system model described in [subclause C.3](#) generates a sequence of codestreams being a sequence of codestream fragments. Each codestream fragment  $f \in \mathbb{N}$  is written to the encoder smoothing buffer at cycle  $t_{\text{enc,write}}(f) \in \mathbb{N}_0$ . The latter depends on the number of coefficient groups  $N_{\text{cg}}(i)$  in codestream fragment  $i$ :

$$t_{\text{enc,write}}(f) = \left( \sum_{i=1}^f N_{\text{cg}}(i) \right) - 1 = N_{\text{cg}}(f) + \begin{cases} -1 & f=1 \\ t_{\text{enc}}(f-1) & \text{otherwise} \end{cases} \quad (\text{D.1})$$

Let  $S_{\text{bits}}(f)$  be the number of coded bits for codestream fragment  $f$ . Then data generation of the encoder model is described by the pseudo code in [Table D.1](#).

**Table D.1 — Encoder pseudo code**

| Operation                               | Notes                                               |
|-----------------------------------------|-----------------------------------------------------|
| $f = 1$                                 | Reset codestream fragment counter                   |
| while (!end of stream) {                | Repeat until the stream is interrupted              |
| wait ( $N_{\text{cg}}(f) - 1$ )         | Wait $N_{\text{cg}}(f) - 1$ clock cycles            |
| writeBits (bits, $S_{\text{bits}}(f)$ ) | Write $S_{\text{bits}}(f)$ bits to smoothing buffer |
| wait (1)                                | Go to next cycle                                    |
| $f = f + 1$                             | Go to next fragment                                 |
| }                                       |                                                     |

### D.3 Buffer relations

For the constant bit rate transmission channel model defined in [subclause C.4.2](#), the fill level of the encoder smoothing buffer at the end of cycle  $t \in \mathbb{N}_0$  is computed by:

$$l_{\text{enc}}(t) = \sum_{f=1}^{\infty} S_{\text{bits}}(f) \times \xi(t - t_{\text{enc,write}}(f)) - \left[ (t+1 - t_{\text{channel,start}}) \times R_{\text{trans}} \right] \times \xi(t - t_{\text{channel,start}}) \quad (\text{D.2})$$

NOTE 1 When  $t_{\text{enc,write}}(f) = 0$  and  $t_{\text{channel,start}} = 0$ , the encoder produces data in the cycle  $t = 0$ . and transmission immediately starts at  $t = 0$ .

From [Formulae \(C.2\)](#) and [\(D.1\)](#), it follows that:

$$t_{\text{dec,read}}(f) = \underbrace{t_{\text{channel,start}} + D_{\text{c2d}}}_{t_{\text{dec,start}}(1)} + t_{\text{enc,write}}(f) \quad (\text{D.3})$$

For a constant bit rate transmission channel model of [subclause C.4.2](#), the fill level of the decoder smoothing buffer at the end of cycle  $t_{\text{dec,start}}(1) + t$  is computed as:

$$l_{\text{dec}}(t_{\text{dec,start}}(1) + t) = \left\lfloor (t_{\text{dec,start}}(1) + t - t_{\text{channel,start}} + 1) \times R_{\text{trans}} \right\rfloor - \sum_{f=1}^{\infty} S_{\text{bits}}(f) \times \xi(t - t_{\text{enc,write}}(f)) \quad (\text{D.4})$$

$t_{\text{dec,start}}(1)$  is the cycle where the decoder starts decoding.