

---

---

**Information technology — Coding of  
audio-visual objects**

**Part 10:  
Advanced Video Coding**

**AMENDMENT 2: New profiles for  
professional applications**

*Technologies de l'information — Codage des objets audiovisuels*

*Partie 10: Codage visuel avancé*

*AMENDEMENT 2: Nouveaux profils pour applications professionnelles*

**PDF disclaimer**

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.



**COPYRIGHT PROTECTED DOCUMENT**

© ISO/IEC 2007

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office  
Case postale 56 • CH-1211 Geneva 20  
Tel. + 41 22 749 01 11  
Fax + 41 22 749 09 47  
E-mail [copyright@iso.org](mailto:copyright@iso.org)  
Web [www.iso.org](http://www.iso.org)

Published in Switzerland

## Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of the joint technical committee is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

Amendment 2 to ISO/IEC 14496-10:2005 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*.

Amendment 2 to ISO/IEC 14496-10:2005 is technically aligned with ITU-T Rec. H.264 (2005)/Amd.2 (2007), but is not published as identical text.

IECNORM.COM : Click to view the full PDF of ISO/IEC 14496-10:2005/Amd 2:2007

# Information technology — Coding of audio-visual objects

## Part 10: Advanced Video Coding

### AMENDMENT 2: New profiles for professional applications

*In subclause 0.4, replace the following:*

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 1 refers to the first (2003) approved version of this Recommendation | International Standard.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 2 refers to the integrated text containing the corrections specified in the first technical corrigendum.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 3 refers to the integrated text containing both the first technical corrigendum (2004) and the first amendment, which is referred to as the "Fidelity range extensions".

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 4 (the current specification) refers to the integrated text containing the first technical corrigendum (2004), the first amendment (the "Fidelity range extensions"), and an additional technical corrigendum (2005). In the ITU-T, the next published version after version 2 was version 4 (due to the completion of the drafting work for version 4 prior to the approval opportunity for a final version 3 text).

*with:*

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 1 refers to the first (2003) approved version of this Recommendation | International Standard. The first published version in ISO/IEC corresponded to version 1.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 2 refers to the integrated text containing the corrections specified in the first technical corrigendum. The first fully-published version in the ITU-T was version 2, due to the development of the corrigendum during the publication process. Version 2 was also published in integrated form by ISO/IEC.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 3 refers to the integrated text containing both the first technical corrigendum (2004) and the first amendment, which is referred to as the "Fidelity range extensions".

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 4 refers to the integrated text containing the first technical corrigendum (2004), the first amendment (the "Fidelity range extensions"), and an additional technical corrigendum (2005). In both ITU-T and ISO/IEC, the next complete published version after version 2 was version 4.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 5 refers to the integrated version 4 text with its specification of the High 4:4:4 profile removed. In ISO/IEC, the changes from version 4 to version 5 were published as a corrigendum text.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 6 refers to the integrated version 5 text after its amendment to support additional colour space indicators. In the ITU-T, the changes for versions 5 and 6 were approved and published as a single amendment.

ITU-T Rec. H.264 | ISO/IEC 14496-10 version 7 refers to the integrated version 6 text after its amendment to define five new profiles intended primarily for professional applications (the High 10 Intra, High 4:2:2 Intra, High 4:4:4 Intra, CAVLC 4:4:4 Intra, and High 4:4:4 Predictive profiles) and two new types of supplemental enhancement information (SEI) messages (the post-filter hint SEI message and the tone mapping information SEI message).

*In the second paragraph of subclause 0.6, replace the sentence:*

With the exception of the transform bypass mode of operation for lossless coding in the I\_PCM mode of operation in all profiles, the algorithm is typically not lossless, as the exact source sample values are typically not preserved through the encoding and decoding processes.

*with:*

With the exception of the transform bypass mode of operation for lossless coding in the High 4:4:4 Intra, CAVLC 4:4:4 Intra, and High 4:4:4 Predictive profiles, and the I\_PCM mode of operation in all profiles, the algorithm is typically not lossless, as the exact source sample values are typically not preserved through the encoding and decoding processes.

*In the third paragraph of subclause 0.7, replace the sentence:*

Annex A specifies six profiles (Baseline, Main, Extended, High, High 10 and High 4:2:2), each being tailored to certain application domains, and defines the so-called levels of the profiles.

*with:*

Annex A specifies eleven profiles (Baseline, Main, Extended, High, High 10, High 4:2:2, High 4:4:4 Predictive, High 10 Intra, High 4:2:2 Intra, High 4:4:4 Intra, and CAVLC 4:4:4 Intra), each being tailored to certain application domains, and defines the so-called levels of the profiles.

*Replace subclause 3.6 with the following:*

- 3.6 arbitrary slice order:** A decoding order of slices in which the macroblock address of the first macroblock of some slice of a picture may be less than the macroblock address of the first macroblock of some other preceding slice of the same coded picture or, in the case of a picture that is coded using three separate colour planes, some other preceding slice of the same colour plane.

*Replace subclause 3.75 with the following:*

- 3.75 macroblock:** A 16x16 block of luma samples and two corresponding blocks of chroma samples of a picture that has three sample arrays; or a 16x16 block of samples of a monochrome picture or a picture that is coded using three separate colour planes. The division of a slice or a macroblock pair into macroblocks is a partitioning.

*Replace subclause 3.136 with the following:*

- 3.136 slice:** An integer number of macroblocks or macroblock pairs ordered consecutively in the raster scan within a particular slice group. For the primary coded picture, the division of each slice group into slices is a partitioning. Although a slice contains macroblocks or macroblock pairs that are consecutive in the raster scan within a slice group, these macroblocks or macroblock pairs are not necessarily consecutive in the raster scan within the picture. The addresses of the macroblocks are derived from the address of the first macroblock in a slice (as represented in the slice header), the macroblock to slice group map, and, when a picture is coded using three separate colour planes, a colour plane identifier.

In subclause 6.2 “Source, decoded, and output picture formats”, make the following changes.

Replace the following:

The variables SubWidthC, and SubHeightC are specified in Table 6-1, depending on the chroma format sampling structure, which is specified through chroma\_format\_idc. An entry marked as “-” in Table 6-1 denotes an undefined value for SubWidthC or SubHeightC. Other values of chroma\_format\_idc, SubWidthC, and SubHeightC may be specified in the future by ITU-T | ISO/IEC.

**Table 6-1 –SubWidthC, and SubHeightC values derived from chroma\_format\_idc**

| chroma_format_idc | Chroma Format | SubWidthC | SubHeightC |
|-------------------|---------------|-----------|------------|
| 0                 | monochrome    | -         | -          |
| 1                 | 4:2:0         | 2         | 2          |
| 2                 | 4:2:2         | 2         | 1          |
| 3                 | 4:4:4         | 1         | 1          |

with:

The variables SubWidthC and SubHeightC are specified in Table 6-1, depending on the chroma format sampling structure, which is specified through chroma\_format\_idc and separate\_colour\_plane\_flag. An entry marked as “-” in Table 6-1 denotes an undefined value for SubWidthC or SubHeightC. Other values of chroma\_format\_idc, SubWidthC, and SubHeightC may be specified in the future by ITU-T | ISO/IEC.

**Table 6-1 –SubWidthC, and SubHeightC values derived from chroma\_format\_idc and separate\_colour\_plane\_flag**

| chroma_format_idc | separate_colour_plane_flag | Chroma Format | SubWidthC | SubHeightC |
|-------------------|----------------------------|---------------|-----------|------------|
| 0                 | 0                          | monochrome    | -         | -          |
| 1                 | 0                          | 4:2:0         | 2         | 2          |
| 2                 | 0                          | 4:2:2         | 2         | 1          |
| 3                 | 0                          | 4:4:4         | 1         | 1          |
| 3                 | 1                          | 4:4:4         | -         | -          |

Replace the following paragraph:

In 4:4:4 sampling, each of the two chroma arrays has the same height and width as the luma array.

with:

In 4:4:4 sampling, depending on the value of separate\_colour\_plane\_flag, the following applies.

- If separate\_colour\_plane\_flag is equal to 0, each of the two chroma arrays has the same height and width as the luma array.

- Otherwise (`separate_colour_plane_flag` is equal to 1), the three colour planes are separately processed as monochrome sampled pictures.

*Replace the following paragraph:*

The number of bits necessary for the representation of each of the samples in the luma and chroma arrays in a video sequence is in the range of 8 to 12, and the number of bits used in the luma array may differ from the number of bits used in the chroma arrays.

*with:*

The number of bits necessary for the representation of each of the samples in the luma and chroma arrays in a video sequence is in the range of 8 to 14, and the number of bits used in the luma array may differ from the number of bits used in the chroma arrays.

*Replace the following paragraph:*

- If `chroma_format_idc` is equal to 0 (monochrome), `MbWidthC` and `MbHeightC` are both equal to 0 (as no chroma arrays are specified for monochrome video).

*with:*

- If `chroma_format_idc` is equal to 0 (monochrome) or `separate_colour_plane_flag` is equal to 1, `MbWidthC` and `MbHeightC` are both set equal to 0.

*In subclause 6.3 “Spatial subdivision of pictures and slices”, make the following changes:*

*Replace the following:*

Each macroblock is comprised of one 16x16 luma array and, when the video format is not monochrome, two corresponding chroma sample arrays. When macroblock-adaptive frame/field decoding is not in use, each macroblock represents a spatial rectangular region of the picture. For example, a picture may be divided into two slices as shown in Figure 6-7.

*with:*

Each macroblock is comprised of one 16x16 luma array and, when the chroma sampling format is not equal to 4:0:0 and `separate_colour_plane_flag` is equal to 0, two corresponding chroma sample arrays. When `separate_colour_plane_flag` is equal to 1, each macroblock is comprised of one 16x16 luma or chroma sample array. When macroblock-adaptive frame/field decoding is not in use, each macroblock represents a spatial rectangular region of the picture. For example, a picture may be divided into two slices as shown in Figure 6-7.

When a picture is coded using three separate colour planes (`separate_colour_plane_flag` is equal to 1), a slice contains only macroblocks of one colour component being identified by the corresponding value of `colour_plane_id`, and each colour component array of a picture consists of slices having the same `colour_plane_id` value. Coded slices with different values of `colour_plane_id` within an access unit can be interleaved with each other under the constraint that for each value of `colour_plane_id`, the coded slice NAL units with that value `colour_plane_id` shall be in the order of increasing macroblock address for the first macroblock of each coded slice NAL unit.

*Insert a new subclause 6.4.3.1 as follows:*

#### **6.4.3.1 Inverse 4x4 Cb or Cr block scanning process for ChromaArrayType equal to 3**

This process is only invoked when ChromaArrayType is equal to 3.

The inverse 4x4 chroma block scanning process is identical to inverse 4x4 luma block scanning process as specified in subclause 6.4.3 when substituting the term “luma” with the term “Cb” or the term “Cr”, and substituting the term “luma4x4BlkIdx” with the term “cb4x4BlkIdx” or the term “cr4x4BlkIdx” in all places in subclause 6.4.3.

*Insert a new subclause 6.4.4.1 as follows:*

#### **6.4.4.1 Inverse 8x8 Cb or Cr block scanning process for ChromaArrayType equal to 3**

This process is only invoked when ChromaArrayType is equal to 3.

The inverse 8x8 chroma block scanning process is identical to inverse 8x8 luma block scanning process as specified in subclause 6.4.4 when substituting the term “luma” with the term “Cb” or the term “Cr”, and substituting the term “luma8x8BlkIdx” with the term “cb8x8BlkIdx” or the term “cr8x8BlkIdx” in all places in subclause 6.4.4.

*In subclause 6.4.8 "Derivation processes for neighbouring macroblocks, blocks, and partitions", make the following changes.*

*Insert the following sentence after the paragraph starting with “Subclause 6.4.8.2 specifies”:*

Subclause 6.4.8.2.1 specifies the derivation process for neighbouring 8x8 chroma blocks for ChromaArrayType equal to 3.

*Insert the following sentence after the paragraph starting with “Subclause 6.4.8.4 specifies”:*

Subclause 6.4.8.4.1 specifies the derivation process for neighbouring 4x4 chroma blocks for ChromaArrayType equal to 3.

*Replace the paragraph starting with “Table 6-2 specifies” with the following:*

Table 6-2 specifies the values for the difference of luma location (  $x_D$ ,  $y_D$  ) for the input and the replacement for N in mbAddrN, mbPartIdxN, subMbPartIdxN, luma8x8BlkIdxN, cb8x8BlkIdxN, cr8x8BlkIdxN, luma4x4BlkIdxN, cb4x4BlkIdxN, cr4x4BlkIdxN, and chroma4x4BlkIdxN for the output. These input and output assignments are used in subclauses 6.4.8.1 to 6.4.8.5. The variable predPartWidth is specified when Table 6-2 is referred to.

*Insert a new subclause 6.4.8.2.1 as follows:*

#### **6.4.8.2.1 Derivation process for neighbouring 8x8 chroma blocks for ChromaArrayType equal to 3**

This process is only invoked when ChromaArrayType is equal to 3.

The derivation process for neighbouring 8x8 chroma block is identical to the derivation process for neighbouring 8x8 luma block as specified in subclause 6.4.8.2 when substituting the term “luma” with the term “Cb” or the term “Cr”, and substituting the term “luma8x8BlkIdx” with the term “cb8x8BlkIdx” or the term “cr8x8BlkIdx” in all places in subclause 6.4.8.2.

In subclause 6.4.8.4 “Derivation process for neighbouring 4x4 chroma blocks”, make the following changes.

Replace the paragraph starting with “Depending on chroma\_format\_idc” with the following:

The position ( x, y ) of the upper-left sample of the 4x4 chroma block with index chroma4x4BlkIdx is derived by

$$x = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 0) \quad (6-25)$$

$$y = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 1) \quad (6-26)$$

Update all equation numbers in the subsequent subclauses due to the removal of equation 6-27 and 6-28.

Insert a new subclause 6.4.8.4.1 as follows:

#### 6.4.8.4.1 Derivation process for neighbouring 4x4 chroma blocks for ChromaArrayType equal to 3

This process is only invoked when ChromaArrayType is equal to 3.

The derivation process for neighbouring 4x4 chroma block in 4:4:4 chroma format is identical to the derivation process for neighbouring 4x4 luma block as specified in subclause 6.4.8.3 when substituting the term “luma” with the term “Cb” or the term “Cr”, and substituting the term “luma4x4BlkIdx” with the term “cb4x4BlkIdx” or the term “cr4x4BlkIdx” in all places in subclause 6.4.8.3.

In subclause 7.3.2.1 “Sequence parameter set RBSP syntax”, make the following changes.

Replace the syntax element “residual\_colour\_transform\_flag” with the syntax element “separate\_colour\_plane\_flag”.

Replace the expression “profile\_idc == 144” with “profile\_idc == 44 || profile\_idc == 244”.

Replace the expression “i < 8” with “i < (( chroma\_format\_idc != 3 ) ? 8 : 12 )”.

In subclause 7.3.2.2 “Picture parameter set RBSP syntax”, replace the expression “i < 6 + 2 \* transform\_8x8\_mode\_flag” with “i < 6 + (( chroma\_format\_idc != 3 ) ? 2 : 6 ) \* transform\_8x8\_mode\_flag”.

Replace the slice data partition B RBSP syntax table of subclause 7.3.2.9.2 “Slice data partition B RBSP syntax” with the following:

| slice_data_partition_b_layer_rbsp( ) {                            | C   | Descriptor |
|-------------------------------------------------------------------|-----|------------|
| <b>slice_id</b>                                                   | All | ue(v)      |
| if( separate_colour_plane_flag == 1 )                             |     |            |
| <b>colour_plane_id</b>                                            | All | u(2)       |
| if( redundant_pic_cnt_present_flag )                              |     |            |
| <b>redundant_pic_cnt</b>                                          | All | ue(v)      |
| slice_data( ) /* only category 3 parts of slice_data( ) syntax */ | 3   |            |
| rbpslice_trailing_bits( )                                         | 3   |            |
| }                                                                 |     |            |

Replace the slice data partition C RBSP syntax table of subclause 7.3.2.9.3 “Slice data partition C RBSP syntax” with the following:

| slice_data_partition_c_layer_rbsp( ) {                            | C   | Descriptor |
|-------------------------------------------------------------------|-----|------------|
| <b>slice_id</b>                                                   | All | ue(v)      |
| if( separate_colour_plane_flag == 1 )                             |     |            |
| <b>colour_plane_id</b>                                            | All | u(2)       |
| if( redundant_pic_cnt_present_flag )                              |     |            |
| <b>redundant_pic_cnt</b>                                          | All | ue(v)      |
| slice_data( ) /* only category 4 parts of slice_data( ) syntax */ | 4   |            |
| rbps_slice_trailing_bits( )                                       | 4   |            |
| }                                                                 |     |            |

Replace the slice header syntax table of subclause 7.3.3 “Slice header syntax” with the following:

| slice_header( ) {                                                    | C | Descriptor |
|----------------------------------------------------------------------|---|------------|
| <b>first_mb_in_slice</b>                                             | 2 | ue(v)      |
| <b>slice_type</b>                                                    | 2 | ue(v)      |
| <b>pic_parameter_set_id</b>                                          | 2 | ue(v)      |
| if( separate_colour_plane_flag == 1 )                                |   |            |
| <b>colour_plane_id</b>                                               | 2 | u(2)       |
| <b>frame_num</b>                                                     | 2 | u(v)       |
| if( !frame_mbs_only_flag ) {                                         |   |            |
| <b>field_pic_flag</b>                                                | 2 | u(1)       |
| if( field_pic_flag )                                                 |   |            |
| <b>bottom_field_flag</b>                                             | 2 | u(1)       |
| }                                                                    |   |            |
| if( nal_unit_type == 5 )                                             |   |            |
| <b>idr_pic_id</b>                                                    | 2 | ue(v)      |
| if( pic_order_cnt_type == 0 ) {                                      |   |            |
| <b>pic_order_cnt_lsb</b>                                             | 2 | u(v)       |
| if( pic_order_present_flag && !field_pic_flag )                      |   |            |
| <b>delta_pic_order_cnt_bottom</b>                                    | 2 | se(v)      |
| }                                                                    |   |            |
| if( pic_order_cnt_type == 1 && !delta_pic_order_always_zero_flag ) { |   |            |
| <b>delta_pic_order_cnt[ 0 ]</b>                                      | 2 | se(v)      |
| if( pic_order_present_flag && !field_pic_flag )                      |   |            |
| <b>delta_pic_order_cnt[ 1 ]</b>                                      | 2 | se(v)      |
| }                                                                    |   |            |
| if( redundant_pic_cnt_present_flag )                                 |   |            |
| <b>redundant_pic_cnt</b>                                             | 2 | ue(v)      |
| if( slice_type == B )                                                |   |            |
| <b>direct_spatial_mv_pred_flag</b>                                   | 2 | u(1)       |
| if( slice_type == P    slice_type == SP    slice_type == B ) {       |   |            |
| <b>num_ref_idx_active_override_flag</b>                              | 2 | u(1)       |
| if( num_ref_idx_active_override_flag ) {                             |   |            |

|                                                                                                                                  |   |       |
|----------------------------------------------------------------------------------------------------------------------------------|---|-------|
| <b>num_ref_idx_l0_active_minus1</b>                                                                                              | 2 | ue(v) |
| if( slice_type == B )                                                                                                            |   |       |
| <b>num_ref_idx_l1_active_minus1</b>                                                                                              | 2 | ue(v) |
| }                                                                                                                                |   |       |
| }                                                                                                                                |   |       |
| ref_pic_list_reordering( )                                                                                                       | 2 |       |
| if( ( weighted_pred_flag &&<br>( slice_type == P    slice_type == SP ) )   <br>( weighted_bipred_idc == 1 && slice_type == B ) ) |   |       |
| pred_weight_table( )                                                                                                             | 2 |       |
| if( nal_ref_idc != 0 )                                                                                                           |   |       |
| dec_ref_pic_marking( )                                                                                                           | 2 |       |
| if( entropy_coding_mode_flag && slice_type != I &&<br>slice_type != SI )                                                         |   |       |
| <b>cabac_init_idc</b>                                                                                                            | 2 | ue(v) |
| <b>slice_qp_delta</b>                                                                                                            | 2 | se(v) |
| if( slice_type == SP    slice_type == SI ) {                                                                                     |   |       |
| if( slice_type == SP )                                                                                                           |   |       |
| <b>sp_for_switch_flag</b>                                                                                                        | 2 | u(1)  |
| <b>slice_qs_delta</b>                                                                                                            | 2 | se(v) |
| }                                                                                                                                |   |       |
| if( deblocking_filter_control_present_flag ) {                                                                                   |   |       |
| <b>disable_deblocking_filter_idc</b>                                                                                             | 2 | ue(v) |
| if( disable_deblocking_filter_idc != 1 ) {                                                                                       |   |       |
| <b>slice_alpha_c0_offset_div2</b>                                                                                                | 2 | se(v) |
| <b>slice_beta_offset_div2</b>                                                                                                    | 2 | se(v) |
| }                                                                                                                                |   |       |
| }                                                                                                                                |   |       |
| if( num_slice_groups_minus1 > 0 &&<br>slice_group_map_type >= 3 && slice_group_map_type <= 5 )                                   |   |       |
| <b>slice_group_change_cycle</b>                                                                                                  | 2 | u(v)  |
| }                                                                                                                                |   |       |

In the syntax table of subclause 7.3.3.2 "Prediction weight table syntax", replace the syntax expression:

chroma\_format\_idc != 0

with:

ChromaArrayType != 0

(in all 3 occurrences)

In the syntax table of subclause 7.3.5.1 “Macroblock prediction syntax”, replace the syntax expression

chroma\_format\_idc != 0

with:

ChromaArrayType == 1 || ChromaArrayType == 2

(in one occurrence)

Replace the content of subclause 7.3.5.3 “Residual data syntax” with the following:

| residual( ) {                                                  | C     | Descriptor |
|----------------------------------------------------------------|-------|------------|
| if( !entropy_coding_mode_flag )                                |       |            |
| residual_block = residual_block_cavlc                          |       |            |
| else                                                           |       |            |
| residual_block = residual_block_cabac                          |       |            |
| residual_luma( i16x16DClevel, i16x16AClevel, level, level8x8 ) |       |            |
| Intra16x16DCLevel = i16x16DClevel                              |       |            |
| Intra16x16ACLevel = i16x16AClevel                              |       |            |
| LumaLevel = level                                              |       |            |
| LumaLevel8x8 = level8x8                                        |       |            |
| if( ChromaArrayType == 1    ChromaArrayType == 2 ) {           |       |            |
| NumC8x8 = 4 / ( SubWidthC * SubHeightC )                       |       |            |
| for( iCbCr = 0; iCbCr < 2; iCbCr++ )                           |       |            |
| if( CodedBlockPatternChroma & 3 )                              |       |            |
| /* chroma DC residual present */                               |       |            |
| residual_block( ChromaDCLevel[ iCbCr ], 4 * NumC8x8 )          | 3   4 |            |
| else                                                           |       |            |
| for( i = 0; i < 4 * NumC8x8; i++ )                             |       |            |
| ChromaDCLevel[ iCbCr ][ i ] = 0                                |       |            |
| for( iCbCr = 0; iCbCr < 2; iCbCr++ )                           |       |            |
| for( i8x8 = 0; i8x8 < NumC8x8; i8x8++ )                        |       |            |
| for( i4x4 = 0; i4x4 < 4; i4x4++ )                              |       |            |
| if( CodedBlockPatternChroma & 2 )                              |       |            |
| /* chroma AC residual present */                               |       |            |
| residual_block( ChromaACLevel[ iCbCr ][ i8x8*4+i4x4 ], 15 )    | 3   4 |            |
| else                                                           |       |            |
| for( i = 0; i < 15; i++ )                                      |       |            |
| ChromaACLevel[ iCbCr ][ i8x8*4+i4x4 ][ i ] = 0                 |       |            |
| } else if( ChromaArrayType == 3 ) {                            |       |            |
| residual_luma( i16x16DClevel, i16x16AClevel, level, level8x8 ) |       |            |
| CbIntra16x16DCLevel = i16x16DClevel                            |       |            |
| CbIntra16x16ACLevel = i16x16AClevel                            |       |            |
| CbLevel = level                                                |       |            |
| CbLevel8x8 = level8x8                                          |       |            |
| residual_luma( i16x16DClevel, i16x16AClevel, level, level8x8 ) |       |            |
| CrIntra16x16DCLevel = i16x16DClevel                            |       |            |

|                                     |  |  |
|-------------------------------------|--|--|
| CrIntra16x16ACLevel = i16x16ACLevel |  |  |
| CrLevel = level                     |  |  |
| CrLevel8x8 = level8x8               |  |  |
| }                                   |  |  |
| }                                   |  |  |

Replace the content of subclause 7.3.5.3.2 “Residual block CABAC syntax” with the following:

| residual_block_cabac( coeffLevel, maxNumCoeff ) {                                                                               | C     | Descriptor |
|---------------------------------------------------------------------------------------------------------------------------------|-------|------------|
| if( maxNumCoeff != 64    (ChromaArrayType == 3) )                                                                               |       |            |
| <b>coded_block_flag</b>                                                                                                         | 3   4 | ae(v)      |
| if( coded_block_flag ) {                                                                                                        |       |            |
| numCoeff = maxNumCoeff                                                                                                          |       |            |
| i = 0                                                                                                                           |       |            |
| do {                                                                                                                            |       |            |
| <b>significant_coeff_flag[ i ]</b>                                                                                              | 3   4 | ae(v)      |
| if( significant_coeff_flag[ i ] ) {                                                                                             |       |            |
| <b>last_significant_coeff_flag[ i ]</b>                                                                                         | 3   4 | ae(v)      |
| if( last_significant_coeff_flag[ i ] ) {                                                                                        |       |            |
| numCoeff = i + 1                                                                                                                |       |            |
| for( j = numCoeff; j < maxNumCoeff; j++ )                                                                                       |       |            |
| coeffLevel[ j ] = 0                                                                                                             |       |            |
| }                                                                                                                               |       |            |
| }                                                                                                                               |       |            |
| i++                                                                                                                             |       |            |
| } while( i < numCoeff - 1 )                                                                                                     |       |            |
| <b>coeff_abs_level_minus1[ numCoeff - 1 ]</b>                                                                                   | 3   4 | ae(v)      |
| <b>coeff_sign_flag[ numCoeff - 1 ]</b>                                                                                          | 3   4 | ae(v)      |
| coeffLevel[ numCoeff - 1 ] =<br>( coeff_abs_level_minus1[ numCoeff - 1 ] + 1 ) *<br>( 1 - 2 * coeff_sign_flag[ numCoeff - 1 ] ) |       |            |
| for( i = numCoeff - 2; i >= 0; i-- )                                                                                            |       |            |
| if( significant_coeff_flag[ i ] ) {                                                                                             |       |            |
| <b>coeff_abs_level_minus1[ i ]</b>                                                                                              | 3   4 | ae(v)      |
| <b>coeff_sign_flag[ i ]</b>                                                                                                     | 3   4 | ae(v)      |
| coeffLevel[ i ] = ( coeff_abs_level_minus1[ i ] + 1 ) *<br>( 1 - 2 * coeff_sign_flag[ i ] )                                     |       |            |
| } else                                                                                                                          |       |            |
| coeffLevel[ i ] = 0                                                                                                             |       |            |
| } else                                                                                                                          |       |            |
| for( i = 0; i < maxNumCoeff; i++ )                                                                                              |       |            |
| coeffLevel[ i ] = 0                                                                                                             |       |            |
| }                                                                                                                               |       |            |

Insert a new subclause 7.3.5.3.3 as follows:

### 7.3.5.3.3 Residual luma data syntax

| residual_luma( i16x16DClevel, i16x16AClevel, level, level8x8 ) { | C     | Descriptor |
|------------------------------------------------------------------|-------|------------|
| if( !entropy_coding_mode_flag )                                  |       |            |
| residual_block = residual_block_cavlc                            |       |            |
| else                                                             |       |            |
| residual_block = residual_block_cabac                            |       |            |
| if( MbPartPredMode( mb_type, 0 ) == Intra_16x16 )                |       |            |
| residual_block( i16x16DClevel, 16 )                              | 3     |            |
| for( i8x8 = 0; i8x8 < 4; i8x8++ )                                |       |            |
| if( !transform_size_8x8_flag    !entropy_coding_mode_flag )      |       |            |
| for( i4x4 = 0; i4x4 < 4; i4x4++ ) {                              |       |            |
| if( CodedBlockPatternLuma & ( 1 << i8x8 ) )                      |       |            |
| if( MbPartPredMode( mb_type, 0 ) == Intra_16x16 )                |       |            |
| residual_block( i16x16AClevel[ i8x8*4+ i4x4 ], 15 )              | 3     |            |
| else                                                             |       |            |
| residual_block( level[ i8x8 * 4 + i4x4 ], 16 )                   | 3   4 |            |
| else if( MbPartPredMode( mb_type, 0 ) == Intra_16x16 )           |       |            |
| for( i = 0; i < 15; i++ )                                        |       |            |
| i16x16AClevel[ i8x8 * 4 + i4x4 ][ i ] = 0                        |       |            |
| else                                                             |       |            |
| for( i = 0; i < 16; i++ )                                        |       |            |
| level[ i8x8 * 4 + i4x4 ][ i ] = 0                                |       |            |
| if( !entropy_coding_mode_flag && transform_size_8x8_flag )       |       |            |
| for( i = 0; i < 16; i++ )                                        |       |            |
| level8x8[ i8x8 ][ 4 * i + i4x4 ] = level[ i8x8 * 4 + i4x4 ][ i ] |       |            |
| }                                                                |       |            |
| else if( CodedBlockPatternLuma & ( 1 << i8x8 ) )                 |       |            |
| residual_block( level8x8[ i8x8 ], 64 )                           | 3   4 |            |
| else                                                             |       |            |
| for( i = 0; i < 64; i++ )                                        |       |            |
| level8x8[ i8x8 ][ i ] = 0                                        |       |            |
| }                                                                |       |            |

In subclause 7.4.1.2.5 “Order of VCL NAL units and association to coded pictures”, replace the following paragraph:

Otherwise (arbitrary slice order is not allowed), the order of coded slice of an IDR picture NAL units shall be in the order of increasing macroblock address for the first macroblock of each coded slice of an IDR picture NAL unit.

with:

- Otherwise (arbitrary slice order is not allowed), the following applies.
  - If separate\_colour\_plane\_flag is equal to 0, the order of coded slices of IDR picture NAL units shall be in the order of increasing macroblock address for the first macroblock of each coded slice of an IDR picture NAL unit.

- Otherwise (separate\_colour\_plane\_flag is equal to 1), the order of coded slices of IDR picture NAL units for each value of colour\_plane\_id shall be in the order of increasing macroblock address for the first macroblock of each coded slice of the particular value of colour\_plane\_id of an IDR picture NAL unit.

NOTE – When separate\_colour\_plane\_flag is equal to 1, the relative ordering of coded slices having different values of colour\_plane\_id is not constrained.

In subclause 7.4.2.1 “Sequence parameter set RBSP semantics”, make the following changes.

Replace the paragraphs that state as follows:

NOTE – When more than one of constraint\_set0\_flag, constraint\_set1\_flag, or constraint\_set2\_flag are equal to 1, the bitstream obeys the constraints of all of the indicated subclauses of subclause A.2.

**constraint\_set3\_flag** indicates the following.

- If profile\_idc is equal to 66, 77, or 88 and level\_idc is equal to 11, constraint\_set3\_flag equal to 1 indicates that the bitstream obeys all constraints specified in Annex A for level 1b and constraint\_set3\_flag equal to 0 indicates that the bitstream may or may not obey all constraints specified in Annex A for level 1b.
- Otherwise (profile\_idc is equal to 100, 110, 122, or 144 or level\_idc is not equal to 11), the value of 1 for constraint\_set3\_flag is reserved for future use by ITU-T | ISO/IEC. constraint\_set3\_flag shall be equal to 0 in bitstreams conforming to this Recommendation | International Standard when profile\_idc is equal to 100, 110, 122, or 144 or level\_idc is not equal to 11. Decoders conforming to this Recommendation | International Standard shall ignore the value of constraint\_set3\_flag when profile\_idc is equal to 100, 110, 122, or 144 or level\_idc is not equal to 11.

with:

NOTE – When one or more than one of constraint\_set0\_flag, constraint\_set1\_flag, or constraint\_set2\_flag are equal to 1, the bitstream must obey the constraints of all of the indicated subclauses of subclause A.2. When profile\_idc is equal to 44, 100, 110, 122, or 244, the values of constraint\_set0\_flag, constraint\_set1\_flag, and constraint\_set2\_flag must all be equal to 0.

**constraint\_set3\_flag** indicates the following.

- If profile\_idc is equal to 66, 77, or 88 and level\_idc is equal to 11, constraint\_set3\_flag equal to 1 indicates that the bitstream obeys all constraints specified in Annex A for level 1b and constraint\_set3\_flag equal to 0 indicates that the bitstream may or may not obey all constraints specified in Annex A for level 1b.
- Otherwise, if profile\_idc is equal to 100 or 110, constraint\_set3\_flag equal to 1 indicates that the bitstream obeys all constraints specified in Annex A for the High 10 Intra profile, and constraint\_set3\_flag equal to 0 indicates that the bitstream may or may not obey these corresponding constraints.
- Otherwise, if profile\_idc is equal to 122, constraint\_set3\_flag equal to 1 indicates that the bitstream obeys all constraints specified in Annex A for the High 4:2:2 Intra profile, and constraint\_set3\_flag equal to 0 indicates that the bitstream may or may not obey these corresponding constraints.
- Otherwise, if profile\_idc is equal to 44, constraint\_set3\_flag shall be equal to 1. When profile\_idc is equal to 44, the value of 0 for constraint\_set3\_flag is forbidden.
- Otherwise, if profile\_idc is equal to 244, constraint\_set3\_flag equal to 1 indicates that the bitstream obeys all constraints specified in Annex A for the High 4:4:4 Intra profile, and constraint\_set3\_flag equal to 0 indicates that the bitstream may or may not obey these corresponding constraints.
- Otherwise (profile\_idc is equal to 66, 77, 88 and level\_idc is not equal to 11), the value of 1 for constraint\_set3\_flag is reserved for future use by ITU-T | ISO/IEC. constraint\_set3\_flag shall be equal to 0 in bitstreams conforming to this Recommendation | International Standard when profile\_idc is equal

to 66, 77, or 88 and level\_idc is not equal to 11. Decoders conforming to this Recommendation | International Standard shall ignore the value of constraint\_set3\_flag when profile\_idc is equal to 66, 77, or 88 and level\_idc is not equal to 11.

Delete the paragraph starting with “residual\_colour\_transform\_flag”.

Add the following paragraph before the paragraph starting with “bit\_depth\_luma\_minus8”.

**separate\_colour\_plane\_flag** equal to 1 specifies that the three colour components of the 4:4:4 chroma format are coded separately. **separate\_colour\_plane\_flag** equal to 0 specifies that the three colour components of the 4:4:4 chroma format are not coded separately. When **separate\_colour\_plane\_flag** is not present, it shall be inferred to be equal to 0. When **separate\_colour\_plane\_flag** is equal to 1, the primary coded picture consists of three separate components, each of which consists of coded samples of one colour plane (Y or Cb or Cr) that conforms to the monochrome coding syntax. In this case, each picture is associated with a specific colour\_plane\_id value.

NOTE – There is no dependency in decoding processes between the colour planes having different colour\_plane\_id values. For example, the decoding process of a monochrome picture with one value of colour\_plane\_id does not use any data from monochrome pictures having different values of colour\_plane\_id for inter prediction.

Depending on the value of **separate\_colour\_plane\_flag**, assign the value of the variable ChromaArrayType as follows.

- If **separate\_colour\_plane\_flag** is equal to 0, ChromaArrayType is set equal to chroma\_format\_idc.
- Otherwise (**separate\_colour\_plane\_flag** is equal to 1), ChromaArrayType is set equal to 0.

Replace the paragraph starting with “bit\_depth\_luma\_minus8” with the following:

**bit\_depth\_luma\_minus8** specifies the bit depth of the samples of the luma array and the value of the luma quantisation parameter range offset  $QpBdOffset_Y$ , as specified by

$$BitDepth_Y = 8 + bit\_depth\_luma\_minus8 \quad (7-1)$$

$$QpBdOffset_Y = 6 * bit\_depth\_luma\_minus8 \quad (7-2)$$

When **bit\_depth\_luma\_minus8** is not present, it shall be inferred to be equal to 0. **bit\_depth\_luma\_minus8** shall be in the range of 0 to 6, inclusive.

Replace the paragraph starting with “bit\_depth\_chroma\_minus8” with the following.

**bit\_depth\_chroma\_minus8** specifies the bit depth of the samples of the chroma arrays and the value of the chroma quantisation parameter range offset  $QpBdOffset_C$ , as specified by

$$BitDepth_C = 8 + bit\_depth\_chroma\_minus8 \quad (7-3)$$

$$QpBdOffset_C = 6 * bit\_depth\_chroma\_minus8 \quad (7-4)$$

When **bit\_depth\_chroma\_minus8** is not present, it shall be inferred to be equal to 0. **bit\_depth\_chroma\_minus8** shall be in the range of 0 to 6, inclusive.

NOTE – The value of **bit\_depth\_chroma\_minus8** is not used in the decoding process when ChromaArrayType is equal to 0. In particular, when **separate\_colour\_plane\_flag** is equal to 1, each colour plane is decoded as a distinct monochrome picture using the luma component decoding process (except for the selection of scaling matrices) and the luma bit depth is used for all three colour components.

Replace the paragraph starting with “seq\_scaling\_matrix\_present\_flag equal to 1” with the following:

seq\_scaling\_matrix\_present\_flag equal to 1 specifies that the flags seq\_scaling\_list\_present\_flag[ i ] for i = 0..11 are present. seq\_scaling\_matrix\_present\_flag equal to 0 specifies that these flags are not present and the sequence-level scaling list specified by Flat\_4x4\_16 shall be inferred for i = 0..5 and the sequence-level scaling list specified by Flat\_8x8\_16 shall be inferred for i = 6..11. When seq\_scaling\_matrix\_present\_flag is not present, it shall be inferred to be equal to 0.

Replace Table 7–2 with the following:

**Table 7-2 – Assignment of mnemonic names to scaling list indices and specification of fall-back rule**

| Value of scaling list index | Mnemonic name   | Block size | MB prediction type | Component | Scaling list fall-back rule set A | Scaling list fall-back rule set B | Default scaling list |
|-----------------------------|-----------------|------------|--------------------|-----------|-----------------------------------|-----------------------------------|----------------------|
| 0                           | Sl_4x4_Intra_Y  | 4x4        | Intra              | Y         | default scaling list              | sequence-level scaling list       | Default_4x4_Intra    |
| 1                           | Sl_4x4_Intra_Cb | 4x4        | Intra              | Cb        | scaling list for i = 0            | scaling list for i = 0            | Default_4x4_Intra    |
| 2                           | Sl_4x4_Intra_Cr | 4x4        | Intra              | Cr        | scaling list for i = 1            | scaling list for i = 1            | Default_4x4_Intra    |
| 3                           | Sl_4x4_Inter_Y  | 4x4        | Inter              | Y         | default scaling list              | sequence-level scaling list       | Default_4x4_Inter    |
| 4                           | Sl_4x4_Inter_Cb | 4x4        | Inter              | Cb        | scaling list for i = 3            | scaling list for i = 3            | Default_4x4_Inter    |
| 5                           | Sl_4x4_Inter_Cr | 4x4        | Inter              | Cr        | scaling list for i = 4            | scaling list for i = 4            | Default_4x4_Inter    |
| 6                           | Sl_8x8_Intra_Y  | 8x8        | Intra              | Y         | default scaling list              | sequence-level scaling list       | Default_8x8_Intra    |
| 7                           | Sl_8x8_Inter_Y  | 8x8        | Inter              | Y         | default scaling list              | sequence-level scaling list       | Default_8x8_Inter    |
| 8                           | Sl_8x8_Intra_Cb | 8x8        | Intra              | Cb        | scaling list for i = 6            | scaling list for i = 6            | Default_8x8_Intra    |
| 9                           | Sl_8x8_Inter_Cb | 8x8        | Inter              | Cb        | scaling list for i = 7            | scaling list for i = 7            | Default_8x8_Inter    |
| 10                          | Sl_8x8_Intra_Cr | 8x8        | Intra              | Cr        | scaling list for i = 8            | scaling list for i = 8            | Default_8x8_Intra    |
| 11                          | Sl_8x8_Inter_Cr | 8x8        | Inter              | Cr        | scaling list for i = 9            | scaling list for i = 9            | Default_8x8_Inter    |

Replace the paragraph starting with “frame\_crop\_left\_offset, frame\_crop\_right\_offset, frame\_crop\_top\_offset, frame\_crop\_bottom\_offset” with the following.

frame\_crop\_left\_offset, frame\_crop\_right\_offset, frame\_crop\_top\_offset, frame\_crop\_bottom\_offset specify the samples of the pictures in the coded video sequence that are output from the decoding process, in terms of a rectangular region specified in frame coordinates for output.

The variables CropUnitX and CropUnitY are derived as follows:

- If ChromaArrayType is equal to 0, CropUnitX and CropUnitY are derived as

$$\text{CropUnitX} = 1 \quad (7-16)$$

$$\text{CropUnitY} = 2 - \text{frame\_mbs\_only\_flag} \quad (7-17)$$

- Otherwise (ChromaArrayType is equal to 1, 2, or 3), CropUnitX and CropUnitY are derived as

$$\text{CropUnitX} = \text{SubWidthC} \quad (7-18)$$

$$\text{CropUnitY} = \text{SubHeightC} * (2 - \text{frame\_mbs\_only\_flag}) \quad (7-19)$$

The frame cropping rectangle contains luma samples with horizontal frame coordinates from  $\text{CropUnitX} * \text{frame\_crop\_left\_offset}$  to  $\text{PicWidthInSamples}_L - (\text{CropUnitX} * \text{frame\_crop\_right\_offset} + 1)$  and vertical frame coordinates from  $\text{CropUnitY} * \text{frame\_crop\_top\_offset}$  to  $(16 * \text{FrameHeightInMbs}) - (\text{CropUnitY} * \text{frame\_crop\_bottom\_offset} + 1)$ , inclusive. The value of  $\text{frame\_crop\_left\_offset}$  shall be in the range of 0 to  $(\text{PicWidthInSamples}_L / \text{CropUnitX}) - (\text{frame\_crop\_right\_offset} + 1)$ , inclusive; and the value of  $\text{frame\_crop\_top\_offset}$  shall be in the range of 0 to  $(16 * \text{FrameHeightInMbs} / \text{CropUnitY}) - (\text{frame\_crop\_bottom\_offset} + 1)$ , inclusive.

When  $\text{frame\_cropping\_flag}$  is equal to 0, the values of  $\text{frame\_crop\_left\_offset}$ ,  $\text{frame\_crop\_right\_offset}$ ,  $\text{frame\_crop\_top\_offset}$ , and  $\text{frame\_crop\_bottom\_offset}$  shall be inferred to be equal to 0.

When ChromaArrayType is not equal to 0, the corresponding specified samples of the two chroma arrays are the samples having frame coordinates  $(x / \text{SubWidthC}, y / \text{SubHeightC})$ , where  $(x, y)$  are the frame coordinates of the specified luma samples.

For decoded fields, the specified samples of the decoded field are the samples that fall within the rectangle specified in frame coordinates.

*In subclause 7.4.2.1.2 “Sequence parameter set extension RBSP semantics”, replace the text:*

The value of  $\text{chroma\_format\_idc}$

*with:*

The value of  $\text{chroma\_format\_idc}$  and the value of ChromaArrayType

*(in one occurrence)*

*Add the following note at the end of subclause 7.4.2.2 “Picture parameter set RBSP semantics”:*

NOTE – The values of  $\text{bit\_depth\_chroma\_minus8}$ ,  $\text{chroma\_qp\_index\_offset}$  and  $\text{second\_chroma\_qp\_index\_offset}$  are not used in the decoding process when ChromaArrayType is equal to 0. In particular, when  $\text{separate\_colour\_plane\_flag}$  is equal to 1, each colour plane is decoded as a distinct monochrome picture using the luma component decoding process (except for the selection of scaling matrices), including the application of the luma quantisation parameter derivation process without application of an offset for the decoding of the pictures having  $\text{colour\_plane\_id}$  not equal to 0.

*In subclause 7.4.2.9.1 “Slice data partition A RBSP semantics”, replace the paragraph that states as follows:*

**slice\_id** identifies the slice associated with the data partition. Each slice shall have a unique  $\text{slice\_id}$  value within the coded picture that contains the slice. When arbitrary slice order is not allowed as specified in Annex A, the first slice of a

coded picture, in decoding order, shall have slice\_id equal to 0 and the value of slice\_id shall be incremented by one for each subsequent slice of the coded picture in decoding order.

with:

**slice\_id** identifies the slice associated with the data partition. The value of slice\_id is constrained as follows.

- If separate\_colour\_plane\_flag is equal to 0, the following applies.
  - If arbitrary slice order is not allowed as specified in Annex A, the first slice of a coded picture, in decoding order, shall have slice\_id equal to 0 and the value of slice\_id shall be incremented by one for each subsequent slice of the coded picture in decoding order.
  - Otherwise (arbitrary slice order is allowed), each slice shall have a unique slice\_id value within the set of slices of the coded picture.
- Otherwise (separate\_colour\_plane\_flag is equal to 1), the following applies.
  - If arbitrary slice order is not allowed as specified in Annex A, the first slice of a coded picture having each value of colour\_plane\_id, in decoding order, shall have slice\_id equal to 0 and the value of slice\_id shall be incremented by one for each subsequent slice of the coded picture having the same value of colour\_plane\_id, in decoding order.
  - Otherwise (arbitrary slice order is allowed) each slice shall have a unique slice\_id value within each set of slices of the coded picture that have the same value of colour\_plane\_id.

In subclause 7.4.2.9.2 “Slice data partition B RBSP semantics”, insert the following after the paragraph starting with “**slice\_id**”.

**colour\_plane\_id** specifies the colour plane associated with the current slice RBSP when separate\_colour\_plane\_flag is equal to 1. The value of colour\_plane\_id shall be in the range of 0 to 2, inclusive. colour\_plane\_id equal to 0, 1, and 2 correspond to the Y, Cb, and Cr planes, respectively.

NOTE – There is no dependency between the decoding processes of pictures having different values of colour\_plane\_id.

In subclause 7.4.2.9.3 “Slice data partition C RBSP semantics”, insert the following after the paragraph starting with “**slice\_id**”:

**colour\_plane\_id** has the same semantics as specified in subclause 7.4.2.9.2.

In subclause 7.4.3 “Slice header semantics”, make the following changes.

Replace the following paragraph:

**first\_mb\_in\_slice** specifies the address of the first macroblock in the slice. When arbitrary slice order is not allowed as specified in Annex A, the value of first\_mb\_in\_slice shall not be less than the value of first\_mb\_in\_slice for any other slice of the current picture that precedes the current slice in decoding order.

with:

**first\_mb\_in\_slice** specifies the address of the first macroblock in the slice. When arbitrary slice order is not allowed as specified in Annex A, the value of first\_mb\_in\_slice is constrained as follows.

- If separate\_colour\_plane\_flag is equal to 0, the value of first\_mb\_in\_slice shall not be less than the value of first\_mb\_in\_slice for any other slice of the current picture that precedes the current slice in decoding order.

- Otherwise (`separate_colour_plane_flag` is equal to 1), the value of `first_mb_in_slice` shall not be less than the value of `first_mb_in_slice` for any other slice of the current picture that precedes the current slice in decoding order and has the same value of `colour_plane_id`.

*Insert the following after the paragraph starting with “`pic_parameter_set_id`”.*

**`colour_plane_id`** has the same semantics as specified in subclause 7.4.2.9.2.

*In subclause 7.4.5 “Macroblock layer semantics”, make the following changes.*

*Replace the paragraph starting with “`transform_size_8x8_flag` equal to 1” with the following.*

**`transform_size_8x8_flag`** equal to 1 specifies that for the current macroblock the transform coefficient decoding process and picture construction process prior to deblocking filter process for residual 8x8 blocks shall be invoked for luma samples, and when `ChromaArrayType` == 3 also for Cb and Cr samples. **`transform_size_8x8_flag`** equal to 0 specifies that for the current macroblock the transform coefficient decoding process and picture construction process prior to deblocking filter process for residual 4x4 blocks shall be invoked for luma samples, and when `ChromaArrayType` == 3 also for Cb and Cr samples. When **`transform_size_8x8_flag`** is not present in the bitstream, it shall be inferred to be equal to 0.

*Replace the paragraph starting with “To each Intra\_16x16” with the following:*

To each Intra\_16x16 prediction macroblock, an `Intra16x16PredMode` is assigned, which specifies the Intra\_16x16 prediction mode.

The meaning of the variables `CodedBlockPatternChroma` and `CodedBlockPatternLuma` is specified with the semantics of `coded_block_pattern`.

*Replace the following paragraphs:*

**`pcm_sample_luma[i]`** is a sample value. The first `pcm_sample_luma[i]` values represent luma sample values in the raster scan within the macroblock. The number of bits used to represent each of these samples is `BitDepthY`. When `profile_idc` is not equal to 100, 110, 122, or 144, `pcm_sample_luma[i]` shall not be equal to 0.

**`pcm_sample_chroma[i]`** is a sample value. The first `MbWidthC * MbHeightC` `pcm_sample_chroma[i]` values represent Cb sample values in the raster scan within the macroblock and the remaining `MbWidthC * MbHeightC` `pcm_sample_chroma[i]` values represent Cr sample values in the raster scan within the macroblock. The number of bits used to represent each of these samples is `BitDepthC`. When `profile_idc` is not equal to 100, 110, 122, or 144, `pcm_sample_chroma[i]` shall not be equal to 0.

*with:*

**`pcm_sample_luma[i]`** is a sample value. The first `pcm_sample_luma[i]` values represent luma sample values in the raster scan within the macroblock. The number of bits used to represent each of these samples is `BitDepthY`. When `profile_idc` is not equal to 44, 100, 110, 122, or 244, `pcm_sample_luma[i]` shall not be equal to 0.

**`pcm_sample_chroma[i]`** is a sample value. The first `MbWidthC * MbHeightC` `pcm_sample_chroma[i]` values represent Cb sample values in the raster scan within the macroblock and the remaining `MbWidthC * MbHeightC` `pcm_sample_chroma[i]` values represent Cr sample values in the raster scan within the macroblock. The number of bits used to represent each of these samples is `BitDepthC`. When `profile_idc` is not equal to 44, 100, 110, 122, or 244, `pcm_sample_chroma[i]` shall not be equal to 0.

Delete the paragraph starting with “When coded\_block\_pattern is present, CodedBlockPatternLuma specifies”.

Insert the following paragraph before the paragraph starting with “mb\_qp\_delta”:

Depending on the value of ChromaArrayType, the following meaning is assigned to CodedBlockPatternLuma and the following restrictions are imposed on CodedBlockPatternChroma.

- If ChromaArrayType is equal to 0, CodedBlockPatternLuma specifies whether and where, for the luma component, non-zero AC transform coefficient levels are present and the derivation of the variable CodedBlockPatternChroma shall result in a value that is equal to 0.
- Otherwise, if ChromaArrayType is equal to 1 or 2, CodedBlockPatternLuma specifies whether, for the luma component, non-zero AC transform coefficient levels are present and CodedBlockPatternChroma may be in the range of 0 to 2, inclusive.
- Otherwise (ChromaArrayType is equal to 3), CodedBlockPatternLuma specifies whether and where, for the luma and the Cb and Cr component, non-zero AC transform coefficient levels are present and the derivation of the variable CodedBlockPatternChroma shall result in a value that is equal to 0.

In subclause 7.4.5.1 “Macroblock prediction semantics”, make the following changes.

Replace the paragraph starting with “prev\_intra4x4\_pred\_mode\_flag” with the following:

**prev\_intra4x4\_pred\_mode\_flag**[ luma4x4BlkIdx ] and **rem\_intra4x4\_pred\_mode**[ luma4x4BlkIdx ] specify the Intra\_4x4 prediction of the 4x4 luma block with index luma4x4BlkIdx = 0..15. When ChromaArrayType is equal to 3, **prev\_intra4x4\_pred\_mode\_flag**[ luma4x4BlkIdx ] and **rem\_intra4x4\_pred\_mode**[ luma4x4BlkIdx ] also specify the Intra\_4x4 prediction of the 4x4 Cb block and 4x4 Cr block with luma4x4BlkIdx equal to index cb4x4BlkIdx = 0..15 or cr4x4BlkIdx = 0..15.

Replace the paragraph starting with “prev\_intra8x8\_pred\_mode\_flag” with the following:

**prev\_intra8x8\_pred\_mode\_flag**[ luma8x8BlkIdx ] and **rem\_intra8x8\_pred\_mode**[ luma8x8BlkIdx ] specify the Intra\_8x8 prediction of the 8x8 luma block with index luma8x8BlkIdx = 0..3. When ChromaArrayType is equal to 3, **prev\_intra8x8\_pred\_mode\_flag**[ luma8x8BlkIdx ] and **rem\_intra8x8\_pred\_mode**[ luma8x8BlkIdx ] also specify the Intra\_8x8 prediction of the 8x8 Cb block and 8x8 Cr block with index luma8x8BlkIdx equal to cb8x8BlkIdx = 0..3 or cr8x8BlkIdx = 0..3.

Replace the content of subclause 7.4.5.3 “Residual data semantics” with the following:

The syntax structure **residual\_block**( ), which is used for parsing the transform coefficient levels, is assigned as follows.

- If **entropy\_coding\_mode\_flag** is equal to 0, **residual\_block** is set equal to **residual\_block\_cavlc**, which is used for parsing the syntax elements for transform coefficient levels.
- Otherwise (**entropy\_coding\_mode\_flag** is equal to 1), **residual\_block** is set equal to **residual\_block\_cabac**, which is used for parsing the syntax elements for transform coefficient levels.

The syntax structure **residual\_luma**( i16x16DClevel, i16x16AClevel, level, level8x8 ) is used with the variables in brackets being its output and being assigned as follows. **Intra16x16DCLevel** is set equal to **i16x16DClevel**, **Intra16x16ACLevel** is set equal to **i16x16AClevel**, **LumaLevel** is set equal to **level**, and **LumaLevel8x8** is set equal to **level8x8**.

When ChromaArrayType is equal to 1 or 2, the following applies.

- For each chroma component, indexed by **iCbCr** = 0..1, the DC transform coefficient levels of the 4 \* NumC8x8 4x4 chroma blocks are parsed into the **iCbCr**-th list **ChromaDCLevel**[ iCbCr ].

- For each of the 4x4 chroma blocks, indexed by  $i_{4x4} = 0..3$  and  $i_{8x8} = 0..NumC8x8 - 1$ , of each chroma component, indexed by  $i_{CbCr} = 0..1$ , the 15 AC transform coefficient levels are parsed into the  $(i_{8x8}*4 + i_{4x4})$ -th list of the  $i_{CbCr}$ -th chroma component  $ChromaACLevel[i_{CbCr}][i_{8x8}*4 + i_{4x4}]$ .

When `ChromaArrayType` is equal to 3, the following applies.

- The syntax structure `residual_luma( i16x16DClevel, i16x16AClevel, level, level8x8 )` is used for the Cb component with the variables in brackets being its output and being assigned as follows. `CbIntra16x16DCLevel` is set equal to `i16x16DClevel`, `CbIntra16x16ACLevel` is set equal to `i16x16AClevel`, `CbLevel` is set equal to `level`, and `CbLevel8x8` is set equal to `level8x8`.
- The syntax structure `residual_luma( i16x16DClevel, i16x16AClevel, level, level8x8 )` is used for the Cr component with the variables in brackets being its output and being assigned as follows. `CrIntra16x16DCLevel` is set equal to `i16x16DClevel`, `CrIntra16x16ACLevel` is set equal to `i16x16AClevel`, `CrLevel` is set equal to `level`, and `CrLevel8x8` is set equal to `level8x8`.

In subclause 7.4.5.3.2 “Residual block CABAC semantics”, replace the paragraph starting with “**coded\_block\_flag**” with the following:

**coded\_block\_flag** specifies whether the block contains non-zero transform coefficient levels as follows.

- If `coded_block_flag` is equal to 0, the block contains no non-zero transform coefficient levels.
- Otherwise (`coded_block_flag` is equal to 1), the block contains at least one non-zero transform coefficient level.

When `maxNumCoeff` is equal to 64 and `ChromaArrayType` is not equal to 3, `coded_block_flag` is set equal to 1.

Insert a new subclause 7.4.5.3.3 as follows:

### 7.3.5.3.3 Residual luma data semantics

Output of this syntax structure are the variables `i16x16DClevel`, `i16x16AClevel`, `level`, and `level8x8`.

The syntax structure `residual_block( )`, which is used for parsing the transform coefficient levels, is assigned as follows.

- If `entropy_coding_mode_flag` is equal to 0, `residual_block` is set equal to `residual_block_cavlc`, which is used for parsing the syntax elements for transform coefficient levels.
- Otherwise (`entropy_coding_mode_flag` is equal to 1), `residual_block` is set equal to `residual_block_cabac`, which is used for parsing the syntax elements for transform coefficient levels.

Depending on `mb_type` the syntax structure `residual_block( coeffLevel, maxNumCoeff )` is used with the arguments `coeffLevel`, which is a list containing the `maxNumCoeff` transform coefficient levels that are parsed in `residual_block( )` and `maxNumCoeff` as follows. Depending on `MbPartPredMode( mb_type, 0 )`, the following applies.

- If `MbPartPredMode( mb_type, 0 )` is equal to `Intra_16x16`, the transform coefficient levels are parsed into the list `i16x16DClevel` and into the 16 lists `i16x16AClevel[ i ]`. `i16x16DClevel` contains the 16 transform coefficient levels of the DC transform coefficient levels for each 4x4 luma block. For each of the 16 4x4 luma blocks indexed by  $i = 0..15$ , the 15 AC transform coefficients levels of the  $i$ -th block are parsed into the  $i$ -th list `i16x16AClevel[ i ]`.
- Otherwise (`MbPartPredMode( mb_type, 0 )` is not equal to `Intra_16x16`), the following applies.
  - If `transform_size_8x8_flag` is equal to 0, for each of the 16 4x4 luma blocks indexed by  $i = 0..15$ , the 16 transform coefficient levels of the  $i$ -th block are parsed into the  $i$ -th list `level[ i ]`.

- Otherwise (transform\_size\_8x8\_flag is equal to 1), for each of the 4 8x8 luma blocks indexed by i8x8 = 0..3, the following applies.
  - If entropy\_coding\_mode\_flag is equal to 0, first for each of the 4 4x4 luma blocks indexed by i4x4 = 0..3, the 16 transform coefficient levels of the i4x4-th block are parsed into the (i8x8 \* 4 + i4x4)-th list level[ i8x8 \* 4 + i4x4 ]. Then, the 64 transform coefficient levels of the i8x8-th 8x8 luma block which are indexed by 4 \* i + i4x4, where i = 0..15 and i4x4 = 0..3, are derived as level8x8[ i8x8 ][ 4 \* i + i4x4 ] = level[ i8x8 \* 4 + i4x4 ][ i ].
 

NOTE – The 4x4 luma blocks with luma4x4BlkIdx = i8x8 \* 4 + i4x4 containing every fourth transform coefficient level of the corresponding i8x8-th 8x8 luma block with offset i4x4 are assumed to represent spatial locations given by the inverse 4x4 luma block scanning process in subclause 6.4.3.
  - Otherwise (entropy\_coding\_mode\_flag is equal to 1), the 64 transform coefficient levels of the i8x8-th block are parsed into the i8x8-th list level8x8[ i8x8 ].

*In clause 8 and all subclauses of clause 8, make the following changes.*

*Replace all occurrences of “chroma\_format\_idc” with “ChromaArrayType”.*

*Delete all occurrences of “(monochrome)”.*

*In clause 8, make the following changes.*

*After the first sentence, insert the following.*

Depending on the value of chroma\_format\_idc, the number of sample arrays of the current picture is as follows.

- If chroma\_format\_idc is equal to 0, the current picture consists of 1 sample array S<sub>L</sub>.
- Otherwise (chroma\_format\_idc is not equal to 0), the current picture consists of 3 sample arrays S<sub>L</sub>, S<sub>Cb</sub>, S<sub>Cr</sub>.

*Replace the paragraph that starts with “Each picture referred” with the following:*

Each picture referred to in this clause is a complete or part of a primary coded picture. Each slice referred to in this clause is a slice of a primary picture. Each slice data partition referred to in this clause is a slice data partition of a primary picture.

Depending on the value of separate\_colour\_plane\_flag, the decoding process is structured as follows.

- If separate\_colour\_plane\_flag is equal to 0, the decoding process is invoked a single time with the current picture being the output.
- Otherwise (separate\_colour\_plane\_flag is equal to 1), the decoding process is invoked three times. Inputs to the decoding process are all NAL units of the primary coded picture with identical value of colour\_plane\_id. The decoding process of NAL units with a particular value of colour\_plane\_id is specified as if only a coded video sequence with monochrome colour format with that particular value of colour\_plane\_id would be present in the bitstream. The output of each of the three decoding processes is assigned to the 3 sample arrays of the current picture with the NAL units with colour\_plane\_id equal to 0 being assigned to S<sub>L</sub>, the NAL units with colour\_plane\_id equal to 1 being assigned to S<sub>Cb</sub>, and the NAL units with colour\_plane\_id equal to 2 being assigned to S<sub>Cr</sub>.

NOTE – The variable ChromaArrayType is derived as 0 when separate\_colour\_plane\_flag is equal to 1 and chroma\_format\_idc is equal to 3. In the decoding process, the value of this variable is evaluated resulting in operations identical to that of monochrome pictures with chroma\_format\_idc being equal to 0.

In subclause 8.3.4 “Intra prediction process for chroma samples”, after the second paragraph, insert the following:

Depending on the value of ChromaArrayType, the following applies.

- If ChromaArrayType is equal to 3, the Intra prediction chroma samples for the current macroblock  $\text{pred}_{Cb}[x, y]$  and  $\text{pred}_{Cr}[x, y]$  are derived using the Intra prediction process for chroma samples with ChromaArrayType equal to 3 as specified in subclause 8.3.4.5.
- Otherwise (ChromaArrayType is equal to 1 or 2), the following text specifies the Intra prediction chroma samples for the current macroblock  $\text{pred}_{Cb}[x, y]$  and  $\text{pred}_{Cr}[x, y]$ .

In subclause 8.3.4.1 “Specification of Intra\_Chroma\_DC prediction mode”, make the following changes.

Replace the following:

- Depending on chroma\_format\_idc, the position of the upper-left sample of a 4x4 chroma block with index chroma4x4BlkIdx is derived as follows

- If chroma\_format\_idc is equal to 1 or 2, the following applies

$$xO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 0) \quad (8-124)$$

$$yO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 1) \quad (8-125)$$

- Otherwise (chroma\_format\_idc is equal to 3), the following applies

$$xO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx} / 4, 8, 8, 16, 0) + \text{InverseRasterScan}(\text{chroma4x4BlkIdx} \% 4, 4, 4, 8, 0) \quad (8-126)$$

$$yO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx} / 4, 8, 8, 16, 1) + \text{InverseRasterScan}(\text{chroma4x4BlkIdx} \% 4, 4, 4, 8, 1) \quad (8-127)$$

with:

- The position of the upper-left sample of a 4x4 chroma block with index chroma4x4BlkIdx is derived as

$$xO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 0) \quad (8-124)$$

$$yO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 1) \quad (8-125)$$

- Depending on the values of xO and yO, the following applies.

Indent all succeeding If/Otherwise statements as necessary.

Update all following equation numbers in clause 8 as necessary.

Insert a new subclause 8.3.4.5 as follows:

#### 8.3.4.5 Intra prediction for chroma samples with ChromaArrayType equal to 3

This process is invoked when ChromaArrayType is equal to 3. This process is invoked for I and SI macroblock types. It specifies how the Intra prediction chroma samples for the current macroblock are derived when ChromaArrayType is equal to 3.

Inputs to this process are constructed samples prior to the deblocking filter process from neighbouring Cb and Cr blocks and for Intra\_NxN (where NxN is equal to 4x4 or 8x8) prediction mode, the associated values of IntraNxNPredMode from neighbouring macroblocks.

Outputs of this process are the Intra prediction samples of the Cb and Cr components of the macroblock or in case of the Intra\_NxN prediction process, the outputs are NxN Cb sample arrays as part of the 16x16 Cb array of prediction samples of the macroblock, and NxN Cr sample arrays as part of the 16x16 Cr array of prediction samples of the macroblock.

Each Cb, Cr, and luma block with the same block index of the macroblock shall use the same prediction mode. The prediction mode is applied to each of the Cb and Cr blocks separately. The process specified in this subclause is invoked for each Cb and Cr block.

Depending on the macroblock prediction mode, the following applies.

- If the macroblock prediction mode is equal to Intra\_4x4, the following applies.
  - The same process described in subclause 8.3.1 shall also be applied to Cb or Cr samples, substituting luma with Cb or Cr, substituting luma4x4BlkIdx with cb4x4BlkIdx or cr4x4BlkIdx, and substituting pred4x4<sub>L</sub> with pred4x4<sub>Cb</sub> or pred4x4<sub>Cr</sub>.
  - The output variable Intra4x4PredMode[luma4x4BlkIdx] from the process described in subclause 8.3.1.1 shall also be used for the 4x4 Cb or 4x4 Cr blocks with index luma4x4BlkIdx equal to index cb4x4BlkIdx or cr4x4BlkIdx.
  - The process to derive prediction Cb or Cr samples shall be identical to the process described in subclause 8.3.1.2 and its subsequent subclauses when substituting luma with Cb or Cr, and substituting pred4x4<sub>L</sub> with pred4x4<sub>Cb</sub> or pred4x4<sub>Cr</sub>.
- Otherwise, if the macroblock prediction mode is equal to Intra\_8x8, the following applies.
  - The same process described in subclause 8.3.2 shall also be applied to Cb or Cr samples, substituting luma with Cb or Cr, substituting luma8x8BlkIdx with cb8x8BlkIdx or cr8x8BlkIdx, and substituting pred8x8<sub>L</sub> with pred8x8<sub>Cb</sub> or pred8x8<sub>Cr</sub>.
  - The output variable Intra8x8PredMode[luma8x8BlkIdx] from the process described in subclause 8.3.2.1 shall also be used for the 8x8 Cb or 8x8 Cr blocks with index luma8x8BlkIdx equal to index cb8x8BlkIdx or cr8x8BlkIdx.
  - The process to derive prediction Cb or Cr samples shall be identical to the process described in subclause 8.3.2.2 and its subsequent subclauses when substituting luma with Cb or Cr, and substituting pred8x8<sub>L</sub> with pred8x8<sub>Cb</sub> or pred8x8<sub>Cr</sub>.
- Otherwise, if the macroblock prediction mode is equal to Intra\_16x16, the following applies.
  - The same process described in subclause 8.3.3 and in the subsequent subclause 8.3.3.1 to 8.3.3.4 shall also be applied to Cb or Cr samples, substituting luma with Cb or Cr, and substituting pred<sub>L</sub> with pred<sub>Cb</sub> or pred<sub>Cr</sub>.

*In subclause 8.4 “Inter prediction process”, replace the paragraph starting with “Outputs of this process are” with the following:*

Outputs of this process are Inter prediction samples for the current macroblock that are a  $16 \times 16$  array  $\text{pred}_L$  of luma samples and when ChromaArrayType is not equal to 0 two  $(\text{MbWidthC}) \times (\text{MbHeightC})$  arrays  $\text{pred}_{Cr}$  and  $\text{pred}_{Cb}$  of chroma samples, one for each of the chroma components Cb and Cr.

*In subclause 8.4.1 “Derivation process for motion vector components and reference indices”, replace the paragraph starting with “Outputs of this process are” with the following:*

Outputs of this process are

- luma motion vectors  $\text{mvL0}$  and  $\text{mvL1}$  and when ChromaArrayType is not equal to 0, the chroma motion vectors  $\text{mvCL0}$  and  $\text{mvCL1}$

*Replace the paragraph starting with “For the derivation of the variables for the chroma motion vectors” with the following:*

When ChromaArrayType is not equal to 0 and  $\text{predFlagLX}$  (with X being either 0 or 1) is equal to 1, the derivation process for chroma motion vectors in subclause 8.4.1.4 is invoked with  $\text{mvLX}$  and  $\text{refIdxLX}$  as input and the output being  $\text{mvCLX}$ .

*In subclause 8.4.2.1 “Reference picture selection process”, make the following changes.*

*Replace the paragraph starting with “Output of this process” with the following:*

Output of this process is a reference picture consisting of a two-dimensional array of luma samples  $\text{refPicLXL}$  and when ChromaArrayType is not equal to 0, two two-dimensional arrays of chroma samples  $\text{refPicLXCb}$  and  $\text{refPicLXCr}$ .

*Replace the paragraph starting with “The reference picture sample arrays” with the following.*

Depending on `separate_colour_plane_flag` the following applies.

- If `separate_colour_plane_flag` is equal to 0, the reference picture sample arrays  $\text{refPicLXL}$ ,  $\text{refPicLXCb}$  (if available), and  $\text{refPicLXCr}$  (if available) correspond to decoded sample arrays  $S_L$ ,  $S_{Cb}$  (if available),  $S_{Cr}$  (if available) derived in subclause 8.7 for a previously-decoded reference field or reference frame or complementary reference field pair or field of a reference frame.
- Otherwise (`separate_colour_plane_flag` is equal to 1), the following applies.
  - If `colour_plane_id` is equal to 0, the reference picture sample array  $\text{refPicLXL}$  corresponds to the decoded sample array  $S_L$  derived in subclause 8.7 for a previously-decoded reference field or reference frame or complementary reference field pair or field of a reference frame.
  - Otherwise, if `colour_plane_id` is equal to 1, the reference picture sample array  $\text{refPicLXL}$  corresponds to the decoded sample array  $S_{Cb}$  derived in subclause 8.7 for a previously-decoded reference field or reference frame or complementary reference field pair or field of a reference frame.
  - Otherwise (`colour_plane_id` is equal to 2), the reference picture sample array  $\text{refPicLXL}$  corresponds to the decoded sample array  $S_{Cr}$  derived in subclause 8.7 for a previously-decoded reference field or reference frame or complementary reference field pair or field of a reference frame.

In subclause 8.4.2.2 “Fractional sample interpolation process”, make the following changes.

Replace the paragraphs:

- a chroma motion vector mvCLX given in eighth-chroma-sample units, and
- the selected reference picture sample arrays refPicLX<sub>L</sub>, and refPicLX<sub>Cb</sub>, and refPicLX<sub>Cr</sub>

with:

- when ChromaArrayType is not equal to 0, a chroma motion vector mvCLX with a precision of (4\*SubWidthC) chroma-sample units horizontally and (4\*SubHeightC) chroma-sample units vertically, and
- the selected reference picture sample arrays refPicLX<sub>L</sub>, and when ChromaArrayType is not equal to 0, refPicLX<sub>Cb</sub>, and refPicLX<sub>Cr</sub>

Replace the paragraph starting with “Let ( xInt<sub>C</sub>, yInt<sub>C</sub> ) be a chroma location” with the following:

Let ( xInt<sub>C</sub>, yInt<sub>C</sub> ) be a chroma location given in full-sample units and ( xFrac<sub>C</sub>, yFrac<sub>C</sub> ) be an offset given in (4\*SubWidthC) chroma-sample units horizontally and (4\*SubHeightC) chroma-sample units vertically. These variables are used only inside this subclause for specifying general fractional-sample locations inside the reference sample arrays refPicLX<sub>Cb</sub>, and refPicLX<sub>Cr</sub>.

Replace the 4 equations following the paragraph starting with “Otherwise (chroma\_format\_idc is equal to 3)” with the following:

$$xIntC = xAC + ( mvLX[ 0 ] >> 2 ) + xC \quad (8-232)$$

$$yIntL = yAC + ( mvLX[ 1 ] >> 2 ) + yC \quad (8-233)$$

$$xFracC = mvLX[ 0 ] \& 3 \quad (8-234)$$

$$yFracC = mvLX[ 1 ] \& 3 \quad (8-235)$$

Replace the following paragraphs:

- The prediction sample value predPartLX<sub>Cb</sub>[ x<sub>C</sub>, y<sub>C</sub> ] is derived by invoking the process specified in subclause 8.4.2.2.2 with ( xInt<sub>C</sub>, yInt<sub>C</sub> ), ( xFrac<sub>C</sub>, yFrac<sub>C</sub> ) and refPicLX<sub>Cb</sub> given as input.
- The prediction sample value predPartLX<sub>Cr</sub>[ x<sub>C</sub>, y<sub>C</sub> ] is derived by invoking the process specified in subclause 8.4.2.2.2 with ( xInt<sub>C</sub>, yInt<sub>C</sub> ), ( xFrac<sub>C</sub>, yFrac<sub>C</sub> ) and refPicLX<sub>Cr</sub> given as input.

with:

- Depending on ChromaArrayType the following applies.
  - If ChromaArrayType is not equal to 3, the following applies.
    - The prediction sample value predPartLX<sub>Cb</sub>[ x<sub>C</sub>, y<sub>C</sub> ] is derived by invoking the process specified in subclause 8.4.2.2.2 with ( xInt<sub>C</sub>, yInt<sub>C</sub> ), ( xFrac<sub>C</sub>, yFrac<sub>C</sub> ) and refPicLX<sub>Cb</sub> given as input.
    - The prediction sample value predPartLX<sub>Cr</sub>[ x<sub>C</sub>, y<sub>C</sub> ] is derived by invoking the process specified in subclause 8.4.2.2.2 with ( xInt<sub>C</sub>, yInt<sub>C</sub> ), ( xFrac<sub>C</sub>, yFrac<sub>C</sub> ) and refPicLX<sub>Cr</sub> given as input.

- Otherwise (ChromaArrayType is equal to 3), the following applies.
  - The prediction sample value  $\text{predPartLXCb}[x_C, y_C]$  is derived by invoking the process specified in subclause 8.4.2.2.1 with  $(x_{\text{Int}_C}, y_{\text{Int}_C})$ ,  $(x_{\text{Frac}_C}, y_{\text{Frac}_C})$  and  $\text{refPicLXCb}$  given as input.
  - The prediction sample value  $\text{predPartLXCr}[x_C, y_C]$  is derived by invoking the process specified in subclause 8.4.2.2.1 with  $(x_{\text{Int}_C}, y_{\text{Int}_C})$ ,  $(x_{\text{Frac}_C}, y_{\text{Frac}_C})$  and  $\text{refPicLXCr}$  given as input.

*In subclause 8.4.2.2.2 “Chroma sample interpolation process”, replace the first paragraph, which states as follows:*

This process shall only be invoked when  $\text{chroma\_format\_idc}$  is not equal to 0 (monochrome).

*with:*

This process shall only be invoked when ChromaArrayType is equal to 1 or 2.

*Replace the content of subclause 8.5 “Transform coefficient decoding process and picture construction process prior to deblocking filter process” with the following:*

Inputs to this process are Intra16x16DCLevel (if available), Intra16x16ACLevel (if available), CbIntra16x16DCLevel (if available), CbIntra16x16ACLevel (if available), CrIntra16x16DCLevel (if available), CrIntra16x16ACLevel (if available), LumaLevel (if available), LumaLevel8x8 (if available), ChromaDCLevel (if available), ChromaACLevel (if available), CbLevel (if available), CrLevel (if available), CbLevel8x8 (if available), CrLevel8x8 (if available), and available Inter or Intra prediction sample arrays for the current macroblock for the applicable components  $\text{pred}_L$ ,  $\text{pred}_{Cb}$ , or  $\text{pred}_{Cr}$ .

NOTE – When decoding a macroblock in Intra\_4x4 (or Intra\_8x8) prediction mode, the luma component of the macroblock prediction array may not be complete, since for each 4x4 (or 8x8) luma block, the Intra\_4x4 (or Intra\_8x8) prediction process for luma samples as specified in subclause 8.3.1 (or 8.3.2) and the process specified in this subclause are iterated. For the same reason, the Cb and Cr component of the macroblock prediction array may not be complete when ChromaArrayType is equal to 3.

Outputs of this process are the constructed sample arrays prior to the deblocking filter process for the applicable components  $S'_L$ ,  $S'_{Cb}$ ,  $S'_{Cr}$ .

NOTE – When decoding a macroblock in Intra\_4x4 (or Intra\_8x8) prediction mode, the luma component of the macroblock constructed sample arrays prior to the deblocking filter process may not be complete, since for each 4x4 (or 8x8) luma block, the Intra\_4x4 (or Intra\_8x8) prediction process for luma samples as specified in subclause 8.3.1 (or 8.3.2) and the process specified in this subclause are iterated. For the same reason, the Cb and Cr component of the macroblock constructed sample arrays prior to the deblocking filter process may not be complete when ChromaArrayType is equal to 3.

This subclause specifies transform coefficient decoding and picture construction prior to the deblocking filter process.

When the current macroblock is coded as P\_Skip or B\_Skip, all values of LumaLevel, LumaLevel8x8, CbLevel, CbLevel8x8, CrLevel, CrLevel8x8, ChromaDCLevel, ChromaACLevel are set equal to 0 for the current macroblock.

*In subclause 8.5.1 “Specification of transform decoding process for 4x4 luma residual blocks”, replace the paragraph starting with “When residual\_colour\_transform\_flag” with the following:*

When  $\text{qpprime\_y\_zero\_transform\_bypass\_flag}$  is equal to 1,  $\text{QP}'_Y$  is equal to 0, the macroblock prediction mode is equal to Intra\_4x4, and  $\text{Intra4x4PredMode}[\text{luma4x4BlkIdx}]$  is equal to 0 or 1, the intra residual transform-bypass decoding process as specified in subclause 8.5.13 is invoked with  $n_{\text{Max}}$  equal to 4,  $\text{horPredFlag}$  equal to  $\text{Intra4x4PredMode}[\text{luma4x4BlkIdx}]$ , and the 4x4 array  $r$  as inputs, and the output is a modified version of the 4x4 array  $r$ .

*In subclause 8.5.2 “Specification of transform decoding process for luma samples of Intra\_16x16 macroblock prediction mode”, replace the paragraph starting with “When residual\_colour\_transform\_flag” with the following:*

When `qpprime_y_zero_transform_bypass_flag` is equal to 1,  $QP'_Y$  is equal to 0, the macroblock prediction mode is equal to `Intra_16x16`, and `Intra16x16PredMode` is equal to 0 or 1, intra residual transform-bypass decoding process as specified in subclause 8.5.13 is invoked with `nMax` equal to 4, `horPredFlag` equal to `Intra16x16PredMode`, and the 4x4 array `r` as inputs, and the output is a modified version of the 4x4 array `r`.

*In subclause 8.5.3 “Specification of transform decoding process for 8x8 luma residual blocks”, replace the paragraph starting with “When residual\_colour\_transform\_flag” with the following:*

When `qpprime_y_zero_transform_bypass_flag` is equal to 1,  $QP'_Y$  is equal to 0, the macroblock prediction mode is equal to `Intra_8x8`, and `Intra8x8PredMode[ luma8x8BlkIdx ]` is equal to 0 or 1, the intra residual transform-bypass decoding process as specified in subclause 8.5.13 is invoked with `nMax` equal to 8, `horPredFlag` equal to `Intra8x8PredMode[ luma8x8BlkIdx ]`, and the 8x8 array `r` as inputs, and the output is a modified version of the 8x8 array `r`.

*In subclause 8.5.4 “Specification of transform decoding process for chroma samples”, make the following changes.*

*Replace the first paragraph of the subclause with the following:*

This process is invoked for each chroma component `Cb` and `Cr` separately when `ChromaArrayType` is not equal to 0.

Depending on `ChromaArrayType`, the following applies.

- If `ChromaArrayType` is equal to 3, the transform decoding process for chroma samples with `ChromaArrayType` equal to 3 as specified in subclause 8.5.4.1 is invoked.
- Otherwise (`ChromaArrayType` is not equal to 3), the following text specifies the transform decoding process for chroma samples.

*Replace the sentence:*

Otherwise, if `chroma_format_idc` is equal to 2, the 2x4 array `c` is derived using the inverse raster scanning process applied to `ChromaDCLevel` as follows

*with:*

Otherwise (`ChromaArrayType` is equal to 2), the 2x4 array `c` is derived using the inverse raster scanning process applied to `ChromaDCLevel` as follows

*Delete the paragraph starting with “- Otherwise (`chroma_format_idc` is equal to 3),”.*

*Delete the case (c) from Figure 8-7 including the corresponding part of the caption.*

*Replace the following:*

Depending on the variable `chroma_format_idc`, the The position of the upper-left sample of a 4x4 chroma block with index `chroma4x4BlkIdx` inside the macroblock is derived as follows.

- If `chroma_format_idc` is equal to 1 or 2, the following applies.

$$xO = \text{InverseRasterScan}( \text{chroma4x4BlkIdx}, 4, 4, 8, 0 ) \quad (8-302)$$

$$yO = \text{InverseRasterScan}( \text{chroma4x4BlkIdx}, 4, 4, 8, 1 ) \quad (8-303)$$

- Otherwise (chroma\_format\_idc is equal to 3), the following applies.

$$xO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx} / 4, 8, 8, 16, 0) + \text{InverseRasterScan}(\text{chroma4x4BlkIdx} \% 4, 4, 4, 8, 0) \quad (8-304)$$

$$yO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx} / 4, 8, 8, 16, 1) + \text{InverseRasterScan}(\text{chroma4x4BlkIdx} \% 4, 4, 4, 8, 1) \quad (8-305)$$

with:

The position of the upper-left sample of a 4x4 chroma block with index chroma4x4BlkIdx inside the macroblock is derived by.

$$xO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 0) \quad (8-302)$$

$$yO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 1) \quad (8-303)$$

Update all following equation numbers in clause 8 as necessary.

Replace the paragraph starting with “When residual\_colour\_transform\_flag” with the following:

When qpprime\_y\_zero\_transform\_bypass\_flag is equal to 1,  $QP'_Y$  is equal to 0, the macroblock prediction mode is equal to Intra\_4x4, Intra\_8x8, or Intra\_16x16, and intra\_chroma\_pred\_mode is equal to 1 or 2, the intra residual transform-bypass decoding process as specified in subclause 8.5.13 is invoked with nMax equal to 4, horPredFlag equal to (intra\_chroma\_pred\_mode – 1), and the 4x4 array r as inputs, and the output is a modified version of the 4x4 array r.

Insert a new subclause 8.5.4.1 as follows:

#### 8.5.4.1 Specification of transform decoding process for chroma samples with ChromaArrayType equal to 3

This process is invoked for each chroma component Cb and Cr separately when ChromaArrayType is equal to 3.

Depending on the macroblock prediction mode and transform\_size\_8x8\_flag, the following applies.

- If the macroblock prediction mode is equal to Intra\_16x16, the transform decoding process for Cb or Cr residual blocks shall be identical to the process described in subclause 8.5.2 when substituting luma with Cb or Cr, substituting Intra16x16DCLevel with CbIntra16x16DCLevel or CrIntra16x16DCLevel, substituting Intra16x16ACLevel with CbIntra16x16ACLevel or CrIntra16x16ACLevel, and substituting pred<sub>L</sub> with pred<sub>Cb</sub> or pred<sub>Cr</sub>, substituting luma4x4BlkIdx with cb4x4BlkIdx or cr4x4BlkIdx, substituting lumaList with CbList or CrList, and substituting Clip1<sub>Y</sub> with Clip1<sub>C</sub>.
- Otherwise, if transform\_size\_8x8\_flag is equal to 1, the transform decoding process for 8x8 Cb or 8x8 Cr residual blocks shall be identical to the process described in subclause 8.5.3 when substituting luma with Cb or Cr, substituting LumaLevel8x8 with CbLevel8x8 or CrLevel8x8, substituting pred<sub>L</sub> with pred<sub>Cb</sub> or pred<sub>Cr</sub>, substituting luma8x8BlkIdx with cb8x8BlkIdx or cr8x8BlkIdx, and substituting Clip1<sub>Y</sub> with Clip1<sub>C</sub>.
- Otherwise (the macroblock prediction mode is not equal to Intra\_16x16 and transform\_size\_8x8\_flag is equal to 0), the transform decoding process for 4x4 Cb or 4x4 Cr residual blocks shall be identical to the process described in subclause 8.5.1 when substituting luma with Cb or Cr, substituting LumaLevel with CbLevel or CrLevel, substituting pred<sub>L</sub> with pred<sub>Cb</sub> or pred<sub>Cr</sub>, substituting luma4x4BlkIdx with cb4x4BlkIdx or cr4x4BlkIdx, and substituting Clip1<sub>Y</sub> with Clip1<sub>C</sub>.

Replace the title of subclause 8.5.6 with the following:

### 8.5.6 Inverse scanning process for 8x8 transform coefficients

In subclause 8.5.7 “Derivation process for the chroma quantisation parameters and scaling function”, make the following changes.

Delete the following:

The value of  $\text{BitDepth}'_c$  for the chroma components is derived as

$$\text{BitDepth}'_c = \text{BitDepth}_c + \text{residual\_colour\_transform\_flag} \quad (8-311)$$

Replace the following:

- The variable  $iYCbCr$  derived as follows.
  - If the input array  $c$  relates to a luma residual block,  $iYCbCr$  is set equal to 0.
  - Otherwise, if the input array  $c$  relates to a chroma residual block and the chroma component is equal to  $Cb$ ,  $iYCbCr$  is set equal to 1.
  - Otherwise (the input array  $c$  relates to a chroma residual block and the chroma component is equal to  $Cr$ ),  $iYCbCr$  is set equal to 2.

with:

- The variable  $iYCbCr$  derived as follows.
  - If  $\text{separate\_colour\_plane\_flag}$  is equal to 1,  $iYCbCr$  is set equal to  $\text{colour\_plane\_id}$ .
  - Otherwise ( $\text{separate\_colour\_plane\_flag}$  is equal to 0), the following applies.
    - If the input array  $c$  relates to a luma residual block,  $iYCbCr$  is set equal to 0.
    - Otherwise, if the input array  $c$  relates to a chroma residual block and the chroma component is equal to  $Cb$ ,  $iYCbCr$  is set equal to 1.
    - Otherwise (the input array  $c$  relates to a chroma residual block and the chroma component is equal to  $Cr$ ),  $iYCbCr$  is set equal to 2.

Replace the paragraph starting with “The inverse scanning process for 8x8 luma transform coefficients” with the following:

- The variable  $iYCbCr$  is derived as follows.
  - If  $\text{separate\_colour\_plane\_flag}$  is equal to 1,  $iYCbCr$  is set equal to  $\text{colour\_plane\_id}$ .
  - Otherwise ( $\text{separate\_colour\_plane\_flag}$  is equal to 0), the following applies.
    - If the input array  $c$  relates to a luma residual block,  $iYCbCr$  is set equal to 0.
    - Otherwise, if the input array  $c$  relates to a chroma residual block and the chroma component is equal to  $Cb$ ,  $iYCbCr$  is set equal to 1.
    - Otherwise (the input array  $c$  relates to a chroma residual block and the chroma component is equal to  $Cr$ ),  $iYCbCr$  is set equal to 2.
- The inverse scanning process for 8x8 luma transform coefficients as specified in subclause 8.5.6 is invoked with  $\text{ScalingList8x8}[2 * iYCbCr + \text{mbIsInterFlag}]$  as the input and the output is assigned to the 8x8 matrix  $\text{weightScale8x8}$ .

In subclause 8.5.8 “Scaling and transformation process for luma DC transform coefficients for Intra\_16x16 macroblock type”, make the following changes.

Change the title of the subclause to:

#### 8.5.8 Scaling and transformation process for DC transform coefficients for Intra\_16x16 macroblock type

Replace the following:

Inputs to this process are transform coefficient level values for luma DC transform coefficients of Intra\_16x16 macroblocks as a 4x4 array  $c$  with elements  $c_{ij}$ , where  $i$  and  $j$  form a two-dimensional frequency index.

Outputs of this process are 16 scaled DC values for luma 4x4 blocks of Intra\_16x16 macroblocks as a 4x4 array  $dcY$  with elements  $dcY_{ij}$ .

with:

Inputs to this process are transform coefficient level values for DC transform coefficients of Intra\_16x16 macroblocks as a 4x4 array  $c$  with elements  $c_{ij}$ , where  $i$  and  $j$  form a two-dimensional frequency index.

Outputs of this process are 16 scaled DC values for 4x4 blocks of Intra\_16x16 macroblocks as a 4x4 array  $dcY$  with elements  $dcY_{ij}$ .

The variables  $bitDepth$  and  $qP$  are derived as follows.

- If the input array  $c$  relates to a luma residual block,  $bitDepth$  is set equal to  $BitDepth_Y$  and  $qP$  is set equal to  $QP'_Y$ .
- Otherwise (the input array  $c$  relates to a chroma residual block),  $bitDepth$  is set equal to  $BitDepth_C$  and  $qP$  is set equal to  $QP'_C$ .

NOTE – When `separate_colour_plane_flag` is equal to 1, all residual blocks are considered to be associated with the luma component for purposes of the decoding process of each colour component of a picture.

Replace the following:

The bitstream shall not contain data that results in any element  $f_{ij}$  of  $f$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + BitDepth_Y)}$  to  $2^{(7 + BitDepth_Y)} - 1$ , inclusive.

After the inverse transform, scaling is performed as follows.

- If  $qP$  is greater than or equal to 36, the scaled result is derived as

$$dcY_{ij} = (f_{ij} * LevelScale(QP'_Y \% 6, 0, 0)) \ll (QP'_Y / 6 - 6), \quad \text{with } i, j = 0..3. \quad (8-320)$$

- Otherwise ( $QP'_Y$  is less than 36), the scaled result is derived as

$$dcY_{ij} = (f_{ij} * LevelScale(QP'_Y \% 6, 0, 0) + (1 \ll (5 - QP'_Y / 6))) \ll (qP / 6 - 6), \quad \text{with } i, j = 0..3 \quad (8-321)$$

The bitstream shall not contain data that results in any element  $dcY_{ij}$  of  $dcY$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + BitDepth_Y)}$  to  $2^{(7 + BitDepth_Y)} - 1$ , inclusive.

NOTE – When `entropy_coding_mode_flag` is equal to 0 and  $QP'_Y$  is less than 10 and `profile_idc` is equal to 66, 77, or 88, the range of values that can be represented for the elements  $c_{ij}$  of  $c$  is not sufficient to represent the full range of values of the elements  $dcY_{ij}$  of  $dcY$  that could be necessary to form a close approximation of the content of any possible source picture by use of the Intra\_16x16 macroblock type.

with:

The bitstream shall not contain data that results in any element  $f_{ij}$  of  $f$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + \text{bitDepth})}$  to  $2^{(7 + \text{bitDepth})} - 1$ , inclusive.

After the inverse transform, scaling is performed as follows.

- If  $qP$  is greater than or equal to 36, the scaled result is derived as

$$\text{dcY}_{ij} = (f_{ij} * \text{LevelScale}(qP \% 6, 0, 0)) \ll (qP / 6 - 6), \quad \text{with } i, j = 0..3. \quad (8-320)$$

- Otherwise ( $qP$  is less than 36), the scaled result is derived as

$$\text{dcY}_{ij} = (f_{ij} * \text{LevelScale}(qP \% 6, 0, 0) + (1 \ll (5 - qP / 6))) \ll (qP / 6 - 6), \quad \text{with } i, j = 0..3 \quad (8-321)$$

The bitstream shall not contain data that results in any element  $\text{dcY}_{ij}$  of  $\text{dcY}$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + \text{bitDepth})}$  to  $2^{(7 + \text{bitDepth})} - 1$ , inclusive.

NOTE – When `entropy_coding_mode_flag` is equal to 0 and  $qP$  is less than 10 and `profile_idc` is equal to 66, 77, or 88, the range of values that can be represented for the elements  $c_{ij}$  of  $c$  is not sufficient to represent the full range of values of the elements  $\text{dcY}_{ij}$  of  $\text{dcY}$  that could be necessary to form a close approximation of the content of any possible source picture by use of the `Intra_16x16` macroblock type.

In subclause 8.5.9 “Scaling and transformation process for chroma DC transform coefficients”, make the following changes.

Add the following paragraph to the beginning of this subclause:

This process is only invoked when `ChromaArrayType` is equal to 1 or 2.

Replace the following:

- Otherwise, if `chroma_format_idc` is equal to 2, the inverse transform for the 2x4 chroma DC transform coefficients is specified as

$$f = \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & 1 & -1 & -1 \\ 1 & -1 & -1 & 1 \\ 1 & -1 & 1 & -1 \end{bmatrix} \begin{bmatrix} c_{00} & c_{01} \\ c_{10} & c_{11} \\ c_{20} & c_{21} \\ c_{30} & c_{31} \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \quad (8-324)$$

- Otherwise (`chroma_format_idc` is equal to 3), the inverse transform for the 4x4 chroma DC transform coefficients is specified as follows.

- If `residual_colour_transform_flag` is equal to 1 and the current macroblock prediction mode `MbPartPredMode(mb_type, 0)` is `Intra_4x4` or `Intra_8x8`, the inverse transform for the 4x4 chroma DC transform coefficients is specified as

$$f_{ij} = c_{ij} \ll 2 \quad \text{with } i, j = 0..3 \quad (8-325)$$

- Otherwise, the inverse transform for the 4x4 chroma DC transform coefficients is specified as

$$f = \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & 1 & -1 & -1 \\ 1 & -1 & -1 & 1 \\ 1 & -1 & 1 & -1 \end{bmatrix} \begin{bmatrix} c_{00} & c_{01} & c_{02} & c_{03} \\ c_{10} & c_{11} & c_{12} & c_{13} \\ c_{20} & c_{21} & c_{22} & c_{23} \\ c_{30} & c_{31} & c_{32} & c_{33} \end{bmatrix} \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & 1 & -1 & -1 \\ 1 & -1 & -1 & 1 \\ 1 & -1 & 1 & -1 \end{bmatrix} \quad (8-326)$$

The bitstream shall not contain data that results in any element  $f_{ij}$  of  $f$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth}'_c)}$  to  $2^{(7 + \text{BitDepth}'_c)} - 1$ , inclusive.

with:

- Otherwise (ChromaArrayType is equal to 2), the inverse transform for the 2x4 chroma DC transform coefficients is specified as

$$f = \begin{bmatrix} 1 & 1 & 1 & 1 \\ 1 & 1 & -1 & -1 \\ 1 & -1 & -1 & 1 \\ 1 & -1 & 1 & -1 \end{bmatrix} \begin{bmatrix} c_{00} & c_{01} \\ c_{10} & c_{11} \\ c_{20} & c_{21} \\ c_{30} & c_{31} \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \quad (8-324)$$

The bitstream shall not contain data that results in any element  $f_{ij}$  of  $f$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + \text{bitDepth}'_c)}$  to  $2^{(7 + \text{bitDepth}'_c)} - 1$ , inclusive.

Update all following equation numbers in clause 8 as necessary.

Replace the following:

- If chroma\_format\_idc is equal to 2, the following applies.

- The variable  $QP'_{C,DC}$  is derived as

$$QP'_{C,DC} = QP'_C + 3 \quad (8-328)$$

- Depending on the value of  $QP'_{C,DC}$ , the following applies.

- If  $QP'_{C,DC}$  is greater than or equal to 36, the scaled result is derived as

$$dcC_{ij} = (f_{ij} * \text{LevelScale}(QP'_{C,DC} \% 6, 0, 0)) \ll (QP'_{C,DC} / 6 - 6), \quad \text{with } i = 0..3, j = 0, 1 \quad (8-329)$$

- Otherwise ( $QP'_{C,DC}$  is less than 36), the scaled result is derived as

$$dcC_{ij} = (f_{ij} * \text{LevelScale}(QP'_{C,DC} \% 6, 0, 0) + 2^{5-QP'_{C,DC}/6}) \gg (6 - QP'_{C,DC} / 6), \quad \text{with } i = 0..3, j = 0, 1 \quad (8-330)$$

- Otherwise (chroma\_format\_idc is equal to 3), the following applies.

- If  $QP'_C$  is greater than or equal to 36, the scaled result is derived as

$$dcC_{ij} = (f_{ij} * \text{LevelScale}(QP'_C \% 6, 0, 0)) \ll (QP'_C / 6 - 6), \quad \text{with } i, j = 0..3. \quad (8-331)$$

- Otherwise ( $QP'_C$  is less than 36), the scaled result is derived as

$$dcC_{ij} = (f_{ij} * \text{LevelScale}(QP'_C \% 6, 0, 0) + 2^{5-QP'_C/6}) \gg (6 - QP'_C / 6), \quad \text{with } i, j = 0..3. \quad (8-332)$$

The bitstream shall not contain data that results in any element  $dcC_{ij}$  of  $dcC$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth}'_c)}$  to  $2^{(7 + \text{BitDepth}'_c)} - 1$ , inclusive.

with:

- Otherwise (ChromaArrayType is equal to 2), the following applies.

- The variable  $QP'_{C,DC}$  is derived as

$$QP'_{C,DC} = QP'_C + 3 \quad (8-328)$$

- Depending on the value of  $QP'_{C,DC}$ , the following applies.
  - If  $QP'_{C,DC}$  is greater than or equal to 36, the scaled result is derived as

$$dcC_{ij} = (f_{ij} * LevelScale(QP'_{C,DC} \% 6, 0, 0)) \ll (QP'_{C,DC} / 6 - 6), \text{ with } i = 0..3, j = 0, 1 \quad (8-329)$$

- Otherwise ( $QP'_{C,DC}$  is less than 36), the scaled result is derived as

$$dcC_{ij} = (f_{ij} * LevelScale(QP'_{C,DC} \% 6, 0, 0) + 2^{5-QP'_{C,DC}/6}) \gg (6 - QP'_{C,DC} / 6), \text{ with } i = 0..3, j = 0, 1 \quad (8-330)$$

The bitstream shall not contain data that results in any element  $dcC_{ij}$  of  $dcC$  with  $i, j = 0..3$  that exceeds the range of integer values from  $-2^{(7 + bitDepth_C)}$  to  $2^{(7 + bitDepth_C)} - 1$ , inclusive.

Update all following equation numbers in clause 8 as necessary.

In subclause 8.5.10 “Scaling and transformation process for residual 4x4 blocks”, replace the following:

- Otherwise (the input array  $c$  relates to a chroma residual block),  $bitDepth$  is set equal to  $BitDepth'_C$ .

with:

- Otherwise (the input array  $c$  relates to a chroma residual block),  $bitDepth$  is set equal to  $BitDepth_C$ .

In subclause 8.5.11 “Scaling and transformation process for residual 8x8 luma blocks”, make the following changes.

Replace the title of the subclause with the following:

#### 8.5.11 Scaling and transformation process for residual 8x8 blocks

Replace the following:

Input to this process is an 8x8 array  $c$  with elements  $c_{ij}$  which is an array relating to an 8x8 residual block of the luma component.

Outputs of this process are residual sample values as 8x8 array  $r$  with elements  $r_{ij}$ .

with:

Input to this process is an 8x8 array  $c$  with elements  $c_{ij}$  which is either an array relating to a residual block of the luma component or an array relating to a residual block of a chroma component when  $ChromaArrayType$  is equal to 3.

NOTE – When `separate_colour_plane_flag` is equal to 1, all residual blocks are considered to be associated with the luma component for purposes of the decoding process of each coded picture (prior to the final assignment of the decoded picture to a particular luma or chroma picture array according to the value of `colour_plane_id`).

Outputs of this process are residual sample values as 8x8 array  $r$  with elements  $r_{ij}$ .

The variables  $bitDepth$  and  $qP$  are derived as follows.

- If the input array  $c$  relates to a luma residual block,  $bitDepth$  is set equal to  $BitDepth_Y$  and  $qP$  is set equal to  $QP'_Y$ .

- Otherwise (the input array  $c$  relates to a chroma residual block),  $\text{bitDepth}$  is set equal to  $\text{BitDepth}_C$  and  $QP$  is set equal to  $QP'_C$ .

NOTE – When `separate_colour_plane_flag` is equal to 1, all residual blocks are considered to be associated with the luma component for purposes of the decoding process of each colour component of a picture.

*Replace the following:*

The bitstream shall not contain data that results in any element  $c_{ij}$  of  $c$  with  $i, j = 0..7$  that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth}_Y)}$  to  $2^{(7 + \text{BitDepth}_Y)} - 1$ , inclusive.

The scaling process for 8x8 block transform coefficient levels  $c_{ij}$  proceeds as follows.

- If  $QP'_Y$  is greater than or equal to 36, the scaled result is derived as

$$d_{ij} = (c_{ij} * \text{LevelScale8x8}(QP'_Y \% 6, i, j)) \ll (QP'_Y / 6 - 6), \quad \text{with } i, j = 0..7. \quad (8-359)$$

- Otherwise ( $QP'_Y$  is less than 36), the scaled result is derived as

$$d_{ij} = (c_{ij} * \text{LevelScale}(QP'_Y \% 6, i, j) + 2^{5 - QP'_Y / 6}) \gg (6 - QP'_Y / 6), \quad \text{with } i, j = 0..7. \quad (8-360)$$

The bitstream shall not contain data that results in any element  $d_{ij}$  of  $d$  with  $i, j = 0..7$  that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth}_Y)}$  to  $2^{(7 + \text{BitDepth}_Y)} - 1$ , inclusive.

*with:*

The bitstream shall not contain data that results in any element  $c_{ij}$  of  $c$  with  $i, j = 0..7$  that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth})}$  to  $2^{(7 + \text{BitDepth})} - 1$ , inclusive.

The scaling process for 8x8 block transform coefficient levels  $c_{ij}$  proceeds as follows.

- If  $qP$  is greater than or equal to 36, the scaled result shall be derived as

$$d_{ij} = (c_{ij} * \text{LevelScale8x8}(qP \% 6, i, j)) \ll (qP / 6 - 6), \quad \text{with } i, j = 0..7. \quad (8-359)$$

- Otherwise ( $qP$  is less than 36), the scaled result shall be derived as

$$d_{ij} = (c_{ij} * \text{LevelScale}(qP \% 6, i, j) + 2^{5 - qP / 6}) \gg (6 - qP / 6), \quad \text{with } i, j = 0..7. \quad (8-360)$$

The bitstream shall not contain data that results in any element  $d_{ij}$  of  $d$  with  $i, j = 0..7$  that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth})}$  to  $2^{(7 + \text{BitDepth})} - 1$ , inclusive.

*Replace the following paragraphs:*

The bitstream shall not contain data that results in any element  $e_{ij}$ ,  $f_{ij}$ ,  $g_{ij}$ ,  $h_{ij}$ , or  $k_{ij}$  for  $i$  and  $j$  in the range of 0..7, inclusive, that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth}_Y)}$  to  $2^{(7 + \text{BitDepth}_Y)} - 1$ , inclusive.

The bitstream shall not contain data that results in any element  $m_{ij}$  for  $i$  and  $j$  in the range of 0..7, inclusive, that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth}_Y)}$  to  $2^{(7 + \text{BitDepth}_Y)} - 33$ , inclusive.

*with:*

The bitstream shall not contain data that results in any element  $e_{ij}$ ,  $f_{ij}$ ,  $g_{ij}$ ,  $h_{ij}$ , or  $k_{ij}$  for  $i$  and  $j$  in the range of 0..7, inclusive, that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth})}$  to  $2^{(7 + \text{BitDepth})} - 1$ , inclusive.

The bitstream shall not contain data that results in any element  $m_{ij}$  for  $i$  and  $j$  in the range of 0..7, inclusive, that exceeds the range of integer values from  $-2^{(7 + \text{BitDepth})}$  to  $2^{(7 + \text{BitDepth})} - 33$ , inclusive.

In subclause 8.5.12 “Picture construction process prior to deblocking filter process”, make the following changes.

Replace the first paragraph with the following:

Inputs to this process are

- luma4x4BlkIdx or chroma4x4BlkIdx or luma8x8BlkIdx or cb4x4BlkIdx or cr4x4BlkIdx or cb8x8BlkIdx or cr8x8BlkIdx
- a sample array  $u$  with elements  $u_{ij}$  which is either a 4x4 luma block or a 4x4 chroma block or an 8x8 luma block or an 8x8 chroma block when ChromaArrayType is equal to 3.

Replace the paragraph starting with “When  $u$  is a chroma block” and all subparagraphs with the following:

When  $u$  is a chroma block, for each sample  $u_{ij}$  of the chroma block, the following applies.

- The subscript  $C$  in the variable  $S'C$  is replaced with  $Cb$  for the  $Cb$  chroma component and with  $Cr$  for the  $Cr$  chroma component.
- Depending on the size of the block  $u$ , the following applies.

- If  $u$  is an 4x4 luma block, the variable  $nE$  is set equal to 4 and depending on the variable ChromaArrayType, the position of the upper-left sample of a 4x4 chroma block inside the macroblock is derived as follows.

- If ChromaArrayType is equal to 1 or 2, the following applies.

$$xO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 0) \quad (8-411)$$

$$yO = \text{InverseRasterScan}(\text{chroma4x4BlkIdx}, 4, 4, 8, 1) \quad (8-412)$$

- Otherwise (ChromaArrayType is equal to 3), the position of the upper-left sample of the 4x4  $Cb$  block with index  $cb4x4BlkIdx$  or the 4x4  $Cr$  block with index  $cr4x4BlkIdx$  inside the macroblock is derived by invoking the inverse 4x4  $Cb$  or  $Cr$  block scanning process in subclause 6.4.3.1 with  $cb4x4BlkIdx$  or  $cr4x4BlkIdx$  as the input and the output being assigned to  $(xO, yO)$ .
- Otherwise ( $u$  is an 8x8  $Cb$  or  $Cr$  block when ChromaArrayType is equal to 3), the position of the upper-left sample of the 8x8  $Cb$  block with index  $cb8x8BlkIdx$  or the  $Cr$  block with index  $cr8x8BlkIdx$  inside the macroblock is derived by invoking the inverse 8x8  $Cb$  or  $Cr$  block scanning process in subclause 6.4.4.1 with  $cb8x8BlkIdx$  or  $cr8x8BlkIdx$  as the input and the output being assigned to  $(xO, yO)$ , and the variable  $nE$  is set equal to 8.

- Depending on the variable MbaffFrameFlag and the current macroblock, the following applies.

- If MbaffFrameFlag is equal to 1 and the current macroblock is a field macroblock

$$S'_c[(xP / \text{SubWidthC}) + xO + j, ((yP + \text{SubHeightC} - 1) / \text{SubHeightC}) + 2 * (yO + i)] = u_{ij} \quad \text{with } i, j = 0..nE - 1 \quad (8-416)$$

- Otherwise (MbaffFrameFlag is equal to 0 or the current macroblock is a frame macroblock),

$$S'_c[(xP / \text{SubWidthC}) + xO + j, (yP / \text{SubHeightC}) + yO + i] = u_{ij} \quad \text{with } i, j = 0..nE - 1 \quad (8-417)$$

Replace subclause 8.5.13 with the following:

### 8.5.13 Intra residual transform-bypass decoding process

This process is invoked when `qpprime_y_zero_transform_bypass_flag` is equal to 1,  $QP'_Y$  is equal to 0, the macroblock prediction mode is equal to `Intra_4x4`, `Intra_8x8` or `Intra_16x16`, and the applicable intra prediction mode is equal to the vertical or horizontal mode. The process for the Cb and Cr components is applied in the same way as for the luma (L or Y) component.

Inputs to this process are

- a variable `nMax`
- a variable `horPredFlag`
- an  $(nMax) \times (nMax)$  array  $r$  with elements  $r_{ij}$  which is either an array relating to a residual transform-bypass block of the luma component or an array relating to a residual transform-bypass block of the Cb and Cr component.

Output of this process is a modified version of the  $(nMax) \times (nMax)$  array  $r$  with elements  $r_{ij}$  containing the result of the intra residual transform-bypass decoding process.

Let  $f$  be a temporary  $(nMax) \times (nMax)$  array with elements  $f_{ij}$ , which are derived by

$$f_{ij} = r_{ij} \quad \text{with } i, j = 0..nMax - 1 \quad (8-417)$$

Depending on `horPredFlag`, the following applies.

- If `horPredFlag` is equal to 0, the modified array  $r$  is derived by.

$$r_{ij} = \sum_{k=0}^i f_{kj} \quad \text{with } i, j = 0..nMax - 1 \quad (8-417)$$

- Otherwise (`horPredFlag` is equal to 1), the modified array  $r$  is derived by

$$r_{ij} = \sum_{k=0}^j f_{ik} \quad \text{with } i, j = 0..nMax - 1 \quad (8-417)$$

Update all following equation numbers in clause 8 as necessary.

In subclause 8.7 “Deblocking filter process”, make the following changes.

Replace the first paragraph, which states as follows.

A conditional filtering process is applied to all  $N \times N$  (where  $N = 4$  or  $N = 8$  for luma, and  $N = 4$  for chroma) block edges of a picture, except edges at the boundary of the picture and any edges for which the deblocking filter process is disabled by `disable_deblocking_filter_idc`, as specified below. This filtering process is performed on a macroblock basis after the completion of the picture construction process prior to deblocking filter process (as specified in subclauses 8.5 and 8.6) for the entire decoded picture, with all macroblocks in a picture processed in order of increasing macroblock addresses.

with:

A conditional filtering process is specified in this subclause that is an integral part of the decoding process which shall be applied by decoders conforming to the Baseline, Extended, Main, High, High 10, High 4:2:2, and High 4:4:4 Predictive profiles. For decoders conforming to the High 10 Intra, High 4:2:2 Intra, High 4:4:4 Intra, and CAVLC 4:4:4 Intra profiles, the filtering process specified in this subclause, or one similar to it, should be applied but is not required.

The conditional filtering is applied to all  $N \times N$  (where  $N = 4$  or  $N = 8$  for luma and for chroma when ChromaArrayType is equal to 3, and  $N = 4$  for chroma when ChromaArrayType is equal to 1 or 2) block edges of a picture, except edges at the boundary of the picture and any edges for which the deblocking filter process is disabled by `disable_deblocking_filter_idc`, as specified below. This filtering process is performed on a macroblock basis after the completion of the picture construction process prior to deblocking filter process (as specified in subclauses 8.5 and 8.6) for the entire decoded picture, with all macroblocks in a picture processed in order of increasing macroblock addresses.

Replace the following:

- Otherwise, if `chroma_format_idc` is equal to 3 (4:4:4 format), both types, the solid bold and dashed bold chroma edges are filtered.

with:

- Otherwise, if ChromaArrayType is equal to 3, depending on the `transform_size_8x8_flag`, the following applies.
  - If `transform_size_8x8_flag` is equal to 0, both types, the solid bold and dashed bold chroma edges are filtered.
  - Otherwise (`transform_size_8x8_flag` is equal to 1), only the solid bold chroma edges are filtered.

Replace the paragraph starting with “For the filtering of both chroma components” with the following:

When ChromaArrayType is not equal to 0, for the filtering of both chroma components with `iCbCr = 0` for Cb and `iCbCr = 1` for Cr, the following applies.

Replace the paragraph starting with “When `filterInternalEdgesFlag` is equal to 1, the filtering of the internal vertical chroma edge is specified as follows” with the following:

- When `filterInternalEdgesFlag` is equal to 1, the filtering of the internal vertical chroma edge is specified as follows.
  - When ChromaArrayType is not equal to 3 or when `transform_size_8x8_flag` is equal to 0, the process specified in subclause 8.7.1 is invoked with `mbAddr`, `chromaEdgeFlag = 1`, `iCbCr`, `verticalEdgeFlag = 1`, `fieldModeFilteringFlag = fieldModeMbFlag`, and  $(xE_k, yE_k) = (4, k)$  with  $k = 0..MbHeightC - 1$  as input and  $S'_C$  with C being replaced by Cb for `iCbCr = 0` and C being replaced by Cr for `iCbCr = 1` as output.
  - When ChromaArrayType is equal to 3, the process specified in subclause 8.7.1 is invoked with `mbAddr`, `chromaEdgeFlag = 1`, `iCbCr`, `verticalEdgeFlag = 1`, `fieldModeFilteringFlag = fieldModeMbFlag`, and  $(xE_k, yE_k) = (8, k)$  with  $k = 0..MbHeightC - 1$  as input and  $S'_C$  with C being replaced by Cb for `iCbCr = 0` and C being replaced by Cr for `iCbCr = 1` as output.
  - When ChromaArrayType is equal to 3 and when `transform_size_8x8_flag` is equal to 0, the process specified in subclause 8.7.1 is invoked with `mbAddr`, `chromaEdgeFlag = 1`, `iCbCr`, `verticalEdgeFlag = 1`, `fieldModeFilteringFlag = fieldModeMbFlag`, and  $(xE_k, yE_k) = (12, k)$  with  $k = 0..MbHeightC - 1$  as input and  $S'_C$  with C being replaced by Cb for `iCbCr = 0` and C being replaced by Cr for `iCbCr = 1` as output.

Replace the paragraph starting with “When `filterInternalEdgesFlag` is equal to 1, the filtering of the internal horizontal chroma edge is specified as follows” with the following:

- When `filterInternalEdgesFlag` is equal to 1, the filtering of the internal horizontal chroma edge is specified as follows.
  - When ChromaArrayType is not equal to 3 or when `transform_size_8x8_flag` is equal to 0, the process specified in subclause 8.7.1 is invoked with `mbAddr`, `chromaEdgeFlag = 1`, `iCbCr`, `verticalEdgeFlag = 0`, `fieldModeFilteringFlag = fieldModeMbFlag`, and  $(xE_k, yE_k) = (k, 4)$  with  $k = 0..MbWidthC - 1$  as input and  $S'_C$  with C being replaced by Cb for `iCbCr = 0` and C being replaced by Cr for `iCbCr = 1` as output.

- When ChromaArrayType is not equal to 1, the process specified in subclause 8.7.1 is invoked with mbAddr, chromaEdgeFlag = 1, iCbCr, verticalEdgeFlag = 0, fieldModeFilteringFlag = fieldModeMbFlag, and  $(xE_k, yE_k) = (k, 8)$  with  $k = 0..MbWidthC - 1$  as input and  $S'_C$  with C being replaced by Cb for iCbCr = 0 and C being replaced by Cr for iCbCr = 1 as output.
- When ChromaArrayType is equal to 2, the process specified in subclause 8.7.1 is invoked with mbAddr, chromaEdgeFlag = 1, iCbCr, verticalEdgeFlag = 0, fieldModeFilteringFlag = fieldModeMbFlag, and  $(xE_k, yE_k) = (k, 12)$  with  $k = 0..MbWidthC - 1$  as input and  $S'_C$  with C being replaced by Cb for iCbCr = 0 and C being replaced by Cr for iCbCr = 1 as output.
- When ChromaArrayType is equal to 3 and when transform\_size\_8x8\_flag is equal to 0, the process specified in subclause 8.7.1 is invoked with mbAddr, chromaEdgeFlag = 1, iCbCr, verticalEdgeFlag = 0, fieldModeFilteringFlag = fieldModeMbFlag, and  $(xE_k, yE_k) = (k, 12)$  with  $k = 0..MbWidthC - 1$  as input and  $S'_C$  with C being replaced by Cb for iCbCr = 0 and C being replaced by Cr for iCbCr = 1 as output.

Replace the paragraph that begins with “Finally, the arrays” with the following:

Depending on separate\_colour\_plane\_flag the following applies.

- If separate\_colour\_plane\_flag is equal to 0, the arrays  $S'_L$ ,  $S'_{Cb}$ ,  $S'_{Cr}$  are assigned to the arrays  $S_L$ ,  $S_{Cb}$ ,  $S_{Cr}$  (which represent the decoded picture), respectively.
- Otherwise (separate\_colour\_plane\_flag is equal to 1), the following applies.
  - If colour\_plane\_id is equal to 0, the arrays  $S'_L$  is assigned to the array  $S_L$  (which represent the luma component of the decoded picture).
  - Otherwise, if colour\_plane\_id is equal to 1, the arrays  $S'_L$  is assigned to the array  $S_{Cb}$  (which represents the Cb component of the decoded picture).
  - Otherwise (colour\_plane\_id is equal to 2), the arrays  $S'_L$  is assigned to the array  $S_{Cr}$  (which represents the Cr component of the decoded picture).

In subclause 8.7.2.3 “Filtering process for edges with bS less than 4”, make the following changes.

Replace the paragraph starting with “The filtered result samples  $p'_0$  and  $q'_0$  are derived by” with the following:

The filtered result samples  $p'_0$  and  $q'_0$  are derived by

$$\Delta = \text{Clip3}(-t_c, t_c, (((q_0 - p_0) << 2) + (p_1 - q_1) + 4) >> 3)) \quad (8-469)$$

$$p'_0 = \text{Clip1}(p_0 + \Delta) \quad (8-470)$$

$$q'_0 = \text{Clip1}(q_0 - \Delta) \quad (8-471)$$

where the threshold  $t_c$  is determined as follows.

- If chromaEdgeFlag is equal to 0,

$$t_c = t_{c0} + ((a_p < \beta) ? 1 : 0) + ((a_q < \beta) ? 1 : 0) \quad (8-472)$$

- Otherwise (chromaEdgeFlag is equal to 1), the following applies.
  - When ChromaArrayType is equal to 3,

$$t_c = t_{c0} + ((a_p < \beta) ? 1 : 0) + ((a_q < \beta) ? 1 : 0) \quad (8-472a)$$

- Otherwise

$$t_c = t_{c0} + 1 \quad (8-473)$$

Update all following equation numbers in clause 8 as necessary.

Replace the paragraph starting with “The filtered result sample  $p'_1$ ” with the following:

The filtered result sample  $p'_1$  is derived as follows:

- If chromaEdgeFlag is equal to 0 and  $a_p$  is less than  $\beta$ ,

$$p'_1 = p_1 + \text{Clip3}(-t_{c0}, t_{c0}, (p_2 + ((p_0 + q_0 + 1) \gg 1) - (p_1 \ll 1)) \gg 1) \quad (8-478)$$

- Otherwise, if chromaEdgeFlag is equal to 1, ChromaArrayType is equal to 3, and  $a_p$  is less than  $\beta$ ,

$$p'_1 = p_1 + \text{Clip3}(-t_{c0}, t_{c0}, (p_2 + ((p_0 + q_0 + 1) \gg 1) - (p_1 \ll 1)) \gg 1) \quad (8-478a)$$

- Otherwise (chromaEdgeFlag is equal to 1 and ChromaArrayType is not equal to 3, or  $a_p$  is greater than or equal to  $\beta$ ),

$$p'_1 = p_1 \quad (8-479)$$

Replace the paragraph starting with “The filtered result sample  $q'_1$ ” with the following:

The filtered result sample  $q'_1$  is derived as follows:

- If chromaEdgeFlag is equal to 0 and  $a_q$  is less than  $\beta$ ,

$$q'_1 = q_1 + \text{Clip3}(-t_{c0}, t_{c0}, (q_2 + ((p_0 + q_0 + 1) \gg 1) - (q_1 \ll 1)) \gg 1) \quad (8-480)$$

- Otherwise, if chromaEdgeFlag is equal to 1, ChromaArrayType is equal to 3, and  $a_q$  is less than  $\beta$ ,

$$q'_1 = q_1 + \text{Clip3}(-t_{c0}, t_{c0}, (q_2 + ((p_0 + q_0 + 1) \gg 1) - (q_1 \ll 1)) \gg 1) \quad (8-480a)$$

- Otherwise (chromaEdgeFlag is equal to 1 and ChromaArrayType is not equal to 3, or  $a_q$  is greater than or equal to  $\beta$ ),

$$q'_1 = q_1 \quad (8-481)$$

Update all following equation numbers in clause 8 as necessary.

In subclause 8.7.2.4 “Filtering process for edges for  $bS$  equal to 4”, make the following changes.

Replace the paragraph starting with “The filtered result samples  $p'_i$  ( $i = 0..2$ ) are derived as follows” with the following:

The filtered result samples  $p'_i$  ( $i = 0..2$ ) are derived as follows.

- If chromaEdgeFlag is equal to 0 and the following condition holds,

$$a_p < \beta \ \&\& \ Abs(p_0 - q_0) < ((\alpha >> 2) + 2) \quad (8-484)$$

then the variables  $p'_0$ ,  $p'_1$ , and  $p'_2$  are derived by

$$p'_0 = (p_2 + 2*p_1 + 2*p_0 + 2*q_0 + q_1 + 4) >> 3 \quad (8-485)$$

$$p'_1 = (p_2 + p_1 + p_0 + q_0 + 2) >> 2 \quad (8-486)$$

$$p'_2 = (2*p_3 + 3*p_2 + p_1 + p_0 + q_0 + 4) >> 3 \quad (8-487)$$

- Otherwise, if chromaEdgeFlag is equal to 1, ChromaArrayType is equal to 3, and the condition in Equation 8-484 holds, the variables  $p'_0$ ,  $p'_1$ , and  $p'_2$  are derived by

$$p'_0 = (p_2 + 2*p_1 + 2*p_0 + 2*q_0 + q_1 + 4) >> 3 \quad (8-485a)$$

$$p'_1 = (p_2 + p_1 + p_0 + q_0 + 2) >> 2 \quad (8-486a)$$

$$p'_2 = (2*p_3 + 3*p_2 + p_1 + p_0 + q_0 + 4) >> 3 \quad (8-487a)$$

- Otherwise (chromaEdgeFlag is equal to 1 and ChromaArrayType is not equal to 3, or the condition in Equation 8-484 does not hold), the variables  $p'_0$ ,  $p'_1$ , and  $p'_2$  are derived by

$$p'_0 = (2*p_1 + p_0 + q_1 + 2) >> 2 \quad (8-488)$$

$$p'_1 = p_1 \quad (8-489)$$

$$p'_2 = p_2 \quad (8-490)$$

Update all following equation numbers in clause 8 as necessary.

Replace the paragraph starting with “The filtered result samples  $q'_i$  ( $i = 0..2$ ) are derived as follows” with the following:

The filtered result samples  $q'_i$  ( $i = 0..2$ ) are derived as follows.

- If chromaEdgeFlag is equal to 0 and the following condition holds,

$$a_q < \beta \ \&\& \ Abs(p_0 - q_0) < ((\alpha >> 2) + 2) \quad (8-491)$$

then the variables  $q'_0$ ,  $q'_1$ , and  $q'_2$  are derived by

$$q'_0 = (p_1 + 2*p_0 + 2*q_0 + 2*q_1 + q_2 + 4) >> 3 \quad (8-492)$$

$$q'_1 = (p_0 + q_0 + q_1 + q_2 + 2) >> 2 \quad (8-493)$$

$$q'_2 = (2*q_3 + 3*q_2 + q_1 + q_0 + p_0 + 4) >> 3 \quad (8-494)$$

- If chromaEdgeFlag is equal to 1, ChromaArrayType is equal to 3, and the condition in Equation 8-491 holds, the variables  $q'_0$ ,  $q'_1$ , and  $q'_2$  are derived by

$$q'_0 = (p_1 + 2 \cdot p_0 + 2 \cdot q_0 + 2 \cdot q_1 + q_2 + 4) \gg 3 \quad (8-492a)$$

$$q'_1 = (p_0 + q_0 + q_1 + q_2 + 2) \gg 2 \quad (8-493a)$$

$$q'_2 = (2 \cdot q_3 + 3 \cdot q_2 + q_1 + q_0 + p_0 + 4) \gg 3 \quad (8-494a)$$

- Otherwise (chromaEdgeFlag is equal to 1 and ChromaArrayType is not equal to 3, or the condition in Equation 8-491 does not hold), the variables  $q'_0$ ,  $q'_1$ , and  $q'_2$  are derived by

$$q'_0 = (2 \cdot q_1 + q_0 + p_1 + 2) \gg 2 \quad (8-495)$$

$$q'_1 = q_1 \quad (8-496)$$

$$q'_2 = q_2 \quad (8-497)$$

Update all following equation numbers in clause 8 as necessary.

In clause 9 and all subclauses of clause 9, make the following changes.

Replace all occurrences of “chroma\_format\_idc” with “ChromaArrayType”.

Delete all occurrences of “(monochrome)”.

In subclause 9.1.2 “Mapping process for coded block pattern”, make the following changes.

Replace the title of the first part of Table 9-4 “(a) chroma\_format\_idc is not equal to 0” with the following:

(a) ChromaArrayType is equal to 1, or 2

Replace the title of the second part of Table 9-4 “(b) chroma\_format\_idc is equal to 0” with the following:

(b) ChromaArrayType is equal to 0, or 3

In subclause 9.2 “CAVLC parsing process for transform coefficient levels”, make the following changes.

Replace the paragraph starting with “Inputs to this process” with the following:

Inputs to this process are bits from slice data, a maximum number of non-zero transform coefficient levels maxNumCoeff, the luma block index luma4x4BlkIdx or the chroma block index chroma4x4BlkIdx or index cb4x4BlkIdx or index cr4x4BlkIdx of the current block of transform coefficient levels.

Replace the paragraph starting with “Output of this process” with the following:

Output of this process is the list coeffLevel containing transform coefficient levels of the luma block with block index luma4x4BlkIdx or the chroma block with block index chroma4x4BlkIdx or index cb4x4BlkIdx or index cr4x4BlkIdx.

In subclause 9.2.1 “Parsing process for total number of transform coefficient levels and trailing ones”, make the following changes.

Replace the paragraph starting with “Inputs to this process” with the following:

Inputs to this process are bits from slice data, a maximum number of non-zero transform coefficient levels `maxNumCoeff`, the luma block index `luma4x4BlkIdx` or the chroma block index `chroma4x4BlkIdx` or index `cb4x4BlkIdx` or index `cr4x4BlkIdx` of the current block of transform.

Delete the paragraph “Otherwise (`chroma_format_idc` is equal to 3), `nC` is set equal to 0”.

Add the following two new paragraphs after the paragraph starting with “When the CAVLC parsing process is invoked for `Intra16x16DCLevel`”:

When the CAVLC parsing process is invoked for `CbIntra16x16DCLevel`, `cb4x4BlkIdx` is set equal to 0.

When the CAVLC parsing process is invoked for `CrIntra16x16DCLevel`, `cr4x4BlkIdx` is set equal to 0.

Add the following two new paragraphs after the paragraph starting with “If the CAVLC parsing process is invoked for `Intra16x16DCLevel`”:

Otherwise, if the CAVLC parsing process is invoked for `CbIntra16x16DCLevel`, `CbIntra16x16ACLevel`, or `CbLevel`, the process specified in subclause 6.4.8.4.1 is invoked with `cb4x4BlkIdx` as the input, and the output is assigned to `mbAddrA`, `mbAddrB`, `cb4x4BlkIdxA`, and `cb4x4BlkIdxB`. The 4x4 Cb block specified by `mbAddrA\cb4x4BlkIdxA` is assigned to `blkA`, and the 4x4 Cb block specified by `mbAddrB\cb4x4BlkIdxB` is assigned to `blkB`.

Otherwise, if the CAVLC parsing process is invoked for `CrIntra16x16DCLevel`, `CrIntra16x16ACLevel`, or `CrLevel`, the process specified in subclause 6.4.8.4.1 is invoked with `cr4x4BlkIdx` as the input, and the output is assigned to `mbAddrA`, `mbAddrB`, `cr4x4BlkIdxA`, and `cr4x4BlkIdxB`. The 4x4 Cr block specified by `mbAddrA\cr4x4BlkIdxA` is assigned to `blkA`, and the 4x4 Cr block specified by `mbAddrB\cr4x4BlkIdxB` is assigned to `blkB`.

Replace the paragraph starting with “NOTE - When parsing for `Intra16x16DCLevel`,” with the following:

NOTE – When parsing for `Intra16x16DCLevel`, `CbIntra16x16DCLevel`, or `CrIntra16x16DCLevel`, the values `nA` and `nB` are based on the number of non-zero transform coefficient levels in adjacent 4x4 blocks and not on the number of non-zero DC transform coefficient levels in adjacent 16x16 blocks.

In subclause 9.3.1.1 “Initialisation process for context variables”, make the following changes.

Replace Table 9-11 with the following:

**Table 9-11 – Association of `ctxIdx` and syntax elements for each slice type in the initialisation process**

|                                 | Syntax element                          | Table                                  | Slice type |         |         |         |
|---------------------------------|-----------------------------------------|----------------------------------------|------------|---------|---------|---------|
|                                 |                                         |                                        | SI         | I       | P, SP   | B       |
| <code>slice_data()</code>       | <code>mb_skip_flag</code>               | Table 9-13<br>Table 9-14               |            |         | 11-13   | 24-26   |
|                                 | <code>mb_field_decoding_flag</code>     | Table 9-18                             | 70-72      | 70-72   | 70-72   | 70-72   |
| <code>macroblock_layer()</code> | <code>mb_type</code>                    | Table 9-12<br>Table 9-13<br>Table 9-14 | 0-10       | 3-10    | 14-20   | 27-35   |
|                                 | <code>transform_size_8x8_flag</code>    | Table 9-16                             | na         | 399-401 | 399-401 | 399-401 |
|                                 | <code>coded_block_pattern (luma)</code> | Table 9-18                             | 73-76      | 73-76   | 73-76   | 73-76   |

|                                |                                |                                                                                                                  |                    |                                                                                      |                                                                                      |                                                                                      |
|--------------------------------|--------------------------------|------------------------------------------------------------------------------------------------------------------|--------------------|--------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|
|                                | coded_block_pattern (chroma)   | Table 9-18                                                                                                       | 77-84              | 77-84                                                                                | 77-84                                                                                | 77-84                                                                                |
|                                | mb_qp_delta                    | Table 9-17                                                                                                       | 60-63              | 60-63                                                                                | 60-63                                                                                | 60-63                                                                                |
| mb_pred()                      | prev_intra4x4_pred_mode_flag   | Table 9-17                                                                                                       | 68                 | 68                                                                                   | 68                                                                                   | 68                                                                                   |
|                                | rem_intra4x4_pred_mode         | Table 9-17                                                                                                       | 69                 | 69                                                                                   | 69                                                                                   | 69                                                                                   |
|                                | prev_intra8x8_pred_mode_flag   | Table 9-17                                                                                                       | na                 | 68                                                                                   | 68                                                                                   | 68                                                                                   |
|                                | rem_intra8x8_pred_mode         | Table 9-17                                                                                                       | na                 | 69                                                                                   | 69                                                                                   | 69                                                                                   |
|                                | intra_chroma_pred_mode         | Table 9-17                                                                                                       | 64-67              | 64-67                                                                                | 64-67                                                                                | 64-67                                                                                |
| mb_pred() and<br>sub_mb_pred() | ref_idx_l0                     | Table 9-16                                                                                                       |                    |                                                                                      | 54-59                                                                                | 54-59                                                                                |
|                                | ref_idx_l1                     | Table 9-16                                                                                                       |                    |                                                                                      |                                                                                      | 54-59                                                                                |
|                                | mvd_l0[ ][ 0 ]                 | Table 9-15                                                                                                       |                    |                                                                                      | 40-46                                                                                | 40-46                                                                                |
|                                | mvd_l1[ ][ 0 ]                 | Table 9-15                                                                                                       |                    |                                                                                      |                                                                                      | 40-46                                                                                |
|                                | mvd_l0[ ][ 1 ]                 | Table 9-15                                                                                                       |                    |                                                                                      | 47-53                                                                                | 47-53                                                                                |
|                                | mvd_l1[ ][ 1 ]                 | Table 9-15                                                                                                       |                    |                                                                                      |                                                                                      | 47-53                                                                                |
| sub_mb_pred()                  | sub_mb_type                    | Table 9-13<br>Table 9-14                                                                                         |                    |                                                                                      | 21-23                                                                                | 36-39                                                                                |
| residual_block_cabac()         | coded_block_flag               | Table 9-18<br>Table 9-24a<br>Table 9-24i                                                                         | 85-104<br>460-483  | 85-104<br>460-483<br>1012-1023                                                       | 85-104<br>460-483<br>1012-1023                                                       | 85-104<br>460-483<br>1012-1023                                                       |
|                                | significant_coeff_flag[ ]      | Table 9-19<br>Table 9-22<br>Table 9-24<br>Table 9-24<br>Table 9-24b<br>Table 9-22f<br>Table 9-24d<br>Table 9-24e | 105-165<br>277-337 | 105-165<br>277-337<br>402-416<br>436-450<br>484-571<br>776-863<br>660-689<br>718-747 | 105-165<br>277-337<br>402-416<br>436-450<br>484-571<br>776-863<br>660-689<br>718-747 | 105-165<br>277-337<br>402-416<br>436-450<br>484-571<br>776-863<br>660-689<br>718-747 |
|                                | last_significant_coeff_flag[ ] | Table 9-20<br>Table 9-23<br>Table 9-24<br>Table 9-24<br>Table 9-24c<br>Table 9-24g<br>Table 9-24d<br>Table 9-24e | 166-226<br>338-398 | 166-226<br>338-398<br>417-425<br>451-459<br>572-659<br>864-951<br>690-707<br>748-765 | 166-226<br>338-398<br>417-425<br>451-459<br>572-659<br>864-951<br>690-707<br>748-765 | 166-226<br>338-398<br>417-425<br>451-459<br>572-659<br>864-951<br>690-707<br>748-765 |
|                                | coeff_abs_level_minus1[ ]      | Table 9-21<br>Table 9-24<br>Table 9-24h<br>Table 9-24d<br>Table 9-24e                                            | 227-275            | 227-275<br>426-435<br>952-1011<br>708-717<br>766-775                                 | 227-275<br>426-435<br>952-1011<br>708-717<br>766-775                                 | 227-275<br>426-435<br>952-1011<br>708-717<br>766-775                                 |

Insert a new Table 9-24a as follows:

Table 9-24a – Values of variables m and n for ctxIdx from 460 to 483

| ctxIdx | I and SI slices |     | Value of cabac_init_idc |     |     |     |     |     | ctxIdx | I and SI slices |     | Value of cabac_init_idc |     |     |     |     |     |
|--------|-----------------|-----|-------------------------|-----|-----|-----|-----|-----|--------|-----------------|-----|-------------------------|-----|-----|-----|-----|-----|
|        |                 |     | 0                       |     | 1   |     | 2   |     |        |                 |     | 0                       |     | 1   |     | 2   |     |
|        | m               | n   | m                       | n   | m   | n   | m   | n   |        | m               | n   | m                       | n   | m   | n   |     |     |
| 460    | -17             | 123 | -7                      | 92  | 0   | 80  | 11  | 80  | 472    | -17             | 123 | -7                      | 92  | 0   | 80  | 11  | 80  |
| 461    | -12             | 115 | -5                      | 89  | -5  | 89  | 5   | 76  | 473    | -12             | 115 | -5                      | 89  | -5  | 89  | 5   | 76  |
| 462    | -16             | 122 | -7                      | 96  | -7  | 94  | 2   | 84  | 474    | -16             | 122 | -7                      | 96  | -7  | 94  | 2   | 84  |
| 463    | -11             | 115 | -13                     | 108 | -4  | 92  | 5   | 78  | 475    | -11             | 115 | -13                     | 108 | -4  | 92  | 5   | 78  |
| 464    | -12             | 63  | -3                      | 46  | 0   | 39  | -6  | 55  | 476    | -12             | 63  | -3                      | 46  | 0   | 39  | -6  | 55  |
| 465    | -2              | 68  | -1                      | 65  | 0   | 65  | 4   | 61  | 477    | -2              | 68  | -1                      | 65  | 0   | 65  | 4   | 61  |
| 466    | -15             | 84  | -1                      | 57  | -15 | 84  | -14 | 83  | 478    | -15             | 84  | -1                      | 57  | -15 | 84  | -14 | 83  |
| 467    | -13             | 104 | -9                      | 93  | -35 | 127 | -37 | 127 | 479    | -13             | 104 | -9                      | 93  | -35 | 127 | -37 | 127 |
| 468    | -3              | 70  | -3                      | 74  | -2  | 73  | -5  | 79  | 480    | -3              | 70  | -3                      | 74  | -2  | 73  | -5  | 79  |
| 469    | -8              | 93  | -9                      | 92  | -12 | 104 | -11 | 104 | 481    | -8              | 93  | -9                      | 92  | -12 | 104 | -11 | 104 |
| 470    | -10             | 90  | -8                      | 87  | -9  | 91  | -11 | 91  | 482    | -10             | 90  | -8                      | 87  | -9  | 91  | -11 | 91  |
| 471    | -30             | 127 | -23                     | 126 | -31 | 127 | -30 | 127 | 483    | -30             | 127 | -23                     | 126 | -31 | 127 | -30 | 127 |

Insert a new Table 9-24b as follows:

Table 9-24b – Values of variables m and n for ctxIdx from 484 to 571

| ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |     |     |     |    | ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |     |     |     |    |
|--------|-----------------|----|-------------------------|-----|-----|-----|-----|----|--------|-----------------|----|-------------------------|-----|-----|-----|-----|----|
|        |                 |    | 0                       |     | 1   |     | 2   |    |        |                 |    | 0                       |     | 1   |     | 2   |    |
|        | m               | n  | m                       | n   | m   | n   | m   | n  |        | m               | n  | m                       | n   | m   | n   | m   | n  |
| 484    | -7              | 93 | -2                      | 85  | -13 | 103 | -4  | 86 | 528    | -7              | 93 | -2                      | 85  | -13 | 103 | -4  | 86 |
| 485    | -11             | 87 | -6                      | 78  | -13 | 91  | -12 | 88 | 529    | -11             | 87 | -6                      | 78  | -13 | 91  | -12 | 88 |
| 486    | -3              | 77 | -1                      | 75  | -9  | 89  | -5  | 82 | 530    | -3              | 77 | -1                      | 75  | -9  | 89  | -5  | 82 |
| 487    | -5              | 71 | -7                      | 77  | -14 | 92  | -3  | 72 | 531    | -5              | 71 | -7                      | 77  | -14 | 92  | -3  | 72 |
| 488    | -4              | 63 | 2                       | 54  | -8  | 76  | -4  | 67 | 532    | -4              | 63 | 2                       | 54  | -8  | 76  | -4  | 67 |
| 489    | -4              | 68 | 5                       | 50  | -12 | 87  | -8  | 72 | 533    | -4              | 68 | 5                       | 50  | -12 | 87  | -8  | 72 |
| 490    | -12             | 84 | -3                      | 68  | -23 | 110 | -16 | 89 | 534    | -12             | 84 | -3                      | 68  | -23 | 110 | -16 | 89 |
| 491    | -7              | 62 | 1                       | 50  | -24 | 105 | -9  | 69 | 535    | -7              | 62 | 1                       | 50  | -24 | 105 | -9  | 69 |
| 492    | -7              | 65 | 6                       | 42  | -10 | 78  | -1  | 59 | 536    | -7              | 65 | 6                       | 42  | -10 | 78  | -1  | 59 |
| 493    | 8               | 61 | -4                      | 81  | -20 | 112 | 5   | 66 | 537    | 8               | 61 | -4                      | 81  | -20 | 112 | 5   | 66 |
| 494    | 5               | 56 | 1                       | 63  | -17 | 99  | 4   | 57 | 538    | 5               | 56 | 1                       | 63  | -17 | 99  | 4   | 57 |
| 495    | -2              | 66 | -4                      | 70  | -78 | 127 | -4  | 71 | 539    | -2              | 66 | -4                      | 70  | -78 | 127 | -4  | 71 |
| 496    | 1               | 64 | 0                       | 67  | -70 | 127 | -2  | 71 | 540    | 1               | 64 | 0                       | 67  | -70 | 127 | -2  | 71 |
| 497    | 0               | 61 | 2                       | 57  | -50 | 127 | 2   | 58 | 641    | 0               | 61 | 2                       | 57  | -50 | 127 | 2   | 58 |
| 498    | -2              | 78 | -2                      | 76  | -46 | 127 | -1  | 74 | 542    | -2              | 78 | -2                      | 76  | -46 | 127 | -1  | 74 |
| 499    | 1               | 50 | 11                      | 35  | -4  | 66  | -4  | 44 | 543    | 1               | 50 | 11                      | 35  | -4  | 66  | -4  | 44 |
| 500    | 7               | 52 | 4                       | 64  | -5  | 78  | -1  | 69 | 544    | 7               | 52 | 4                       | 64  | -5  | 78  | -1  | 69 |
| 501    | 10              | 35 | 1                       | 61  | -4  | 71  | 0   | 62 | 545    | 10              | 35 | 1                       | 61  | -4  | 71  | 0   | 62 |
| 502    | 0               | 44 | 11                      | 35  | -8  | 72  | -7  | 51 | 546    | 0               | 44 | 11                      | 35  | -8  | 72  | -7  | 51 |
| 503    | 11              | 38 | 18                      | 25  | 2   | 59  | -4  | 47 | 547    | 11              | 38 | 18                      | 25  | 2   | 59  | -4  | 47 |
| 504    | 1               | 45 | 12                      | 24  | -1  | 55  | -6  | 42 | 548    | 1               | 45 | 12                      | 24  | -1  | 55  | -6  | 42 |
| 505    | 0               | 46 | 13                      | 29  | -7  | 70  | -3  | 41 | 549    | 0               | 46 | 13                      | 29  | -7  | 70  | -3  | 41 |
| 506    | 5               | 44 | 13                      | 36  | -6  | 75  | -6  | 53 | 550    | 5               | 44 | 13                      | 36  | -6  | 75  | -6  | 53 |
| 507    | 31              | 17 | -10                     | 93  | -8  | 89  | 8   | 76 | 551    | 31              | 17 | -10                     | 93  | -8  | 89  | 8   | 76 |
| 508    | 1               | 51 | -7                      | 73  | -34 | 119 | -9  | 78 | 552    | 1               | 51 | -7                      | 73  | -34 | 119 | -9  | 78 |
| 509    | 7               | 50 | -2                      | 73  | -3  | 75  | -11 | 83 | 553    | 7               | 50 | -2                      | 73  | -3  | 75  | -11 | 83 |
| 510    | 28              | 19 | 13                      | 46  | 32  | 20  | 9   | 52 | 554    | 28              | 19 | 13                      | 46  | 32  | 20  | 9   | 52 |
| 511    | 16              | 33 | 9                       | 49  | 30  | 22  | 0   | 67 | 555    | 16              | 33 | 9                       | 49  | 30  | 22  | 0   | 67 |
| 512    | 14              | 62 | -7                      | 100 | -44 | 127 | -5  | 90 | 556    | 14              | 62 | -7                      | 100 | -44 | 127 | -5  | 90 |

|     |     |     |     |    |     |    |     |    |     |     |     |     |    |     |    |     |    |
|-----|-----|-----|-----|----|-----|----|-----|----|-----|-----|-----|-----|----|-----|----|-----|----|
| 513 | -13 | 108 | 9   | 53 | 0   | 54 | 1   | 67 | 557 | -13 | 108 | 9   | 53 | 0   | 54 | 1   | 67 |
| 514 | -15 | 100 | 2   | 53 | -5  | 61 | -15 | 72 | 558 | -15 | 100 | 2   | 53 | -5  | 61 | -15 | 72 |
| 515 | -13 | 101 | 5   | 53 | 0   | 58 | -5  | 75 | 559 | -13 | 101 | 5   | 53 | 0   | 58 | -5  | 75 |
| 516 | -13 | 91  | -2  | 61 | -1  | 60 | -8  | 80 | 560 | -13 | 91  | -2  | 61 | -1  | 60 | -8  | 80 |
| 517 | -12 | 94  | 0   | 56 | -3  | 61 | -21 | 83 | 561 | -12 | 94  | 0   | 56 | -3  | 61 | -21 | 83 |
| 518 | -10 | 88  | 0   | 56 | -8  | 67 | -21 | 64 | 562 | -10 | 88  | 0   | 56 | -8  | 67 | -21 | 64 |
| 519 | -16 | 84  | -13 | 63 | -25 | 84 | -13 | 31 | 563 | -16 | 84  | -13 | 63 | -25 | 84 | -13 | 31 |
| 520 | -10 | 86  | -5  | 60 | -14 | 74 | -25 | 64 | 564 | -10 | 86  | -5  | 60 | -14 | 74 | -25 | 64 |
| 521 | -7  | 83  | -1  | 62 | -5  | 65 | -29 | 94 | 565 | -7  | 83  | -1  | 62 | -5  | 65 | -29 | 94 |
| 522 | -13 | 87  | 4   | 57 | 5   | 52 | 9   | 75 | 566 | -13 | 87  | 4   | 57 | 5   | 52 | 9   | 75 |
| 523 | -19 | 94  | -6  | 69 | 2   | 57 | 17  | 63 | 567 | -19 | 94  | -6  | 69 | 2   | 57 | 17  | 63 |
| 524 | 1   | 70  | 4   | 57 | 0   | 61 | -8  | 74 | 568 | 1   | 70  | 4   | 57 | 0   | 61 | -8  | 74 |
| 525 | 0   | 72  | 14  | 39 | -9  | 69 | -5  | 35 | 569 | 0   | 72  | 14  | 39 | -9  | 69 | -5  | 35 |
| 526 | -5  | 74  | 4   | 51 | -11 | 70 | -2  | 27 | 570 | -5  | 74  | 4   | 51 | -11 | 70 | -2  | 27 |
| 527 | 18  | 59  | 13  | 68 | 18  | 55 | 13  | 91 | 571 | 18  | 59  | 13  | 68 | 18  | 55 | 13  | 91 |

Insert a new Table 9-24c as follows:

Table 9-24c – Values of variables m and n for ctxIdx from 572 to 659

| ctxIdx | I and SI slices |    | Value of cabac_init_idc |    |     |     |    |    | ctxIdx | I and SI slices |    | Value of cabac_init_idc |    |     |     |    |    |
|--------|-----------------|----|-------------------------|----|-----|-----|----|----|--------|-----------------|----|-------------------------|----|-----|-----|----|----|
|        |                 |    | 0                       |    | 1   |     | 2  |    |        |                 |    | 0                       |    | 1   |     | 2  |    |
|        | m               | n  | m                       | n  | m   | n   | m  | n  |        | m               | n  | m                       | n  | m   | n   | m  | n  |
| 572    | 24              | 0  | 11                      | 28 | 4   | 45  | 4  | 39 | 616    | 24              | 0  | 11                      | 28 | 4   | 45  | 4  | 39 |
| 573    | 15              | 9  | 2                       | 40 | 10  | 28  | 0  | 42 | 617    | 15              | 9  | 2                       | 40 | 10  | 28  | 0  | 42 |
| 574    | 8               | 25 | 3                       | 44 | 10  | 31  | 7  | 34 | 618    | 8               | 25 | 3                       | 44 | 10  | 31  | 7  | 34 |
| 575    | 13              | 18 | 0                       | 49 | 33  | -11 | 11 | 29 | 619    | 13              | 18 | 0                       | 49 | 33  | -11 | 11 | 29 |
| 576    | 15              | 9  | 0                       | 46 | 52  | -43 | 8  | 31 | 620    | 15              | 9  | 0                       | 46 | 52  | -43 | 8  | 31 |
| 577    | 13              | 19 | 2                       | 44 | 18  | 15  | 6  | 37 | 621    | 13              | 19 | 2                       | 44 | 18  | 15  | 6  | 37 |
| 578    | 10              | 37 | 2                       | 51 | 28  | 0   | 7  | 42 | 622    | 10              | 37 | 2                       | 51 | 28  | 0   | 7  | 42 |
| 579    | 12              | 18 | 0                       | 47 | 35  | -22 | 3  | 40 | 623    | 12              | 18 | 0                       | 47 | 35  | -22 | 3  | 40 |
| 580    | 6               | 29 | 4                       | 39 | 38  | -25 | 8  | 33 | 624    | 6               | 29 | 4                       | 39 | 38  | -25 | 8  | 33 |
| 581    | 20              | 33 | 2                       | 62 | 34  | 0   | 13 | 43 | 625    | 20              | 33 | 2                       | 62 | 34  | 0   | 13 | 43 |
| 582    | 15              | 30 | 6                       | 46 | 39  | -18 | 13 | 36 | 626    | 15              | 30 | 6                       | 46 | 39  | -18 | 13 | 36 |
| 583    | 4               | 45 | 0                       | 54 | 32  | -12 | 4  | 47 | 627    | 4               | 45 | 0                       | 54 | 32  | -12 | 4  | 47 |
| 584    | 1               | 58 | 3                       | 54 | 102 | -94 | 3  | 55 | 628    | 1               | 58 | 3                       | 54 | 102 | -94 | 3  | 55 |

|     |    |     |    |    |    |     |    |     |     |    |     |    |    |    |     |    |     |
|-----|----|-----|----|----|----|-----|----|-----|-----|----|-----|----|----|----|-----|----|-----|
| 585 | 0  | 62  | 2  | 58 | 0  | 0   | 2  | 58  | 629 | 0  | 62  | 2  | 58 | 0  | 0   | 2  | 58  |
| 586 | 7  | 61  | 4  | 63 | 56 | -15 | 6  | 60  | 630 | 7  | 61  | 4  | 63 | 56 | -15 | 6  | 60  |
| 587 | 12 | 38  | 6  | 51 | 33 | -4  | 8  | 44  | 631 | 12 | 38  | 6  | 51 | 33 | -4  | 8  | 44  |
| 588 | 11 | 45  | 6  | 57 | 29 | 10  | 11 | 44  | 632 | 11 | 45  | 6  | 57 | 29 | 10  | 11 | 44  |
| 589 | 15 | 39  | 7  | 53 | 37 | -5  | 14 | 42  | 633 | 15 | 39  | 7  | 53 | 37 | -5  | 14 | 42  |
| 590 | 11 | 42  | 6  | 52 | 51 | -29 | 7  | 48  | 634 | 11 | 42  | 6  | 52 | 51 | -29 | 7  | 48  |
| 591 | 13 | 44  | 6  | 55 | 39 | -9  | 4  | 56  | 635 | 13 | 44  | 6  | 55 | 39 | -9  | 4  | 56  |
| 592 | 16 | 45  | 11 | 45 | 52 | -34 | 4  | 52  | 636 | 16 | 45  | 11 | 45 | 52 | -34 | 4  | 52  |
| 593 | 12 | 41  | 14 | 36 | 69 | -58 | 13 | 37  | 637 | 12 | 41  | 14 | 36 | 69 | -58 | 13 | 37  |
| 594 | 10 | 49  | 8  | 53 | 67 | -63 | 9  | 49  | 638 | 10 | 49  | 8  | 53 | 67 | -63 | 9  | 49  |
| 595 | 30 | 34  | -1 | 82 | 44 | -5  | 19 | 58  | 639 | 30 | 34  | -1 | 82 | 44 | -5  | 19 | 58  |
| 596 | 18 | 42  | 7  | 55 | 32 | 7   | 10 | 48  | 640 | 18 | 42  | 7  | 55 | 32 | 7   | 10 | 48  |
| 597 | 10 | 55  | -3 | 78 | 55 | -29 | 12 | 45  | 641 | 10 | 55  | -3 | 78 | 55 | -29 | 12 | 45  |
| 598 | 17 | 51  | 15 | 46 | 32 | 1   | 0  | 69  | 642 | 17 | 51  | 15 | 46 | 32 | 1   | 0  | 69  |
| 599 | 17 | 46  | 22 | 31 | 0  | 0   | 20 | 33  | 643 | 17 | 46  | 22 | 31 | 0  | 0   | 20 | 33  |
| 600 | 0  | 89  | -1 | 84 | 27 | 36  | 8  | 63  | 644 | 0  | 89  | -1 | 84 | 27 | 36  | 8  | 63  |
| 601 | 26 | -19 | 25 | 7  | 33 | -25 | 35 | -18 | 645 | 26 | -19 | 25 | 7  | 33 | -25 | 35 | -18 |
| 602 | 22 | -17 | 30 | -7 | 34 | -30 | 33 | -25 | 646 | 22 | -17 | 30 | -7 | 34 | -30 | 33 | -25 |
| 603 | 26 | -17 | 28 | 3  | 36 | -28 | 28 | -3  | 647 | 26 | -17 | 28 | 3  | 36 | -28 | 28 | -3  |
| 604 | 30 | -25 | 28 | 4  | 38 | -28 | 24 | 10  | 648 | 30 | -25 | 28 | 4  | 38 | -28 | 24 | 10  |
| 605 | 28 | -20 | 32 | 0  | 38 | -27 | 27 | 0   | 649 | 28 | -20 | 32 | 0  | 38 | -27 | 27 | 0   |
| 606 | 33 | -23 | 34 | -1 | 34 | -18 | 34 | -14 | 650 | 33 | -23 | 34 | -1 | 34 | -18 | 34 | -14 |
| 607 | 37 | -27 | 30 | 6  | 35 | -16 | 52 | -44 | 651 | 37 | -27 | 30 | 6  | 35 | -16 | 52 | -44 |
| 608 | 33 | -23 | 30 | 6  | 34 | -14 | 39 | -24 | 652 | 33 | -23 | 30 | 6  | 34 | -14 | 39 | -24 |
| 609 | 40 | -28 | 32 | 9  | 32 | -8  | 19 | 17  | 653 | 40 | -28 | 32 | 9  | 32 | -8  | 19 | 17  |
| 610 | 38 | -17 | 31 | 19 | 37 | -6  | 31 | 25  | 654 | 38 | -17 | 31 | 19 | 37 | -6  | 31 | 25  |
| 611 | 33 | -11 | 26 | 27 | 35 | 0   | 36 | 29  | 655 | 33 | -11 | 26 | 27 | 35 | 0   | 36 | 29  |
| 612 | 40 | -15 | 26 | 30 | 30 | 10  | 24 | 33  | 656 | 40 | -15 | 26 | 30 | 30 | 10  | 24 | 33  |
| 613 | 41 | -6  | 37 | 20 | 28 | 18  | 34 | 15  | 657 | 41 | -6  | 37 | 20 | 28 | 18  | 34 | 15  |
| 614 | 38 | 1   | 28 | 34 | 26 | 25  | 30 | 20  | 658 | 38 | 1   | 28 | 34 | 26 | 25  | 30 | 20  |
| 615 | 41 | 17  | 17 | 70 | 29 | 41  | 22 | 73  | 659 | 41 | 17  | 17 | 70 | 29 | 41  | 22 | 73  |

Insert a new Table 9-24d as follows:

Table 9-24d– Values of variables m and n for ctxIdx from 660 to 717

| ctxIdx | I<br>slices |     | Value of cabac_init_idc |    |     |    |     |    | ctxIdx | I<br>slices |     | Value of cabac_init_idc |     |    |     |     |     |
|--------|-------------|-----|-------------------------|----|-----|----|-----|----|--------|-------------|-----|-------------------------|-----|----|-----|-----|-----|
|        |             |     | 0                       |    | 1   |    | 2   |    |        |             |     | 0                       |     | 1  |     | 2   |     |
|        | m           | n   | m                       | n  | m   | n  | m   | n  |        | m           | n   | m                       | n   | m  | n   | m   | n   |
| 660    | -17         | 120 | -4                      | 79 | -5  | 85 | -3  | 78 | 689    | 2           | 59  | 2                       | 59  | 2  | 58  | -11 | 68  |
| 661    | -20         | 112 | -7                      | 71 | -6  | 81 | -8  | 74 | 690    | 23          | -13 | 9                       | -2  | 17 | -10 | 9   | -2  |
| 662    | -18         | 114 | -5                      | 69 | -10 | 77 | -9  | 72 | 691    | 26          | -13 | 26                      | -9  | 32 | -13 | 30  | -10 |
| 663    | -11         | 85  | -9                      | 70 | -7  | 81 | -10 | 72 | 692    | 40          | -15 | 33                      | -9  | 42 | -9  | 31  | -4  |
| 664    | -15         | 92  | -8                      | 66 | -17 | 80 | -18 | 75 | 693    | 49          | -14 | 39                      | -7  | 49 | -5  | 33  | -1  |
| 665    | -14         | 89  | -10                     | 68 | -18 | 73 | -12 | 71 | 694    | 44          | 3   | 41                      | -2  | 53 | 0   | 33  | 7   |
| 666    | -26         | 71  | -19                     | 73 | -4  | 74 | -11 | 63 | 695    | 45          | 6   | 45                      | -3  | 64 | 3   | 31  | 12  |
| 667    | -15         | 81  | -12                     | 69 | -10 | 83 | -5  | 70 | 696    | 44          | 34  | 49                      | 9   | 68 | 10  | 37  | 23  |
| 668    | -14         | 80  | -16                     | 70 | -9  | 71 | -17 | 75 | 697    | 33          | 54  | 45                      | 27  | 66 | 27  | 31  | 38  |
| 669    | 0           | 68  | -15                     | 67 | -9  | 67 | -14 | 72 | 698    | 19          | 82  | 36                      | 59  | 47 | 57  | 20  | 64  |
| 670    | -14         | 70  | -20                     | 62 | -1  | 61 | -16 | 67 | 699    | 21          | -10 | 21                      | -13 | 17 | -10 | 9   | -2  |
| 671    | -24         | 56  | -19                     | 70 | -8  | 66 | -8  | 53 | 700    | 24          | -11 | 33                      | -14 | 32 | -13 | 30  | -10 |
| 672    | -23         | 68  | -16                     | 66 | -14 | 66 | -14 | 59 | 701    | 28          | -8  | 39                      | -7  | 42 | -9  | 31  | -4  |
| 673    | -24         | 50  | -22                     | 65 | 0   | 59 | -9  | 52 | 702    | 28          | -1  | 46                      | -2  | 49 | -5  | 33  | -1  |
| 674    | -11         | 74  | -20                     | 63 | 2   | 59 | -11 | 68 | 703    | 29          | 3   | 51                      | 2   | 53 | 0   | 33  | 7   |
| 675    | -14         | 106 | -5                      | 85 | -3  | 81 | -3  | 78 | 704    | 29          | 9   | 60                      | 6   | 64 | 3   | 31  | 12  |
| 676    | -13         | 97  | -6                      | 81 | -3  | 76 | -8  | 74 | 705    | 35          | 20  | 61                      | 17  | 68 | 10  | 37  | 23  |
| 677    | -15         | 90  | -10                     | 77 | -7  | 72 | -9  | 72 | 706    | 29          | 36  | 55                      | 34  | 66 | 27  | 31  | 38  |
| 678    | -12         | 90  | -7                      | 81 | -6  | 78 | -10 | 72 | 707    | 14          | 67  | 42                      | 62  | 47 | 57  | 20  | 64  |
| 679    | -18         | 88  | -17                     | 80 | -12 | 72 | -18 | 75 | 708    | -3          | 75  | -6                      | 66  | -5 | 71  | -9  | 71  |
| 680    | -10         | 73  | -18                     | 73 | -14 | 68 | -12 | 71 | 709    | -1          | 23  | -7                      | 35  | 0  | 24  | -7  | 37  |
| 681    | -9          | 79  | -4                      | 74 | -3  | 70 | -11 | 63 | 710    | 1           | 34  | -7                      | 42  | -1 | 36  | -8  | 44  |
| 682    | -14         | 86  | -10                     | 83 | -6  | 76 | -5  | 70 | 711    | 1           | 43  | -8                      | 45  | -2 | 42  | -11 | 49  |
| 683    | -10         | 73  | -9                      | 71 | -5  | 66 | -17 | 75 | 712    | 0           | 54  | -5                      | 48  | -2 | 52  | -10 | 56  |
| 684    | -10         | 70  | -9                      | 67 | -5  | 62 | -14 | 72 | 713    | -2          | 55  | -12                     | 56  | -9 | 57  | -12 | 59  |
| 685    | -10         | 69  | -1                      | 61 | 0   | 57 | -16 | 67 | 714    | 0           | 61  | -6                      | 60  | -6 | 63  | -8  | 63  |
| 686    | -5          | 66  | -8                      | 66 | -4  | 61 | -8  | 53 | 715    | 1           | 64  | -5                      | 62  | -4 | 65  | -9  | 67  |
| 687    | -9          | 64  | -14                     | 66 | -9  | 60 | -14 | 59 | 716    | 0           | 68  | -8                      | 66  | -4 | 67  | -6  | 68  |
| 688    | -5          | 58  | 0                       | 59 | 1   | 54 | -9  | 52 | 717    | -9          | 92  | -8                      | 76  | -7 | 82  | -10 | 79  |

Insert a new Table 9-24e as follows.

Table 9-24e— Values of variables m and n for ctxIdx from 718 to 775

| ctxIdx | I<br>slices |     | Value of cabac_init_idc |    |     |    |     |    | ctxIdx | I<br>slices |     | Value of cabac_init_idc |     |    |     |     |     |
|--------|-------------|-----|-------------------------|----|-----|----|-----|----|--------|-------------|-----|-------------------------|-----|----|-----|-----|-----|
|        |             |     | 0                       |    | 1   |    | 2   |    |        |             |     | 0                       |     | 1  |     | 2   |     |
|        | m           | n   | m                       | n  | m   | n  | m   | n  |        | m           | n   | m                       | n   | m  | n   | m   | n   |
| 718    | -17         | 120 | -4                      | 79 | -5  | 85 | -3  | 78 | 747    | 2           | 59  | 2                       | 59  | 2  | 58  | -11 | 68  |
| 719    | -20         | 112 | -7                      | 71 | -6  | 81 | -8  | 74 | 748    | 23          | -13 | 9                       | -2  | 17 | -10 | 9   | -2  |
| 720    | -18         | 114 | -5                      | 69 | -10 | 77 | -9  | 72 | 749    | 26          | -13 | 26                      | -9  | 32 | -13 | 30  | -10 |
| 721    | -11         | 85  | -9                      | 70 | -7  | 81 | -10 | 72 | 750    | 40          | -15 | 33                      | -9  | 42 | -9  | 31  | -4  |
| 722    | -15         | 92  | -8                      | 66 | -17 | 80 | -18 | 75 | 751    | 49          | -14 | 39                      | -7  | 49 | -5  | 33  | -1  |
| 723    | -14         | 89  | -10                     | 68 | -18 | 73 | -12 | 71 | 752    | 44          | 3   | 41                      | -2  | 53 | 0   | 33  | 7   |
| 724    | -26         | 71  | -19                     | 73 | -4  | 74 | -11 | 63 | 753    | 45          | 6   | 45                      | 3   | 64 | 3   | 31  | 12  |
| 725    | -15         | 81  | -12                     | 69 | -10 | 83 | -5  | 70 | 754    | 44          | 34  | 49                      | 9   | 68 | 10  | 37  | 23  |
| 726    | -14         | 80  | -16                     | 70 | -9  | 71 | -17 | 75 | 755    | 33          | 54  | 45                      | 27  | 66 | 27  | 31  | 38  |
| 727    | 0           | 68  | -15                     | 67 | -9  | 67 | -14 | 72 | 756    | 19          | 82  | 36                      | 59  | 47 | 57  | 20  | 64  |
| 728    | -14         | 70  | -20                     | 62 | -1  | 61 | -16 | 67 | 757    | 21          | -10 | 21                      | -13 | 17 | -10 | 9   | -2  |
| 729    | -24         | 56  | -19                     | 70 | -8  | 66 | -8  | 53 | 758    | 24          | -11 | 33                      | -14 | 32 | -13 | 30  | -10 |
| 730    | -23         | 68  | -16                     | 66 | -14 | 66 | -14 | 59 | 759    | 28          | -8  | 39                      | -7  | 42 | -9  | 31  | -4  |
| 731    | -24         | 50  | -22                     | 65 | 0   | 59 | -9  | 52 | 760    | 28          | -1  | 46                      | -2  | 49 | -5  | 33  | -1  |
| 732    | -11         | 74  | -20                     | 63 | 2   | 59 | -11 | 68 | 761    | 29          | 3   | 51                      | 2   | 53 | 0   | 33  | 7   |
| 733    | -14         | 106 | -5                      | 85 | -3  | 81 | -3  | 78 | 762    | 29          | 9   | 60                      | 6   | 64 | 3   | 31  | 12  |
| 734    | -13         | 97  | -6                      | 81 | -3  | 76 | -8  | 74 | 763    | 35          | 20  | 61                      | 17  | 68 | 10  | 37  | 23  |
| 735    | -15         | 90  | -10                     | 77 | -7  | 72 | -9  | 72 | 764    | 29          | 36  | 55                      | 34  | 66 | 27  | 31  | 38  |
| 736    | -12         | 90  | -7                      | 81 | -6  | 78 | -10 | 72 | 765    | 14          | 67  | 42                      | 62  | 47 | 57  | 20  | 64  |
| 737    | -18         | 88  | -17                     | 80 | -12 | 72 | -18 | 75 | 766    | -3          | 75  | -6                      | 66  | -5 | 71  | -9  | 71  |
| 738    | -10         | 73  | -18                     | 73 | -14 | 68 | -12 | 71 | 767    | -1          | 23  | -7                      | 35  | 0  | 24  | -7  | 37  |
| 739    | -9          | 79  | -4                      | 74 | -3  | 70 | -11 | 63 | 768    | 1           | 34  | -7                      | 42  | -1 | 36  | -8  | 44  |
| 740    | -14         | 86  | -10                     | 83 | -6  | 76 | -5  | 70 | 769    | 1           | 43  | -8                      | 45  | -2 | 42  | -11 | 49  |
| 741    | -10         | 73  | -9                      | 71 | -5  | 66 | -17 | 75 | 770    | 0           | 54  | -5                      | 48  | -2 | 52  | -10 | 56  |
| 742    | -10         | 70  | -9                      | 67 | -5  | 62 | -14 | 72 | 771    | -2          | 55  | -12                     | 56  | -9 | 57  | -12 | 59  |
| 743    | -10         | 69  | -1                      | 61 | 0   | 57 | -16 | 67 | 772    | 0           | 61  | -6                      | 60  | -6 | 63  | -8  | 63  |
| 744    | -5          | 66  | -8                      | 66 | -4  | 61 | -8  | 53 | 773    | 1           | 64  | -5                      | 62  | -4 | 65  | -9  | 67  |
| 745    | -9          | 64  | -14                     | 66 | -9  | 60 | -14 | 59 | 774    | 0           | 68  | -8                      | 66  | -4 | 67  | -6  | 68  |
| 746    | -5          | 58  | 0                       | 59 | 1   | 54 | -9  | 52 | 775    | -9          | 92  | -8                      | 76  | -7 | 82  | -10 | 79  |

Insert a new Table 9-24f as follows:

Table 9-24f – Values of variables m and n for ctxIdx from 776 to 863

| ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |     |     |     |     | ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |     |     |     |     |
|--------|-----------------|----|-------------------------|-----|-----|-----|-----|-----|--------|-----------------|----|-------------------------|-----|-----|-----|-----|-----|
|        |                 |    | 0                       |     | 1   |     | 2   |     |        |                 |    | 0                       |     | 1   |     | 2   |     |
|        | m               | n  | m                       | n   | m   | n   | m   | n   |        | m               | n  | m                       | n   | m   | n   |     |     |
| 776    | -6              | 93 | -13                     | 106 | -21 | 126 | -22 | 127 | 820    | -6              | 93 | -13                     | 106 | -21 | 126 | -22 | 127 |
| 777    | -6              | 84 | -16                     | 106 | -23 | 124 | -25 | 127 | 821    | -6              | 84 | -16                     | 106 | -23 | 124 | -25 | 127 |
| 778    | -8              | 79 | -10                     | 87  | -20 | 110 | -25 | 120 | 822    | -8              | 79 | -10                     | 87  | -20 | 110 | -25 | 120 |
| 779    | 0               | 66 | -21                     | 114 | -26 | 126 | -27 | 127 | 823    | 0               | 66 | -21                     | 114 | -26 | 126 | -27 | 127 |
| 780    | -1              | 71 | -18                     | 110 | -25 | 124 | -19 | 114 | 824    | -1              | 71 | -18                     | 110 | -25 | 124 | -19 | 114 |
| 781    | 0               | 62 | -14                     | 98  | -17 | 105 | -23 | 117 | 825    | 0               | 62 | -14                     | 98  | -17 | 105 | -23 | 117 |
| 782    | -2              | 60 | -22                     | 110 | -27 | 121 | -25 | 118 | 826    | -2              | 60 | -22                     | 110 | -27 | 121 | -25 | 118 |
| 783    | -2              | 59 | -21                     | 106 | -27 | 117 | -26 | 117 | 827    | -2              | 59 | -21                     | 106 | -27 | 117 | -26 | 117 |
| 784    | -5              | 75 | -18                     | 103 | -17 | 102 | -24 | 113 | 828    | -5              | 75 | -18                     | 103 | -17 | 102 | -24 | 113 |
| 785    | -3              | 62 | -21                     | 107 | -26 | 117 | -28 | 118 | 829    | -3              | 62 | -21                     | 107 | -26 | 117 | -28 | 118 |
| 786    | -4              | 58 | -23                     | 108 | -27 | 116 | -31 | 120 | 830    | -4              | 58 | -23                     | 108 | -27 | 116 | -31 | 120 |
| 787    | -9              | 66 | -26                     | 112 | -33 | 122 | -37 | 124 | 831    | -9              | 66 | -26                     | 112 | -33 | 122 | -37 | 124 |
| 788    | -1              | 79 | -10                     | 96  | -10 | 95  | -10 | 94  | 832    | -1              | 79 | -10                     | 96  | -10 | 95  | -10 | 94  |
| 789    | 0               | 71 | -12                     | 95  | -14 | 100 | -15 | 102 | 833    | 0               | 71 | -12                     | 95  | -14 | 100 | -15 | 102 |
| 790    | 3               | 68 | -5                      | 91  | -8  | 95  | -10 | 99  | 834    | 3               | 68 | -5                      | 91  | -8  | 95  | -10 | 99  |
| 791    | 10              | 44 | -9                      | 93  | -17 | 111 | -13 | 106 | 835    | 10              | 44 | -9                      | 93  | -17 | 111 | -13 | 106 |
| 792    | -7              | 62 | -22                     | 94  | -28 | 114 | -50 | 127 | 836    | -7              | 62 | -22                     | 94  | -28 | 114 | -50 | 127 |
| 793    | 15              | 36 | -5                      | 86  | -6  | 89  | -5  | 92  | 837    | 15              | 36 | -5                      | 86  | -6  | 89  | -5  | 92  |
| 794    | 14              | 40 | 9                       | 67  | -2  | 80  | 17  | 57  | 838    | 14              | 40 | 9                       | 67  | -2  | 80  | 17  | 57  |
| 795    | 16              | 27 | -4                      | 80  | -4  | 82  | -5  | 86  | 839    | 16              | 27 | -4                      | 80  | -4  | 82  | -5  | 86  |
| 796    | 12              | 29 | -10                     | 85  | -9  | 85  | -13 | 94  | 840    | 12              | 29 | -10                     | 85  | -9  | 85  | -13 | 94  |
| 797    | 1               | 44 | -1                      | 70  | -8  | 81  | -12 | 91  | 841    | 1               | 44 | -1                      | 70  | -8  | 81  | -12 | 91  |
| 798    | 20              | 36 | 7                       | 60  | -1  | 72  | -2  | 77  | 842    | 20              | 36 | 7                       | 60  | -1  | 72  | -2  | 77  |
| 799    | 18              | 32 | 9                       | 58  | 5   | 64  | 0   | 71  | 843    | 18              | 32 | 9                       | 58  | 5   | 64  | 0   | 71  |
| 800    | 5               | 42 | 5                       | 61  | 1   | 67  | -1  | 73  | 844    | 5               | 42 | 5                       | 61  | 1   | 67  | -1  | 73  |
| 801    | 1               | 48 | 12                      | 50  | 9   | 56  | 4   | 64  | 845    | 1               | 48 | 12                      | 50  | 9   | 56  | 4   | 64  |
| 802    | 10              | 62 | 15                      | 50  | 0   | 69  | -7  | 81  | 846    | 10              | 62 | 15                      | 50  | 0   | 69  | -7  | 81  |
| 803    | 17              | 46 | 18                      | 49  | 1   | 69  | 5   | 64  | 847    | 17              | 46 | 18                      | 49  | 1   | 69  | 5   | 64  |
| 804    | 9               | 64 | 17                      | 54  | 7   | 69  | 15  | 57  | 848    | 9               | 64 | 17                      | 54  | 7   | 69  | 15  | 57  |

|     |     |     |    |    |     |    |     |    |     |     |     |    |    |     |    |     |    |
|-----|-----|-----|----|----|-----|----|-----|----|-----|-----|-----|----|----|-----|----|-----|----|
| 805 | -12 | 104 | 10 | 41 | -7  | 69 | 1   | 67 | 849 | -12 | 104 | 10 | 41 | -7  | 69 | 1   | 67 |
| 806 | -11 | 97  | 7  | 46 | -6  | 67 | 0   | 68 | 850 | -11 | 97  | 7  | 46 | -6  | 67 | 0   | 68 |
| 807 | -16 | 96  | -1 | 51 | -16 | 77 | -10 | 67 | 851 | -16 | 96  | -1 | 51 | -16 | 77 | -10 | 67 |
| 808 | -7  | 88  | 7  | 49 | -2  | 64 | 1   | 68 | 852 | -7  | 88  | 7  | 49 | -2  | 64 | 1   | 68 |
| 809 | -8  | 85  | 8  | 52 | 2   | 61 | 0   | 77 | 853 | -8  | 85  | 8  | 52 | 2   | 61 | 0   | 77 |
| 810 | -7  | 85  | 9  | 41 | -6  | 67 | 2   | 64 | 854 | -7  | 85  | 9  | 41 | -6  | 67 | 2   | 64 |
| 811 | -9  | 85  | 6  | 47 | -3  | 64 | 0   | 68 | 855 | -9  | 85  | 6  | 47 | -3  | 64 | 0   | 68 |
| 812 | -13 | 88  | 2  | 55 | 2   | 57 | -5  | 78 | 856 | -13 | 88  | 2  | 55 | 2   | 57 | -5  | 78 |
| 813 | 4   | 66  | 13 | 41 | -3  | 65 | 7   | 55 | 857 | 4   | 66  | 13 | 41 | -3  | 65 | 7   | 55 |
| 814 | -3  | 77  | 10 | 44 | -3  | 66 | 5   | 59 | 858 | -3  | 77  | 10 | 44 | -3  | 66 | 5   | 59 |
| 815 | -3  | 76  | 6  | 50 | 0   | 62 | 2   | 65 | 859 | -3  | 76  | 6  | 50 | 0   | 62 | 2   | 65 |
| 816 | -6  | 76  | 5  | 53 | 9   | 51 | 14  | 54 | 860 | -6  | 76  | 5  | 53 | 9   | 51 | 14  | 54 |
| 817 | 10  | 58  | 13 | 49 | -1  | 66 | 15  | 44 | 861 | 10  | 58  | 13 | 49 | -1  | 66 | 15  | 44 |
| 818 | -1  | 76  | 4  | 63 | -2  | 71 | 5   | 60 | 862 | -1  | 76  | 4  | 63 | -2  | 71 | 5   | 60 |
| 819 | -1  | 83  | 6  | 64 | -2  | 75 | 2   | 70 | 863 | -1  | 83  | 6  | 64 | -2  | 75 | 2   | 70 |

Insert a new Table 9-24g as follows:

Table 9-24g – Values of variables *m* and *n* for *ctxIdx* from 864 to 951

| ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |    |     |    |     | ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |    |     |    |     |
|--------|-----------------|----|-------------------------|-----|----|-----|----|-----|--------|-----------------|----|-------------------------|-----|----|-----|----|-----|
|        |                 |    | 0                       |     | 1  |     | 2  |     |        |                 |    | 0                       |     | 1  |     | 2  |     |
|        | m               | n  | m                       | n   | m  | n   | m  | n   |        | m               | n  | m                       | n   | m  | n   | m  | n   |
| 864    | 15              | 6  | 14                      | 11  | 19 | -6  | 17 | -13 | 908    | 15              | 6  | 14                      | 11  | 19 | -6  | 17 | -13 |
| 865    | 6               | 19 | 11                      | 14  | 18 | -6  | 16 | -9  | 909    | 6               | 19 | 11                      | 14  | 18 | -6  | 16 | -9  |
| 866    | 7               | 16 | 9                       | 11  | 14 | 0   | 17 | -12 | 910    | 7               | 16 | 9                       | 11  | 14 | 0   | 17 | -12 |
| 867    | 12              | 14 | 18                      | 11  | 26 | -12 | 27 | -21 | 911    | 12              | 14 | 18                      | 11  | 26 | -12 | 27 | -21 |
| 868    | 18              | 13 | 21                      | 9   | 31 | -16 | 37 | -30 | 912    | 18              | 13 | 21                      | 9   | 31 | -16 | 37 | -30 |
| 869    | 13              | 11 | 23                      | -2  | 33 | -25 | 41 | -40 | 913    | 13              | 11 | 23                      | -2  | 33 | -25 | 41 | -40 |
| 870    | 13              | 15 | 32                      | -15 | 33 | -22 | 42 | -41 | 914    | 13              | 15 | 32                      | -15 | 33 | -22 | 42 | -41 |
| 871    | 15              | 16 | 32                      | -15 | 37 | -28 | 48 | -47 | 915    | 15              | 16 | 32                      | -15 | 37 | -28 | 48 | -47 |
| 872    | 12              | 23 | 34                      | -21 | 39 | -30 | 39 | -32 | 916    | 12              | 23 | 34                      | -21 | 39 | -30 | 39 | -32 |
| 873    | 13              | 23 | 39                      | -23 | 42 | -30 | 46 | -40 | 917    | 13              | 23 | 39                      | -23 | 42 | -30 | 46 | -40 |
| 874    | 15              | 20 | 42                      | -33 | 47 | -42 | 52 | -51 | 918    | 15              | 20 | 42                      | -33 | 47 | -42 | 52 | -51 |
| 875    | 14              | 26 | 41                      | -31 | 45 | -36 | 46 | -41 | 919    | 14              | 26 | 41                      | -31 | 45 | -36 | 46 | -41 |
| 876    | 14              | 44 | 46                      | -28 | 49 | -34 | 52 | -39 | 920    | 14              | 44 | 46                      | -28 | 49 | -34 | 52 | -39 |

|     |     |     |     |     |    |     |    |     |     |     |     |     |     |    |     |    |     |
|-----|-----|-----|-----|-----|----|-----|----|-----|-----|-----|-----|-----|-----|----|-----|----|-----|
| 877 | 17  | 40  | 38  | -12 | 41 | -17 | 43 | -19 | 921 | 17  | 40  | 38  | -12 | 41 | -17 | 43 | -19 |
| 878 | 17  | 47  | 21  | 29  | 32 | 9   | 32 | 11  | 922 | 17  | 47  | 21  | 29  | 32 | 9   | 32 | 11  |
| 879 | 24  | 17  | 45  | -24 | 69 | -71 | 61 | -55 | 923 | 24  | 17  | 45  | -24 | 69 | -71 | 61 | -55 |
| 880 | 21  | 21  | 53  | -45 | 63 | -63 | 56 | -46 | 924 | 21  | 21  | 53  | -45 | 63 | -63 | 56 | -46 |
| 881 | 25  | 22  | 48  | -26 | 66 | -64 | 62 | -50 | 925 | 25  | 22  | 48  | -26 | 66 | -64 | 62 | -50 |
| 882 | 31  | 27  | 65  | -43 | 77 | -74 | 81 | -67 | 926 | 31  | 27  | 65  | -43 | 77 | -74 | 81 | -67 |
| 883 | 22  | 29  | 43  | -19 | 54 | -39 | 45 | -20 | 927 | 22  | 29  | 43  | -19 | 54 | -39 | 45 | -20 |
| 884 | 19  | 35  | 39  | -10 | 52 | -35 | 35 | -2  | 928 | 19  | 35  | 39  | -10 | 52 | -35 | 35 | -2  |
| 885 | 14  | 50  | 30  | 9   | 41 | -10 | 28 | 15  | 929 | 14  | 50  | 30  | 9   | 41 | -10 | 28 | 15  |
| 886 | 10  | 57  | 18  | 26  | 36 | 0   | 34 | 1   | 930 | 10  | 57  | 18  | 26  | 36 | 0   | 34 | 1   |
| 887 | 7   | 63  | 20  | 27  | 40 | -1  | 39 | 1   | 931 | 7   | 63  | 20  | 27  | 40 | -1  | 39 | 1   |
| 888 | -2  | 77  | 0   | 57  | 30 | 14  | 30 | 17  | 932 | -2  | 77  | 0   | 57  | 30 | 14  | 30 | 17  |
| 889 | -4  | 82  | -14 | 82  | 28 | 26  | 20 | 38  | 933 | -4  | 82  | -14 | 82  | 28 | 26  | 20 | 38  |
| 890 | -3  | 94  | -5  | 75  | 23 | 37  | 18 | 45  | 934 | -3  | 94  | -5  | 75  | 23 | 37  | 18 | 45  |
| 891 | 9   | 69  | -19 | 97  | 12 | 55  | 15 | 54  | 935 | 9   | 69  | -19 | 97  | 12 | 55  | 15 | 54  |
| 892 | -12 | 109 | -35 | 125 | 11 | 65  | 0  | 79  | 936 | -12 | 109 | -35 | 125 | 11 | 65  | 0  | 79  |
| 893 | 36  | -35 | 27  | 0   | 37 | -33 | 36 | -16 | 937 | 36  | -35 | 27  | 0   | 37 | -33 | 36 | -16 |
| 894 | 36  | -34 | 28  | 0   | 39 | -36 | 37 | -14 | 938 | 36  | -34 | 28  | 0   | 39 | -36 | 37 | -14 |
| 895 | 32  | -26 | 31  | -4  | 40 | -37 | 37 | -17 | 939 | 32  | -26 | 31  | -4  | 40 | -37 | 37 | -17 |
| 896 | 37  | -30 | 27  | 6   | 38 | -30 | 32 | 1   | 940 | 37  | -30 | 27  | 6   | 38 | -30 | 32 | 1   |
| 897 | 44  | -32 | 34  | 8   | 46 | -33 | 34 | 15  | 941 | 44  | -32 | 34  | 8   | 46 | -33 | 34 | 15  |
| 898 | 34  | -18 | 30  | 10  | 42 | -30 | 29 | 15  | 942 | 34  | -18 | 30  | 10  | 42 | -30 | 29 | 15  |
| 899 | 34  | -15 | 24  | 22  | 40 | -24 | 24 | 25  | 943 | 34  | -15 | 24  | 22  | 40 | -24 | 24 | 25  |
| 900 | 40  | -15 | 33  | 19  | 49 | -29 | 34 | 22  | 944 | 40  | -15 | 33  | 19  | 49 | -29 | 34 | 22  |
| 901 | 33  | -7  | 22  | 32  | 38 | -12 | 31 | 16  | 945 | 33  | -7  | 22  | 32  | 38 | -12 | 31 | 16  |
| 902 | 35  | -5  | 26  | 31  | 40 | -10 | 35 | 18  | 946 | 35  | -5  | 26  | 31  | 40 | -10 | 35 | 18  |
| 903 | 33  | 0   | 21  | 41  | 38 | -3  | 31 | 28  | 947 | 33  | 0   | 21  | 41  | 38 | -3  | 31 | 28  |
| 904 | 38  | 2   | 26  | 44  | 46 | -5  | 33 | 41  | 948 | 38  | 2   | 26  | 44  | 46 | -5  | 33 | 41  |
| 905 | 33  | 13  | 23  | 47  | 31 | 20  | 36 | 28  | 949 | 33  | 13  | 23  | 47  | 31 | 20  | 36 | 28  |
| 906 | 23  | 35  | 16  | 65  | 29 | 30  | 27 | 47  | 950 | 23  | 35  | 16  | 65  | 29 | 30  | 27 | 47  |
| 907 | 13  | 58  | 14  | 71  | 25 | 44  | 21 | 62  | 951 | 13  | 58  | 14  | 71  | 25 | 44  | 21 | 62  |

Insert a new Table 9-24h as follows:

Table 9-24h – Values of variables m and n for ctxIdx from 952 to 1011

| ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |     |     |     |     | ctxIdx | I and SI slices |    | Value of cabac_init_idc |     |     |     |     |     |
|--------|-----------------|----|-------------------------|-----|-----|-----|-----|-----|--------|-----------------|----|-------------------------|-----|-----|-----|-----|-----|
|        |                 |    | 0                       |     | 1   |     | 2   |     |        |                 |    | 0                       |     | 1   |     | 2   |     |
|        | m               | n  | m                       | n   | m   | n   | m   | n   |        | m               | n  | m                       | n   | m   | n   | m   | n   |
| 952    | -3              | 71 | -6                      | 76  | -23 | 112 | -24 | 115 | 982    | -3              | 71 | -6                      | 76  | -23 | 112 | -24 | 115 |
| 953    | -6              | 42 | -2                      | 44  | -15 | 71  | -22 | 82  | 983    | -6              | 42 | -2                      | 44  | -15 | 71  | -22 | 82  |
| 954    | -5              | 50 | 0                       | 45  | -7  | 61  | -9  | 62  | 984    | -5              | 50 | 0                       | 45  | -7  | 61  | -9  | 62  |
| 955    | -3              | 54 | 0                       | 52  | 0   | 53  | 0   | 53  | 985    | -3              | 54 | 0                       | 52  | 0   | 53  | 0   | 53  |
| 956    | -2              | 62 | -3                      | 64  | -5  | 66  | 0   | 59  | 986    | -2              | 62 | -3                      | 64  | -5  | 66  | 0   | 59  |
| 957    | 0               | 58 | -2                      | 59  | -11 | 77  | -14 | 85  | 987    | 0               | 58 | -2                      | 59  | -11 | 77  | -14 | 85  |
| 958    | 1               | 63 | -4                      | 70  | -9  | 80  | -13 | 89  | 988    | 1               | 63 | -4                      | 70  | -9  | 80  | -13 | 89  |
| 959    | -2              | 72 | -4                      | 75  | -9  | 84  | -13 | 94  | 989    | -2              | 72 | -4                      | 75  | -9  | 84  | -13 | 94  |
| 960    | -1              | 74 | -8                      | 82  | -10 | 87  | -11 | 92  | 990    | -1              | 74 | -8                      | 82  | -10 | 87  | -11 | 92  |
| 961    | -9              | 91 | -17                     | 102 | -34 | 127 | -29 | 127 | 991    | -9              | 91 | -17                     | 102 | -34 | 127 | -29 | 127 |
| 962    | -5              | 67 | -9                      | 77  | -21 | 101 | -21 | 100 | 992    | -5              | 67 | -9                      | 77  | -21 | 101 | -21 | 100 |
| 963    | -5              | 27 | 3                       | 24  | -3  | 39  | -14 | 57  | 993    | -5              | 27 | 3                       | 24  | -3  | 39  | -14 | 57  |
| 964    | -3              | 39 | 0                       | 42  | -5  | 53  | -12 | 67  | 994    | -3              | 39 | 0                       | 42  | -5  | 53  | -12 | 67  |
| 965    | -2              | 44 | 0                       | 48  | -7  | 61  | -11 | 71  | 995    | -2              | 44 | 0                       | 48  | -7  | 61  | -11 | 71  |
| 966    | 0               | 46 | 0                       | 55  | -11 | 75  | -10 | 77  | 996    | 0               | 46 | 0                       | 55  | -11 | 75  | -10 | 77  |
| 967    | -16             | 64 | -6                      | 59  | -15 | 77  | -21 | 85  | 997    | -16             | 64 | -6                      | 59  | -15 | 77  | -21 | 85  |
| 968    | -8              | 68 | -7                      | 71  | -17 | 91  | -16 | 88  | 998    | -8              | 68 | -7                      | 71  | -17 | 91  | -16 | 88  |
| 969    | -10             | 78 | -12                     | 83  | -25 | 107 | -23 | 104 | 999    | -10             | 78 | -12                     | 83  | -25 | 107 | -23 | 104 |
| 970    | -6              | 77 | -11                     | 87  | -25 | 111 | -15 | 98  | 1000   | -6              | 77 | -11                     | 87  | -25 | 111 | -15 | 98  |
| 971    | -10             | 86 | -30                     | 119 | -28 | 122 | -37 | 127 | 1001   | -10             | 86 | -30                     | 119 | -28 | 122 | -37 | 127 |
| 972    | -12             | 92 | 1                       | 58  | -11 | 76  | -10 | 82  | 1002   | -12             | 92 | 1                       | 58  | -11 | 76  | -10 | 82  |
| 973    | -15             | 55 | -3                      | 29  | -10 | 44  | -8  | 48  | 1003   | -15             | 55 | -3                      | 29  | -10 | 44  | -8  | 48  |
| 974    | -10             | 60 | -1                      | 36  | -10 | 52  | -8  | 61  | 1004   | -10             | 60 | -1                      | 36  | -10 | 52  | -8  | 61  |
| 975    | -6              | 62 | 1                       | 38  | -10 | 57  | -8  | 66  | 1005   | -6              | 62 | 1                       | 38  | -10 | 57  | -8  | 66  |
| 976    | -4              | 65 | 2                       | 43  | -9  | 58  | -7  | 70  | 1006   | -4              | 65 | 2                       | 43  | -9  | 58  | -7  | 70  |

|     |     |     |     |    |     |    |     |     |      |     |     |     |    |     |    |     |     |
|-----|-----|-----|-----|----|-----|----|-----|-----|------|-----|-----|-----|----|-----|----|-----|-----|
| 977 | -12 | 73  | -6  | 55 | -16 | 72 | -14 | 75  | 1007 | -12 | 73  | -6  | 55 | -16 | 72 | -14 | 75  |
| 978 | -8  | 76  | 0   | 58 | -7  | 69 | -10 | 79  | 1008 | -8  | 76  | 0   | 58 | -7  | 69 | -10 | 79  |
| 979 | -7  | 80  | 0   | 64 | -4  | 69 | -9  | 83  | 1009 | -7  | 80  | 0   | 64 | -4  | 69 | -9  | 83  |
| 980 | -9  | 88  | -3  | 74 | -5  | 74 | -12 | 92  | 1010 | -9  | 88  | -3  | 74 | -5  | 74 | -12 | 92  |
| 981 | -17 | 110 | -10 | 90 | -9  | 86 | -18 | 108 | 1011 | -17 | 110 | -10 | 90 | -9  | 86 | -18 | 108 |

Insert a new Table 9-24i as follows:

Table 9-24i – Values of variables m and n for ctxIdx from 1012 to 1023

| ctxIdx | I and SI slices |     | Value of cabac_init_idc |     |     |     |     |     | ctxIdx | I and SI slices |     | Value of cabac_init_idc |     |     |     |     |     |
|--------|-----------------|-----|-------------------------|-----|-----|-----|-----|-----|--------|-----------------|-----|-------------------------|-----|-----|-----|-----|-----|
|        |                 |     | 0                       |     | 1   |     | 2   |     |        |                 |     | 0                       |     | 1   |     | 2   |     |
|        | m               | n   | m                       | n   | m   | n   | m   | n   |        | m               | n   | m                       | n   | m   | N   | m   | n   |
| 1012   | -3              | 70  | -3                      | 74  | -2  | 73  | -5  | 79  | 1018   | -10             | 90  | -8                      | 87  | -9  | 91  | -11 | 91  |
| 1013   | -8              | 93  | -9                      | 92  | -12 | 104 | -11 | 104 | 1019   | -30             | 127 | -23                     | 126 | -31 | 127 | -30 | 127 |
| 1014   | -10             | 90  | -8                      | 87  | -9  | 91  | -11 | 91  | 1020   | -3              | 70  | -3                      | 74  | -2  | 73  | -5  | 79  |
| 1015   | -30             | 127 | -23                     | 126 | -31 | 127 | -30 | 127 | 1021   | -8              | 93  | -9                      | 92  | -12 | 104 | -11 | 104 |
| 1016   | -3              | 70  | -3                      | 74  | -2  | 73  | -5  | 79  | 1022   | -10             | 90  | -8                      | 87  | -9  | 91  | -11 | 91  |
| 1017   | -8              | 93  | -9                      | 92  | -12 | 104 | -11 | 104 | 1023   | -30             | 127 | -23                     | 126 | -31 | 127 | -30 | 127 |

In subclause 9.3.2 “Binarization process”, make the following changes.

Replace the paragraph starting with “The possible values of the context index ctxIdx” with the following.

The possible values of the context index ctxIdx are in the range 0 to 1023, inclusive. The value assigned to ctxIdxOffset specifies the lower value of the range of ctxIdx assigned to the corresponding binarization or binarization part of a syntax element.

Replace Table 9-25 with the following:

**Table 9-25 – Syntax elements and associated types of binarization, maxBinIdxCtx, and ctxIdxOffset**

| Syntax element                                                           | Type of binarization                                                 | maxBinIdxCtx            | ctxIdxOffset                                   |
|--------------------------------------------------------------------------|----------------------------------------------------------------------|-------------------------|------------------------------------------------|
| mb_type<br>(SI slices only)                                              | prefix and suffix<br>as specified in subclause 9.3.2.5               | prefix: 0<br>suffix: 6  | prefix: 0<br>suffix: 3                         |
| mb_type (I slices only)                                                  | as specified in subclause 9.3.2.5                                    | 6                       | 3                                              |
| mb_skip_flag<br>(P, SP slices only)                                      | FL, cMax=1                                                           | 0                       | 11                                             |
| mb_type (P, SP slices only)                                              | prefix and suffix<br>as specified in subclause 9.3.2.5               | prefix: 2<br>suffix: 5  | prefix: 14<br>suffix: 17                       |
| sub_mb_type<br>(P, SP slices only)                                       | as specified in subclause 9.3.2.5                                    | 2                       | 21                                             |
| mb_skip_flag<br>(B slices only)                                          | FL, cMax=1                                                           | 0                       | 24                                             |
| mb_type (B slices only)                                                  | prefix and suffix<br>as specified in subclause 9.3.2.5               | prefix: 3<br>suffix: 5  | prefix: 27<br>suffix: 32                       |
| sub_mb_type (B slices only)                                              | as specified in subclause 9.3.2.5                                    | 3                       | 36                                             |
| mvd_l0[ ][ 0 ], mvd_l1[ ][ 0 ]                                           | prefix and suffix as given by UEG3<br>with signedValFlag=1, uCoff=9  | prefix: 4<br>suffix: na | prefix: 40<br>suffix: na (uses DecodeBypass)   |
| mvd_l0[ ][ 1 ], mvd_l1[ ][ 1 ]                                           |                                                                      | prefix: 4<br>suffix: na | prefix: 47<br>suffix: na (uses DecodeBypass)   |
| ref_idx_l0, ref_idx_l1                                                   | U                                                                    | 2                       | 54                                             |
| mb_qp_delta                                                              | as specified in subclause 9.3.2.7                                    | 2                       | 60                                             |
| intra_chroma_pred_mode                                                   | TU, cMax=3                                                           | 1                       | 64                                             |
| prev_intra4x4_pred_mode_flag,<br>prev_intra8x8_pred_mode_flag            | FL, cMax=1                                                           | 0                       | 68                                             |
| rem_intra4x4_pred_mode,<br>rem_intra8x8_pred_mode                        | FL, cMax=7                                                           | 0                       | 69                                             |
| mb_field_decoding_flag                                                   | FL, cMax=1                                                           | 0                       | 70                                             |
| coded_block_pattern                                                      | prefix and suffix<br>as specified in subclause 9.3.2.6               | prefix: 3<br>suffix: 1  | prefix: 73<br>suffix: 77                       |
| coded_block_flag<br>(ctxBlockCat < 5)                                    | FL, cMax=1                                                           | 0                       | 85                                             |
| significant_coeff_flag<br>(frame coded blocks with ctxBlockCat < 5)      | FL, cMax=1                                                           | 0                       | 105                                            |
| last_significant_coeff_flag<br>(frame coded blocks with ctxBlockCat < 5) | FL, cMax=1                                                           | 0                       | 166                                            |
| coeff_abs_level_minus1<br>(blocks with ctxBlockCat < 5)                  | prefix and suffix as given by UEG0<br>with signedValFlag=0, uCoff=14 | prefix: 1<br>suffix: na | prefix: 227<br>suffix: na, (uses DecodeBypass) |
| coeff_sign_flag                                                          | FL, cMax=1                                                           | 0                       | na, (uses DecodeBypass)                        |
| end_of_slice_flag                                                        | FL, cMax=1                                                           | 0                       | 276                                            |

|                                                                               |                                                                      |                         |                                                |
|-------------------------------------------------------------------------------|----------------------------------------------------------------------|-------------------------|------------------------------------------------|
| significant_coeff_flag<br>(field coded blocks with ctxBlockCat < 5)           | FL, cMax=1                                                           | 0                       | 277                                            |
| last_significant_coeff_flag<br>(field coded blocks with ctxBlockCat < 5)      | FL, cMax=1                                                           | 0                       | 338                                            |
| transform_size_8x8_flag                                                       | FL, cMax=1                                                           | 0                       | 399                                            |
| significant_coeff_flag<br>(frame coded blocks with ctxBlockCat == 5)          | FL, cMax=1                                                           | 0                       | 402                                            |
| last_significant_coeff_flag<br>(frame coded blocks with ctxBlockCat == 5)     | FL, cMax=1                                                           | 0                       | 417                                            |
| coeff_abs_level_minus1<br>(blocks with ctxBlockCat == 5)                      | prefix and suffix as given by UEG0<br>with signedValFlag=0, uCoff=14 | prefix: 1<br>suffix: na | prefix: 426<br>suffix: na, (uses DecodeBypass) |
| significant_coeff_flag<br>(field coded blocks with ctxBlockCat == 5)          | FL, cMax=1                                                           | 0                       | 436                                            |
| last_significant_coeff_flag<br>(field coded blocks with ctxBlockCat == 5)     | FL, cMax=1                                                           | 0                       | 451                                            |
| coded_block_flag<br>(5 < ctxBlockCat < 9)                                     | FL, cMax=1                                                           | 0                       | 460                                            |
| coded_block_flag<br>(9 < ctxBlockCat < 13)                                    | FL, cMax=1                                                           | 0                       | 472                                            |
| coded_block_flag<br>(ctxBlockCat == 5, 9, or 13)                              | FL, cMax=1                                                           | 0                       | 1012                                           |
| significant_coeff_flag<br>(frame coded blocks with 5 < ctxBlockCat < 9)       | FL, cMax=1                                                           | 0                       | 484                                            |
| significant_coeff_flag<br>(frame coded blocks with 9 < ctxBlockCat < 13)      | FL, cMax=1                                                           | 0                       | 528                                            |
| last_significant_coeff_flag<br>(frame coded blocks with 5 < ctxBlockCat < 9)  | FL, cMax=1                                                           | 0                       | 572                                            |
| last_significant_coeff_flag<br>(frame coded blocks with 9 < ctxBlockCat < 13) | FL, cMax=1                                                           | 0                       | 616                                            |
| coeff_abs_level_minus1<br>(blocks with 5 < ctxBlockCat < 9)                   | prefix and suffix as given by UEG0<br>with signedValFlag=0, uCoff=14 | prefix: 1<br>suffix: na | prefix: 952<br>suffix: na, (uses DecodeBypass) |
| coeff_abs_level_minus1<br>(blocks with 9 < ctxBlockCat < 13)                  | prefix and suffix as given by UEG0<br>with signedValFlag=0, uCoff=14 | prefix: 1<br>suffix: na | prefix: 982<br>suffix: na, (uses DecodeBypass) |
| significant_coeff_flag<br>(field coded blocks with 5 < ctxBlockCat < 9)       | FL, cMax=1                                                           | 0                       | 776                                            |
| significant_coeff_flag<br>(field coded blocks with 9 < ctxBlockCat < 13)      | FL, cMax=1                                                           | 0                       | 820                                            |
| last_significant_coeff_flag<br>(field coded blocks with 5 < ctxBlockCat < 9)  | FL, cMax=1                                                           | 0                       | 864                                            |
| last_significant_coeff_flag<br>(field coded blocks with 9 < ctxBlockCat < 13) | FL, cMax=1                                                           | 0                       | 908                                            |
| significant_coeff_flag<br>(frame coded blocks with ctxBlockCat == 9)          | FL, cMax=1                                                           | 0                       | 660                                            |

|                                                                               |                                                                      |                         |                                                |
|-------------------------------------------------------------------------------|----------------------------------------------------------------------|-------------------------|------------------------------------------------|
| significant_coeff_flag<br>(frame coded blocks with<br>ctxBlockCat == 13)      | FL, cMax=1                                                           | 0                       | 718                                            |
| last_significant_coeff_flag<br>(frame coded blocks with ctxBlockCat == 9)     | FL, cMax=1                                                           | 0                       | 690                                            |
| last_significant_coeff_flag<br>(frame coded blocks with<br>ctxBlockCat == 13) | FL, cMax=1                                                           | 0                       | 748                                            |
| coeff_abs_level_minus1<br>(blocks with ctxBlockCat == 9)                      | prefix and suffix as given by UEG0<br>with signedValFlag=0, uCoff=14 | prefix: 1<br>suffix: na | prefix: 708<br>suffix: na, (uses DecodeBypass) |
| coeff_abs_level_minus1<br>(blocks with ctxBlockCat == 13)                     | prefix and suffix as given by UEG0<br>with signedValFlag=0, uCoff=14 | prefix: 1<br>suffix: na | prefix: 766<br>suffix: na, (uses DecodeBypass) |
| significant_coeff_flag<br>(field coded blocks with ctxBlockCat == 9)          | FL, cMax=1                                                           | 0                       | 675                                            |
| significant_coeff_flag<br>(field coded blocks with ctxBlockCat == 13)         | FL, cMax=1                                                           | 0                       | 733                                            |
| last_significant_coeff_flag<br>(field coded blocks with ctxBlockCat == 9)     | FL, cMax=1                                                           | 0                       | 699                                            |
| last_significant_coeff_flag<br>(field coded blocks with ctxBlockCat == 13)    | FL, cMax=1                                                           | 0                       | 757                                            |

In subclause 9.3.2.6 “Binarization process for coded block pattern”, replace the paragraph starting with “The binarization of coded\_block\_pattern consists of...” with the following:

The binarization of coded\_block\_pattern consists of a prefix part and (when present) a suffix part. The prefix part of the binarization is given by the FL binarization of CodedBlockPatternLuma with cMax = 15. When ChromaArrayType is not equal to 0 or 3, the suffix part is present and consists of the TU binarization of CodedBlockPatternChroma with cMax = 2. The relationship between the value of the syntax element coded\_block\_pattern and the values of CodedBlockPatternLuma and CodedBlockPatternChroma is given as specified in subclause 7.4.5.

In subclause 9.3.3.1 “Derivation process for ctxIdx”, replace Table 9-31 with the following:

**Table 9-31 – Assignment of ctxIdxBlockCatOffset to ctxBlockCat for syntax elements coded\_block\_flag, significant\_coeff\_flag, last\_significant\_coeff\_flag, and coeff\_abs\_level\_minus1**

| Syntax element              | ctxBlockCat (as specified in Table 9-33) |    |    |    |    |   |   |    |    |   |    |    |    |    |
|-----------------------------|------------------------------------------|----|----|----|----|---|---|----|----|---|----|----|----|----|
|                             | 0                                        | 1  | 2  | 3  | 4  | 5 | 6 | 7  | 8  | 9 | 10 | 11 | 12 | 13 |
| coded_block_flag            | 0                                        | 4  | 8  | 12 | 16 | 0 | 0 | 4  | 8  | 4 | 0  | 4  | 8  | 8  |
| significant_coeff_flag      | 0                                        | 15 | 29 | 44 | 47 | 0 | 0 | 15 | 29 | 0 | 0  | 15 | 29 | 0  |
| last_significant_coeff_flag | 0                                        | 15 | 29 | 44 | 47 | 0 | 0 | 15 | 29 | 0 | 0  | 15 | 29 | 0  |
| coeff_abs_level_minus1      | 0                                        | 10 | 20 | 30 | 39 | 0 | 0 | 10 | 20 | 0 | 0  | 10 | 20 | 0  |

In subclause 9.3.3.1.1.9 “Derivation process of *ctxIdxInc* for the syntax element *coded\_block\_flag*”, make the following changes.

Replace the first paragraph with the following:

Input to this process is *ctxBlockCat* and additional input is specified as follows.

- If *ctxBlockCat* is equal to 0, 6, or 10, no additional input
- Otherwise, if *ctxBlockCat* is equal to 1 or 2, *luma4x4BlkIdx*
- Otherwise, if *ctxBlockCat* is equal to 3, the chroma component index *iCbCr*
- Otherwise, if *ctxBlockCat* is equal to 4, *chroma4x4BlkIdx* and the chroma component index *iCbCr*
- Otherwise, if *ctxBlockCat* is equal to 5, *luma8x8BlkIdx*
- Otherwise, if *ctxBlockCat* is equal to 7 or 8, *cb4x4BlkIdx*
- Otherwise, if *ctxBlockCat* is equal to 9, *cb8x8BlkIdx*
- Otherwise, if *ctxBlockCat* is equal to 11 or 12, *cr4x4BlkIdx*
- Otherwise, (*ctxBlockCat* is equal to 13), *cr8x8BlkIdx*

Replace the paragraph starting with “If *ctxBlockCat* is equal to 0, the following applies.” with the following:

- If *ctxBlockCat* is equal to 0, 6, or 10, the following applies.
  - The derivation process for neighbouring macroblocks specified in subclause 6.4.8.1 is invoked and the output is assigned to *mbAddrN* (with *N* being either A or B).
  - The variable *transBlockN* is derived as follows.
    - If *mbAddrN* is available and the macroblock *mbAddrN* is coded in *Intra\_16x16* prediction mode, the following applies.
      - When *ctxBlockCat* is equal to 0, the luma DC block of macroblock *mbAddrN* is assigned to *transBlockN*
      - When *ctxBlockCat* is equal to 6, the Cb DC block of macroblock *mbAddrN* is assigned to *transBlockN*
      - When *ctxBlockCat* is equal to 10, the Cr DC block of macroblock *mbAddrN* is assigned to *transBlockN*
    - Otherwise, *transBlockN* is marked as not available.

Replace the sentence “Otherwise (*ctxBlockCat* is equal to 4), the following applies” with the following:

Otherwise, if *ctxBlockCat* is equal to 4, the following applies

Insert the following paragraphs before the paragraph starting with “Let the variable *condTermFlagN* (with *N* being either A or B) be derived as follows”:

- Otherwise, if *ctxBlockCat* is equal to 5, the following applies.
  - The derivation process for neighbouring 8x8 luma blocks specified in subclause 6.4.8.2 is invoked with *luma8x8BlkIdx* as input and the output is assigned to *mbAddrN*, *luma8x8BlkIdxN* (with *N* being either A or B).
  - The variable *transBlockN* is derived as follows.
    - If *mbAddrN* is available, the macroblock *mbAddrN* does not have *mb\_type* equal to *P\_Skip*, *B\_Skip*, or *I\_PCM*, ( ( *CodedBlockPatternLuma* >> *luma8x8BlkIdx* ) & 1 ) is not equal to 0 for the macroblock *mbAddrN*, and *transform\_size\_8x8\_flag* is equal to 1 for the macroblock *mbAddrN*, the 8x8 luma block with index *luma8x8BlkIdxN* of macroblock *mbAddrN* is assigned to *transBlockN*.

- Otherwise, transBlockN is marked as not available.
- Otherwise, if ctxBlockCat is equal to 7 or 8, the following applies.
  - The derivation process for neighbouring 4x4 Cb blocks specified in subclause 6.4.8.4.1 is invoked with cb4x4BlkIdx as input and the output is assigned to mbAddrN, cb4x4BlkIdxN (with N being either A or B).
  - The variable transBlockN is derived as follows.
    - If mbAddrN is available, the macroblock mbAddrN does not have mb\_type equal to P\_Skip, B\_Skip, or I\_PCM,  $((\text{CodedBlockPatternLuma} \gg (\text{cb4x4BlkIdxN} \gg 2)) \& 1)$  is not equal to 0 for the macroblock mbAddrN, and transform\_size\_8x8\_flag is equal to 0 for the macroblock mbAddrN, the 4x4 Cb block with index cb4x4BlkIdxN of macroblock mbAddrN is assigned to transBlockN.
    - Otherwise, if mbAddrN is available, the macroblock mbAddrN does not have mb\_type equal to P\_Skip or B\_Skip,  $((\text{CodedBlockPatternLuma} \gg (\text{cb4x4BlkIdxN} \gg 2)) \& 1)$  is not equal to 0 for the macroblock mbAddrN, and transform\_size\_8x8\_flag is equal to 1 for the macroblock mbAddrN, the 8x8 Cb block with index  $(\text{cb4x4BlkIdxN} \gg 2)$  of macroblock mbAddrN is assigned to transBlockN.
    - Otherwise, transBlockN is marked as not available.
- Otherwise, if ctxBlockCat is equal to 9, the following applies.
  - The derivation process for neighbouring 8x8 Cb blocks specified in subclause 6.4.8.2.1 is invoked with cb8x8BlkIdx as input and the output is assigned to mbAddrN, cb8x8BlkIdxN (with N being either A or B).
  - The variable transBlockN is derived as follows.
    - If mbAddrN is available, the macroblock mbAddrN does not have mb\_type equal to P\_Skip, B\_Skip, or I\_PCM,  $((\text{CodedBlockPatternLuma} \gg \text{cb8x8BlkIdx}) \& 1)$  is not equal to 0 for the macroblock mbAddrN, and transform\_size\_8x8\_flag is equal to 1 for the macroblock mbAddrN, the 8x8 Cb block with index cb8x8BlkIdxN of macroblock mbAddrN is assigned to transBlockN.
    - Otherwise, transBlockN is marked as not available.
- Otherwise, if ctxBlockCat is equal to 11 or 12, the following applies.
  - The derivation process for neighbouring 4x4 Cr blocks specified in subclause 6.4.8.4.1 is invoked with cr4x4BlkIdx as input and the output is assigned to mbAddrN, cr4x4BlkIdxN (with N being either A or B).
  - The variable transBlockN is derived as follows.
    - If mbAddrN is available, the macroblock mbAddrN does not have mb\_type equal to P\_Skip, B\_Skip, or I\_PCM,  $((\text{CodedBlockPatternLuma} \gg (\text{cr4x4BlkIdxN} \gg 2)) \& 1)$  is not equal to 0 for the macroblock mbAddrN, and transform\_size\_8x8\_flag is equal to 0 for the macroblock mbAddrN, the 4x4 Cr block with index cr4x4BlkIdxN of macroblock mbAddrN is assigned to transBlockN.
    - Otherwise, if mbAddrN is available, the macroblock mbAddrN does not have mb\_type equal to P\_Skip or B\_Skip,  $((\text{CodedBlockPatternLuma} \gg (\text{cr4x4BlkIdxN} \gg 2)) \& 1)$  is not equal to 0 for the macroblock mbAddrN, and transform\_size\_8x8\_flag is equal to 1 for the macroblock mbAddrN, the 8x8 Cr block with index  $(\text{cr4x4BlkIdxN} \gg 2)$  of macroblock mbAddrN is assigned to transBlockN.
    - Otherwise, transBlockN is marked as not available.
- Otherwise (ctxBlockCat is equal to 13), the following applies.
  - The derivation process for neighbouring 8x8 Cr blocks specified in subclause 6.4.8.2.1 is invoked with cr8x8BlkIdx as input and the output is assigned to mbAddrN, cr8x8BlkIdxN (with N being either A or B).
  - The variable transBlockN is derived as follows.
    - If mbAddrN is available, the macroblock mbAddrN does not have mb\_type equal to P\_Skip, B\_Skip, or I\_PCM,  $((\text{CodedBlockPatternLuma} \gg \text{cr8x8BlkIdx}) \& 1)$  is not equal to 0 for the macroblock mbAddrN, and transform\_size\_8x8\_flag is equal to 1 for the macroblock mbAddrN, the 8x8 Cr block with index cr8x8BlkIdxN of macroblock mbAddrN is assigned to transBlockN.
    - Otherwise, transBlockN is marked as not available.