
**Information technology — UPnP
Device Architecture —**
Part 31-1:
**Energy management device control
protocol — Energy management
service**

*Technologies de l'information — Architecture de dispositif UPnP —
Partie 31-1: Protocole de contrôle du dispositif de management de
l'énergie — Service de management de l'énergie*



IECNORM.COM : Click to view the full PDF of ISO/IEC 29341-31-1:2017



COPYRIGHT PROTECTED DOCUMENT

© ISO/IEC 2017, Published in Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

CONTENTS

1	Scope	v
2	Normative references	1
3	Terms, definitions, symbols and abbreviated terms.....	2
4	Notations and Conventions	2
4.1	Notation	2
4.1.1	Data Types	2
4.2	Derived Data Types	3
4.3	Management of XML Namespaces in Standardized DCPs.....	3
4.3.1	Namespace Prefix Requirements.....	4
4.3.2	Namespace Names, Namespace Versioning and Schema Versioning	5
4.3.3	Namespace Usage Examples	7
4.4	Vendor-defined Extensions	7
4.4.1	Vendor-defined Action Names	7
4.4.2	Vendor-defined State Variable Names	8
4.4.3	Vendor-defined XML Elements and attributes	8
4.4.4	Vendor-defined Property Names.....	8
5	Service modelling definitions	8
5.1	Service type	8
5.2	Security feature	8
5.2.1	Overview	8
5.2.2	Restrictable and non-restrictatable actions	8
5.3	State variables	9
5.3.1	General	9
5.3.2	State variable overview	9
5.3.3	<u>NetworkInterfaceInfo</u>	9
5.3.4	<u>ProxiedNetworkInterfaceInfo</u>	13
5.3.5	<u>A_ARG_TYPE_Duration</u>	13
5.3.6	<u>A_ARG_TYPE_ServiceSubscriptionID</u>	13
5.3.7	<u>A_ARG_TYPE_UniqueServiceName</u>	13
5.3.8	<u>A_ARG_TYPE_URI</u>	14
5.4	Eventing and moderation	14
5.5	Actions	14
5.5.1	Overview	14
5.5.2	<u>GetInterfaceInfo()</u>	16
5.5.3	<u>ServiceSubscription()</u>	16
5.5.4	<u>ServiceRenewal()</u>	18
5.5.5	<u>ServiceRelease()</u>	19
6	Theory of operations.....	20
6.1	Overview	20
6.2	WakeOnPattern theory of operation	20
6.2.1	Overview	20
6.2.2	EnergyManagement service operation	21
6.2.3	WakeOnPattern signaling operation.....	21

6.2.4	Usability considerations	21
6.3	Service subscription theory of operation	22
6.4	EnergyManagement service theory of operation	23
6.5	EnergyManagement control point theory of operation	23
6.6	Network Interface Mode of Operation	23
6.7	<u>ProxiedNetworkInterfaceInfo</u> theory of operation	24
7	XML service description	24
Table 1	— Namespace Definitions	4
Table 2	— Schema-related Information	4
Table 3	— Default Namespaces for the EnergyManagement Specifications	5
Table 4	— Assignment of Restrictable/Non-Restrictable Roles	9
Table 5	— State variables	9
Table 6	— Event moderation	14
Table 7	— Actions	15
Table 8	— Arguments for <u>GetInterfaceInfo()</u>	16
Table 9	— Error codes for <u>GetInterfaceInfo()</u>	16
Table 10	— Arguments for <u>ServiceSubscription()</u>	16
Table 11	— Error Codes for <u>ServiceSubscription()</u>	18
Table 12	— Arguments for <u>ServiceRenewal()</u>	18
Table 13	— Error codes for <u>ServiceRenewal()</u>	19
Table 14	— Arguments for <u>ServiceRelease()</u>	19
Table 15	— Error codes for <u>ServiceRelease()</u>	20

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular the different approval criteria needed for the different types of document should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see <http://www.iso.org/directives>).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation on the voluntary nature of Standard, the meaning of the ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the WTO principles in the Technical Barriers to Trade (TBT) see the following URL: [Foreword – Supplementary information](#)

ISO/IEC 29341-31-1 was prepared by UPnP Forum and adopted, under the PAS procedure, by joint technical committee ISO/IEC JTC 1, *Information technology*, in parallel with its approval by national bodies of ISO and IEC.

The list of all currently available parts of ISO/IEC 29341 series, under the general title *Information technology — UPnP Device Architecture*, can be found on the [ISO web site](#).

Introduction

ISO and IEC draw attention to the fact that it is claimed that compliance with this document may involve the use of patents as indicated below.

ISO and IEC take no position concerning the evidence, validity and scope of these patent rights. The holders of these patent rights have assured ISO and IEC that they are willing to negotiate licenses under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statements of the holders of these patent rights are registered with ISO and IEC.

Intel Corporation has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Intel Corporation
Standards Licensing Department
5200 NE Elam Young Parkway
MS: JFS-98
USA – Hillsboro, Oregon 97124

Microsoft Corporation has informed IEC and ISO that it has patent applications or granted patents as listed below:

6101499 / US; 6687755 / US; 6910068 / US; 7130895 / US; 6725281 / US; 7089307 / US; 7069312 / US; 10/783 524 / US

Information may be obtained from:

Microsoft Corporation
One Microsoft Way
USA – Redmond WA 98052

Philips International B.V. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Philips International B.V. – IP&S
High Tech campus, building 44 3A21
NL – 5656 Eindhoven

NXP B.V. (NL) has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

NXP B.V. (NL)
High Tech campus 60
NL – 5656 AG Eindhoven

Matsushita Electric Industrial Co. Ltd. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Matsushita Electric Industrial Co. Ltd.
1-3-7 Shiromi, Chuoh-ku
JP – Osaka 540-6139

Hewlett Packard Company has informed IEC and ISO that it has patent applications or granted patents as listed below:

5 956 487 / US; 6 170 007 / US; 6 139 177 / US; 6 529 936 / US; 6 470 339 / US; 6 571 388 / US; 6 205 466 / US

Information may be obtained from:

Hewlett Packard Company
1501 Page Mill Road
USA – Palo Alto, CA 94304

Samsung Electronics Co. Ltd. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Digital Media Business, Samsung Electronics Co. Ltd.
416 Maetan-3 Dong, Yeongtang-Gu,
KR – Suwon City 443-742

Huawei Technologies Co., Ltd. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Huawei Technologies Co., Ltd.
Administration Building, Bantian Longgang District
Shenzhen – China 518129

Qualcomm Incorporated has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Qualcomm Incorporated
5775 Morehouse Drive
San Diego, CA – USA 92121

Telecom Italia S.p.A. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Telecom Italia S.p.A.
Via Reiss Romoli, 274
Turin - Italy 10148

Cisco Systems informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA – USA 95134

ISO/IEC 29341-31-1:2017(E)

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those identified above. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

IECNORM.COM : Click to view the full PDF of ISO/IEC 29341-31-1:2017

Original UPnP Document

Reference may be made in this document to original UPnP documents. These references are retained in order to maintain consistency between the specifications as published by ISO/IEC and by UPnP Implementers Corporation and later by UPnP Forum. The following table indicates the original UPnP document titles and the corresponding part of ISO/IEC 29341:

UPnP Document Title	ISO/IEC 29341 Part
UPnP Device Architecture 1.0	ISO/IEC 29341-1:2008
UPnP Device Architecture Version 1.0	ISO/IEC 29341-1:2011
UPnP Device Architecture 1.1	ISO/IEC 29341-1-1:2011
UPnP Device Architecture 2.0	ISO/IEC 29341-1-2
UPnP Basic:1 Device	ISO/IEC 29341-2
UPnP AV Architecture:1	ISO/IEC 29341-3-1:2008
UPnP AV Architecture:1	ISO/IEC 29341-3-1:2011
UPnP AVTransport:1 Service	ISO/IEC 29341-3-10
UPnP ConnectionManager:1 Service	ISO/IEC 29341-3-11
UPnP ContentDirectory:1 Service	ISO/IEC 29341-3-12
UPnP RenderingControl:1 Service	ISO/IEC 29341-3-13
UPnP MediaRenderer:1 Device	ISO/IEC 29341-3-2
UPnP MediaRenderer:2 Device	ISO/IEC 29341-3-2:2011
UPnP MediaServer:1 Device	ISO/IEC 29341-3-3
UPnP AVTransport:2 Service	ISO/IEC 29341-4-10:2008
UPnP AVTransport:2 Service	ISO/IEC 29341-4-10:2011
UPnP ConnectionManager:2 Service	ISO/IEC 29341-4-11:2008
UPnP ConnectionManager:2 Service	ISO/IEC 29341-4-11:2011
UPnP ContentDirectory:2 Service	ISO/IEC 29341-4-12
UPnP RenderingControl:2 Service	ISO/IEC 29341-4-13:2008
UPnP RenderingControl:2 Service	ISO/IEC 29341-4-13:2011
UPnP ScheduledRecording:1	ISO/IEC 29341-4-14
UPnP ScheduledRecording:2	ISO/IEC 29341-4-14:2011
UPnP MediaRenderer:2 Device	ISO/IEC 29341-4-2
UPnP MediaServer:2 Device	ISO/IEC 29341-4-3
UPnP AV Datastructure Template:1	ISO/IEC 29341-4-4:2008
UPnP AV Datastructure Template:1	ISO/IEC 29341-4-4:2011
UPnP DigitalSecurityCamera:1 Device	ISO/IEC 29341-5-1
UPnP DigitalSecurityCameraMotionImage:1 Service	ISO/IEC 29341-5-10
UPnP DigitalSecurityCameraSettings:1 Service	ISO/IEC 29341-5-11
UPnP DigitalSecurityCameraStillImage:1 Service	ISO/IEC 29341-5-12
UPnP HVAC_System:1 Device	ISO/IEC 29341-6-1
UPnP ControlValve:1 Service	ISO/IEC 29341-6-10
UPnP HVAC_FanOperatingMode:1 Service	ISO/IEC 29341-6-11
UPnP FanSpeed:1 Service	ISO/IEC 29341-6-12
UPnP HouseStatus:1 Service	ISO/IEC 29341-6-13
UPnP HVAC_SetpointSchedule:1 Service	ISO/IEC 29341-6-14
UPnP TemperatureSensor:1 Service	ISO/IEC 29341-6-15
UPnP TemperatureSetpoint:1 Service	ISO/IEC 29341-6-16
UPnP HVAC_UserOperatingMode:1 Service	ISO/IEC 29341-6-17

UPnP HVAC_ZoneThermostat:1 Device	ISO/IEC 29341-6-2
UPnP BinaryLight:1 Device	ISO/IEC 29341-7-1
UPnP Dimming:1 Service	ISO/IEC 29341-7-10
UPnP SwitchPower:1 Service	ISO/IEC 29341-7-11
UPnP DimmableLight:1 Device	ISO/IEC 29341-7-2
UPnP InternetGatewayDevice:1 Device	ISO/IEC 29341-8-1
UPnP LANHostConfigManagement:1 Service	ISO/IEC 29341-8-10
UPnP Layer3Forwarding:1 Service	ISO/IEC 29341-8-11
UPnP LinkAuthentication:1 Service	ISO/IEC 29341-8-12
UPnP RadiusClient:1 Service	ISO/IEC 29341-8-13
UPnP WANCableLinkConfig:1 Service	ISO/IEC 29341-8-14
UPnP WANCommonInterfaceConfig:1 Service	ISO/IEC 29341-8-15
UPnP WANDSLLinkConfig:1 Service	ISO/IEC 29341-8-16
UPnP WANEthernetLinkConfig:1 Service	ISO/IEC 29341-8-17
UPnP WANIPConnection:1 Service	ISO/IEC 29341-8-18
UPnP WANPOTSLinkConfig:1 Service	ISO/IEC 29341-8-19
UPnP LANDevice:1 Device	ISO/IEC 29341-8-2
UPnP WANPPPConnection:1 Service	ISO/IEC 29341-8-20
UPnP WLANConfiguration:1 Service	ISO/IEC 29341-8-21
UPnP WANDevice:1 Device	ISO/IEC 29341-8-3
UPnP WANConnectionDevice:1 Device	ISO/IEC 29341-8-4
UPnP WLANAccessPointDevice:1 Device	ISO/IEC 29341-8-5
UPnP Printer:1 Device	ISO/IEC 29341-9-1
UPnP ExternalActivity:1 Service	ISO/IEC 29341-9-10
UPnP Feeder:1.0 Service	ISO/IEC 29341-9-11
UPnP PrintBasic:1 Service	ISO/IEC 29341-9-12
UPnP Scan:1 Service	ISO/IEC 29341-9-13
UPnP Scanner:1.0 Device	ISO/IEC 29341-9-2
UPnP QoS Architecture:1.0	ISO/IEC 29341-10-1
UPnP QosDevice:1 Service	ISO/IEC 29341-10-10
UPnP QosManager:1 Service	ISO/IEC 29341-10-11
UPnP QosPolicyHolder:1 Service	ISO/IEC 29341-10-12
UPnP QoS Architecture:2	ISO/IEC 29341-11-1
UPnP QosDevice:2 Service	ISO/IEC 29341-11-10
UPnP QosManager:2 Service	ISO/IEC 29341-11-11
UPnP QosPolicyHolder:2 Service	ISO/IEC 29341-11-12
UPnP QOS v2 Schema Files	ISO/IEC 29341-11-2
UPnP RemoteUIClientDevice:1 Device	ISO/IEC 29341-12-1
UPnP RemoteUIClient:1 Service	ISO/IEC 29341-12-10
UPnP RemoteUIServer:1 Service	ISO/IEC 29341-12-11
UPnP RemoteUIServerDevice:1 Device	ISO/IEC 29341-12-2
UPnP DeviceSecurity:1 Service	ISO/IEC 29341-13-10
UPnP SecurityConsole:1 Service	ISO/IEC 29341-13-11
UPnP ContentDirectory:3 Service	ISO/IEC 29341-14-12:2011
UPnP MediaServer:3 Device	ISO/IEC 29341-14-3:2011
UPnP ContentSync:1	ISO/IEC 29341-15-10:2011
UPnP Low Power Architecture:1	ISO/IEC 29341-16-1:2011

UPnP LowPowerProxy:1 Service	ISO/IEC 29341-16-10:2011
UPnP LowPowerDevice:1 Service	ISO/IEC 29341-16-11:2011
UPnP QoS Architecture:3	ISO/IEC 29341-17-1:2011
UPnP QosDevice:3 Service	ISO/IEC 29341-17-10:2011
UPnP QosManager:3 Service	ISO/IEC 29341-17-11:2011
UPnP QosPolicyHolder:3 Service	ISO/IEC 29341-17-12:2011
UPnP QosDevice:3 Addendum	ISO/IEC 29341-17-13:2011
UPnP RemoteAccessArchitecture:1	ISO/IEC 29341-18-1:2011
UPnP InboundConnectionConfig:1 Service	ISO/IEC 29341-18-10:2011
UPnP RADAConfig:1 Service	ISO/IEC 29341-18-11:2011
UPnP RADASync:1 Service	ISO/IEC 29341-18-12:2011
UPnP RATAConfig:1 Service	ISO/IEC 29341-18-13:2011
UPnP RAClient:1 Device	ISO/IEC 29341-18-2:2011
UPnP RAServer:1 Device	ISO/IEC 29341-18-3:2011
UPnP RADiscoveryAgent:1 Device	ISO/IEC 29341-18-4:2011
UPnP SolarProtectionBlind:1 Device	ISO/IEC 29341-19-1:2011
UPnP TwoWayMotionMotor:1 Service	ISO/IEC 29341-19-10:2011
UPnP AV Architecture:2	ISO/IEC 29341-20-1
UPnP AVTransport:3 Service	ISO/IEC 29341-20-10
UPnP ConnectionManager:3 Service	ISO/IEC 29341-20-11
UPnP ContentDirectory:4 Device	ISO/IEC 29341-20-12
UPnP RenderingControl:3 Service	ISO/IEC 29341-20-13
UPnP ScheduledRecording:2 Service	ISO/IEC 29341-20-14
UPnP MediaRenderer:3 Service	ISO/IEC 29341-20-2
UPnP MediaServer:4 Device	ISO/IEC 29341-20-3
UPnP AV Datastructure Template:1	ISO/IEC 29341-20-4
UPnP InternetGatewayDevice:2 Device	ISO/IEC 29341-24-1
UPnP WANIPConnection:2 Service	ISO/IEC 29341-24-10
UPnP WANIPv6FirewallControl:1 Service	ISO/IEC 29341-24-11
UPnP WANConnectionDevice:2 Service	ISO/IEC 29341-24-2
UPnP WANDevice:2 Device	ISO/IEC 29341-24-3
UPnP Telephony Architecture:2	ISO/IEC 29341-26-1
UPnP CallManagement:2 Service	ISO/IEC 29341-26-10
UPnP MediaManagement:2 Service	ISO/IEC 29341-26-11
UPnP Messaging:2 Service	ISO/IEC 29341-26-12
UPnP PhoneManagement:2 Service	ISO/IEC 29341-26-13
UPnP AddressBook:1 Service	ISO/IEC 29341-26-14
UPnP Calendar:1 Service	ISO/IEC 29341-26-15
UPnP Presense:1 Service	ISO/IEC 29341-26-16
UPnP TelephonyClient:2 Device	ISO/IEC 29341-26-2
UPnP TelephonyServer:2 Device	ISO/IEC 29341-26-3
UPnP Friendly Info Update:1 Service	ISO/IEC 29341-27-1
UPnP MultiScreen MultiScreen Architecture:1	ISO/IEC 29341-28-1
UPnP MultiScreen Application Management:1 Service	ISO/IEC 29341-28-10
UPnP MultiScreen Screen:1 Device	ISO/IEC 29341-28-2
UPnP MultiScreen Application Management:2 Service	ISO/IEC 29341-29-10
UPnP MultiScreen Screen:2 Device	ISO/IEC 29341-29-2

ISO/IEC 29341-31-1:2017(E)

UPnP IoT Management and Control Architecture Overview:1	ISO/IEC 29341-30-1
UPnP DataStore:1 Service	ISO/IEC 29341-30-10
UPnP IoT Management and Control Data Model:1 Service	ISO/IEC 29341-30-11
UPnP IoT Management and Control Transport Generic:1 Service	ISO/IEC 29341-30-12
UPnP IoT Management and Control:1 Device	ISO/IEC 29341-30-2
UPnP Energy Management:1 Service	ISO/IEC 29341-31-1

IECNORM.COM : Click to view the full PDF of ISO/IEC 29341-31-1:2017

1 Scope

This specification is compliant with the UPnP Device Architecture version 1.0. It defines a service type named EnergyManagement service. It is scoped to any UPnP Device that needs to convey energy management functionality available for the UPnP Device and its services.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO/IEC 29341-1, *Information Technology – UPnP Device Architecture – Part 1-1: UPnP Device Architecture Version 1.0*

ISO/IEC 29341-4-12, *Information Technology – UPnP Device Architecture – Part 4-12: Audio video Device Control Protocol – Level 2 – Content Directory Service*

IETF RFC 1738, *Uniform Resource Locators (URL)*, Tim Berners-Lee, et. Al., December 1994.

Available at: <http://www.ietf.org/rfc/rfc1738.txt>.

IETF RFC 2396, *Uniform Resource Identifiers (URI): Generic Syntax*, Tim Berners-Lee, et al., 1998.

Available at: <http://www.ietf.org/rfc/rfc2396.txt>.

IETF RFC 4291, *IP Version 6 Addressing Architecture*, February 2006

Available at: <http://www.ietf.org/rfc/rfc4291.txt>

IETF RFC 5952, *A Recommendation for IPv6 Address Text Representation*, August 2010

Available at: <http://www.ietf.org/rfc/rfc5952.txt>

W3C XML, *Extensible Markup Language (XML) 1.0 (Third Edition)*, W3C Recommendation, February 4, 2004.

Available at: <http://www.w3.org/TR/2004/REC-xml-20040204>.

W3C XML-NS, *The “xml:” Namespace*, October 26, 2009.

Available at: <http://www.w3.org/XML/1998/namespace>.

W3C XML-XSD, *XML Schema for the “xml:” Namespace*.

Available at: <http://www.w3.org/2001/xml.xsd>.

W3C XML-NMSP, *Namespaces in XML*, Tim Bray, Dave Hollander, Andrew Layman, eds., W3C Recommendation, January 14, 1999.

Available at: <http://www.w3.org/TR/1999/REC-xml-names-19990114>.

W3C XML Schema-1, *XML Schema Part1: Structures, Second Edition*, Henry S. Thompson, David Beech, Murray Maloney, Noah Mendelsohn, W3C Recommendation, 28 October 2004.

Available at: <http://www.w3.org/TR/2004/REC-xmlschema-1-20041028>.

W3C XML Schema-2, *XML Schema Part 2:Data Types, Second Edition*, Paul V. Biron, Ashok Malhotra, W3C Recommendation, 28 October 2004.

Available at: <http://www.w3.org/TR/2004/REC-xmlschema-2-20041028>.

W3C XML Schema, *XML Schema for XML Schema*.

Available at: <http://www.w3.org/2001/XMLSchema.xsd>.

UPnP DP, *DeviceProtection:1*, UPnP Forum, February 24, 2011.

Available at: <http://www.upnp.org/specs/gw/UPnP-gw-DeviceProtection-v1-Service-20110224.pdf>.

Latest version available at: <http://www.upnp.org/specs/gw/UPnP-gw-DeviceProtection-v1-Service.pdf>.

UPnP EM-NII-XSD, XML Schema for EnergyManagement NetworkInterfaceInfo, UPnP Forum, June 30, 2013.

Available at: <http://www.upnp.org/schemas/lp/em-NetworkInterfaceInfo-v1-20130830.xsd>.

Latest version available at: <http://www.upnp.org/schemas/lp/em-NetworkInterfaceInfo.xsd>

3 Terms, definitions, symbols and abbreviated terms

For the purposes of this document, the terms and definitions given in ISO/IEC 29341-1 and the following apply.

3.1 Provisioning terms

3.1.1

conditionally allowed

CA

The definition or behavior depends on a condition. If the specified condition is met, then the definition or behavior is allowed, otherwise it is not allowed.

3.1.2

conditionally required

CR

The definition or behavior depends on a condition. If the specified condition is met, then the definition or behavior is required, otherwise it is not allowed.

3.1.3

not allowed

The definition or behavior is prohibited by this specification. Opposite of required.

3.2 Abbreviated terms

3.2.1

A

allowed

4 Notations and Conventions

4.1 Notation

- Strings that are to be taken literally are enclosed in “double quotes”.
- Words that are emphasized are printed in *italic*.
- Keywords that are defined by the UPnP EnergyManagement Working Committee are printed using the *forum* character style.
- Keywords that are defined by the UPnP Device Architecture specification [ISO/IEC 29341-1] are printed using the *arch* character style.

4.1.1 Data Types

This specification uses data type definitions from two different sources. The UPnP Device Architecture [ISO/IEC 29341-1] defined data types are used to define state variable and action argument data types. The XML Schema namespace is used to define property data types [W3C XML Schema-2].

For UPnP Device Architecture [ISO/IEC 29341-1] defined **boolean** data types, it is strongly recommended to use the value “**0**” for false, and the value “**1**” for true. However, when used as input arguments, the values “**false**”, “**no**”, “**true**”, “**yes**” can

also be encountered and shall be accepted. Nevertheless, it is strongly recommended that all **boolean** state variables and output arguments be represented as “**0**” and “**1**”.

For XML Schema [W3C XML Schema-2] defined Boolean data types, it is strongly recommended to use the value “**0**” for false, and the value “**1**” for true. However, when used as input properties, the values “**false**”, “**true**” can also be encountered and shall be accepted. Nevertheless, it is strongly recommended that all Boolean properties be represented as “**0**” and “**1**”.

4.2 Derived Data Types

Subclause 4.2 defines a derived data type that is represented as a string data type with special syntax. This specification uses string data type definitions that originate from two different sources. The UPnP Device Architecture defined **string** data type is used to define state variable and action argument **string** data types. The XML Schema namespace is used to define property xsd:string data types. The following definition applies to both string data types.

4.3 Management of XML Namespaces in Standardized DCPs

UPnP specifications make extensive use of XML namespaces. This enables separate DCPs, and even separate components of an individual DCP, to be designed independently and still avoid name collisions when they share XML documents. Every name in an XML document belongs to exactly one namespace. In documents, XML names appear in one of two forms: qualified or unqualified. An unqualified name (or no-colon-name) contains no colon (“:”) characters. An unqualified name belongs to the document’s default namespace. A qualified name is two no-colon-names separated by one colon character. The no-colon-name before the colon is the qualified name’s namespace prefix, the no-colon-name after the colon is the qualified name’s “local” name (meaning local to the namespace identified by the namespace prefix). Similarly, the unqualified name is a local name in the default namespace.

The formal name of a namespace is a URI. The namespace prefix used in an XML document is *not* the name of the namespace. The namespace name shall be globally unique. It has a single definition that is accessible to anyone who uses the namespace. It has the same meaning anywhere that it is used, both inside and outside XML documents. The namespace prefix, however, in formal XML usage, is defined only in an XML document. It shall be locally unique to the document. Any valid XML no-colon-name may be used. And, in formal XML usage, different XML documents may use different namespace prefixes to refer to the same namespace. The creation and use of the namespace prefix was standardized by the W3C XML Committee in [W3C XML-NMSP] strictly as a convenient local shorthand replacement for the full URI name of a namespace in individual documents.

Some EnergyManagement state variables and action output parameters are represented in XML by element and attribute names, therefore, all property names belong to an XML namespace.

For the same reason that namespace prefixes are convenient in XML documents, it is convenient in specification text to refer to namespaces using a namespace prefix. Therefore, this specification declares a “standard” prefix for all XML namespaces used herein. In addition, this specification expands the scope where these prefixes have meaning, beyond a single XML document, to all of its text, XML examples, and certain string-valued properties. This expansion of scope *does not* supersede XML rules for usage in documents, it only augments and complements them in important contexts that are out-of-scope for the XML specifications.

All of the namespaces used in this specification are listed in Table 1 and Table 2. For each such namespace, Table 1 gives a brief description of it, its name (a URI) and its defined “standard” prefix name. The standard prefixes are also used in Table 2 to cross-reference additional namespace information. This second table includes each namespace’s valid XML document root element(s) (if any), its schema file name,

versioning information (to be discussed in more detail below), and a link to the entry in Clause 2 for its associated schema.

The normative definitions for these namespaces are the documents referenced in Table 1. The schemas are designed to support these definitions for both human understanding and as test tools. However, limitations of the XML Schema language itself make it difficult for the UPnP-defined schemas to accurately represent all details of the namespace definitions. As a result, the schemas will validate many XML documents that are not valid according to the specifications.

The Working Committee expects to continue refining these schemas after specification release to reduce the number of documents that are validated by the schemas while violating the specifications; but the schemas will still be informative, supporting documents. Some schemas might become normative in future versions of the specifications.

Table 1 — Namespace Definitions

Standard Name-space Prefix	Namespace Name	Namespace Description	Normative Definition Document Reference
<i>LP Working Committee defined namespaces</i>			
em-nii	urn:schemas-upnp-org:lp:em-NetworkInterfaceInfo	<u>NetworkInterfaceInfo</u> and <u>ProxiedNetworkInterfaceInfo</u> state variables	UPnP EM-NII-XSD
<i>Externally defined namespaces</i>			
xsd	http://www.w3.org/2001/XMLSchema	XML Schema Language 1.0	W3C XML Schema-1 W3C XML Schema-2
xsi	http://www.w3.org/2001/XMLSchema-instance	XML Schema Instance Document schema	W3C XML Schema-1 2.6 & 3.2.7
xml	http://www.w3.org/XML/1998/namespace	The "xml:" Namespace	W3C XML-NS

Table 2 — Schema-related Information

Standard Name-space Prefix	Relative URI and File Name ^a • Form 1, Form 2, Form3	Valid Root Element(s)	Schema Reference
<i>LP Working Committee Defined Namespaces</i>			
	em-NetworkInterfaceInfo-vn- yyyyymmdd.xsd em-NetworkInterfaceInfo- vn.xsd em-NetworkInterfaceInfo.xsd	<NetworkInterfaceInfo>	UPnP EM-NII-XSD
<i>Externally Defined Namespaces</i>			
xsd	<i>n/a</i>	<schema>	W3C XML Schema
xsi	<i>n/a</i>		<i>n/a</i>
xml	<i>n/a</i>		W3C XML-XSD
^a Absolute URIs are generated by prefixing the relative URIs with " http://www.upnp.org/schemas/lp/ "			

4.3.1 Namespace Prefix Requirements

There are many occurrences in this specification of string data types that contain XML names (property names). These XML names in strings will not be processed under namespace-aware conditions. Therefore, all occurrences in instance documents of

XML names in strings shall use the standard namespace prefixes as declared in Table 1. In order to properly process the XML documents described herein, control points and devices shall use namespace-aware XML processors [W3C XML-NMSP] for both reading and writing. As allowed by [W3C XML-NMSP], the namespace prefixes used in an instance document are at the sole discretion of the document creator. Therefore, the declared prefix for a namespace in a document may be different from the standard prefix. All devices shall be able to correctly process any valid XML instance document, even when it uses a non-standard prefix for ordinary XML names. However, it is strongly recommended that all devices use these standard prefixes for all instance documents to avoid confusion on the part of both human and machine readers. These standard prefixes are used in all descriptive text and all XML examples in this and related UPnP specifications. However, each individual specification may assume a default namespace for its descriptive text. In that case, names from that namespace may appear with no prefix.

The assumed default namespace, if any, for the EnergyManagement specification is given in Table 3.

Note: all UPnP EnergyManagement schemas declare attributes to be “unqualified”, so namespace prefixes are never used with EnergyManagement Working Committee defined attribute names.

Table 3 — Default Namespaces for the EnergyManagement Specifications

Specification Name	Default Namespace Prefix
EnergyManagement	em

4.3.2 Namespace Names, Namespace Versioning and Schema Versioning

The UPnP EnergyManagement service specifications define several data structures (such as state variables and action arguments) whose format is an XML instance document that complies with one or more specific XML schemas, which define XML namespaces. Each namespace is uniquely identified by an assigned namespace name. The namespace names that are defined by the EnergyManagement Working Committee are URNs. See Table 1 for a current list of namespace names. Additionally, each namespace corresponds to an XML schema document that provides a machine-readable representation of the associated namespace to enable automated validation of the XML (state variable or action parameter) instance documents.

Within an XML schema and XML instance document, the name of each corresponding namespace appears as the value of an `xmlns` attribute within the root element. Each `xmlns` attribute also includes a namespace prefix that is associated with that namespace in order to qualify and disambiguate element and attribute names that are defined within different namespaces. The schemas that correspond to the listed namespaces are identified by URI values that are listed in the `schemaLocation` attribute also within the root element. (See 4.3.3)

In order to enable both forward and backward compatibility, namespace names are permanently assigned and shall not change even when a new version of a specification changes the definition of a namespace. However, all changes to a namespace definition shall be backward-compatible. In other words, the updated definition of a namespace shall not invalidate any XML documents that comply with an earlier definition of that same namespace. This means, for example, that a namespace shall not be changed so that a new element or attribute becomes required in a conforming instance document. Although namespace names shall not change, namespaces still have version numbers that reflect a specific set of definitional changes. Each time the definition of a namespace is changed, the namespace's version number is incremented by one.

Whenever a new namespace version is created, a new XML schema document (.xsd) is created and published so that the new namespace definition is represented in a machine-readable form. Since a XML schema document is just a representation of a namespace definition, translation errors can occur. Therefore, it is sometimes necessary to re-release a published schema in order to correct typos or other namespace representation errors. In order to easily identify the potential multiplicity of schema releases for the same namespace, the URI of each released schema shall conform to the following format (called Form 1):

Form 1: "http://www.upnp.org/schemas/lp/" **schema-root-name** "-v" **ver** "-" **yyyymmdd** where

- **schema-root-name** is the name of the root element of the namespace that this schema represents.
- **ver** corresponds to the version number of the namespace that is represented by the schema.
- **yyyymmdd** is the year, month and day (in the Gregorian calendar) that this schema was released.

Table 2 identifies the URI formats for each of the namespaces that are currently defined by the UPnP EnergyManagement Working Committee.

As an example, the original schema URI for the "em-nii" namespace (that was released with the original publication of the UPnP EnergyManagement service specification in the year 2013) was "<http://www.upnp.org/schemas/lp/em-NetworkInterfaceInfo-v1-20130630.xsd>". When the UPnP EnergyManagement service specification is subsequently updated in the year 2014, the URI for the updated version of the "em-nii" namespace will be "<http://www.upnp.org/schemas/lp/em-NetworkInterfaceInfo-v2-20140531.xsd>".

In addition to the dated schema URIs that are associated with each namespace, each namespace also has a set of undated schema URIs. These undated schema URIs have two distinct formats with slightly different meanings:

Form 2: "http://www.upnp.org/schemas/lp/" **schema-root-name** "-v" **ver**
where **ver** is described above.

Form 3: "http://www.upnp.org/schemas/lp/" **schema-root-name**

Form 2 of the undated schema URI is always linked to the most recent release of the schema that represents the version of the namespace indicated by **ver**. For example, the undated URI ".../lp/em-NetworkInterfaceInfo-v2.xsd" is linked to the most recent schema release of version 2 of the "em-nii" namespace. Therefore, on May 31, 2014 (20140531), the undated schema URI was linked to the schema that is otherwise known as ".../lp/em-NetworkInterfaceInfo-v2-20060531.xsd". Furthermore, if the schema for version 2 of the "em-nii" namespace was ever re-released, for example to fix a typo in the 20060531 schema, then the same undated schema URI (".../lp/em-NetworkInterfaceInfo-v2.xsd") would automatically be updated to link to the updated version 2 schema for the "em-nii" namespace.

Form 3 of the undated schema URI is always linked to the most recent release of the schema that represents the highest version of the namespace that has been published. For example, on June 30, 2013 (20130630), the undated schema URI ".../lp/em-NetworkInterfaceInfo.xsd" was linked to the schema that is otherwise known as ".../lp/em-NetworkInterfaceInfo-v1-20130630.xsd". However, on May 31, 2014 (20140531), that same undated schema URI will link to the schema that is otherwise known as ".../lp/em-NetworkInterfaceInfo-v2-20140531.xsd".

When referencing a schema URI within an XML instance document or a referencing XML schema document, the following usage rules apply:

- All instance documents, whether generated by a service or a control point, shall use Form 3.
- All UPnP EnergyManagement published schemas that reference other UPnP schemas shall also use Form 3.

Within an XML instance document, the definition for the `schemaLocation` attribute comes from the XML Schema namespace “<http://www.w3.org/2002/XMLSchema-instance>”. A single occurrence of the attribute can declare the location of one or more schemas. The `schemaLocation` attribute value consists of a whitespace separated list of values that is interpreted as a namespace name followed by its schema location URL. This pair-sequence is repeated as necessary for the schemas that need to be located for this instance document.

In addition to the schema URI naming and usage rules described above, each released schema shall contain a `version` attribute in the `<schema>` root element. Its value shall correspond to the format:

ver “-” **yyyymmdd** where **ver** and **yyyymmdd** are described above.

The `version` attribute provides self-identification of the namespace version and release date of the schema itself. For example, within the original schema released for the “rsc-event” namespace (`.../rsc-event-v2-20020625.xsd`), the `<schema>` root element contains the following attribute: `version="2-20020625"`.

4.3.3 Namespace Usage Examples

The `schemaLocation` attribute for XML instance documents comes from the XML Schema instance namespace “<http://www.w3.org/2002/XMLSchema-instance>”. A single occurrence of the attribute can declare the location of one or more schemas. The `schemaLocation` attribute value consists of a whitespace separated list of values: namespace name followed by its schema location URL. This pair-sequence is repeated as necessary for the schemas that need to be located for this instance document.

Example 1:

Sample *NetworkInterfaceInfo* state variable XML Instance Document. Note that the references to the UPnP EnergyManagement schemas do not contain any version or release date information. In other words, the references follow Form 3 from above. Consequently, this example is valid for all releases of the UPnP EnergyManagement service specifications.

```
<?xml version="1.0" encoding="UTF-8"?>
< NetworkInterfaceInfo
  xmlns="urn:schemas-upnp-org:lp:em-NetworkInterfaceInfo"
  xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
  xsi:schemaLocation="urn:schemas-upnp-org:lp:em-NetworkInterfaceInfo
http://www.upnp.org/schemas/lp/em-NetworkInterfaceInfo.xsd"
  < DeviceInterface>
    ...
  </ DeviceInterface>
</ NetworkInterfaceInfo>
```

4.4 Vendor-defined Extensions

Whenever vendors create additional vendor-defined state variables, actions or properties, their assigned names and XML representation shall follow the naming conventions and XML rules as specified below.

4.4.1 Vendor-defined Action Names

Vendor-defined action names shall begin with “**X**”. Additionally, it should be followed by an ICANN assigned domain name owned by the vendor followed by the underscore character (“_”). It shall then be followed by the vendor-assigned action name. The

vendor-assigned action name shall not contain a hyphen character (“-”, 2D Hex in UTF-8) nor a hash character (“#”, 23 Hex in UTF-8). Vendor-assigned action names are case sensitive. The first character of the name shall be a US-ASCII letter (“A”-“Z”, “a”-“z”), US-ASCII digit (“0”-“9”), an underscore (“_”), or a non-experimental Unicode letter or digit greater than U+007F. Succeeding characters shall be a US-ASCII letter (“A”-“Z”, “a”-“z”), US-ASCII digit (“0”-“9”), an underscore (“_”), a period (“.”), a Unicode combining char, an extender, or a non-experimental Unicode letter or digit greater than U+007F. The first three letters shall not be “XML” in any combination of case.

4.4.2 Vendor-defined State Variable Names

Vendor-defined state variable names shall begin with “**X**”. Additionally, it should be followed by an ICANN assigned domain name owned by the vendor, followed by the underscore character (“_”). It shall then be followed by the vendor-assigned state variable name. The vendor-assigned state variable name shall not contain a hyphen character (“-”, 2D Hex in UTF-8). Vendor-assigned action names are case sensitive. The first character of the name shall be a US-ASCII letter (“A”-“Z”, “a”-“z”), US-ASCII digit (“0”-“9”), an underscore (“_”), or a non-experimental Unicode letter or digit greater than U+007F. Succeeding characters shall be a US-ASCII letter (“A”-“Z”, “a”-“z”), US-ASCII digit (“0”-“9”), an underscore (“_”), a period (“.”), a Unicode combining char, an extender, or a non-experimental Unicode letter or digit greater than U+007F. The first three letters shall not be “XML” in any combination of case.

4.4.3 Vendor-defined XML Elements and attributes

UPnP vendors may add non-standard elements and attributes to a UPnP standard XML document, such as a device or service description. Each addition shall be scoped by a vendor-owned XML namespace. Arbitrary XML shall be enclosed in an element that begins with “**X**,” and this element shall be a sub element of a standard complex type. Non-standard attributes may be added to standard elements provided these attributes are scoped by a vendor-owned XML namespace and begin with “**X**”.

4.4.4 Vendor-defined Property Names

UPnP vendors may add non-standard properties to the EnergyManagement service. Each property addition shall be scoped by a vendor-owned namespace. The vendor-assigned property name shall not contain a hyphen character (“-”, 2D Hex in UTF-8). Vendor-assigned property names are case sensitive. The first character of the name shall be a US-ASCII letter (“A”-“Z”, “a”-“z”), US-ASCII digit (“0”-“9”), an underscore (“_”), or a non-experimental Unicode letter or digit greater than U+007F. Succeeding characters shall be a US-ASCII letter (“A”-“Z”, “a”-“z”), US-ASCII digit (“0”-“9”), an underscore (“_”), a period (“.”), a Unicode combining char, an extender, or a non-experimental Unicode letter or digit greater than U+007F. The first three letters shall not be “XML” in any combination of case.

5 Service modelling definitions

5.1 Service type

The following service type identifies a service that is compliant with this template:

urn:schemas-upnp-org:service:EnergyManagement:1

EnergyManagement service is used herein to refer to this service type.

5.2 Security feature

5.2.1 Overview

In the specification, if support for the Security Feature is referenced, this indicates that the device implements the UPnP DeviceProtection service [UPnP DP].

5.2.2 Restrictable and non-restrictatable actions

The EnergyManagement service actions defined in this specification have the *Restrictable*, *Non-Restrictable* assignments as indicated in Table 4.

Table 4 — Assignment of Restrictable/Non-Restrictable Roles

Action Name	Restrictable/Non-Restrictable to Indicated Role ^a			
	<u>Public</u>	<u>Basic</u>	<u>Admin</u>	<u>Vendor Defined</u>
<u>GetInterfaceInfo()</u>	NO	NO	NO	NO
<u>ServiceSubscription()</u>	NO	NO	NO	NO
<u>ServiceRenewal()</u>	NO	NO	NO	NO
<u>ServiceRelease()</u>	NO	NO	NO	NO
^a A YES value in the table indicates that the action shall be Restrictable when the Security Feature is supported and a control point with only the Role indicated shall not have Action level access and shall receive an error code 606 (see UPnP Device Architecture [ISO/IEC 29341-1]) in response to the action invocation. A NO value in the table indicates that the action shall be Non-Restrictable, meaning that even if the Security Feature is supported all control points shall have Action level access when control point invoking the action and shall not receive an error code 606 based on the Security Feature.				

5.3 State variables

5.3.1 General

For a first-time reader, it might be more helpful to read the action definitions before reading the state variable definitions.

5.3.2 State variable overview

Table 5 lists all of the state variables defined for the EnergyManagement service.

Table 5 — State variables

Variable Name	R/A ^a	Data Type	Allowed Value	Default Value	Eng. Units
<u>NetworkInterfaceInfo</u>	<u>R</u>	<u>string (XML document)</u>	See 5.3.3		
<u>ProxiedNetworkInterfaceInfo</u>	<u>R</u>	<u>string (XML document)</u>	See 5.3.4		
<u>A_ARG_TYPE_Duration</u>	<u>CR</u> ^b	<u>string</u>	See 5.3.5		
<u>A_ARG_TYPE_ServiceSubscriptionID</u>	<u>CR</u> ^b	<u>ui4</u>	See 5.3.6		
<u>A_ARG_TYPE_UniqueServiceName</u>	<u>CR</u> ^b	<u>string</u>	See 5.3.7		
<u>A_ARG_TYPE_URI</u>	<u>CR</u> ^b	<u>uri</u>	See 5.3.8		
<i>Non-standard state variables implemented by a UPnP vendor go here</i>	<u>X</u>	<i>TBD</i>	<i>TBD</i>	<i>TBD</i>	<i>TBD</i>
^a For a device this column indicates whether the state variable shall be implemented or not, where <u>R</u> = required, <u>A</u> = allowed, <u>CR</u> = conditionally required, <u>CA</u> = conditionally allowed, <u>X</u> = Non-standard, add <u>-D</u> when deprecated (e.g., <u>R-D</u> , <u>A-D</u>). ^b <u>CR</u> = conditionally required. See referenced subclause for implementation requirements.					

5.3.3 NetworkInterfaceInfo

This required state variable shall be supported for the EnergyManagement service GetInterfaceInfo() action. NetworkInterfaceInfo out argument in the EnergyManagement service GetInterfaceInfo() action shall represent information about one or more network interfaces for the device. The following is the XML template for the NetworkInterfaceInfo state variable:

```
<?xml version="1.0" encoding="UTF-8"?>
```

```

<NetworkInterfaceInfo xsi:schemaLocation="urn:schemas-upnp-org:lp:em-
NetworkInterfaceInfo http://www.upnp.org/schemas/lp/em-
NetworkInterfaceInfo.xsd" xmlns="urn:schemas-upnp-org:lp:em-
NetworkInterfaceInfo" xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance">
  <DeviceInterface>
    <DeviceUUID>UPnP device UUID</DeviceUUID>
    <FriendlyName>UPnP device friendly name</FriendlyName>
    <NetworkInterface>
      <SystemName>Device network interface system name</SystemName>
      <Description>Device network interface text
description</Description>
      <MacAddress>Device network interface MAC address</MacAddress>
      <InterfaceType>Device network Interface type</InterfaceType>
      <NetworkInterfaceMode>Device network Interface
mode</NetworkInterfaceMode>
      <AssociatedIpAddresses>
        <Ipv4>Device network interface IPv4 address</Ipv4>
        <Ipv6>Device network interface IPv6 address</Ipv6>
      </AssociatedIpAddresses>
      <WakeOnPattern>Device network interface wake on
pattern</WakeOnPattern>
      <WakeSupportedTransport>Device network interface wake on pattern
transport</WakeSupportedTransport>
      <MaxWakeOnDelay>Device network interface wake on pattern
delay</MaxWakeOnDelay>
      <DozeDuration>Device network interface doze duration</DozeDuration>
    </NetworkInterface>
    <NetworkInterface>
      . . . Additional <NetworkInterface> elements . . .
    </NetworkInterface>
  </DeviceInterface>
  <DeviceInterface>
    . . . Additional <DeviceInterface> elements . . .
  </DeviceInterface>
</NetworkInterfaceInfo>

```

<?xml>

Allowed. Case sensitive.

<NetworkInterfaceInfo>

Required. <XML>. Shall include a namespace declaration for the EnergyManagement service Common Datastructures Schema ("urn:schemas-upnp-org:em:nii-events"). This is the base wrapper element for the state variable. Shall include one or more of the <DeviceInterface> elements for each UPnP device network interfaces being described.

<DeviceInterface>

Required. <XML>. One or more elements. Shall include the following elements to describe the network interfaces for a UPnP device:

<DeviceUUID>

Required. xsd:string. Maximum length 70 characters. Exactly one element. The UPnP device-UUID that is used by the UPnP Device containing this service ISO/IEC 29341-1. For proxied information the field contains the UPnP device-UUID of the proxied device.

<FriendlyName>

Required. xsd:string. Maximum length 64 characters. Exactly one element. This field contains the device's friendlyName ISO/IEC 29341-1. For proxied information the field contains the friendlyName of the proxied device. If the friendlyName of the device is greater than 64 characters, it shall be truncated to 64 characters.

<NetworkInterface>

Required. <XML>. One or more elements. Each instance of the element is to describe a network interface for a UPnP Device. Shall include the following elements to describe a physical network interface for a UPnP device:

<SystemName>

Required. xsd:string. Unique name. Maximum length 64 characters. Exactly one element. This is the name provided by the underlying system to the network interface. The names are unique for a given interface on the device.

NOTE Examples: eth0, wlan2.

<Description>

Allowed. xsd:string. Maximum length 256 characters. Zero or one element. Textual description of the interface. It should contain the hardware description of the network interface. For example, it might include manufacturer name or model number. The format is specified in ISO/IEC 29341-4-12Appendix B.3.

<MACAddress>

Required. xsd:string. Exactly 17 characters. Exactly one element. The MAC-48 address of the physical interface in human-friendly form represented as a string in six groups of two hexadecimal digits, separated by colons (:), in transmission order.

<InterfaceType>

Required. xsd:NMTOKEN. Exactly one element. Type of this physical interface as an enumerated string. Values are:

- "Ethernet"
- "Wi-Fi"
- "HPNAoverCoax"
- "HomePlug"
- "MoCA"
- "1905"
- "Other"

<NetworkInterfaceMode>

Required. xsd:NMTOKEN. Exactly one element. Operation mode of a network interface. Enumeration of string values and their definition are as follows:

- "Unimplemented": No information regarding any low power interface mode of this network interface;
- "IP-up": IP interface is fully operational. UPnP services may be available;
- "IP-up-Periodic": IP interface will be periodically unavailable for durations of 2 second or less when the physical interface is placed in a low power mode of operation;
- "IP-down-no-Wake": IP interface is down;
- "IP-down-with-WakeOn": IP interface is down. IP interface can be woken externally;
- "IP-down-with-WakeAuto": IP interface is down in doze state for duration of more than 2 seconds. IP interface will be woken internally;
- "IP-down-with-WakeOnAuto": IP interface is down in doze state for duration of more than 2 seconds. IP interface will be woken internally or can be woken externally.

<AssociatedIPAddresses>

Conditionally Required. xsd:string. Shall be included when at least one IP address is associated with the enclosing <networkInterface> element (i.e. MAC address). A list of IP addresses that use this network interface. Limit:17 addresses. In XML the list is a sequence of IP addresses. IP address may contain any combination of <Ipv4> or <Ipv6> elements. If the network interface has no IP addresses assigned, the <AssociateIPAddresses> element should be absent.

<Ipv4>

IPv4 address are of the form nnn.nnn.nnn.nnn where n is a decimal digit and leading zeros may be omitted.

<Ipv6>

IPv6 address of either the first or second form described in [IETF RFC 4291]. The first is the preferred form of x:x:x:x:x:x:x:x, where the 'x's are one to four hexadecimal digits of the eight 16-bit pieces of the address. The second is the special compressed syntax that uses "::" to indicate one or more groups of 16 bits of zeros. The additional restriction from IETF RFC 5952 that requires letters used in hex digits to be lowercase also applies.

<WakeOnPattern>

Allowed. xsd:hexBinary. Zero or one element. Length unlimited. Wake-up bit pattern, expressed in hex. This is the entire xsd:hexBinary that is expected by the network interface. If the expected pattern is a sequence of "1" bits followed by multiple iterations of the MAC address, then this parameter will include all bits, including all iterations of the MAC address. If a security string is expected after the MAC address iterations, those bits shall be included, as well.

<WakeSupportedTransport>

Allowed. xsd:NMTOKEN. Zero or one element. Supported transport mechanisms for receipt of the <WakeOnPattern> value as an enumerated string. Values are:

- "UDP-Broadcast"
- "UDP-Unicast"
- "TCP-Unicast"
- "Other"

<MaxWaitOnDelay>

Allowed. xsd:unsignedInt. Zero or one element. Estimate of maximum time in seconds it would take from time <WakeOnPattern> value is received until ssdp:alive messages are sent. A value of 0 (zero) indicates that no estimate is provided and the value is unknown.

<DozeDuration>

Allowed. xsd:unsignedInt. Zero or one element. Time in milliseconds that interface is configured to doze. This value is only meaningful if "IP-down-with-WakeAuto", "IP-down-with-WakeOnAuto", or "IP-up-Periodic" <NetworkInterfaceMode> values are supported.

- If <NetworkInterfaceMode> is "IP-up", this indicates the internally-set duration of the next future-occurring doze state "IP-down-with-WakeAuto" or "IP-down-with-WakeOnAuto" operation mode.
- If <NetworkInterfaceMode> is "IP-down-with-WakeAuto" or "IP-down-with-WakeOnAuto", this indicates the remaining time until the interface is automatically enabled.
- If <NetworkInterfaceMode> is "IP-up-Periodic", this indicates the periodic sleep interval.

A 0 (zero) value means this parameter is not set.

An example XML for the NetworkInterfaceInfo state variable:

```
<?xml version="1.0" encoding="UTF-8"?>
<NetworkInterfaceInfo xsi:schemaLocation="urn:schemas-upnp-org:lp:em-
NetworkInterfaceInfo http://www.upnp.org/schemas/lp/em-
NetworkInterfaceInfo.xsd" xmlns="urn:schemas-upnp-org:lp:em-
NetworkInterfaceInfo" xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance">
  <DeviceInterface>
    <DeviceUUID>uuid:00000000-0000-1010-8000-4424991A912</DeviceUUID>
```

```

<FriendlyName>My Family Room TV</FriendlyName>
<NetworkInterface>
  <SystemName>eth0</SystemName>
  <Description>Ethernet 802.3 NIC</Description>
  <MacAddress>54:42:49:91:A9:12</MacAddress>
  <InterfaceType>Ethernet</InterfaceType>
  <NetworkInterfaceMode>IP-up</NetworkInterfaceMode>
  <AssociatedIpAddresses>
    <Ipv4>192.168.1.125</Ipv4>
    <Ipv6>805b:2d9d:dc28:0:0:fc57:d4c8:1fff</Ipv6>
  </AssociatedIpAddresses>
  <WakeOnPattern>
    FFFFFFFF54424991A91254424991A91254424991A91254424991A91254424991A9125442
    4991A91254424991A91254424991A91254424991A91254424991A91254424991A91254424991
    A91254424991A91254424991A91254424991A91254424991A91254424991A91254424991A912
    </WakeOnPattern>
  <WakeSupportedTransport>UDP-Broadcast</WakeSupportedTransport>
  <MaxWakeOnDelay>5</MaxWakeOnDelay>
  <DozeDuration>0</DozeDuration>
</NetworkInterface>
</DeviceInterface>
</NetworkInterfaceInfo>

```

5.3.4 **ProxiedNetworkInterfaceInfo**

This required state variable shall be supported for the EnergyManagement service [GetInterfaceInfo\(\)](#) action. The [ProxiedNetworkInterfaceInfo](#) output argument in the EnergyManagement service [GetInterfaceInfo\(\)](#) action shall represent information received from one or more EnergyManagement services in physical devices other than the one with this instance of the EnergyManagement service. The XML schema for the [ProxiedNetworkInterfaceInfo](#) state variable is identical to that of the [NetworkInterfaceInfo](#) state variable defined in 5.3.3, except it can contain zero <DeviceInterface> elements when it contains no proxied device information, but it supports proxying. If the service does not support proxying, it shall be set to an empty XML element (i.e. contains no text between the start and end tags; e.g. <NetworkInterfaceInfo></NetworkInterfaceInfo>).

5.3.5 **A ARG TYPE Duration**

This conditionally required state variable shall be supported if the EnergyManagement service implements the [ServiceSubscription\(\)](#) and [ServiceRenewal\(\)](#) actions. This state variable is introduced to provide type information for the [Duration](#) and [DurationRequest](#) arguments in various actions. [DurationRequest](#) input and [Duration](#) output arguments in EnergyManagement service actions shall represent the duration of time using the format of the res@duration property as defined in ISO/IEC 29341-4-12. The format of this state variable is a string with a value of "0" indicating infinite time.

5.3.6 **A ARG TYPE ServiceSubscriptionID**

This conditionally required state variable shall be supported if the EnergyManagement service implements the [ServiceSubscription\(\)](#), [ServiceRenewal\(\)](#) or [ServiceRelease\(\)](#) actions. This state variable is introduced to provide type information for the [ServiceSubscriptionID](#) argument in various actions. [ServiceSubscriptionID](#) input and output arguments in EnergyManagement service actions shall represent a numerical value that is unique across all service subscriptions created with the [ServiceSubscription\(\)](#) action. The format of this state variable is a positive integer.

5.3.7 **A ARG TYPE UniqueServiceName**

This conditionally required state variable shall be supported if the EnergyManagement service implements the [ServiceSubscription\(\)](#) action. This state variable is introduced to provide type information for the [UniqueServiceName](#) argument in the [ServiceSubscription\(\)](#) action. [UniqueServiceName](#) input argument in the EnergyManagement service actions shall indicate the specific service in the device to

be subscribed. The format of this state variable is a string as defined in ISO/IEC 29341-1

5.3.8 A ARG TYPE URI

This conditionally required state variable shall be supported if the EnergyManagement service implements the ServiceSubscription() action. This state variable is introduced to provide type information for the ResourceURI argument in the ServiceSubscription() action. ResourceURI input argument in the EnergyManagement service actions shall be properly escaped URIs as described in IETF RFC 2396. In addition, ResourceURI argument shall be escaped according to the requirements of IETF RFC 1738.

5.4 Eventing and moderation

Table 6 lists all of the state variables defined for the EnergyManagement service and which state variables are evented and whether they are moderated.

Table 6 — Event moderation

| Variable Name | Evented | Moderate
d Event | Min Event
Interval ^a
(seconds) | Logical
Combination | Min Delta
per Event ^b |
|--|------------|---------------------|---|------------------------|-------------------------------------|
| <u>NetworkInterfaceInfo</u> | <u>YES</u> | <u>NO</u> | | | |
| <u>ProxiedNetworkInterfaceInfo</u> | <u>NO</u> | <u>NO</u> | | | |
| <u>A ARG TYPE Duration</u> | <u>NO</u> | <u>NO</u> | | | |
| <u>A ARG TYPE ServiceSubscriptionID</u> | <u>NO</u> | <u>NO</u> | | | |
| <u>A ARG TYPE UniqueServiceName</u> | <u>NO</u> | <u>NO</u> | | | |
| <u>A ARG TYPE URI</u> | <u>NO</u> | <u>NO</u> | | | |
| <i>Non-standard state variables
implemented by a UPnP vendor go here</i> | <i>TBD</i> | <i>TBD</i> | <i>TBD</i> | <i>TBD</i> | <i>TBD</i> |
| ^a Max event rate is determined by N , where $Rate = 1/N$, where N is the Min Event Interval in seconds.
^b $(N) * (allowedValueRange Step)$ | | | | | |

5.5 Actions

5.5.1 Overview

The following subclauses define the various EnergyManagement service actions.

Except where noted, if an invoked action returns an error, the state of the device will be unaffected.

Table 7 lists all of the actions defined for the EnergyManagement service.

Table 7 — Actions

| Name | R/A ^a | Control Point R/A ^b |
|--|--------------------------|--------------------------------|
| <u>GetInterfaceInfo()</u> | <u>R</u> | <u>R</u> |
| <u>ServiceSubscription()</u> | <u>A</u> | <u>A</u> |
| <u>ServiceRenewal()</u> | <u>A</u> | <u>A</u> |
| <u>ServiceRelease()</u> | <u>A</u> | <u>A</u> |
| <i>Non-standard actions implemented by an UPnP vendor go here.</i> | <u>X</u> | <u>X</u> |
| <p>^a For a device this column indicates whether the action shall be implemented or not, where <u>R</u> = required, <u>A</u> = allowed, <u>CR</u> = conditionally required, <u>CA</u> = conditionally allowed, <u>X</u> = Non-standard, add <u>-D</u> when deprecated (e.g., <u>R-D</u>, <u>A-D</u>).</p> <p>^b For a control point this column indicates whether a control point shall be capable of invoking this action, where <u>R</u> = required, <u>A</u> = allowed, <u>CR</u> = conditionally required, <u>CA</u> = conditionally allowed, <u>X</u> = Non-standard, add <u>-D</u> when deprecated (e.g., <u>R-D</u>, <u>A-D</u>).</p> | | |

Non-standard actions shall be implemented in such a way that they do not interfere with the basic operation of the EnergyManagement service, that is: these actions shall be allowed and do not need to be invoked for the EnergyManagement service to operate normally.

5.5.2 GetInterfaceInfo()

This required action is used to get the current information and current mode of the power state for all of the network interfaces that the service can be discovered on. It can also supply information received from EnergyManagement services on other physical devices through the ProxiedNetworkInterfaceInfo parameter.

5.5.2.1 Arguments

Table 8 lists all of the input and output arguments for the GetInterfaceInfo() action.

Table 8 — Arguments for GetInterfaceInfo()

| Argument | Direction | Related State Variable |
|------------------------------------|------------|------------------------------------|
| <u>NetworkInterfaceInfo</u> | <u>OUT</u> | <u>NetworkInterfaceInfo</u> |
| <u>ProxiedNetworkInterfaceInfo</u> | <u>OUT</u> | <u>ProxiedNetworkInterfaceInfo</u> |

5.5.2.2 Device Requirements

If the *Security Feature* is supported the action is defined as a *Non-Restrictable* action and the targeted device is not allowed to restrict its invocation by any control point.

5.5.2.3 Control Point Requirements When Calling The Action

None.

5.5.2.4 Dependency on state

Return values are dependent on current values of the NetworkInterfaceInfo and ProxiedNetworkInterfaceInfo state variables.

5.5.2.5 Effect on state

None.

Table 9 lists all of the possible error codes for the GetInterfaceInfo() action.

Table 9 — Error codes for GetInterfaceInfo()

| errorCode | errorDescription | Description |
|-----------|------------------|--|
| 400-499 | TBD | See UPnP Device Architecture section on Control. |
| 500-599 | TBD | See UPnP Device Architecture section on Control. |
| 600-699 | TBD | See UPnP Device Architecture section on Control. |

5.5.3 ServiceSubscription()

This allowed action notifies the device that the control point is requesting resources for general or specific uses. When this action is implemented the ServiceRenewal() and ServiceRelease() actions shall also be implemented.

5.5.3.1 Arguments

Table 10 lists all of the input and output arguments for the ServiceSubscription() action.

Table 10 — Arguments for ServiceSubscription()

| Argument | Direction | Related State Variable |
|--------------------------|-----------|-------------------------------------|
| <u>UniqueServiceName</u> | <u>IN</u> | <u>A_ARG_TYPE_UniqueServiceName</u> |
| <u>ResourceURI</u> | <u>IN</u> | <u>A_ARG_TYPE_URI</u> |

| Argument | Direction | Related State Variable |
|------------------------------|------------|---|
| <u>DurationRequest</u> | <u>IN</u> | <u>A_ARG_TYPE_Duration</u> |
| <u>ServiceSubscriptionID</u> | <u>OUT</u> | <u>A_ARG_TYPE_ServiceSubscriptionID</u> |
| <u>Duration</u> | <u>OUT</u> | <u>A_ARG_TYPE_Duration</u> |

The UniqueServiceName input argument is used by the control point to indicate the specific service in the device to be subscribed. The information contained in the argument is the values of USN defined in ISO/IEC 29341-1.

The ResourceURI input argument is used by the control point to indicate a specific content binary of interest or empty. The A_ARG_TYPE_URI state variable is defined in 5.3.8.

The DurationRequest input argument indicates the duration the resources are requested for. A value of "0" requests a duration of infinite. The syntax of the A_ARG_TYPE_Duration state variable is defined in 5.3.5.

The ServiceSubscriptionID output argument is an identifier set by the device that is unique to each service subscription request. The syntax of the A_ARG_TYPE_ServiceSubscriptionID state variable is defined in 5.3.6.

The Duration output argument is the actual duration given to the subscription request by the device. The device may round the duration up or down to meet supported time increments. The syntax of the A_ARG_TYPE_Duration state variable is defined in 5.3.5.

5.5.3.2 Device Requirements

If the *Security Feature* is supported the action is defined as a *Non-Restrictable* action and the targeted device is not allowed to restrict its invocation by any control point.

5.5.3.3 Control Point Requirements When Calling The Action

None.

5.5.3.4 Dependency on state

None.

5.5.3.5 Effect on state

A device may associate specific resources with the request for a specific content binary indicated by A_ARG_TYPE_URI. If A_ARG_TYPE_URI is empty, service wide resources may be needed. For example, if a URI points to live content, the device may not need to keep storage resources awake. In contrast, if a URI points to pre-recorded content, the device may not need to keep tuner resources awake.

Even when the UPnP service identified by the UniqueServiceName input argument does not deal with content binaries, the device may still be able to identify all resources needed for that service and make those resources available. In all cases, the architecture is designed to give the device ultimate authority over its resources.

5.5.3.6 Errors

Table 11 lists all of the possible error codes for the ServiceSubscription() action.

Table 11 — Error Codes for ServiceSubscription()

| errorCode | errorDescription | Description |
|-------------------|-------------------------------|--|
| 402 | Invalid Args | Not enough in args, no in arg by that name, one or more in args are of the wrong data type. |
| 401, 403-499 | TBD | See UPnP Device Architecture section on Control. |
| 501 | Action Failed | To indicate that the current state of service prevents invoking the action. |
| 500, 502-599 | TBD | See UPnP Device Architecture section on Control. |
| 600 | The argument value is invalid | The argument value is invalid. |
| 601 | Argument Value Out of Range | An argument value is less than the minimum or more than the maximum value of the allowedValueRange, or is not in the allowedValueList. |
| 603 | Out of Memory | To indicate that device does not have sufficient resources available to complete the action. |
| 605 | String Argument Too Long | A string argument is too long for the device to handle properly. |
| 602, 604, 606-699 | TBD | See UPnP Device Architecture section on Control. |

NOTE This action will always return a valid ServiceSubscriptionID even if no associated resources are going to change power status for the UniqueServiceName input argument. To the control point the request is always valid unless one the UPnP Device Architecture [ISO/IEC 29341-1] errors (errors 400-699) are generated.

5.5.4 ServiceRenewal()

This allowed action that notifies the device that the control point is renewing a resource request. When this action is implemented the ServiceSubscription() and ServiceRelease() actions shall also be implemented.

5.5.4.1 Arguments

Table 12 lists all of the input and output arguments for the ServiceRenewal() action.

Table 12 — Arguments for ServiceRenewal()

| Argument | Direction | Related State Variable |
|------------------------------|------------|---|
| <u>DurationRequest</u> | <u>IN</u> | <u>A_ARG_TYPE_Duration</u> |
| <u>ServiceSubscriptionID</u> | <u>IN</u> | <u>A_ARG_TYPE_ServiceSubscriptionID</u> |
| <u>Duration</u> | <u>OUT</u> | <u>A_ARG_TYPE_Duration</u> |

The DurationRequest input argument indicates the duration the resources are requested for. A duration value of "0" requests a duration of infinite. The syntax of the A_ARG_TYPE_Duration state variable is defined in 5.3.5.

The ServiceSubscriptionID input argument is an identifier set by the device in a previous response to the ServiceSubscription() action. The syntax of the ServiceSubscriptionID state variable is defined in 5.3.6.

The Duration output argument is the actual duration given to the subscription request by the device. The device may round the duration up or down to meet supported time increments. The syntax of the A_ARG_TYPE_Duration state variable is defined in 5.3.5.

5.5.4.2 Device Requirements

If the *Security Feature* is supported the action is defined as a *Non-Restrictable* action and the targeted device is not allowed to restrict its invocation by any control point.

5.5.4.3 Control Point Requirements When Calling The Action

None.

5.5.4.4 Dependency on state

None.

5.5.4.5 Effect on state

None.

5.5.4.6 Errors

Table 13 lists all of the possible error codes for the [ServiceRenewal\(\)](#) action.

Table 13 — Error codes for [ServiceRenewal\(\)](#)

| errorCode | errorDescription | Description |
|-----------|------------------|--|
| 400-499 | TBD | See UPnP Device Architecture section on Control. |
| 500-599 | TBD | See UPnP Device Architecture section on Control. |
| 600-699 | TBD | See UPnP Device Architecture section on Control. |
| 700 | | Reserved for future extensions. |
| 701 | Invalid ID | The ServiceSubscriptionID input argument is not recognized |

5.5.5 [ServiceRelease\(\)](#)

This allowed action notifies the device that the control point is no longer requesting resources for the associated [ServiceSubscriptionID](#) input argument. When this action is implemented the [ServiceSubscription\(\)](#) and [ServiceRenewal\(\)](#) actions shall also be implemented.

5.5.5.1 Arguments

Table 14 lists all of the input and output arguments for the [ServiceRelease\(\)](#) action.

Table 14 — Arguments for [ServiceRelease\(\)](#)

| Argument | Direction | Related State Variable |
|--|---------------------------|---|
| <u>ServiceSubscriptionID</u> | <u>IN</u> | <u>A_ARG_TYPE_ServiceSubscriptionID</u> |

The [ServiceSubscriptionID](#) input argument is an identifier set by the device in a previous response to the [ServiceSubscription\(\)](#) action. The syntax of the [A_ARG_TYPE_ServiceSubscriptionID](#) state variable is defined in 5.3.6

5.5.5.2 Device Requirements

If the *Security Feature* is supported the action is defined as a *Non-Restrictable* action and the targeted device is not allowed to restrict its invocation by any control point.

5.5.5.3 Control Point Requirements When Calling The Action

None.

5.5.5.4 Dependency on state

None.

5.5.5.5 Effect on state

None.

5.5.5.6 Errors

Table 15 lists all of the possible error codes for the [ServiceRelease\(\)](#) action.

Table 15 — Error codes for ServiceRelease()

| errorCode | errorDescription | Description |
|-----------|------------------|--|
| 400-499 | TBD | See UPnP Device Architecture section on Control. |
| 500-599 | TBD | See UPnP Device Architecture section on Control. |
| 600-699 | TBD | See UPnP Device Architecture section on Control. |
| 700 | | Reserved for future extensions. |
| 701 | Invalid ID | The ServiceSubscriptionID input argument is not recognized |

6 Theory of operations

6.1 Overview

The EnergyManagement service functionality is built on two fundamental premises: 1) a physical device is the only entity capable of knowing all of its internal resources and considerations for management of energy and 2) a modern physical device implements multiple functionalities so it cannot be considered a monolithic entity that is either “on” or “off”. This is in stark contrast to the existing UPnP LowPower:1 service which attempted to only allow external control of a physical device considered to be monolithic.

If a physical device decides to reduce energy by placing one or more of its network interfaces in a reduced power state there are two implications to normal operations: 1) traditional discovery of the physical device could be impaired or unusable; and 2) the physical device could be unaware of the intentions of control points.

EnergyManagement service functionality does recognize and embrace that external entities (i.e. control points) desire to make requests of the resources of a physical device. External entities can make requests using WakeOnPatterns and service subscription. However, though control points may be able to make these requests, the architecture is designed to give the device ultimate authority over its resources.

The ProxiedNetworkInterfaceInfo state variable allows the resources of a physical device to be discovered even if its network interfaces are currently unavailable.

6.2 WakeOnPattern theory of operation

6.2.1 Overview

Various physical network interface technologies support a mode of operation that has all functions of the network interface shut down, other than the ability to recognize bits that appear on the network interface. It is necessary for the network interface to be powered for this function to operate.

The most common reaction to a received bit pattern is to boot the operating system of the device. Other behaviors are also possible. These other behaviors are generally defined by the manufacturer of the network interface.

The most commonly used bit pattern is hex:FFFFFFFFFFFF (48 “1” bits) followed by multiple repetitions of the network interface’s MAC address. This is often referred to as a “magic packet”. Other bit patterns are also possible, and not uncommon. These other bit patterns are generally defined by the manufacturer of the network interface, and are often proprietary to that manufacturer’s products.

If another device wants to invoke the behavior that a bit pattern will cause when received by a particular network interface, it can transmit the bit pattern in such a way that the bit pattern is delivered by the intervening network to the network interface. Depending on the nature of the intervening network, this is not always a simple task. It is made particularly complex by the fact that the network interface often does not have an IP address. Since the network interface is only looking for a particular sequence of bits, any bits that come before or after the desired bit pattern are of no consequence to the network interface. They are only important to the transport of the bits across the intervening network. Whatever link or transport protocol, addresses, or mechanisms will allow for the bit pattern to successfully arrive at the network