

INTERNATIONAL STANDARD

IEC
60287-3-2

First edition
1995-06

**Electric cables –
Calculation of the current rating –
Part 3-2:
Sections on operating conditions –
Economic optimization of power cable size**

*This **English-language** version is derived from the original **bilingual** publication by leaving out all French-language pages. Missing page numbers correspond to the French-language pages.*



Reference number
IEC 60287-3-2:1995(E)

Publication numbering

As from 1 January 1997 all IEC publications are issued with a designation in the 60000 series. For example, IEC 34-1 is now referred to as IEC 60034-1.

Consolidated editions

The IEC is now publishing consolidated versions of its publications. For example, edition numbers 1.0, 1.1 and 1.2 refer, respectively, to the base publication, the base publication incorporating amendment 1 and the base publication incorporating amendments 1 and 2.

Further information on IEC publications

The technical content of IEC publications is kept under constant review by the IEC, thus ensuring that the content reflects current technology. Information relating to this publication, including its validity, is available in the IEC Catalogue of publications (see below) in addition to new editions, amendments and corrigenda. Information on the subjects under consideration and work in progress undertaken by the technical committee which has prepared this publication, as well as the list of publications issued, is also available from the following:

- **IEC Web Site** (www.iec.ch)

- **Catalogue of IEC publications**

The on-line catalogue on the IEC web site (www.iec.ch/searchpub) enables you to search by a variety of criteria including text searches, technical committees and date of publication. On-line information is also available on recently issued publications, withdrawn and replaced publications, as well as corrigenda.

- **IEC Just Published**

This summary of recently issued publications (www.iec.ch/online_news/justpub) is also available by email. Please contact the Customer Service Centre (see below) for further information.

- **Customer Service Centre**

If you have any questions regarding this publication or need further assistance, please contact the Customer Service Centre:

Email: custserv@iec.ch
Tel: +41 22 919 02 11
Fax: +41 22 919 03 00

INTERNATIONAL STANDARD

IEC
60287-3-2

First edition
1995-06

Electric cables – Calculation of the current rating – Part 3-2: Sections on operating conditions – Economic optimization of power cable size

© IEC 1995 Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembe, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE

U

For price, see current catalogue

CONTENTS

	Page
FOREWORD	5
Clause	
0 Introduction	7
1 Scope	13
2 Normative references	13
3 Symbols	15
4 Calculation of total costs	17
5 Determination of economic conductor sizes	23
5.1 First approach: economic current range for each conductor in a series of sizes	23
5.2 Second approach: economic conductor size for a given load	25
Annexes	
A Examples of calculation of economic conductor sizes	29
B Mean conductor temperature and resistance	51

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ELECTRIC CABLES –
CALCULATION OF THE CURRENT RATING –****Part 3: Sections on operating conditions –
Section 2: Economic optimization of power cable size**

FOREWORD

- 1) The IEC (International Electrotechnical Commission) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international cooperation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of the IEC on technical matters, prepared by technical committees on which all the National Committees having a special interest therein are represented, express, as nearly as possible, an international consensus of opinion on the subjects dealt with.
- 3) They have the form of recommendations for international use published in the form of standards, technical reports or guides and they are accepted by the National Committees in that sense.
- 4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.

International Standard IEC 287-3-2 has been prepared by sub-committee 20A: High-voltage cables, of IEC technical committee 20: Electric cables.

This first edition of 287-3-2 cancels and replaces the first edition of IEC 1059 published in 1991 without technical changes.

IEC 287-1-1 replaces sections one and two of the second edition of IEC 287; IEC 287-2-1 replaces section three and annexes C and D of the second edition of IEC 287; IEC 287-3-1 replaces annexes A and B of the second edition of IEC 287.

The text of this standard is based on the following documents:

DIS	Report on voting
20A(CO)131	20A(CO)139

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

Annexes A and B are for information only.

0 Introduction

IEC 287 has been divided into three parts and sections so that revisions of, and additions to, the document can be carried out more conveniently.

Each part is divided into sections which are published as separate standards.

Part 1: Current rating equations (100 % load factor) and calculation of losses

Part 2: Thermal resistance

Part 3: Sections on operating conditions

This section was previously IEC 1059.

0.1 General part

The procedure generally used for the selection of a cable size leads to the minimum admissible cross-sectional area, which also minimizes the initial investment cost of the cable. It does not take into account the cost of the losses that will occur during the life of the cable.

The increasing cost of energy, together with the high energy losses which follow from the operating temperatures possible with the newer insulating materials (e.g. 90 °C for XLPE and EPR), now requires that cable size selection be considered on wider economic grounds. Rather than minimizing the initial cost only, the sum of the initial cost and the cost of the losses over the economic life of the cable should also be minimized. For this latter condition a larger size of conductor than would be chosen based on minimum initial cost will lead to a lower power loss for the same current and will, when considered over its economic life, be much less expensive.

The future costs of energy losses during the economic life of the cable can be calculated by making suitable estimates of load growth and cost of energy. The most economical size of conductor is achieved when the sum of the future costs of energy losses and the initial cost of purchase and installation are minimized.

The saving in overall cost, when a conductor size larger than that determined by thermal constraints is chosen, is due to the considerable reduction in the cost of the joule losses compared with the increase in cost of purchase. For the values of the financial and electrical parameters used in this standard, which are not exceptional, the saving in the combined cost of purchase and operation is of the order of 50 % (see clause A.6 in annex A). Calculations for much shorter financial periods can show a similar pattern.

A further important feature, which is demonstrated by examples, is that the savings possible are not critically dependent on the conductor size when it is in the region of the economic value, see figure A.3. This has two implications:

- a) The impact of errors in financial data, particularly those which determine future costs, is small. While it is advantageous to seek data having the best practicable accuracy, considerable savings can be achieved using data based on reasonable estimates.
- b) Other considerations with regard to the choice of conductor size which feature in the overall economics of an installation, such as fault currents, voltage drop and size rationalization, can all be given appropriate emphasis without losing too many of the benefits arising from the choice of an economic size.

0.2 Economic aspects

In order to combine the purchase and installation costs with costs of energy losses arising during the economic life of a cable, it is necessary to express them in comparable economic values, that is values which relate to the same point in time. It is convenient to use the date of purchase of the installation as this point and to refer to it as the "present". The "future" costs of the energy losses are then converted to their equivalent "present values". This is done by the process of discounting, the discounting rate being linked to the cost of borrowing money.

In the procedure given here inflation has been omitted on the grounds that it will affect both the cost of borrowing money and the cost of energy. If these items are considered over the same period of time and the effect of inflation is approximately the same for both, the choice of an economic size can be made satisfactorily without introducing the added complication of inflation.

To calculate the present value of the costs of the losses it is necessary to choose appropriate values for the future development of the load, annual increases in kWh price and annual discounting rates over the economic life of the cable, which could be 25 years or more. It is not possible to give guidance on these aspects in this standard because they are dependent on the conditions and financial constraints of individual installations. Only the appropriate formulae are given: it is the responsibility of the designer and the user to agree on the economic factors to be used.

The formulae proposed in this standard are straightforward, but in their application due regard should be taken of the assumption that the financial parameters are assumed to remain unchanged during the economic life of the cable. Nevertheless, the above comments on the effect of the accuracy of these parameters is relevant here also.

There are two approaches to the calculation of the economic size, based on the same financial concepts. The first, where a series of conductor sizes is being considered, is to calculate a range of economic currents for each of the conductor sizes envisaged for particular installation conditions and then to select that size whose economic range contains the required value of the load. This approach is appropriate where several similar installations are under consideration. The second method, which may be more suitable where only one installation is involved, is to calculate the optimum cross-sectional area for the required load and then to select the closest standard conductor size.

0.3 Other criteria

Other criteria, for example short-circuit current and its duration, voltage drop and cable size rationalization, must be considered also. However, a cable chosen to have an economical size of conductor may well be satisfactory also from these other points of view, so that when sizing a cable the following sequence may be advantageous:

- a) calculate the economic cross-sectional area;
- b) check by the methods given in IEC 287-1, in IEC 287-2 and in IEC 853 that the size indicated by a) is adequate to carry the maximum load expected to occur at the end of the economic period without its conductor temperature exceeding the maximum permitted value;
- c) check that the size of cable selected can safely withstand the prospective short-circuit and earth fault currents for the corresponding durations;
- d) check that the voltage drop at the end of the cable remains within acceptable limits;
- e) check against other criteria appropriate to the installation.

To complete the field of economic selection, proper weight should be given to the consequences of interruption of supply. It may be necessary to use a larger cross-section of conductor than the normal load conditions require and/or the economic choice would suggest, or to adapt the network accordingly.

A further cost component may be recognized in the financial consequence of making a faulty decision weighted by its probability. However, in doing so one enters the field of decision theory which is outside the scope of this standard.

Thus, economic cable sizing is only a part of the total economic consideration of a system and may give way to other important economic factors.

ELECTRIC CABLES – CALCULATION OF THE CURRENT RATING –

Part 3: Sections on operating conditions – Section 2: Economic optimization of power cable size

1 Scope

This International Standard deals solely with the economic choice of conductor size based on joule losses. Voltage dependent losses have not been considered.

NOTES

- 1 It is recommended that the method given in this standard should not be used for cables operating on system voltages equal to or greater than the following (see IEC 287-1-1):

Type of cable	System voltage U_0 kV
Cables insulated with impregnated paper:	
solid type	38
oil-filled and gas pressure	63,5
Cables with other types of insulation:	
butyl rubber	18
EPR	63,5
PVC	6
PE (HD and LD)	127
XLPE (unfilled)	127
XLPE (filled)	63,5

- 2 Modifications to the method given in this standard in order to take dielectric losses into account are under consideration.

Likewise, matters such as maintenance, energy losses in forced cooling systems and time of day energy costs have not been included in this standard.

An example of the application of the method to a hypothetical supply system is given in annex A.

2 Normative references

The following normative documents contain provisions which, through reference in this text, constitute provisions of this section of IEC 287-3. At the time of publication, the editions indicated were valid. All normative documents are subject to revision, and parties to agreements based on this section of IEC 287-3 are encouraged to investigate the possibility of applying the most recent editions of the normative documents indicated below. Members of IEC and ISO maintain registers of currently valid International Standards.

IEC 228: 1978, *Conductors of insulated cables*

IEC 287-1-1: 1994, *Electric cables – Calculation of the current rating – Part 1: Current rating equations (100 % load factor) and calculation of losses – Section 1: General*

IEC 287-2-1: 1994, *Electric cables – Calculation of the current rating – Part 2: Thermal resistance – Section 1: Calculation of thermal resistance*

IEC 853, *Calculation of the cyclic and emergency current rating of cables*

3 Symbols

The symbols used in this standard and the quantities which they represent are given in the following list:

A	variable component of cost per unit length related to conductor size	cu/m.mm ²
B	auxiliary quantity defined by equation (16)	–
C	constant component of cost per unit length related to laying conditions, etc.	cu/m
CT	total cost of a system	cu
D	demand charge each year	cu/W.year
F	auxiliary quantity defined by equation (10)	cu/W
$I_{\max}$	maximum load in first year i.e. the highest hourly mean value	A
$I(t)$	load as a function of time	A
l	cable length	m
CJ	present value of the cost of joule losses during N years	cu
N	period covered by financial calculations, also referred to as "economic life"	year
N_p	number of phase conductors per circuit	–
N_c	number of circuits carrying the same type and value of load	–
P	cost of one watt-hour at relevant voltage level	cu/W.h
CI	installed cost of the length of cable being considered	cu
CI_2	installed cost of the next larger standard size of conductor	cu
CI_1	installed cost of the next smaller standard size of conductor	cu
$CI(S)$	installed cost of a cable as a function of its cross-sectional area	cu
Q	auxiliary quantity defined by equation (8)	–
R	cable a.c. resistance per unit length, including the effect of $\gamma_p, \gamma_s, \lambda_1, \lambda_2$ (considered to be a constant value at an average operating temperature, see clause 4)	Ω/m
R_2	a.c. resistance per unit length of next larger standard conductor size	Ω/m

R_1	a.c. resistance per unit length of next smaller standard conductor size	Ω/m
$R(S)$	a.c. resistance per unit length of a conductor as a function of its area	Ω/m
S	cross-sectional area of a cable conductor	mm^2
S_{ec}	economic conductor size	mm^2
T	operating time at maximum joule loss	h/year
a	annual increase in I_{max}	%
b	annual increase in P , not covered by inflation	%
i	discounting rate used to compute present values	%
r	auxiliary quantity defined by equation (9)	—
t	time	h
γ_p	proximity effect factor, see IEC 287-1-1	—
γ_s	skin effect factor, see IEC 287 1-1	—
α_{20}	temperature coefficient of conductor resistance at 20 °C	$1/\text{K}$
θ	maximum rated conductor operating temperature	°C
θ_a	ambient average temperature	°C
θ_m	mean operating conductor temperature	°C
λ_1, λ_2	sheath and armour loss factors, see IEC 287-1-1	—
μ	loss load factor, see IEC 853	—
ρ_{20}	conductor resistivity at 20 °C, see 5.2	$\Omega.\text{m}$

4 Calculation of total costs

The total cost of installing and operating a cable during its economic life, expressed in present values, is calculated as follows. Note that all financial quantities are expressed in arbitrary currency units, (cu).

$$\text{The total cost} = CT = CI + CJ \text{ (cu)} \quad (1)$$

where

CI is the cost of the installed length of cable, cu;

CJ is the equivalent cost at the date the installation was purchased, i.e. the present value, of the joule losses during an economic life of N years, cu.

Evaluation of CJ

The total cost due to the losses is composed of two parts: a) the energy charge and b) the charge for the additional supply capacity to provide the losses.

a) *Cost due to energy charge*

$$\text{Energy loss during the first year} = (I_{\max}^2 \cdot R \cdot l \cdot N_p \cdot N_c) T \text{ (W.h)} \quad (2)$$

where

$I_{\max}$ is the maximum load on the cable during the first year, A;

l is the length of cable, m;

R is the apparent a.c. resistance of a conductor per unit length, taking into account both skin and proximity effects (γ_p , γ_s) and losses in metal screens and armour (λ_1 , λ_2), Ω/m .

As the economic conductor size is usually larger than the size based on thermal considerations (i.e. the size determined by the use of IEC 287-1, IEC 287-2 and/or IEC 853), its temperature will be lower than the maximum permissible value. It is convenient to assume, in the absence of more precise information, that R is constant and has a value corresponding to a temperature of $(\theta - \theta_a)/3 + \theta_a$.

Here θ is the maximum rated conductor temperature for the type of cable concerned and θ_a is the ambient average temperature. Factor 3 is empirical, see annex B.

NOTE – If greater precision is required (for example where the calculations do not indicate clearly which nominal conductor size should be chosen or the growth in load is such that its value during the final years is significantly higher than that of the first year) a better estimate of conductor temperature can be made using as a starting point the conductor size obtained from the approximate temperature given above.

Methods for making a more refined estimate of conductor temperature and resistance are given in annex B. The economical size is then redetermined using the revised value of conductor resistance.

The effect of conductor resistance on the value of the economical size is small and it is seldom worthwhile to perform the iteration more than once.

N_p is the number of phase conductors per circuit;

N_c is the number of circuits carrying the same value and type of load;

T is the operating time at maximum joule loss, h/year;

is the number of hours per year that the maximum current $I_{\max}$ would need to flow in order to produce the same total yearly energy losses as the actual, variable, load current;

$$T = \int_0^{8760} \frac{I(t)^2 \cdot dt}{I_{\max}^2}$$

If the loss load factor μ is known and can be assumed to be constant during the economic life, then:

T is equal to $\mu \cdot 8760$

See IEC 853 for the derivation of the loss load factor, μ ;

t is the time, h;

$I(t)$ is the load current as a function of time, A.

The cost of the first year's losses is:

$$= (I_{\max}^2 \cdot R \cdot l \cdot N_p \cdot N_c) \cdot T \cdot P \text{ (cu)} \quad (3)$$

where

P is the cost of one watt-hour of energy at the relevant voltage level, cu/W.h.

b) Cost due to additional supply capacity

The cost of additional supply capacity to provide these losses is:

$$= (I_{\max}^2 \cdot R \cdot l \cdot N_p \cdot N_c) \cdot D \text{ (cu/year)} \quad (4)$$

where

D is the demand charge per year, cu/W.year.

The overall cost of the first year's losses is therefore:

$$= (I_{\max}^2 \cdot R \cdot l \cdot N_p \cdot N_c) \cdot (T \cdot P + D) \text{ (cu)} \quad (5)$$

If costs are paid at the end of the year, then at the date of the purchase of the installation their present value is:

$$= \frac{(I_{\max}^2 \cdot R \cdot l \cdot N_p \cdot N_c) \cdot (T \cdot P + D)}{(1 + i/100)} \text{ (cu)} \quad (6)$$

where

i is the discount rate, not including the effect of inflation, %.

Similarly, the present value of energy costs during N years of operation, discounted to the date of purchase is:

$$C_d = (I_{\max}^2 \cdot R \cdot l \cdot N_p \cdot N_c) \cdot (T \cdot P + D) \cdot \frac{Q}{(1 + i/100)} \text{ (cu)} \quad (7)$$

where

Q is a coefficient taking into account the increase in load, the increase in cost of energy over N years and the discount rate.

$$= \sum_{n=1}^N (r^{n-1}) = \frac{1 - r^N}{1 - r} \quad (8)$$

$$r = \frac{(1 + a/100)^2 \cdot (1 + b/100)}{(1 + i/100)} \quad (9)$$

and

a is the increase in load per year, %;

b is the increase in cost of energy per year, not including the effect of inflation, %.

Where a number of calculations involving different sizes of conductor are required, it is advantageous to express all the parameters excepting conductor current and resistance in one coefficient F , where

$$F = N_p \cdot N_c \cdot (T \cdot P + D) \cdot \frac{Q}{(1 + i/100)} \quad (\text{cu/W}) \quad (10)$$

The total cost is then given by:

$$CT = CI + I_{\max}^2 \cdot R \cdot L \cdot F \quad (\text{cu}) \quad (11)$$

5 Determination of economic conductor sizes

5.1 First approach: economic current range for each conductor in a series of sizes

All conductor sizes have an economic current range for given installation conditions. The upper and lower limits of the economic range for a given conductor size are given by:

$$\text{lower limit of } I_{\max} = \sqrt{\frac{CI - CI_1}{F \cdot L \cdot (R_1 - R)}} \quad (\text{A}) \quad (12)$$

$$\text{upper limit } I_{\max} = \sqrt{\frac{CI_2 - CI}{F \cdot L \cdot (R - R_2)}} \quad (\text{A}) \quad (13)$$

where

CI is the installed cost of the length of cable whose conductor size is being considered, cu;

R is the a.c. resistance per unit length of the conductor size being considered, Ω/m ;

CI_1 is the installed cost of the next smaller standard conductor, cu;

R_1 is the a.c. resistance per unit length of the next smaller standard conductor, Ω/m ;

CI_2 is the installed cost of the next larger standard conductor, cu;

R_2 is the a.c. resistance per unit length of the next larger standard conductor, Ω/m .

NOTES

1 The upper and lower economic current limits of each conductor size may be tabulated and used to select the most economic size of conductor for a particular load.

2 The upper economic current limit of one conductor size is the lower economic current limit for the next larger conductor size.

5.2 Second approach: economic conductor size for a given load

5.2.1 General equation

The economic conductor size, S_{ec} is the cross-section that minimizes the total cost function:

$$CT(S) = C(S) + I_{\max}^2 \cdot R(S) \cdot L \cdot F \quad (\text{cu}) \quad (14)$$

where $C(S)$ and $R(S)$ are expressed as functions of the conductor cross-section S , see 5.2.2.

The equation for the relationship between $C(S)$ and conductor size can be derived from known costs of standard cable sizes. In general, if a reasonably linear relationship can be fitted to the costs, possibly over a restricted range of conductor sizes, it should be used. This will cause little error in the results, in view of the possible uncertainties in the assumed financial parameters for the economic life period chosen.

According to IEC 287-1-1, the apparent conductor resistance can be expressed as a function of the cross-section by:

$$R(S) = \frac{\rho_{20} \cdot B [1 + \alpha_{20} (\theta_m - 20)]}{S} \times 10^6 \quad (\Omega/\text{m}) \quad (15)$$

$$B = (1 + y_p + y_s) (1 + \lambda_1 + \lambda_2) \quad (16)$$

where

ρ_{20} is the d.c. resistivity of the conductor, $\Omega \cdot \text{m}$.

NOTE – The economic conductor size is unlikely to be identical to a standard size and so it is necessary to provide a continuous relationship between resistance and size. This is done by assuming a value of resistivity for each conductor material. The values recommended here for ρ_{20} are: $18,35 \times 10^{-9}$ for copper and $30,3 \times 10^{-9}$ for aluminium. These values are not the actual values for the materials, but are compromise values chosen so that conductor resistances can be calculated directly from nominal conductor sizes, rather than from the actual effective cross-sectional areas.

y_p, y_s are the skin and proximity effect factors, see IEC 287-1-1;

λ_1, λ_2 are the sheath and armour loss factors, see IEC 287-1-1;

α_{20} is the temperature coefficient of resistivity for the particular conductor material at 20°C , K^{-1} ;

θ_m is the conductor temperature, see explanation given in the definition of R for equation (2), $^\circ\text{C}$;

B is the auxiliary value defined by equation (16), which can be calculated from IEC 287-1-1 by assuming a probable value for the economic size of conductor;

S is the cross-sectional area of cable conductor, mm^2 .

5.2.2 Linear cost function for cable costs

If a linear model can be fitted to the values of initial cost for the type of cable and installation under consideration, then:

$$Cl(S) = l.(A.S + C) \quad (\text{cu}) \quad (17)$$

where

A is the variable component of cost, related to conductor size, cu/m.mm²;

C is the constant component of cost, unaffected by size of cable, cu/m;

l is the length of cable, m.

Then the optimum size S_{ec} (mm²) can be obtained by equating to zero the derivative of equation (14) with respect to S , giving:

$$S_{ec} = 1\,000 \left[\frac{I_{\max}^2 \cdot F \cdot \rho_{20} \cdot B [1 + \alpha_{20} (\theta_m - 20)]}{A} \right]^{0.5} (\text{mm}^2) \quad (18)$$

NOTES

1 As the economic size is unknown, it is necessary to make an assumption as to the probable cable size in order that reasonable values of y_p , y_s , λ_1 and λ_2 can be calculated. Recalculation may be necessary if the economic size is too different.

2 The constant component of the cost, C , in equation (17), does not affect the evaluation of the economic size S_{ec} .

S_{ec} is unlikely to be exactly equal to a standard size (see IEC 228) and so the cost for the adjacent larger and smaller standard sizes shall be calculated and the most economical one chosen.

Annex A (informative)

Examples of calculation of economic conductor sizes

A.1 General

Example calculations are given for a supply system feeding ten equal loads uniformly spaced along a route for the following cases:

- a) An application of the first approach (see 5.1), the economic current range method, to size each cable between adjacent loads.
- b) An application of the second method (see 5.2), the economic conductor size method, to size each cable between adjacent loads.
- c) An application of both methods to give the most economical conductor size where only one size of cable is used throughout the whole route.

The results are summarized in A.6 to show the saving that can be obtained by choosing a conductor size which reduces the overall costs, rather than by minimizing the first cost.

A.2 Cable and supply system details

Load and route data

A 10 kV cable circuit has to be sized to supply ten 10 kV/0,4 kV substations equally spaced along a route from a 150 kV/10 kV station (see figure A.1). (There is only one three-phase circuit so $N_c = 1$ and $N_p = 3$.)

The cable length between substations is 500 m.

The highest hourly mean values of current $I_{\max}$, in the first year for each section of the route are:

Section	Current (A)
1	160
2	144
3	128
reducing by 16 A at each station to:	
9	32
10	16

The cyclic rating factor, M , for all loads is 1,11 (see IEC 853). It is assumed that this factor remains constant during the economic life of the cable.

For each section of the route the cable size is chosen according to the following criteria:

- a) The minimized sum of the primary cost plus the present value of the joule losses for the economic life of the cable.

b) The current-carrying capacity required for the load during the last year of the economic life of the cable. The required current-carrying capacity for this example is 0,9 times the maximum load, i.e. the maximum load divided by the cyclic rating factor of 1,11.

c) Other factors, such as short-circuit withstand and voltage drop, have not been considered in this example, but can be introduced as indicated in clause 0.3 of the introduction to this standard.

Financial data

economic life	<i>N</i>	30	(year)
operating time at maximum loss (the value of 2 250 includes the effect of the daily cyclic load)	<i>T</i>	2 250	(h/year)
price of joule losses at end of first year at 10 kV	<i>P</i>	$60,9 \times 10^{-6}$	(cu./W.h)
demand charges	<i>D</i>	0,003	(cu/W.year)
Cable and installation costs per unit length are given in table A.1			(cu/m)
For this example, the coefficient of that part of the installation costs which depends on conductor size has been calculated to be	<i>A</i>	0,1133	(cu/m.mm ²)
annual increase of load	<i>a</i>	0,5	(%)
annual increase of cost of energy (kW.h price)	<i>b</i>	2,0	(%)
annual discounting rate	<i>i</i>	5,0	(%)

Cable data

For the purpose of this example a fictional three-core 6/10 kV type of cable has been assumed. The a.c. resistances of the conductors at 40 °C and 80 °C are given in columns (2) and (3) of table A.1 and the financial details are given in columns (4) to (6). It has a permissible maximum conductor temperature of 80 °C and when laid in the ground the steady-state ratings at this temperature, for a 20 °C ground ambient temperature, are those given in A.3.3.

Calculation of auxiliary quantities

$$r = \frac{[1 + (0,5/100)]^2 \times [1 + (2/100)]}{1 + (5/100)} = 0,98117 \quad (\text{equation (9)})$$

$$Q = \frac{1 - 0,9812^{30}}{1 - 0,9812} = 23,081 \quad (\text{equation (8)})$$

$$F = \frac{3 \times 1 \times (2\,250 \times 60,9 \times 10^{-6} + 0,003) \times 23,08}{1 + (5/100)} = 9,2341 \quad (\text{equation (10)})$$

A.3 Calculation using the economic current range method (see 5.1)

A.3.1 Calculation of the economic current range of one size

As an example, the economic current range for a 240 mm² conductor will be found. Equations (12) and (13) are used.

$$\text{Lower limit of } I_{\max} = \sqrt{\frac{500 \times (52,2 - 45,96) \times 10^3}{9,2341 \times 500 \times (0,181 - 0,140)}} = 128 \text{ A} \quad (\text{equation (12)})$$

$$\text{Upper limit of } I_{\max} = \sqrt{\frac{500 \times (58,99 - 52,2) \times 10^3}{9,2341 \times 500 \times (0,140 - 0,114)}} = 168 \text{ A} \quad (\text{equation (13)})$$

The upper limits of current for a range of standard conductor sizes, when installed under the conditions assumed for this example, have been similarly worked out. Since the lower limit of current for a given size of conductor is also the upper limit for the next smaller conductor, the values calculated can be expressed as current ranges as shown in the following table:

Economic current ranges for cable sizes 25 mm² to 400 mm²

Nominal size mm ²	Current range A	
25	–	19
35	19	27
50	27	34
70	34	48
95	48	66
120	66	85
150	85	98
185	98	128
240	128	168
300	168	231
400	231	–

Relationships between maximum load during the first year and total cost per unit length for three sizes of cable are given in figure A.2. It can be seen that each size of cable provides the most economical installation over a range of currents.

The effect of a change in conductor size on the overall costs, when carrying a given load, is shown in figure A.3. Here the cable and financial parameters of this example have been retained, but a fixed load, $I_{\max}$, of 100 A has been assumed. It can be seen that, in the region of the most economic size, the total costs are not greatly affected by the choice of cable size. However, the reduction in costs, compared with those based on the use of a size chosen from thermal considerations, is very significant.

A.3.2 Selection of an economic conductor size for each section

From the economic current ranges tabulated in A.3.1 above it is possible to select an appropriate conductor size for each section of the cable route, based on each value of $I_{\max}$ for the first year. The sizes so selected for each section are given in table A.2 together with the costs calculated by means of equation (11).

A typical example of the calculation of costs is given below.

For section 1, $I_{\max}$ is 160 A.

The economic conductor size selected from the table in A.3.1 is 240 mm², which has an economic current range of 128 A to 168 A.

$$\begin{aligned} CT &= [52,2 \times 500] + [160^2 \times (0,140/1\ 000) \times 500 \times 9,2341] \\ &= 26\ 100 + 16\ 548 \\ &= 42\ 648 \text{ cu} \end{aligned}$$

The costs for each section of the route are summarized in table A.2.

It can be seen from table A.2 that the total cost for the cable installation over 30 years on an economic basis is 290 535 cu.

A.3.3 Conductor size based on maximum load - Choice based on thermal ratings

The cable size for each section is chosen so as to carry the anticipated maximum load for the last year of the economic life and not to exceed the maximum permissible conductor temperature.

For section 1:

$$I_{\max} \text{ (first year)} = 160 \text{ A}$$

$$\begin{aligned} \text{Maximum current in last year} &= 160 \times [1 + (0,5/100)]^{30-1} \\ &= 160 \times 1,1556 \\ &= 185 \text{ A} \end{aligned}$$

The required current-carrying capacity (100 % load factor), I , for the final year shall be not less than:

$$185/1,11 = 167 \text{ A}$$

where the number 1,11 is the cyclic rating factor assumed in A.2 b) above.

From the following table of current ratings (calculated according to the methods in IEC 287-1-1 and IEC 287-2-1, for this type of cable when installed in the ground) the required conductor size is 70 mm².

Nominal size, mm ²	25	35	50	70	95	120	150	185	240	300	400
Current-carrying capacity, A	103	125	147	181	221	255	281	328	382	429	482

In order to make a fair comparison with the losses and financial figures calculated for the economic choice of conductor size, it is necessary to assume an appropriate conductor temperature at which to calculate the losses. For the economic choice it was assumed that the temperature of the conductor would be about 40 °C (see clause 4). It is proposed here that a comparable assumption for the temperature of conductors chosen on the basis of thermal ratings would be the maximum permissible value of 80 °C.

The conductor resistance at a temperature of 80 °C is given in table A.1.

The total cost of section 1 during the 30-year period is obtained from equation (11).

$$\begin{aligned}
 CT &= [32,95 \times 500] + [160^2 \times (0,553/1\,000) \times 500 \times 9,2341] \\
 &= 16\,475 + 65\,363 \\
 &= 81\,838 \text{ cu}
 \end{aligned}$$

Comparison with the cost for this section when using the economical size of conductor, evaluated in A.3.2, shows that the saving in cost for this section is $(81\,838 - 42\,648) \times 100/81\,838 = 48\%$.

Similar calculations using sizes based on maximum thermal current-carrying capacity have been made for all the sections and are given in table A.3. The total saving for the ten sections is $(547\,864 - 290\,535) \times 100/547\,864 = 47\%$.

A.4 Calculation using the economic conductor size method (see 5.2)

Route section 1 is used as an example.

$$\begin{aligned}
 I_{\max} &= 160 \text{ A} \\
 \rho_{20} &= 30,3 \times 10^{-9} \Omega \cdot \text{m} \text{ (see 5.2.1)} \\
 \alpha_{20} &= 0,00403 \text{ K}^{-1} \\
 B &= 1,023 \text{ (assuming initially that a conductor size of } 185 \text{ mm}^2 \text{ could be the economic optimum)} \\
 A &= 0,1133 \text{ cu/m} \cdot \text{mm}^2 \text{ (coefficient of the variable part of the installation costs, see 5.2.2)}
 \end{aligned}$$

$$F = 9,2341 \text{ cu/W}$$

$$\theta_m = (80 - 20)/3 + 20 = 40 \text{ }^{\circ}\text{C}$$

$$S_{ec} = 1\,000 \times \left[\frac{160^2 \times 9,2341 \times 30,3 \times 10^{-9} \times 1,023[1 + 0,00403(40 - 20)]}{0,1133} \right]^{0,5}$$

$$= 264 \text{ mm}^2$$

Thus either a 240 mm² or a 300 mm² conductor size could be chosen.

The initial choice of a 185 mm² conductor for the estimation of B can now be improved.

Recalculating with a value of $B = 1,057$, for a 300 mm² conductor, gives a value for S_{ec} of 269 mm², which is also within the 240 mm² to 300 mm² range.

The total cost for each of the possible conductor sizes is now calculated with the aid of equation (11).

$$CT_{240} = [52,2 \times 500] + [160^2 \times (0,140/1\,000) \times 500 \times 9,2341]$$

$$= 26\,100 + 16\,548$$

$$= 42\,648 \text{ cu}$$

$$CT_{300} = [58,99 \times 500] + [160^2 \times (0,114/1\,000) \times 500 \times 9,2341]$$

$$= 29\,495 + 13\,474$$

$$= 42\,969 \text{ cu}$$

The 240 mm² conductor is therefore the more economical size.

Sizes and costs for the other sections have been calculated in a similar manner. The values agree identically with those derived by the previous method demonstrated in A.3.1 and A.3.2 and the summary of sizes and cost is the same as that already given in table A.2.

A.5 Calculation based on the use of one standard conductor size for all sections of the route

A.5.1 Using the economic current range method

It is first necessary to assume a probable conductor size and the total cost is calculated with equation (11) using this size for all sections. Then costs assuming the use of the next smaller and larger sizes of conductor are calculated in order to confirm that the assumed size is indeed the most economical.

For the purpose of this example it is assumed that a 185 mm² conductor would be the best choice.

The costs for all sections using 185 mm², and then 150 mm² and 240 mm² have been calculated and are set out in table A.4.

The total costs are:

150 mm ²	312 841 cu
185 mm ²	312 166 cu
240 mm ²	324 707 cu

This indicates that, if for the purpose of standardization one conductor size only can be used, 185 mm² is the most economic choice.

The small change in total cost with change in conductor size noted in A.3.1, and figure A.3, can be seen to apply here also.

A.5.2 Economic conductor size method

Although only one conductor size is used, the current is different for each cable section, so that the average losses must be computed (all sections are assumed to operate at the same temperature and hence the same conductor resistance).

$$\frac{\text{Average losses}}{\text{Maximum losses}} = \frac{500 \times 160^2 + 500 \times 144^2 + \dots + \dots + 500 \times 16^2}{10 \times 500 \times 160^2} = 0,385$$

From equation (18), using B for a 185 mm² conductor

$$S_{ec} = 1\,000 \times \left[\frac{160^2 \times 1,023 \times 30,3 \times 10^{-9} [1 + 0,00403(40 - 20)] \times 9,2341 \times 0,385}{0,1133} \right]^{0,5} = 164 \text{ mm}^2$$

So that either 150 mm² or 185 mm² conductors could prove to be the most economic.

Total costs for each of these conductors are:

$$\begin{aligned} CT_{150} &= 42,00 \times 500 \times 10 + 160^2 \times (0,226/1\,000) \times 500 \times 10 \times 9,2341 \times 0,385 \\ &= 210\,000 + 102\,843 \\ &= 312\,843 \text{ cu} \end{aligned}$$

$$\begin{aligned} CT_{185} &= 45,96 \times 500 \times 10 + 160^2 \times (0,181/1\,000) \times 500 \times 10 \times 9,2341 \times 0,385 \\ &= 229\,800 + 82\,365 \\ &= 312\,165 \text{ cu} \end{aligned}$$

Thus the 185 mm² size is confirmed as the most economic size to use if only one conductor size is to be used throughout the route.

It is clear, by comparison with the sizes chosen in table A.3, that a 185 mm² conductor is thermally adequate to carry the maximum load at the end of the 30-year period.

A.6 Summary of results

A summary of the results of the calculations for the cable and conditions described in A.2 is given below.

Summary of costs

Basis of costing	<i>C</i> / cu	<i>C</i> / cu	TOTAL cu	%
Thermal current-carrying capacity for each section	146 330	401 534	547 864	100
Economic size for each section	202 095	88 440	290 535	53
Economic size using one standard size of 185 mm ² throughout	229 800	82 365	312 165	57

Table A.1 – Cable details

Cable size mm ² (1)	Resistance by phase at		Cable cu/m (4)	Primary cost	
	40 °C Ω/km (2)	80 °C Ω/km (3)		Laying cu/m (5)	Sum cu/m (6)
25	1,298	1,491	10,62	17,23	27,85
35	0,939	1,079	11,65	17,33	28,98
50	0,694	0,798	13,19	17,49	30,68
70	0,481	0,553	15,24	17,71	32,95
95	0,348	0,400	17,81	17,97	35,78
120	0,277	0,318	20,37	18,24	38,61
150	0,226	0,259	23,45	18,55	42,00
185	0,181	0,208	27,04	18,92	45,96
240	0,140	0,161	32,69	19,51	52,20
300	0,114	0,131	38,85	20,14	58,99
400	0,091	0,104	49,11	21,20	70,31

Table A.2 – Economic loading

Section number	1	2	3	4	5	6	7	8	9	10	
Load											
I_{max} (A)	160	144	128	112	96	80	64	48	32	16	
Cable											
Size (mm ²)	240	240	185	185	150	120	95	70	50	25	
Capacity (A)	382	382	328	328	281	255	221	181	147	103	
Costs per section and total											Sum
Cable (cu)	16 345	16 345	13 520	13 520	11 725	10 185	8 905	7 620	6 595	5 310	110 070
Laying (cu)	9 755	9 755	9 460	9 460	9 275	9 120	8 985	8 855	8 745	8 615	92 025
<i>CI</i> (cu)	26 100	26 100	22 980	22 980	21 000	19 305	17 890	16 475	15 340	13 925	202 095
<i>CJ</i> (cu)	16 548	13 403	13 692	10 483	9 616	8 185	6 581	5 117	3 281	1 534	88 440
<i>CT</i> (cu)	42 648	39 503	36 672	33 463	30 616	27 490	24 471	21 592	18 621	15 459	290 535

Table A.3 – Current-carrying capacity criterion

Section number	1	2	3	4	5	6	7	8	9	10	
Load											
I_{max} (A)	160	144	128	112	96	80	64	48	32	16	
I_{end} (A)	185	166	148	129	111	92	74	55	37	18	
$I_{end}/1,11$ (A)	167	150	133	117	100	83	67	50	33	17	
Cable											
Size (mm ²)	70	70	50	35	25	25	25	25	25	25	
Capacity (A)	181	181	147	125	103	103	103	103	103	103	
Costs per section and total											Sum
Cable (cu)	7 620	7 620	6 595	5 825	5 310	5 310	5 310	5 310	5 310	5 310	59 520
Laying (cu)	8 855	8 855	8 745	8 665	8 615	8 615	8 615	8 615	8 615	8 615	86 810
<i>CI</i> (cu)	16 475	16 475	15 340	14 490	13 925	13 925	13 925	13 925	13 925	13 925	146 330
<i>CJ</i> (cu)	65 363	52 944	60 365	62 492	63 443	44 058	28 197	15 861	7 049	1 762	401 534
<i>CT</i> (cu)	81 838	69 419	75 705	76 982	77 368	57 983	42 122	29 786	20 974	15 687	547 864

Table A.4 – Economic loading, standard conductor size for all sections
Standard size: 150 mm²

Section number	1	2	3	4	5	6	7	8	9	10	
$I_{\max}$ (A)	160	144	128	112	96	80	64	48	32	16	
Cable											
Size (mm ²)	150	150	150	150	150	150	150	150	150	150	
Capacity (A)	281	281	281	281	281	281	281	281	281	281	
Costs per section and total											Sum
Cable (cu)	11 725	11 725	11 725	11 725	11 725	11 725	11 725	11 725	11 725	11 725	117 250
Laying (cu)	9 275	9 275	9 275	9 275	9 275	9 275	9 275	9 275	9 275	9 275	92 750
CI (cu)	21 000	21 000	21 000	21 000	21 000	21 000	21 000	21 000	21 000	21 000	210 000
CJ (cu)	26 712	21 637	17 096	13 089	9 616	6 678	4 274	2 404	1 068	267	102 841
CT (cu)	47 712	42 637	38 096	34 089	30 616	27 678	25 274	23 404	22 068	21 267	312 841


Standard size: 185 mm²

Section number	1	2	3	4	5	6	7	8	9	10	
$I_{\max}$ (A)	160	144	128	112	96	80	64	48	32	16	
Cable											
Size (mm ²)	185	185	185	185	185	185	185	185	185	185	
Capacity (A)	328	328	328	328	328	328	328	328	328	328	
Costs per section and total											Sum
Cable (cu)	13 520	13 520	13 520	13 520	13 520	13 520	13 520	13 520	13 520	13 520	135 200
Laying (cu)	9 460	9 460	9 460	9 460	9 460	9 460	9 460	9 460	9 460	9 460	94 600
CI (cu)	22 980	22 980	22 980	22 980	22 980	22 980	22 980	22 980	22 980	22 980	229 800
CJ (cu)	21 393	17 329	13 692	10 483	7 702	5 348	3 423	1 925	856	214	82 365
CT (cu)	44 373	40 309	36 672	33 463	30 682	28 328	26 403	24 905	23 836	23 194	312 165

Standard size: 240 mm²


Section number	1	2	3	4	5	6	7	8	9	10	
$I_{\max}$ (A)	160	144	128	112	96	80	64	48	32	16	
Cable											
Size (mm ²)	240	240	240	240	240	240	240	240	240	240	
Capacity (A)	382	382	382	382	382	382	382	382	382	382	
Costs per section and total											Sum
Cable (cu)	16 345	16 345	16 345	16 345	16 345	16 345	16 345	16 345	16 345	16 345	163 450
Laying (cu)	9 755	9 755	9 755	9 755	9 755	9 755	9 755	9 755	9 755	9 755	97 550
CI (cu)	26 100	26 100	26 100	26 100	26 100	26 100	26 100	26 100	26 100	26 100	261 000
CJ (cu)	16 548	13 403	10 590	8 108	5 957	4 137	2 648	1 489	662	165	63 707
CT (cu)	42 648	39 503	36 690	34 208	32 057	30 237	28 748	27 589	26 762	26 265	324 707

Poste source
Main station




CEI-IEC 201/91

Figure A.1 - Disposition de la liaison
System layout



CEI-IEC 202/91

Figure A.2 - Fourchettes de courant économique
Economic current ranges



CEI-IEC 203/91

Figure A.3 - Variation du coût en fonction de la section d'âme
Variation of cost with conductor size