

TECHNICAL SPECIFICATION

**Piezoelectric, dielectric and electrostatic devices and associated materials for frequency control, selection and detection – Glossary –
Part 5: Piezoelectric sensors**

IECNORM.COM : Click to view the full PDF of IEC TS 61994-5:2023



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2023 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 300 terminological entries in English and French, with equivalent terms in 19 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IECNORM.COM : Click to view the full PDF of IEC 150199-5:2023

TECHNICAL SPECIFICATION

**Piezoelectric, dielectric and electrostatic devices and associated materials for
frequency control, selection and detection – Glossary –
Part 5: Piezoelectric sensors**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 01.040.31; 31.140

ISBN 978-2-8322-7500-9

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD	3
1 Scope	5
2 Normative references	5
3 Terms and definitions	5
Bibliography	11

IECNORM.COM : Click to view the full PDF of IEC TS 61994-5:2023

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**PIEZOELECTRIC, DIELECTRIC AND ELECTROSTATIC DEVICES
AND ASSOCIATED MATERIALS FOR FREQUENCY CONTROL,
SELECTION AND DETECTION –
GLOSSARY –****Part 5: Piezoelectric sensors****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

IEC TS 61944-5 has been prepared by IEC technical committee 49: Piezoelectric, dielectric and electrostatic devices and associated materials for frequency control, selection and detection. It is a Technical Specification.

This second edition cancels and replaces the first edition published in 2019. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) New terms and definitions have been added from IEC 63041-1:2021 and IEC 63041-3:2020.

The text of this Technical Specification is based on the following documents:

Draft	Report on voting
49/1421/DTS	49/1439/RVDTS

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Specification is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts in the IEC 61994 series, published under the general title *Piezoelectric, dielectric and electrostatic devices and associated materials for frequency control, selection and detection – Glossary*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IECNORM.COM : Click to view the full PDF of IEC TS 61994-5:2023

PIEZOELECTRIC, DIELECTRIC AND ELECTROSTATIC DEVICES AND ASSOCIATED MATERIALS FOR FREQUENCY CONTROL, SELECTION AND DETECTION – GLOSSARY –

Part 5: Piezoelectric sensors

1 Scope

This part of IEC 61994 gives the terms and definitions for sensors representing the state of the art, which are intended for manufacturing piezoelectric elements, cells, modules and the systems.

2 Normative references

There are no normative references in this document.

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at <https://www.electropedia.org/>
- ISO Online browsing platform: available at <https://www.iso.org/obp>

3.1

delay line type sensor element

piezoelectric sensor component using a delay line of SAW transversal filter type

[SOURCE: IEC 63041-1:2021, 3.1.3, modified – "surface acoustic wave (SAW) transversal filter type" of the definition has been replaced by "SAW transversal filter type".]

3.2

differential sensor

piezoelectric sensor element that can detect physical quantities from a differential change in resonance frequencies or delays of two independent and same micro-acoustic structures assembled on the same or different piezoelectric plates

Note 1 to entry: The differential sensor is a general term for sensors of the above type.

[SOURCE: IEC 63041-3:2020, 3.1.6, modified – "piezoelectric sensor which is able to" of the definition has been replaced by "piezoelectric sensor element that can". "from a change in resonance frequencies" has been replaced by "from a differential change in resonance frequencies".]

3.3

dual mode sensor

piezoelectric sensor element that can detect physical quantities from a change in resonance frequencies of two independent modes on a single piezoelectric plate

Note 1 to entry: In order to achieve improved precision and/or to eliminate undesirable influence factors, sensor solutions are employed that utilize two or more modes. By evaluation of combinations of those modes' sensitivities to various ambient conditions, improved detection sensitivity can be achieved, whereas undesirable sensitivities can be reduced or eliminated.

Note 2 to entry: The dual mode sensor is a general term for sensors of the above type

[SOURCE: IEC 63041-3:2020, 3.1.5, modified – "piezoelectric sensor which is able to" of definition has been replaced by "piezoelectric sensor element that can". Note 1 to entry has been rewritten. Note 2 to entry has been added.]

3.4

dual mode sensor module

dual mode sensor element or cell equipped with circuit units for temperature compensation and electronic accessories for interfacing to external data acquisitions

[SOURCE: IEC 63041-1:2021, 3.4.2, modified – The note to entry has been removed.]

3.5

dual mode sensor system

system that consists of dual mode sensor modules, electronic devices, PCs, memory, wired or wireless devices, software, etc.

Note 1 to entry: The dual mode quartz crystal sensor system is used in oil-well exploration and gas-well exploration systems.

[SOURCE: IEC 63041-1:2021, 3.5.2, modified – Since the dual mode sensor is not necessarily limited to quartz crystal-based sensors, the definition was rewritten as above.]

3.6

multi-measurand sensor

piezoelectric sensor element that can detect two or more different physical quantities from an analysis of different sensor responses

Note 1 to entry: The multi-measurand sensor is a general term for sensors of the above type,

[SOURCE: IEC 63041-3:2020, 3.1.7, modified – The words "piezoelectric sensor which is able to" of the definition have been replaced by "piezoelectric sensor element that can". Note 1 to entry has been added.]

3.7

piezoelectric acceleration sensor element

piezoelectric sensor component whose resonance frequency or delay is used to measure the change in velocity of an object with time

[SOURCE: IEC 63041-3:2020, 3.1.1.]

3.8

piezoelectric biochemical sensor element

piezoelectric sensor component including a receptive layer, which is necessary for the practical measurement of complex biological molecules in quantity, and which works mainly in aqueous media and detects biomolecules therein

Note 1 to entry: The receptive layer is usually formed as a thin film of a target recognition material on the surface of the piezoelectric sensor element and is often called a target recognition material.

[SOURCE: IEC 63041-1:2021, 3.2.2, modified – In the definition, "(target recognition material)" has been deleted. Note 1 to entry has been added.]

3.9

piezoelectric chemical sensor element

piezoelectric sensor component including a sensitive layer, which is necessary for the practical measurement of simple non-biological molecules in quantity, and which works and detects chemical substances mainly in the gas phase

Note 1 to entry: The sensitive layer is usually formed as a thin film of a target recognition material on the surface of the piezoelectric sensor element and is often called a target recognition material.

Note 2 to entry: A gas sensor element is one of the chemical sensor elements

[SOURCE: IEC 63041-1:2021, 3.2.1, modified – In the definition, "(target recognition material)" has been deleted. Note 1 to entry has been moved to Note 2 to entry. A new Note 1 to entry has been added.]

3.10

piezoelectric film-thickness sensor element

piezoelectric sensor component whose resonance frequency is used for film-thickness measurement

EXAMPLE Film-thickness control in vacuum deposition and sputter deposition

[SOURCE: IEC 63041-1:2021, 3.3.6, modified – The example has been added.]

3.11

piezoelectric force sensor element

piezoelectric sensor component whose resonance frequency, delay, electrical charge, or voltage is used for force measurement

EXAMPLE Inertial measurement system

[SOURCE: IEC 63041-1:2021, 3.3.1, modified – "delay or electrical charge/voltage" of the definition has been replaced by "delay, electrical charge, or voltage". The example has been added.]

3.12

piezoelectric humidity sensor element

piezoelectric sensor component whose resonance frequency or delay is used for dew point and moisture detection

[SOURCE: IEC 63041-3:2020, 3.1.2]

3.13

piezoelectric pressure sensor element

piezoelectric sensor component whose resonance frequency, delay, electrical charge, or voltage is used for pressure measurement

EXAMPLE Oil pressure measuring device and flow meter.

[SOURCE: IEC 63041-1:2021, 3.3.2, modified – "delay or electrical charge/voltage" of the definition has been replaced by "delay, electrical charge, or voltage". The example has been added.]

3.14

piezoelectric sensor

general term for a piezoelectric sensor element, piezoelectric sensor cell, piezoelectric sensor module, and piezoelectric sensor system

[SOURCE: IEC 63041-1:2021, 3.1.8, modified – In the definition, "a sensor element, cell, module and system" has been replaced by "piezoelectric sensor element, piezoelectric cell, piezoelectric module, and piezoelectric system".]

3.15

piezoelectric sensor cell

piezoelectric sensor element equipped with necessary mechanical accessories and attachments to correctly detect the parameters to be measured

[SOURCE: IEC 63041-1:2021, 3.1.5, modified – In the definition, "sensor" has been replaced by "piezoelectric sensor".]

3.16

piezoelectric sensor element

electronic component that can piezoelectrically detect physical quantities as a change in its frequency, phase, delay, electrical charge, resistance, Q-value, bandwidth, etc.

Note 1 to entry: For chemical and biochemical sensor applications, the piezoelectric sensor element includes a sensitive or receptive layer (target recognition material).

[SOURCE: IEC 63041-1:2021, 3.1.1, modified – In the definition, "which is able to" has been replaced by "that can piezoelectrically detect".]

3.17

piezoelectric sensor module

piezoelectric sensor element or cell equipped with electronic accessories for interfacing to external data acquisitions

[SOURCE: IEC 63041-1:2021, 3.1.6, modified – In the definition, "sensor element" has been replaced by "piezoelectric sensor element".]

3.18

piezoelectric sensor system

organized system including detection and amplification of raw data, communication with other equipment, and processing and analysis of observation data

[SOURCE: IEC 63041-1:2021, 3.1.7, modified – In the definition "amplification of detected value" has been replaced by "amplification of raw data" and "analysis of detected value" has been replaced by "analysis of observation data".]

3.19**piezoelectric temperature sensor element**

piezoelectric sensor component whose resonance frequency or delay is used for temperature measurement

[SOURCE: IEC 63041-1:2021, 3.3.5.]

3.20**piezoelectric tilt angle sensor element**

piezoelectric sensor component whose resonance frequency or delay is used to measure tilt angles, elevation, or depression of an object with respect to gravity's detection

EXAMPLE Gyro sensor

[SOURCE: IEC 63041-3:2020, 3.1.3, modified – The example has been added.]

3.21**piezoelectric torque sensor element**

piezoelectric sensor component whose resonance frequency, delay or electrical charge, or voltage is used for torque measurement

[SOURCE: IEC 63041-1:2021, 3.3.3., modified – In the definition, "delay or electrical charge/voltage" has been replaced by "delay, electrical charge, or voltage".]

3.22**piezoelectric vibration sensor element**

piezoelectric sensor component whose resonance frequency or delay is used for measurement of vibration

EXAMPLE Volcano infrasound monitoring system

[SOURCE: IEC 63041-3:2020, 3.1.4, modified – The example has been added.]

3.23**piezoelectric viscosity sensor element**

piezoelectric sensor component whose resonance frequency, delay, insertion loss, or gain is used for viscosity measurement

EXAMPLE Hydrogen leak detector for fuel-cell

[SOURCE: IEC 63041-1:2021, 3.3.4, modified – In the definition, "delay, or insertion loss/gain" has been replaced by "delay, insertion loss, or gain". The example has been added.]

3.24**quartz crystal microbalance**

QCM

piezoelectric sensor element for detecting small mass change using quartz crystal resonators

Note 1 to entry: A thickness shear mode (TSM) sensor is identical with a QCM.

[SOURCE: IEC 63041-1:2021, 3.1.9, modified – "one of the families of chemical and biochemical sensors using crystal resonators" of the definition has been replaced by "piezoelectric sensor element for detecting small mass change using quartz crystal resonators" to make it easier to understand if the principle of the sensor is specified.]

3.25

quasi-static piezoelectric sensor element

piezoelectric sensor component using the electrical charge induced by a quasi-static force, torque, or the like

[SOURCE: IEC 63041-1:2021, 3.1.4, modified – The term "non-acoustic type sensor element" has been replaced by "quasi-static piezoelectric sensor element" has been replaced as the first preferred term. The note to entry has been removed.]

3.26

resonator type sensor element

piezoelectric sensor component using acoustic resonances

[SOURCE: IEC 63041-1:2021, 3.1.2]

3.27

wireless and passive SAW sensor module

SAW sensor element or cell equipped with an antenna for wireless connection, and powered by electromagnetic wave

Note 1 to entry: Here, SAW resonators and delay lines are used for the wireless SAW sensor element or cell.

[SOURCE: IEC 63041-1:2021, 3.4.1, modified – The term "wireless SAW sensor module" has been changed to "wireless and passive SAW sensor module". In addition, "piezoelectric sensor" and "wirelessly connecting with interrogation unit" have been replaced by "SAW sensor", and "wireless connection, and powered by electromagnetic wave", respectively. Note 1 to entry has been modified.]

3.28

wireless and passive SAW sensor system

system that consists of wireless and passive SAW sensor modules, and an RF transmitter and receiver for getting observation data

IECNORM.COM : Click to view the full PDF of IEC TS 61994-5:2023